

Branch : CS & IT

Subject : Digital Logic

Chapter : Minimization

Topic : Boolean Algebra

DPP-01

1. Find out minimize expression for following function.

$$f = ABC\bar{C} + ABC + \bar{A}BC$$

- (a) $AB + BC$ (b) $A\bar{C} + \bar{A}B$
 (c) $BC + \bar{A}B$ (d) $\bar{A}B + B\bar{C}$

2. Find out minimize expression for following function.

$$f = AB + A\bar{B} + \bar{A}\bar{B}$$

- (a) $\bar{A} + B$ (b) $A + \bar{B}$
 (c) $\bar{A} + \bar{B}$ (d) $A + B$

3. Find out minimize expression for following function.

$$f = (A + B)(A + \bar{B})(\bar{A} + B)(\bar{A} + \bar{B})$$

- (a) 1 (b) $\bar{A}\bar{B}$
 (c) 0 (d) $A\bar{B}$

4. Find out minimize expression for following function.

$$f = (A + B + C)(A + B + \bar{C})$$

- (a) $(A + C)B$ (b) $A + B$
 (c) $AB\bar{C}$ (d) $A(B + C)$

5. The Boolean expression

$$f = (X + Y)(X + \bar{Y}) + \overline{\bar{X}\bar{Y} + \bar{X}}$$

- (a) Y (b) X
 (c) $\bar{X}\bar{Y}$ (d) $X + \bar{Y}$

6. The logic expression

$$f = X + \bar{X}Y$$

Is equivalent to

- (a) $X + Y$ (b) XY
 (c) $\bar{X} + Y$ (d) $X + \bar{Y}$

7. The logic expression

$$f = (A + B)(A + C)$$

Is equivalent to

- (a) $A + BC$ (b) $B + AC$
 (c) $C + AC$ (d) $\bar{A} + BC$

8. The Boolean expression

$$f = (1 + \bar{A})(B + AC)$$

is equivalent to

- (a) $AC + B$ (b) $\bar{A}C + B$
 (c) $\bar{A} + BC$ (d) 1

9. Find minimization expression

$$f = (A + \bar{A}) + (BC + AC)(A + D)$$

- (a) 1 (b) 0
 (c) $AB + CD$ (d) $ABC + BCD + ACD$

10. Find out minimization

$$f = (A + B)(A + B + C)$$

- (a) $B + C$ (b) $A + B$
 (c) $A + B + C$ (d) $AB + BC + AC$

Answer Key

1. (a)
2. (b)
3. (c)
4. (b)
5. (b)

6. (a)
7. (a)
8. (a)
9. (a)
10. (b)



Hints and solutions

1. $f = ABC\bar{C} + ABC + \bar{A}BC$

$$= AB + \bar{A}BC$$

$$= B(A + \bar{A}C)$$

$$= B(A + C)(A + \bar{A})$$

$$= AB + BC$$

2. $f = AB + A\bar{B} + \bar{A}\bar{B}$

$$= AB + (A + \bar{A})\bar{B}$$

$$= AB + \bar{B}$$

$$= (A + \bar{B})(B + \bar{B})$$

$$= A + \bar{B}$$

3. $f = (A + AB + A\bar{B})(\bar{A} + \bar{A}B + \bar{A}\bar{B})$

$$f = 0$$

4. $f = (A + B + C)(A + B + \bar{C})$

$$f = (A + AB + AC)(AB + B + BC)(A\bar{C} + B\bar{C} + 0)$$

$$f = (A)(B)(A\bar{C} + B\bar{C})$$

$$f = ABC\bar{C} + AB\bar{C}$$

$$f = ABC\bar{C}$$

5. Let $f = (X + Y)(X + \bar{Y}) + \overline{(\bar{X}\bar{Y})} + \bar{X}$

$$f = (X + Y)(X + \bar{Y}) + \bar{X}\bar{Y} \cdot \bar{X}$$

$$f = (X + Y)(X + \bar{Y}) + (X + Y)X$$

$$f = (X + Y)(X + \bar{Y}) + X + XY$$

$$f = X + XY + X\bar{Y} + Y\bar{Y} + X + XY$$

$$f = X[1 + Y + \bar{Y} + 1 + Y]$$

$$f = X$$

6. $f = X + \bar{X}Y$

$$f = (X + \bar{X})(X + Y)$$

$$f = X + Y$$

7. $f = (A + B)(A + C)$

$$f = A + AB + AC + BC$$

$$f = A + BC$$

8. $f = (1 + \bar{A})(B + AC)$

$$f = 1 \cdot (AC + B)$$

$$f = AC + B$$

9. $f = (A + \bar{A}) + (BC + AC)(A + D)$

$$f = 1 + (BC + AC)(A + D)$$

$$f = 1$$

10. $f = (A + B)(A + B + C)$

$$f = A + AB + AB + B + AC + BC$$

$$f = A + B$$



For more questions, kindly visit the library section: Link for app: <https://physicswallah.live/tabs/tabs/library-tab>

For more questions, kindly visit the library section: Link for web: <https://links.physicswallah.live/vyJw>

Any issue with DPP, please report by clicking here- <https://forms.gle/t2SzQVvQcs638c4r5>



PW Mobile APP: <https://physicswala.page.link/?type=contact-us&data=open>

For PW Website: <https://www.physicswallah.live/contact-us>