Interface truncation and verified design gradients in a nonlinear motor model

October 2026

Abstract

A motor optimization target can change with the numerical interface even when average torque agrees closely. We reconstruct a published nonlinear permanent-magnet motor with piecewise-linear finite elements and compare conforming and harmonic rotor–stator coupling on identical meshes. The conforming model reproduces loaded mean torque within 0.16%, but its torque standard deviation is 9.9–11.3% above the saved reference. Transmitting the reference's eight harmonic orders reduces that ripple discrepancy to 1.3–1.7% and the largest full-current waveform gap from 0.0272 to 0.0034 N m. Cogging amplitude remains 12.9% high, with reference and geometry errors still unbounded. We then differentiate the converged nonlinear model through mesh motion, excitation and torque evaluation. Across 800 loaded finite-difference comparisons, 782 agree within 2.8×10^{-7} relatively; the largest error is 1.1×10^{-5} on a small gradient component. The excitation rule can reverse the sign of a design sensitivity. Recorded gradient evaluations cost 1.13–1.20 forward evaluations, compared with 7.2–9.5 for warm-started central differences, under uncontrolled host load. These results establish an objective-sensitive model comparison and discrete derivative verification; optimization time to a common validated target remains to be measured.

1 Introduction

A small error in mean torque can conceal a large change in the quantity being optimized. Reconstructing the initial motor of Wiesheu et al. (2024), we find mean torque within 0.16% of its saved output while torque ripple differs by about 10–11% under load. Changing only the rotor–stator coupling to the published harmonic truncation removes most of that gap. Thus a numerical modeling choice changes the objective at a scale relevant to a torque-ripple study.

The same distinction applies to derivatives. An adjoint can produce many design sensitivities without a field solve per parameter (Scotzniovsky et al., 2025), but it differentiates the chosen discrete model and excitation policy. It does not establish that the objective is resolved, or that following its gradients beats a cheaper design model. These questions require separate checks of the field model, derivatives and optimization outcome.

We report a four-mesh comparison of conforming and truncated harmonic coupling, including two torque estimators and a harmonic-order ladder. We also verify derivatives of mean torque and ripple with respect to 12 design parameters at initial and perturbed designs, and expose the effect of holding current rather than current density fixed. The contribution is a reproducible account of model and derivative errors in this published benchmark. The numerical methods are established; the results supply the evidence needed before comparing optimization costs.

2 Related work

Wiesheu et al. (2024) combine spline-based rotor and stator shape optimization with engineering parameters for a nonlinear permanent-magnet synchronous motor. Their public implementation and saved outputs provide the reproduction target here. Their related study compares parameter and shape optimization with isogeometric analysis (Wiesheu et al., 2025). We inherit the initial geometry, material table and excitation conventions; we replace the field discretization and compare two rotor–stator couplings. The resulting comparison is between numerical models, rather than a comparison with a measured physical motor.

Differentiable motor design is established prior work. Scotzniovsky et al. (2025) combine geometric deformation, mesh motion and electromagnetic analysis with adjoint-based derivatives. The existence of a differentiable implementation is therefore insufficient as a novelty claim. A useful comparison must establish what designs can be reached, how accurately they are evaluated and how much computation is required.

Harmonic rotor–stator coupling is also established. Bontinck et al. (2018) use separate isogeometric subdomains and harmonic interface constraints; their exact circular geometry avoids polygonal air-gap error. Egger et al. (2022) derive torque from the energy of a harmonic mortar formulation and examine its numerical accuracy for ripple evaluation. We compare that coupling torque with the gap-averaged stress expression of Arkkio (1987). These works motivate checking interface order, field resolution and torque evaluation together, rather than treating small mean-torque error as sufficient validation. Mesh selection for torque computation is itself an established concern (Arkkio and Hannukainen, 2012).

Ion et al. (2018) compare deterministic gradient-based optimization with stochastic search for electric devices, including a permanent-magnet motor, using geometry parametrizations that avoid remeshing. Therefore, a gradient-versus-stochastic comparison or a differentiable motor solver alone would not establish a new optimization result. Our eventual cost comparison must also include competitive inexpensive models and evaluate all candidates against a common refined target.

Inexpensive alternatives also need substantive treatment. Kemmetmüller et al. (2015) use nonlinear magnetic equivalent circuits for torque control, including saturation and nonsinusoidal behavior. Their control problem differs from shape optimization, but it demonstrates why saturation alone does not establish the need for a full-field model. Farshbaf Roomi et al. (2022) develop a waveform-targeting surrogate for electrical machine design, while Wen and Zahr (2023) adapt reduced models along a shape-optimization trajectory in fluid examples. These approaches motivate waveform-aware and adaptive baselines. Their published performance is not transferred to the motor studied here.

3 Motor model and reconstruction

3.1 Geometry and operating states

The full machine has six poles and 36 stator slots. We model a 60° sector, occupying $60° \leq \theta \leq 120°$ at zero rotation, with antiperiodic conditions on the radial boundaries. The rotor inner and outer radii are 16 and 44 mm; the stator inner and outer radii are 45 and 67.5 mm. Axial length is $L = 0.1\,\mathrm{m}$. The 1 mm air gap is split at the coupling radius $r_c = 44.5\,\mathrm{mm}$. Figure 1 shows the material-tagged reconstruction.

The reconstruction uses the initial NURBS exports in the public snapshot. Their control points are stored with weights already multiplied in, and patch orientation must be accounted for when integrating areas. Two thin rotor patches described as air slits in source comments receive iron under the reference's material assignment; we follow that assignment. The mesh generator preserves




Figure 1: Initial-design geometry rendered directly from the committed coarsest mesh. The dashed line is the rotor–stator coupling circle. The right panel enlarges the gap and slot openings. Material boundaries are shown without the element edges; the geometry is not an optimized result.

the winding groups separately, since their two characteristic areas are approximately 36.29 and $31.22\,\mathrm{mm}^2$.

At mechanical angle β, phase currents are

$$I_q(\beta) = aI_* \sin(\phi_0 + 3\beta + \delta_q), \qquad (\delta_U, \delta_V, \delta_W) = (0, -2\pi/3, 2\pi/3), \tag{1}$$

where $a \in \{0, 0.5, 1\}$, $I_* = 9.677657374\,\mathrm{A}$, and the electrical phase offset $\phi_0 = 0$ for the initial design. Angles in Eq. (1) are in radians. Each winding group carries current density $J_g = 12 s_g I_q / |\Omega_g|$, with its own area and prescribed sign $s_g \in \{-1, 1\}$. Using a common area would change the current density between groups by about 16%. We compare 20 distinct mechanical angles, $0°, 1°, \ldots, 19°$, excluding the duplicated endpoint in the source CSV. The reference's optimization grid contains the ten even angles; both grids are retained in the artifacts.

3.2 Nonlinear field equation

The two-dimensional magnetic vector potential $A = A_z$ determines the flux density $\mathbf{B} = (\partial_y A, -\partial_x A)$. Iron is described by an isotropic reluctivity $\nu(|\mathbf{B}|^2)$, where reluctivity is the inverse of permeability. For a test function v that satisfies the homogeneous constraints, the weak equation is

$$\int_\Omega \nu(|\nabla A|^2) \nabla A \cdot \nabla v \, \mathrm{d}\Omega = \int_\Omega J_z v \, \mathrm{d}\Omega + \int_{\Omega_m} \mathbf{M} \cdot (\partial_y v, -\partial_x v) \, \mathrm{d}\Omega. \tag{2}$$

Here $\mathbf{M}$ denotes the permanent-magnet source in $\mathbf{H} = \nu\mathbf{B} - \mathbf{M}$. In the magnet, $\mu_r = 1.05$ and $B_r = 1.4\,\mathrm{T}$, so its source magnitude is $H_c = B_r/(\mu_0 \mu_r)$, not B_r/μ_0. Its direction is $\pi/2$ in the rotor frame and rotates with the rotor. Air and windings have $\mu_r = 1$. The inner and outer circular boundaries have $A = 0$.

We use continuous piecewise-linear triangles. With nodal vector u, element gradients $g_i = \nabla\varphi_i$, $G = \nabla A$ and $s = G \cdot G$, the residual derivative on one element is

$$K^e_{ij} = |\Omega_e| \left[\nu(s) g_i \cdot g_j + 2\nu'(s)(g_i \cdot G)(g_j \cdot G)\right]. \tag{3}$$

The second term is required when the material changes with field strength. Newton steps use this consistent tangent, with damping and a stopping reference independent of the initial guess. Constant potential offsets, where allowed by the boundary conditions, do not change that reference. The solver reports whether it stopped at the requested tolerance or an estimated floating-point floor. All 500 baseline and sensitivity solves, and all 1,140 additional harmonic-coupling solves, stopped at the requested tolerance.

The iron law uses 47 tabulated M27 B–H points from 0 to 2.30 T. Monotonicity is imposed on $H(B)$, not on $\nu(B^2) = H(B)/B$. The tabulated H/B is non-monotone up to about 0.75 T. The two material tangent eigenvalues must satisfy

$$\nu > 0, \qquad \nu + 2s\nu' = \frac{\mathrm{d}H}{\mathrm{d}B} > 0. \tag{4}$$

The GEODE and reference interpolants agree to round-off between 0.05 and 2.25 T. GEODE uses an odd cubic near zero and a continuous slope into the vacuum-slope tail above 2.30 T. The reference uses a low-field clamp and a different last-knot slope. The maximum relative difference in reluctivity near zero is 6.66%; the last segment differs in H by at most 2.17×10^{-4} relatively. We test the torque effect of the low-field difference in Section 5.3.

3.3 Rotation and torque

At the modeled angles, the two circular traces have matching nodes after rotation. The sliding interface identifies their potentials, including the antiperiodic sign on sector wrap-around. Writing the full nodal vector as $u = P\hat{u} + u_D$, the reduced residual and tangent are $\hat{R} = P^T R(P\hat{u} + u_D)$ and $\hat{K} = P^T K P$. The rotor geometry and magnet source rotate together; currents use the same mechanical angle in Eq. (1).

We average Maxwell stress over the air gap using the Arkkio expression (Arkkio, 1987)

$$T(\beta) = \frac{L}{\mu_0(r_2 - r_1)} \int_{\Omega_{\mathrm{gap}}} r B_r B_\theta \,\mathrm{d}\Omega, \qquad (r_1, r_2) = (44, 45)\ \mathrm{mm}. \tag{5}$$

Positive torque acts counter-clockwise on the rotor. All torques in this paper include axial length and refer to the modeled sector. We apply no factor of six when comparing with the saved reference arrays, despite a per-length label appearing in the reference evaluation plots.

The alternative harmonic model imposes

$$\int_{\Gamma_c} (A_s - A_r) e_n \,\mathrm{d}\Gamma = 0, \qquad e_n \in \{\sin(n\theta), \cos(n\theta)\}, \quad n = 3, 9, \ldots, 45. \tag{6}$$

The 16 constraints match the reference's eight orders. Rotor and stator retain distinct trace unknowns. With constraint matrix C, Lagrange multipliers η and reduced potential $\hat{u}$, Newton's method uses the saddle tangent

$$\begin{bmatrix} K & C \\ C^T & 0 \end{bmatrix}. \tag{7}$$

The trace moments use the exact Fourier integrals of the piecewise-linear hats. Rotation enters their centers; the constrained energy derivative gives

$$T_c = -L\eta^T \frac{\partial(C^T\hat{u})}{\partial\beta}, \tag{8}$$

with the state held fixed in the partial derivative, consistent with Egger et al. (2022). Forward comparisons use Arkkio for both GEODE couplings to isolate the interface change; coupling torque is a separate check. The derivative study uses coupling torque for the harmonic model and Arkkio for the conforming model. The two objectives and their gradients are consequently comparisons of those specified model–estimator pairs.

The main harmonic runs retain antiperiodic trace-end pairing. An additional set frees those ends, matching the reference's treatment. Increasing the transmitted orders to every mode below the trace Nyquist limit reproduces the conforming Arkkio torques within $4.1 \times 10^{-9}\,\mathrm{N\,m}$ on L0 and $1.3 \times 10^{-9}\,\mathrm{N\,m}$ on L1. This checks the interface implementation without fitting any parameter to the saved torque.

4 Verification and experiment design

The implementation is checked before the motor comparison. With constant material laws it agrees with the linear assembly to approximately 2×10^{-14} in potential. Central differences of the nonlinear residual agree with the tangent action to below 10^{-9} at favorable step sizes on the synthetic material tests. A manufactured solution gives fitted spatial rates 1.002 in the H^1 seminorm and 2.007 in L^2. For a saturated iron annulus carrying enclosed current I, the independent radial field relation is $H(r) = I/(2\pi r)$, followed by inversion of the material law. The M27 test reaches a mid-annulus relative field error of 3.76×10^{-4} on its finest mesh. These are verification results for the forward model; they do not verify motor shape derivatives.

Sector tests compare the constrained solution with a full-machine solve, check the reduced tangent by finite differences, and exercise positive, negative and wrapped rotation steps. Clockwise and counter-clockwise triangle orderings give equivalent magnet sources and fields. The motor regression also detects changes in magnet strength, magnet direction, phase ordering and rotation direction. Detailed logs accompany the code.

The motor study uses four meshes, L0–L3, with 3,153, 9,937, 36,083 and 139,268 nodes. The 60° coupling arc has $120\,2^\ell$ segments at level ℓ, so integer-degree rotation is represented at every level. Each level contains 60 baseline solves: three current levels and 20 angles. A solution at one angle initializes the next angle at the same current. We report the mean and population standard deviation,

$$\bar{T} = \frac{1}{N}\sum_{k=1}^{N} T_k, \qquad \sigma_T = \left[\frac{1}{N}\sum_{k=1}^{N}(T_k - \bar{T})^2\right]^{1/2}, \quad N = 20. \tag{9}$$

The standard deviation is the ripple metric used for the comparison. At zero current it measures cogging, the torque variation caused by the permanent magnets and slots without applied phase current.

For a scalar statistic q, the estimated L3 refinement interval is

$$q_3 \;\pm\; e_q, \qquad e_q = \max\{|q_2 - q_1|, |q_3 - q_2|\}. \tag{10}$$

We use the same construction pointwise for waveforms. This interval is a refinement diagnostic, not a proven error bound or a statistical confidence interval. It does not cover reference-model error or angular quadrature error. The loaded means change direction between the last two increments, so a last-increment estimate alone would be particularly weak.

5 Forward reproduction results

5.1 Coupling changes the ripple objective

Table 1 compares the same geometry, material and excitation with two interface models. The conforming L3 means are 0.15% and 0.16% low at half and full current. Harmonic coupling reduces the mean deviations to −0.002% and +0.051%, with both reference means inside the estimated refinement intervals. The loaded ripple deviations fall from +9.9% and +11.3% to +1.7% and +1.3%.

Table 1: L3 population standard deviation and mean torque, in N m per sector, on the 20-angle grid. The last column gives ripple deviation from the saved reference. Relative zero-current mean error is not used.

Current fraction	Model	Mean	Std	Std deviation
0	Reference	0.00010	0.01071	n/a
0	Conforming	0.00001	0.00760	-29.1%
0	Harmonic	-0.00000	0.01209	+12.9%
0.5	Reference	0.66208	0.03895	n/a
0.5	Conforming	0.66106	0.04279	+9.9%
0.5	Harmonic	0.66206	0.03961	+1.7%
1	Reference	1.44248	0.07935	n/a
1	Conforming	1.44023	0.08829	+11.3%
1	Harmonic	1.44322	0.08036	+1.3%

Figure 2 shows the improvement angle by angle. The largest full-current difference falls from 0.0272 to 0.0034 N m. The harmonic full-current ripple interval contains the saved reference; the half-current value lies approximately 5×10^{-5} N m below its interval. Mean agreement is therefore insufficient to characterize waveform accuracy.

The zero-current result is less resolved. Harmonic coupling changes the cogging standard deviation from 29.1% below to 12.9% above the reference. Its waveform is close to a 1.13-fold scaling of the saved waveform, but the reference lies outside the estimated ripple interval. We retain this amplitude mismatch rather than interpreting improved waveform shape as a complete reproduction.

5.2 Spatial resolution and transmitted order

Spatial refinement at fixed order and order refinement on a fixed mesh answer different questions (Fig. 3). At L3, order 45 and the conforming model differ in ripple by about 59% at zero current and 7–9% under load, relative to the conforming values. At L1 and L2, order 189 approaches the conforming torque to within 1.1×10^{-4} N m. A spatially refined order-45 solution thus remains a solution of a truncated interface model. Matching that truncation improves reproduction of the published calculation; it does not establish which model better represents the physical motor.

Two additional controls narrow the explanation. At L3, coupling torque and the inner- and outer-half Arkkio estimates are each within 9×10^{-5} N m of full-band Arkkio in the order-45 solution. Freeing the coupling-arc ends changes torque by less than 5.4×10^{-5} N m. These effects are too small to explain the remaining cogging gap at the tested resolution.

5.3 Sensitivity and unresolved causes

The controlled changes in Table 2 are too small to explain the observed waveform gap at the tested settings. The near-zero material difference has particularly little effect on torque despite its 6.66% local reluctivity difference. This is a measured sensitivity of the initial design and does not establish insensitivity after optimization.




Figure 2: Top: L3 torque for conforming and order-45 harmonic coupling, compared with the saved reference. Bottom: each GEODE waveform minus the reference; shading is the harmonic model's pointwise estimated refinement interval from Eq. (10). Residual panels have independent scales. All GEODE curves use Arkkio torque, so the paired difference changes the coupling while holding the estimator fixed.

Table 2: Maximum absolute torque change relative to the baseline at the same mesh level. Entries summarize the recorded angle/current subsets.

Change	Levels	Max. $\lvert\Delta T\rvert$ (N m)
Reference low-field interpolation and clamp	L2, L3	2.1×10^{-6}
Relative Newton tolerance 10^{-12} vs 10^{-8}	L2; L3 full current	7.3×10^{-8}
Exact winding areas vs mesh areas	L2	3.9×10^{-4}
Inner or outer half of the Arkkio band	L3	7.3×10^{-5}




Figure 3: Left: ripple deviation from the reference under spatial refinement, with solid lines for harmonic order 45 and dashed lines for conforming coupling; L3 bars use Eq. (10). Right: order refinement on L1, normalized by the conforming ripple at that same level. The reference uses order 45. Colors identify current, not coupling.

Single-circle Maxwell-stress estimates are more sensitive to the piecewise-constant field than the gap average. The paired coupling-torque and half-band checks above provide stronger support for the estimator than selecting a favorable integration radius.

Filtering a solved conforming field is not equivalent to imposing a truncated interface during the field solve. For completeness, the earlier order-45 post-processing diagnostic changed the cogging standard deviation from about 0.0075 to 0.0184 N m, the half-current value from 0.04280 to 0.04460, and the full-current value from 0.08832 to 0.08775. The zero-current values at cuts 9, 21, 45, 93 and 189 were 0.0077, 0.0300, 0.0184, 0.0077 and 0.0075. That non-monotone diagnostic neither supports nor excludes the coupling explanation. The paired field solves, which reduce both loaded discrepancies, supply the evidence for it.

The remaining cogging difference has unbounded contributions from the reference's degree-two isogeometric discretization with 3×3 subdivisions per patch and from GEODE's straight-sided approximation of curved material boundaries. The reference has not been rerun at finer resolution. Torque-method differences have been measured within GEODE, but a cross-code comparison on the same converged fields is unavailable. The iron-law check covers the low-field difference only: the final tabular segment and the extrapolated high-field regime have not been varied in a paired torque experiment, although local bridge fields exceed the table. These limitations preclude assigning the residual cogging error to a single cause.

6 Design-gradient verification

6.1 Differentiated model and excitation policy

For a design vector p, the converged state z contains the reduced potential and, for harmonic coupling, its multipliers. Writing the full constrained residual as $R(z, p) = 0$, the discrete adjoint is

$$R_z^T \psi = F_z^T, \qquad \frac{\mathrm{d}F}{\mathrm{d}p} = F_p - \psi^T R_p. \tag{11}$$

We differentiate mesh coordinates, element terms, magnet sources, current loads, harmonic constraints and the torque functional. The explicit coordinate derivative of Arkkio is included for conforming coupling. Fixed-topology mesh motion $X(p)$ supplies the chain rule $\mathrm{d}F/\,\mathrm{d}p_k = \langle \mathrm{d}F/\,\mathrm{d}X, \partial X/\partial p_k \rangle$ for geometric parameters, with direct terms added where needed.

The 12 parameters comprise nine geometric lengths (MAG, MH, MW, SW1–SW4, SD1 and Sr1), axial length, operating angle and radial scale. The two designs are the initial parameters and an interior point halfway toward the saved optimized scalar parameters (Appendix B). This verifies a local scalar parametrization. The reference's optimized geometry also uses grouped surface-control displacements; reproducing its 12 scalar values alone does not reproduce that geometry. The present gradient comparison does not include derivatives of those additional groups or a new optimized motor.

The primary current rule fixes peak current, so $J_g = 12 s_g I_q / |\Omega_g(X)|$ changes when a slot changes area. For comparison we implement the reference optimizer's rule, denoted *fixed group-1 density*: $I_* \propto |\Omega_1(X)| s$, where s is radial scale, with the proportionality constant fixed at the initial design. The unscaled geometry is evaluated and torque is multiplied by s^2, following the reference. Both rules agree at the initial geometry but have different derivatives. At L1 with harmonic coupling and full current, the mean-torque derivative with respect to SW1 is $+1.68\,\mathrm{N\,m/m}$ under fixed current and $-220.85\,\mathrm{N\,m/m}$ under fixed group-1 density (Fig. 4). SW1 is the stator-tooth-width parameter. The sign change comes from the additional winding-area/current term, not an adjoint discrepancy. A future optimization comparison must hold this policy fixed across methods.

6.2 Finite differences and Taylor remainders

The derivative objectives are mean torque and population standard deviation on the ten even mechanical angles, matching the reference's optimization grid. Central differences move the same mesh at $p \pm h e_k$; step sweeps separate truncation from floating-point and nonlinear-solve error. We also check the first-order remainder $|F(p + h e_k) - F(p) - h\ \mathrm{d}F/\,\mathrm{d}p_k|$ for quadratic decay.

Across initial and perturbed designs, both couplings, L0–L2 and the recorded loaded current/rule subsets, there are 800 objective–parameter comparisons. Of these, 782 have a best-step relative error at most 2.8×10^{-7}; the maximum is 1.07×10^{-5} for a small Sr1 ripple derivative. This is a best-step verification statistic, not the accuracy of a single finite-difference step chosen in advance. Figure 4 includes all 800 cases as well as one explicit Taylor sweep. The artifact retains each step, rejected displacement and relative error. Not every combination is run on every mesh; the count refers to the recorded cases, not a full factorial study.

Taylor sweeps show quadratic regions, with smaller gradients reaching round-off sooner. An anchored-window diagnostic fails for two loaded SW1 ripple cases because the remainder changes sign near the anchor; their widest quadratic windows span two decades. The nearly cancelling zero-current mean is a weaker check: its best relative errors reach 7.0×10^{-4}. Cogging standard-deviation errors are at most 8.9×10^{-7}. Thus the loaded agreement does not describe every zero-current derivative.

Discrete derivative accuracy also does not imply mesh convergence. In the harmonic model, SW3 mean-torque sensitivities change sign between coarse levels and converge approximately linearly; ripple gradients converge more slowly than most mean gradients. Fresh-remesh finite differences for MW, SW1 and SW2 show decreasing discrepancies from moved-mesh derivatives, but small remeshing steps are dominated by changes in connectivity. For example, the fitted full-current MW mean derivative gap falls from about 5.4×10^{-3} relatively at L0 to below the remesh-scatter resolution at L2; the fitted 2.6×10^{-6} value is not a resolved accuracy bound. These checks support the discrete chain rule while leaving refinement of candidate designs necessary.




Figure 4: Discrete gradient evidence. (a) All 800 loaded best-step finite-difference errors, sorted; each point is one recorded objective–parameter case. (b) SW1 Taylor remainders at L1, initial design, full current, harmonic coupling, fixed current; the guide is anchored at $h = 10^{-5}$ m. (c) Mean-torque sensitivities for the nine geometric parameters under two current rules at that same state. (d) Recorded cost ratios for harmonic coupling at tolerance 10^{-14}; gradients include the forward evaluation. L0/L1 are medians of three runs, L2 a single run. These timing data were collected under uncontrolled host load.

6.3 Recorded derivative cost

The recorded timings use an Apple M3 Ultra with 28 cores, default solver threading, and concurrent host load averaging 14–24. The effective thread count was not pinned. A forward evaluation covers ten angles, starts from zero, and warm-starts successive angles. The full gradient includes that forward, ten torque adjoints, mesh derivatives and contractions for all 12 parameters and both aggregate objectives. Both aggregates reuse the per-angle torque derivatives. Central differences use 24 forward sweeps, each warm-started from the base states.

Across L0–L2, both couplings and tolerances 10^{-8} and 10^{-14}, the full gradient costs 1.13–1.20 forwards, whereas central differences cost 7.2–9.5. Table 3 gives the harmonic tight-tolerance subset. Shape-map setup is recorded separately and must be included in a complete optimization budget. The timing advantage concerns derivative evaluation on one loaded host. It provides no measurement of optimizer iterations, surrogate calibration cost or time to a validated target.

Table 3: Recorded harmonic-model cost at relative tolerance 10^{-14}, initial design and full current. Times are seconds for ten-angle sweeps; setup is a one-time shape-map cost.

Mesh	Forward	Forward + gradient	Central FD	Setup
L0	0.664	0.748	6.333	0.011
L1	3.174	3.658	29.637	0.041
L2	12.702	14.644	116.687	0.222

7 Discussion and limitations

The controlled interface change explains most of the loaded ripple gap while preserving mean-torque agreement. The order ladder shows why this matters for optimization: interface truncation changes the objective even as spatial error decreases. A gradient of that objective can be numerically correct and inexpensive while pointing toward a design whose improvement does not survive a change in the model.

The model is two-dimensional and magnetostatic. It does not evaluate thermal behavior, demagnetization, fatigue, end effects, losses or a complete efficiency map. The comparison uses published computational artifacts, with no new measurements on a physical motor. The strongest forward comparison concerns the initial design; local derivative tests at a second design do not validate an optimization trajectory. Denser and shifted angular grids, tighter spatial resolution and additional current levels remain necessary for candidate validation.

A useful next comparison fixes the outer envelope, axial length, excitation policy and geometric constraints, then measures time to the same refined ripple target. It should separately compare optimization methods in a common space and additional shape freedom under common constraints. The reference already combines scalar and surface controls, so their combination alone is not a new contribution. Costs must include mesh updates, solves, gradients, line searches and calibration, with equivalent reuse allowed to each method and failed targets reported explicitly.

A cheap waveform or reduced physical model is an essential baseline. The linear slotless screening control in Appendix A admits a three-coefficient angular fit at one geometry. That does not establish generalization across shapes, but it cautions against inferring an optimization advantage from parameter count or adjoint cost alone.

8 Conclusion

On identical meshes of a published nonlinear motor, matching the reference's harmonic interface reduces the loaded ripple discrepancy from 9.9–11.3% to 1.3–1.7%. The remaining 12.9% cogging-amplitude difference is unresolved. Design gradients pass finite-difference and Taylor checks at two parameter points, while a change in excitation policy can reverse a sensitivity. The results establish model-specific ripple and derivative evidence. Demonstrating a practical speedup requires the next experiment: optimization against strong inexpensive baselines at a common independently refined target.

Code and data availability

The evidence used here is fixed at GEODE commit `910593ba`. The repository contains the raw motor runs and analysis, geometry and mesh-generation scripts, design-gradient sweeps and timing records, and solver verification logs. Reference data are extracted from the authors' ICEM snapshot at `b145aaf4`, a later repository revision rather than a claim to the original conference release. Source hashes, extraction checks and the upstream GPL-3.0-or-later license are retained. The paper package includes a manifest, copied figure inputs and a regeneration script; it does not require rerunning FEM to rebuild the figures. Recomputing the physical study requires the separately documented mesh and solver commands.

A Linear slotless screening control

The stored slotless model has 24 distinct angles. Fitting $T(\phi) = c_0 + c_1 \cos\phi + c_2 \sin\phi$, with electrical angle $\phi = p\theta_r$, mechanical rotor angle θ_r and pole-pair count p, on alternate angles and evaluating on the other twelve gives normalized held-out RMSE 3.08×10^{-10} and maximum error 6.83×10^{-10}, using the recorded analytic-amplitude normalization. This is a locked-rotor angle sweep, not synchronous operating ripple. For a fixed linear field operator and sinusoidal sources, the field lies in a small basis of source responses; a quadratic torque functional can contain only the corresponding finite set of harmonics. The particular model needs just the three fitted coefficients. This is an angular interpolation test at one geometry, not a shape-gradient test or evidence of generalization across designs.

B Design points for derivative checks

Table 4 identifies the coordinates used in the scalar derivative study. Values are rounded for display; the accompanying records retain full precision. The operating angle is stored in degrees and converted to radians in the current equation. These coordinates describe the scalar design space; the saved reference optimum additionally contains surface-control offsets.

Table 4: Initial and interior perturbed design points for the derivative checks. Lengths refer to the unscaled geometry.

Parameter	Meaning	Unit	Initial	Perturbed
MAG	Pole-axis iron depth above magnet	mm	7.0000	6.5506
MH	Radial magnet height	mm	7.0000	4.8722
MW	Magnet width	mm	19.0000	19.8670
SW1	Stator tooth width	mm	4.0000	4.0309
SW2	Slot-opening width	mm	2.3000	1.6500
SW3	Slot-opening depth	mm	1.0000	0.7502
SW4	Back-iron depth on slot axis	mm	8.2500	6.8418
SD1	Stator outer diameter	mm	135.0000	132.6466
Sr1	Slot-bottom fillet radius	mm	1.0000	1.4999
LENGTH	Axial length	mm	100.0000	90.0003
ϕ_0	Electrical current offset	°	0.0000	-5.8231
ScaleR	Radial similarity scale	1	1.0000	1.0239

References

Antero Arkkio. *Analysis of Induction Motors Based on the Numerical Solution of the Magnetic Field and Circuit Equations*. PhD thesis, Helsinki University of Technology, 1987. URL https://aaltodoc.aalto.fi/handle/123456789/2158.

Antero Arkkio and Antti Hannukainen. Proper finite-element discretization for torque computation of cage induction motors. *International Symposium on Power Electronics Power Electronics, Electrical Drives, Automation and Motion*, pages 1456–1461, 2012. doi: 10.1109/speedam.2012.6264430. URL https://doi.org/10.1109/speedam.2012.6264430.

Zeger Bontinck, Jacopo Corno, Sebastian Schöps, and Herbert De Gersem. Isogeometric analysis and harmonic stator–rotor coupling for simulating electric machines. *Computer Methods in Applied Mechanics and Engineering*, 334:40–55, 2018. doi: 10.1016/j.cma.2018.01.047. URL https://doi.org/10.1016/j.cma.2018.01.047.

Herbert Egger, Mané Harutyunyan, Richard Löscher, Melina Merkel, and Sebastian Schöps. On torque computation in electric machine simulation by harmonic mortar methods. *Journal of Mathematics in Industry*, 12(1), 2022. doi: 10.1186/s13362-022-00121-2. URL https://doi.org/10.1186/s13362-022-00121-2.

Farnam Farshbaf Roomi, Abolfazl Vahedi, and Amin Nobahari. Electrical machines surrogate-based design optimization based on novel waveform targeting strategy with improvement of the computational efficiency. *IET Electric Power Applications*, 16(11):1286–1299, 2022. doi: 10.1049/elp2.12226. URL https://doi.org/10.1049/elp2.12226.

Ion Gabriel Ion, Zeger Bontinck, Dimitrios Loukrezis, Ulrich Römer, Oliver Lass, Stefan Ulbrich, Sebastian Schöps, and Herbert De Gersem. Robust shape optimization of electric devices based on deterministic optimization methods and finite-element analysis with affine parametrization and design elements. *Electrical Engineering*, 100(4):2635–2647, 2018. doi: 10.1007/s00202-018-0716-6. URL https://doi.org/10.1007/s00202-018-0716-6.

Wolfgang Kemmetmüller, David Faustner, and Andreas Kugi. Optimal torque control of permanent magnet synchronous machines using magnetic equivalent circuits. *Mechatronics*, 32:22–33, 2015.

doi: 10.1016/j.mechatronics.2015.10.007. URL https://doi.org/10.1016/j.mechatronics.2015.10.007.

Luca Scotzniovsky, Ru Xiang, Zeyu Cheng, Gabriel Rodriguez, David Kamensky, Chris Mi, and John T. Hwang. Geometric design of electric motors using adjoint-based shape optimization. *Optimization and Engineering*, 26(1):121–158, 2025. doi: 10.1007/s11081-024-09892-6. URL https://doi.org/10.1007/s11081-024-09892-6.

Tianshu Wen and Matthew J. Zahr. A globally convergent method to accelerate large-scale optimization using on-the-fly model hyperreduction: Application to shape optimization. *Journal of Computational Physics*, 484:112082, 2023. doi: 10.1016/j.jcp.2023.112082. URL https://doi.org/10.1016/j.jcp.2023.112082.

Michael Wiesheu, Theodor Komann, Melina Merkel, Sebastian Schöps, Stefan Ulbrich, and Idoia Cortes Garcia. Spline-Based Rotor and Stator Optimization of a Permanent Magnet Synchronous Motor. In *2024 International Conference on Electrical Machines (ICEM)*, pages 1–6, 2024. doi: 10.1109/icem60801.2024.10700065. URL https://doi.org/10.1109/icem60801.2024.10700065.

Michael Wiesheu, Theodor Komann, Melina Merkel, Sebastian Schöps, Stefan Ulbrich, and Idoia Cortes Garcia. Combined parameter and shape optimization of electric machines with isogeometric analysis, 2025. URL https://arxiv.org/abs/2311.06046v2. Version 2, revised 17 March 2025; originally submitted in 2023.