

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Scaler
Manufacturer: Extron
Firmware Version: 1.00
Model(s): DSC 12G-HD A

Tested on the Following Software and Firmware Versions

ControlScript Deployment Utility	1.14.0-b.36
IP Link Pro Control Processor Firmware	3.18.0001-b002
IP Link Pro Control Processor xi Firmware	1.13.0001-b001
IP Link Pro Control Processor Q xi Firmware	1.13.0001-b001

Version History

Module Version	Date	Notes
1_0_0_0	8/19/2026	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- If login credentials are required, devicePassword and deviceUsername must be set accordingly.
deviceUsername default value is admin respectively.
Example: `InterfaceName.deviceUsername = 'extron'`

Supported Class and Example

SSHClass

#Password Required

```
InterfaceName = ModuleName.SSHClass('192.168.254.254', 22023, Credentials=('admin', 'extron'),  
Model='DSC 12G-HD A')
```

#No Password Required

```
InterfaceName = ModuleName.SSHClass('192.168.254.254', 22023, Credentials=('admin', ''),  
Model='DSC 12G-HD A')
```

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	Value
AspectRatio	'Fill'	'Follow'	
# AspectRatio example InterfaceName.Set('AspectRatio', 'Fill')			
Command	Value	Value	Value
AudioFormat	None 'Multi-Ch'	'Analog'	'LPCM-2Ch'
# AudioFormat example InterfaceName.Set('AudioFormat', None)			
Command	Value	Value	
AudioMute	'On'	'Off'	
Qualifier Key	Qualifier Value	Qualifier Value	
'Output'	'Analog'	'Digital'	
# AudioMute example InterfaceName.Set('AudioMute', 'On', {'Output': 'Analog'})			
Command	Value	Value	Value
AutoImage	'Execute'	'Execute and Fill'	'Execute and Follow'
# AutoImage example InterfaceName.Set('AutoImage', 'Execute')			
Command	Value	Value	
ExecutiveMode	'On'	'Off'	
# ExecutiveMode example InterfaceName.Set('ExecutiveMode', 'On')			
Command	Value	Value	
FilmModeDetection	'On'	'Off'	
# FilmModeDetection example InterfaceName.Set('FilmModeDetection', 'On')			
Command	Value	Value	
Freeze	'On'	'Off'	
# Freeze example InterfaceName.Set('Freeze', 'On')			
Command	Value	Value	
GlobalAudioMute	'On'	'Off'	
# GlobalAudioMute example InterfaceName.Set('GlobalAudioMute', 'On')			
Command	Value		
InputGain	-18 to 24 in steps of 1		
# InputGain example InterfaceName.Set('InputGain', 24)			
Command	Value		
InputPresetRecall	'1' – '128'		
# InputPresetRecall example InterfaceName.Set('InputPresetRecall', '1')			

Command	Value		
InputPresetSave	'1' – '128'		
# InputPresetSave example InterfaceName.Set('InputPresetSave', '1')			
Command	Value	Value	Value
Logo	'1' – '16' 'Off'	'Screen Saver'	'HDCP'
# Logo example InterfaceName.Set('Logo', '1')			
Command	Value		
LogoAssignment	'String'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Logo'	'1' – '16'	'Screen Saver'	'HDCP'
# LogoAssignment example InterfaceName.Set('LogoAssignment', 'String', {'Logo': '1'})			
Command	Value	Value	Value
LogoKeySetting	'Disabled' 'Level Key'	'Transparency' 'Alpha Key'	'RGB Key'
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Logo'	'1' – '16'	'Screen Saver'	'HDCP'
# LogoKeySetting example InterfaceName.Set('LogoKeySetting', 'Disabled', {'Logo': '1'})			
Command	Value	Value	Value
OutputResolution	'720p (25Hz)' '720p (50Hz)' '1080i (50Hz)' '1080p (23.98Hz)' '1080p (29.97Hz)' '1080p (59.94Hz)' '2048x1080 (24Hz)' '2048x1080 (30Hz)' '2048x1080 (60Hz)' '3480x2160 (25Hz)' '3480x2160 (50Hz)' '4096x2160 (23.98Hz)' '4096x2160 (29.97Hz)' '4096x2160 (59.94Hz)' 'Custom Rate 2' '800x600 (60Hz)' '1280x800 (60Hz)' '1366x768 (60Hz)' '1600x900 (60Hz)' '1920x1200 (60Hz)' '576p (50Hz)' '2560x1080 (60Hz)' '3840x2160 (60Hz)'	'720p (29.97Hz)' '720p (59.94Hz)' '1080i (59.94Hz)' '1080p (24Hz)' '1080p (30Hz)' '1080p (60Hz)' '2048x1080 (25Hz)' '2048x1080 (50Hz)' '3480x2160 (23.98Hz)' '3480x2160 (29.97Hz)' '3480x2160 (59.94Hz)' '4096x2160 (24Hz)' '4096x2160 (30Hz)' '4096x2160 (60Hz)' 'Custom Rate 3' '1024x768 (60Hz)' '1280x1024 (60Hz)' '1440x900 (60Hz)' '1680x1050 (60Hz)' '480p (59.94Hz)' '2048x1200 (60Hz)' '2560x1440 (60Hz)' 'Custom Rate 4'	'720p (30Hz)' '720p (60Hz)' '1080i (60Hz)' '1080p (25Hz)' '1080p (50Hz)' '2048x1080 (23.98Hz)' '2048x1080 (29.97Hz)' '2048x1080 (59.94Hz)' '3480x2160 (24Hz)' '3480x2160 (30Hz)' '3480x2160 (60Hz)' '4096x2160 (25Hz)' '4096x2160 (50Hz)' 'Custom Rate 1' '640x480 (60Hz)' '1280x768 (60Hz)' '1360x768 (60Hz)' '1400x1050 (60Hz)' '1600x1200 (60Hz)' '480p (60Hz)' '2048x1536 (60Hz)' '2560x1600 (60Hz)' 'Custom Rate 5'
# OutputResolution example InterfaceName.Set('OutputResolution', '720p (25Hz)')			
Command	Value	Value	
PowerSaveMode	'On'	'Off'	
# PowerSaveMode example InterfaceName.Set('PowerSaveMode', 'On')			

Global Scripter Module Communication Sheet

Command TestPattern	Value 'Off' 'Crosshatch' 'Audio Test'	Value 'Crop' 'Color Bars'	Value 'Alternating Pixels' '32-level split Grayscale'
# TestPattern example InterfaceName.Set('TestPattern', 'Off')			
Command VideoMute	Value 'On'	Value 'On with Sync'	Value 'Off'
# VideoMute example InterfaceName.Set('VideoMute', 'On')			
Command Volume	Value -100 to 0 in steps of 1 dB		
# Volume example InterfaceName.Set('Volume', 0)			

Status Available

For all commands except for InputSignalStatus, LogoAvailability, and Temperature, Update should be called only once since the command's status will be updated automatically as the device's status changes. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})  
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})  
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},  
FeedbackHandler)
```

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)  
Value = InterfaceName.ReadStatus(Command)  
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)  
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AspectRatio	Value 'Fill'	Value 'Follow'
# AspectRatio example InterfaceName.Update('AspectRatio') Value = InterfaceName.ReadStatus('AspectRatio') InterfaceName.SubscribeStatus('AspectRatio', None, FeedbackHandler)		
Command AudioFormat	Value 'None' 'Multi-Ch'	Value 'Analog' Value 'LPCM-2Ch'
# AudioFormat example InterfaceName.Update('AudioFormat') Value = InterfaceName.ReadStatus('AudioFormat') InterfaceName.SubscribeStatus('AudioFormat', None, FeedbackHandler)		
Command AudioMute	Value 'On'	Value 'Off'
Qualifier Key 'Output'	Qualifier Value 'Analog'	Qualifier Value 'Digital'
# AudioMute example InterfaceName.Update('AudioMute', {'Output': 'Analog'}) Value = InterfaceName.ReadStatus('AudioMute', {'Output': 'Analog'}) InterfaceName.SubscribeStatus('AudioMute', None, FeedbackHandler)		
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command ExecutiveMode	Value 'On'	Value 'Off'
# ExecutiveMode example InterfaceName.Update('ExecutiveMode') Value = InterfaceName.ReadStatus('ExecutiveMode') InterfaceName.SubscribeStatus('ExecutiveMode', None, FeedbackHandler)		

Global Scripter Module
Communication Sheet

Command	Value	Value	
FilmModeDetection	'On'	'Off'	
# FilmModeDetection example InterfaceName.Update('FilmModeDetection') Value = InterfaceName.ReadStatus('FilmModeDetection') InterfaceName.SubscribeStatus('FilmModeDetection', None, FeedbackHandler)			
Command	Value		
Firmware	'String'		
# Firmware example InterfaceName.Update('Firmware') Value = InterfaceName.ReadStatus('Firmware') InterfaceName.SubscribeStatus('Firmware', None, FeedbackHandler)			
Command	Value	Value	
Freeze	'On'	'Off'	
# Freeze example InterfaceName.Update('Freeze') Value = InterfaceName.ReadStatus('Freeze') InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)			
Command	Value		
InputGain	-18 to 24 in steps of 1		
# InputGain example InterfaceName.Update('InputGain') Value = InterfaceName.ReadStatus('InputGain') InterfaceName.SubscribeStatus('InputGain', None, FeedbackHandler)			
Command	Value	Value	
InputSignalStatus	'Active'	'Not Active'	
# InputSignalStatus example InterfaceName.Update('InputSignalStatus') Value = InterfaceName.ReadStatus('InputSignalStatus') InterfaceName.SubscribeStatus('InputSignalStatus', None, FeedbackHandler)			
Command	Value	Value	Value
Logo	'1' – '16' 'Off'	'Screen Saver'	'HDCP'
# Logo example InterfaceName.Update('Logo') Value = InterfaceName.ReadStatus('Logo') InterfaceName.SubscribeStatus('Logo', None, FeedbackHandler)			
Command	Value		
LogoAssignment	'String'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Logo'	'1' – '16'	'Screen Saver'	'HDCP'
# LogoAssignment example InterfaceName.Update('LogoAssignment', {'Logo': '1'}) Value = InterfaceName.ReadStatus('LogoAssignment', {'Logo': '1'}) InterfaceName.SubscribeStatus('LogoAssignment', None, FeedbackHandler)			
Command	Value	Value	
LogoAvailability	'Saved'	'Empty'	
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Logo'	'1' – '16'	'Screen Saver'	'HDCP'
# LogoAvailability example InterfaceName.Update('LogoAvailability', {'Logo': '1'}) Value = InterfaceName.ReadStatus('LogoAvailability', {'Logo': '1'}) InterfaceName.SubscribeStatus('LogoAvailability', None, FeedbackHandler)			

Global Scriptor Module
Communication Sheet

Revision: 8/19/2026

Command LogoKeySetting	Value 'Disabled' 'Level Key'	Value 'Transparency' 'Alpha Key'	Value 'RGB Key'
Qualifier Key 'Logo'	Qualifier Value '1' – '16'	Qualifier Value 'Screen Saver'	Qualifier Value 'HDCP'
# LogoKeySetting example InterfaceName.Update('LogoKeySetting', {'Logo': '1'}) Value = InterfaceName.ReadStatus('LogoKeySetting', {'Logo': '1'}) InterfaceName.SubscribeStatus('LogoKeySetting', None, FeedbackHandler)			
Command MACAddress	Value 'String'		
# MACAddress example InterfaceName.Update('MACAddress') Value = InterfaceName.ReadStatus('MACAddress') InterfaceName.SubscribeStatus('MACAddress', None, FeedbackHandler)			
Command ModelName	Value 'String'		
# ModelName example InterfaceName.Update('ModelName') Value = InterfaceName.ReadStatus('ModelName') InterfaceName.SubscribeStatus('ModelName', None, FeedbackHandler)			
Command OutputResolution	Value '720p (25Hz)' '720p (50Hz)' '1080i (50Hz)' '1080p (23.98Hz)' '1080p (29.97Hz)' '1080p (59.94Hz)' '2048x1080 (24Hz)' '2048x1080 (30Hz)' '2048x1080 (60Hz)' '3480x2160 (25Hz)' '3480x2160 (50Hz)' '4096x2160 (23.98Hz)' '4096x2160 (29.97Hz)' '4096x2160 (59.94Hz)' 'Custom Rate 2' '800x600 (60Hz)' '1280x800 (60Hz)' '1366x768 (60Hz)' '1600x900 (60Hz)' '1920x1200 (60Hz)' '576p (50Hz)' '2560x1080 (60Hz)' '3840x2160 (60Hz)'	Value '720p (29.97Hz)' '720p (59.94Hz)' '1080i (59.94Hz)' '1080p (24Hz)' '1080p (30Hz)' '1080p (60Hz)' '2048x1080 (25Hz)' '2048x1080 (50Hz)' '3480x2160 (23.98Hz)' '3480x2160 (29.97Hz)' '3480x2160 (59.94Hz)' '4096x2160 (24Hz)' '4096x2160 (30Hz)' '4096x2160 (60Hz)' 'Custom Rate 3' '1024x768 (60Hz)' '1280x1024 (60Hz)' '1440x900 (60Hz)' '1680x1050 (60Hz)' '480p (59.94Hz)' '2048x1200 (60Hz)' '2560x1440 (60Hz)' 'Custom Rate 4'	Value '720p (30Hz)' '720p (60Hz)' '1080i (60Hz)' '1080p (25Hz)' '1080p (50Hz)' '2048x1080 (23.98Hz)' '2048x1080 (29.97Hz)' '2048x1080 (59.94Hz)' '3480x2160 (24Hz)' '3480x2160 (30Hz)' '3480x2160 (60Hz)' '4096x2160 (25Hz)' '4096x2160 (50Hz)' 'Custom Rate 1' '640x480 (60Hz)' '1280x768 (60Hz)' '1360x768 (60Hz)' '1400x1050 (60Hz)' '1600x1200 (60Hz)' '480p (60Hz)' '2048x1536 (60Hz)' '2560x1600 (60Hz)' 'Custom Rate 5'
# OutputResolution example InterfaceName.Update('OutputResolution') Value = InterfaceName.ReadStatus('OutputResolution') InterfaceName.SubscribeStatus('OutputResolution', None, FeedbackHandler)			

Command	Value		
PartNumber	'String'		
# PartNumber example InterfaceName.Update('PartNumber') Value = InterfaceName.ReadStatus('PartNumber') InterfaceName.SubscribeStatus('PartNumber', None, FeedbackHandler)			
Command	Value	Value	
PowerSaveMode	'On'	'Off'	
# PowerSaveMode example InterfaceName.Update('PowerSaveMode') Value = InterfaceName.ReadStatus('PowerSaveMode') InterfaceName.SubscribeStatus('PowerSaveMode', None, FeedbackHandler)			
Command	Value	Value	Value
ScreenSaverStatus	'Active Input Detected; Timer not running'	'No Active Input; Timer expired; Output sync disabled'	'No Active Input; Timer running; Output sync enabled'
# ScreenSaverStatus example InterfaceName.Update('ScreenSaverStatus') Value = InterfaceName.ReadStatus('ScreenSaverStatus') InterfaceName.SubscribeStatus('ScreenSaverStatus', None, FeedbackHandler)			
Command	Value		
SerialNumber	'String'		
# SerialNumber example InterfaceName.Update('SerialNumber') Value = InterfaceName.ReadStatus('SerialNumber') InterfaceName.SubscribeStatus('SerialNumber', None, FeedbackHandler)			
Command	Value		
Temperature	—		
# Temperature example InterfaceName.Update('Temperature') Value = InterfaceName.ReadStatus('Temperature') InterfaceName.SubscribeStatus('Temperature', None, FeedbackHandler)			
Command	Value	Value	Value
TestPattern	'Off' 'Crosshatch' 'Audio Test'	'Crop' 'Color Bars'	'Alternating Pixels' '32-level split Grayscale'
# TestPattern example InterfaceName.Update('TestPattern') Value = InterfaceName.ReadStatus('TestPattern') InterfaceName.SubscribeStatus('TestPattern', None, FeedbackHandler)			
Command	Value	Value	Value
VideoMute	'On'	'On with Sync'	'Off'
# VideoMute example InterfaceName.Update('VideoMute') Value = InterfaceName.ReadStatus('VideoMute') InterfaceName.SubscribeStatus('VideoMute', None, FeedbackHandler)			
Command	Value		
Volume	-100 to 0 in steps of 1 dB		
# Volume example InterfaceName.Update('Volume') Value = InterfaceName.ReadStatus('Volume') InterfaceName.SubscribeStatus('Volume', None, FeedbackHandler)			

Network Communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (SSH)

Default Port: 22023

Logon Credentials Supported: Yes

Default Username: admin

Default Password:

Multi-Connection Yes

Capabilities:

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Aspect Ratio Fill	w1*1ASPR\x0D
Aspect Ratio Follow	w1*2ASPR\x0D
Audio Format Analog	wI1*1AFMT\x0D
Audio Format LPCM-2Ch	wI1*2AFMT\x0D
Audio Format Multi-Ch	wI1*3AFMT\x0D
Audio Format None	wI1*0AFMT\x0D
Audio Mute Off Output Analog	1*0Z
Audio Mute Off Output Digital	2*0Z
Audio Mute On Output Analog	1*1Z
Audio Mute On Output Digital	2*1Z
Auto Image Execute	1*0A
Auto Image Execute and Fill	1*1A
Auto Image Execute and Follow	1*2A
Executive Mode Off	0X
Executive Mode On	1X
Film Mode Detection Off	w1*0FILM\x0D
Film Mode Detection On	w1*1FILM\x0D
Freeze Off	1*0F
Freeze On	1*1F
Global Audio Mute Off	0Z
Global Audio Mute On	1Z
Input Gain -18	-18G
Input Gain 24	24G
Input Preset Recall 1	2*1.
Input Preset Recall 128	2*128.
Input Preset Save 1	2*1,
Input Preset Save 128	2*128,
Logo 1	wE1*1LOGO\x0D
Logo 16	wE1*16LOGO\x0D
Logo HDCP	wE1*201LOGO\x0D
Logo Key Setting Alpha Key Logo 1	w1*4LKEF\x0D
Logo Key Setting Alpha Key Logo 16	w16*4LKEF\x0D
Logo Key Setting Alpha Key Logo HDCP	w201*4LKEF\x0D
Logo Key Setting Alpha Key Logo Screen Saver	w101*4LKEF\x0D
Logo Key Setting Disabled Logo 1	w1*0LKEF\x0D
Logo Key Setting Disabled Logo 16	w16*0LKEF\x0D
Logo Key Setting Disabled Logo HDCP	w201*0LKEF\x0D
Logo Key Setting Disabled Logo Screen Saver	w101*0LKEF\x0D
Logo Key Setting Level Key Logo 1	w1*3LKEF\x0D
Logo Key Setting Level Key Logo 16	w16*3LKEF\x0D
Logo Key Setting Level Key Logo HDCP	w201*3LKEF\x0D
Logo Key Setting Level Key Logo Screen Saver	w101*3LKEF\x0D

Logo Key Setting RGB Key Logo 1	w1*2LKEF\x0D
Logo Key Setting RGB Key Logo 16	w16*2LKEF\x0D
Logo Key Setting RGB Key Logo HDCP	w201*2LKEF\x0D
Logo Key Setting RGB Key Logo Screen Saver	w101*2LKEF\x0D
Logo Key Setting Transparency Logo 1	w1*1LKEF\x0D
Logo Key Setting Transparency Logo 16	w16*1LKEF\x0D
Logo Key Setting Transparency Logo HDCP	w201*1LKEF\x0D
Logo Key Setting Transparency Logo Screen Saver	w101*1LKEF\x0D
Logo Off	wE1*0LOGO\x0D
Logo Screen Saver	wE1*101LOGO\x0D
Output Resolution 1024x768 (60Hz)	w1*12RATE\x0D
Output Resolution 1080i (50Hz)	w1*35`RATE\x0D
Output Resolution 1080i (59.94Hz)	w1*36RATE\x0D
Output Resolution 1080i (60Hz)	w1*37RATE\x0D
Output Resolution 1080p (23.98Hz)	w1*38RATE\x0D
Output Resolution 1080p (24Hz)	w1*39RATE\x0D
Output Resolution 1080p (25Hz)	w1*40RATE\x0D
Output Resolution 1080p (29.97Hz)	w1*41RATE\x0D
Output Resolution 1080p (30Hz)	w1*42RATE\x0D
Output Resolution 1080p (50Hz)	w1*43RATE\x0D
Output Resolution 1080p (59.94Hz)	w1*44RATE\x0D
Output Resolution 1080p (60Hz)	w1*45RATE\x0D
Output Resolution 1280x1024 (60Hz)	w1*15RATE\x0D
Output Resolution 1280x768 (60Hz)	w1*13RATE\x0D
Output Resolution 1280x800 (60Hz)	w1*14RATE\x0D
Output Resolution 1360x768 (60Hz)	w1*16RATE\x0D
Output Resolution 1366x768 (60Hz)	w1*17RATE\x0D
Output Resolution 1400x1050 (60Hz)	w1*19RATE\x0D
Output Resolution 1440x900 (60Hz)	w1*18RATE\x0D
Output Resolution 1600x1200 (60Hz)	w1*22RATE\x0D
Output Resolution 1600x900 (60Hz)	w1*20RATE\x0D
Output Resolution 1680x1050 (60Hz)	w1*21RATE\x0D
Output Resolution 1920x1200 (60Hz)	w1*23RATE\x0D
Output Resolution 2048x1080 (23.98Hz)	w1*46RATE\x0D
Output Resolution 2048x1080 (24Hz)	w1*47RATE\x0D
Output Resolution 2048x1080 (25Hz)	w1*48RATE\x0D
Output Resolution 2048x1080 (29.97Hz)	w1*49RATE\x0D
Output Resolution 2048x1080 (30Hz)	w1*50RATE\x0D
Output Resolution 2048x1080 (50Hz)	w1*51RATE\x0D
Output Resolution 2048x1080 (59.94Hz)	w1*52RATE\x0D
Output Resolution 2048x1080 (60Hz)	w1*53RATE\x0D
Output Resolution 2048x1200 (60Hz)	w1*54RATE\x0D
Output Resolution 2048x1536 (60Hz)	w1*55RATE\x0D
Output Resolution 2560x1080 (60Hz)	w1*56RATE\x0D

Output Resolution 2560x1440 (60Hz)	w1*57RATE\x0D
Output Resolution 2560x1600 (60Hz)	w1*58RATE\x0D
Output Resolution 3480x2160 (23.98Hz)	w1*59RATE\x0D
Output Resolution 3480x2160 (24Hz)	w1*60RATE\x0D
Output Resolution 3480x2160 (25Hz)	w1*61RATE\x0D
Output Resolution 3480x2160 (29.97Hz)	w1*62RATE\x0D
Output Resolution 3480x2160 (30Hz)	w1*63RATE\x0D
Output Resolution 3480x2160 (50Hz)	w1*64RATE\x0D
Output Resolution 3480x2160 (59.94Hz)	w1*65RATE\x0D
Output Resolution 3480x2160 (60Hz)	w1*66RATE\x0D
Output Resolution 3840x2160 (60Hz)	w1*59RATE\x0D
Output Resolution 4096x2160 (23.98Hz)	w1*69RATE\x0D
Output Resolution 4096x2160 (24Hz)	w1*70RATE\x0D
Output Resolution 4096x2160 (25Hz)	w1*71RATE\x0D
Output Resolution 4096x2160 (29.97Hz)	w1*72RATE\x0D
Output Resolution 4096x2160 (30Hz)	w1*73RATE\x0D
Output Resolution 4096x2160 (50Hz)	w1*74RATE\x0D
Output Resolution 4096x2160 (59.94Hz)	w1*75RATE\x0D
Output Resolution 4096x2160 (60Hz)	w1*76RATE\x0D
Output Resolution 480p (59.94Hz)	w1*24RATE\x0D
Output Resolution 480p (60Hz)	w1*25RATE\x0D
Output Resolution 576p (50Hz)	w1*26RATE\x0D
Output Resolution 640x480 (60Hz)	w1*10RATE\x0D
Output Resolution 720p (25Hz)	w1*29RATE\x0D
Output Resolution 720p (29.97Hz)	w1*30RATE\x0D
Output Resolution 720p (30Hz)	w1*31RATE\x0D
Output Resolution 720p (50Hz)	w1*32RATE\x0D
Output Resolution 720p (59.94Hz)	w1*33RATE\x0D
Output Resolution 720p (60Hz)	w1*34RATE\x0D
Output Resolution 800x600 (60Hz)	w1*11RATE\x0D
Output Resolution Custom Rate 1	w1*201RATE\x0D
Output Resolution Custom Rate 2	w1*202RATE\x0D
Output Resolution Custom Rate 3	w1*203RATE\x0D
Output Resolution Custom Rate 4	w1*204RATE\x0D
Output Resolution Custom Rate 5	w1*205RATE\x0D
Power Save Mode Off	w0PSAV\x0D
Power Save Mode On	w1PSAV\x0D
Test Pattern 32-level split Grayscale	w1*5TEST\x0D
Test Pattern Alternating Pixels	w1*2TEST\x0D
Test Pattern Audio Test	w1*6TEST\x0D
Test Pattern Color Bars	w1*4TEST\x0D
Test Pattern Crop	w1*1TEST\x0D
Test Pattern Crosshatch	w1*3TEST\x0D
Test Pattern Off	w1*0TEST\x0D

Global Scripter Module Communication Sheet

Video Mute Off	0B
Video Mute On	1B
Video Mute On with Sync	2B
Volume 0	0V
Volume -100	-100V

Appendix B. Update Commands

Aspect Ratio	w1ASPR\x0D
Audio Format	wI1AFMT\x0D
Audio Mute Output Analog	Z
Audio Mute Output Digital	Z
Executive Mode	X
Film Mode Detection	w1FILM\x0D
Firmware	*q
Freeze	1F
Input Gain	G
Input Signal Status	w0LS\x0D
Logo	wE1LOGO\x0D
Logo Availability Logo 1	wQLOGO\x0D
Logo Availability Logo 16	wQLOGO\x0D
Logo Availability Logo HDCP	wQLOGO\x0D
Logo Availability Logo Screen Saver	wQLOGO\x0D
Logo Key Setting Logo 1	w1LKEF\x0D
Logo Key Setting Logo 16	w16LKEF\x0D
Logo Key Setting Logo HDCP	w201LKEF\x0D
Logo Key Setting Logo Screen Saver	w101LKEF\x0D
MAC Address	wCH\x0D
Model Name	1i
Output Resolution	w1RATE\x0D
Part Number	n
Power Save Mode	wPSAV\x0D
Screen Saver Status	wS1SSAV\x0D
Serial Number	19i
Temperature	w28STAT\x0D
Test Pattern	w1TEST\x0D
Video Mute	B
Volume	V