

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Matrix Switcher
Manufacturer: Extron
Firmware Version: 1.01.0000-b002
Model(s): DTP3 CrossPoint 42, DTP3 CrossPoint 42 USB

Tested on the Following Software and Firmware Versions

ControlScript Deployment Utility	1.14.0-b.36
IP Link Pro Control Processor Firmware	3.18.0001-b002
IP Link Pro Control Processor xi Firmware	1.13.0001-b001
IP Link Pro Control Processor Q xi Firmware	1.13.0001-b001

Version History

Module Version	Date	Notes
1_2_0_0	6/24/2026	Renamed module from extr_matrix_DTP3_CrossPoint_42 → extr_matrix_DTP3_CrossPoint_42_Series. Added support for audio-only output 3. Removed unsupported Video tie type. Added Mode 2 to Executive Mode. Removed unsupported HDCP Input Status and HDCP Output Status. Added USB Input command. Removed unsupported 6 from USB Device Port.
1_0_1_0	5/28/2026	Added USB model and Volume command.
1_0_0_0	4/9/2026	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- If login credentials are required, devicePassword and deviceUsername must be set accordingly.
deviceUsername default value is admin respectively.
Example: `InterfaceName.deviceUsername = 'extron'`

Supported Class and Example

SSHClass

#Password Required

```
InterfaceName = ModuleName.SSHClass('192.168.254.254', 22023, Credentials=('admin', 'extron'),  
Model='DTP3 CrossPoint 42')
```

#No Password Required

```
InterfaceName = ModuleName.SSHClass('192.168.254.254', 22023, Credentials=('admin', ''),  
Model='DTP3 CrossPoint 42')
```

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	
AudioMute	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '3'		
# AudioMute example InterfaceName.Set('AudioMute', 'On', {'Output': '1'})			
Command	Value	Value	Value
AutoImage	'Execute'	'Execute and Fill'	'Execute and Follow'
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# AutoImage example InterfaceName.Set('AutoImage', 'Execute', {'Output': '1'})			
Command	Value	Value	Value
ExecutiveMode	'Off'	'Mode 1'	'Mode 2'
# ExecutiveMode example InterfaceName.Set('ExecutiveMode', 'Off')			
Command	Value	Value	
Freeze	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# Freeze example InterfaceName.Set('Freeze', 'On', {'Output': '1'})			
Command	Value	Value	
GlobalUSBDevicePort ¹	'On'	'Off'	
# GlobalUSBDevicePort example InterfaceName.Set('GlobalUSBDevicePort', 'On')			
Command	Value	Value	Value
GlobalVideoMute	'Video'	'Video & Sync'	'Off'
# GlobalVideoMute example InterfaceName.Set('GlobalVideoMute', 'Video')			
Command	Value	Value	
HDCPInputAuthorization	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Input'	'1' – '4'		
# HDCPInputAuthorization example InterfaceName.Set('HDCPInputAuthorization', 'On', {'Input': '1'})			
Command	Value	Value	
Logo	'1' – '16'	'Off'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# Logo example InterfaceName.Set('Logo', '1', {'Output': '1'})			

Global Scripter Module
Communication Sheet

Revision: 6/24/2026

Command MatrixIONameCommand	Value None		
Qualifier Key 'Type'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Number'	Qualifier Value String		
Qualifier Key 'Name'	Qualifier Value String		
# MatrixIONameCommand example InterfaceName.Set('MatrixIONameCommand', None, {'Type': 'Input', 'Number': 'String', 'Name': 'String'})			
Command MatrixIONumberSelect	Value '1' – '4'		
# MatrixIONumberSelect example InterfaceName.Set('MatrixIONumberSelect', '1')			
Command MatrixTieCommand ²	Value None		
Qualifier Key 'Input'	Qualifier Value '0' – '4'		
Qualifier Key 'Output'	Qualifier Value '1' – '3'	Qualifier Value 'All'	
Qualifier Key 'Tie Type'	Qualifier Value 'Audio' ³	Qualifier Value 'Audio/Video' ⁴	
# MatrixTieCommand example InterfaceName.Set('MatrixTieCommand', None, {'Input': '0', 'Output': '1', 'Tie Type': 'Audio'})			
Command OutputResolution	Value '640x480 (60Hz)' '1280x768 (60Hz)' '1360x768 (60Hz)' '1400x1050 (60Hz)' '1600x1200 (60Hz)' '480p (60Hz)' '720p (29.97Hz)' '720p (59.94Hz)' '1080i (59.94Hz)' '1080p (24Hz)' '1080p (30Hz)' '1080p (60Hz)' '2048x1080 (25Hz)' '2048x1080 (50Hz)' '2048x1200 (60Hz)' '2560x1440 (60Hz)' '3840x2160 (24Hz)' '3840x2160 (30Hz)' '3840x2160 (60Hz)' '4096x2160 (25Hz)' '4096x2160 (50Hz)' 'Custom 1' 'Custom 4'	Value '800x600 (60Hz)' '1280x800 (60Hz)' '1366x768 (60Hz)' '1600x900 (60Hz)' '1920x1200 (60Hz)' '576p (50Hz)' '720p (30Hz)' '720p (60Hz)' '1080i (60Hz)' '1080p (25Hz)' '1080p (50Hz)' '2048x1080 (23.98Hz)' '2048x1080 (29.97Hz)' '2048x1080 (59.94Hz)' '2048x1536 (60Hz)' '2560x1600 (60Hz)' '3840x2160 (25Hz)' '3840x2160 (50Hz)' '4096x2160 (23.98Hz)' '4096x2160 (29.97Hz)' '4096x2160 (59.94Hz)' 'Custom 2'	Value '1024x768 (60Hz)' '1280x1024 (60Hz)' '1440x900 (60Hz)' '1680x1050 (60Hz)' '480p (59.94Hz)' '720p (25Hz)' '720p (50Hz)' '1080i (50Hz)' '1080p (23.98Hz)' '1080p (29.97Hz)' '1080p (59.94Hz)' '2048x1080 (24Hz)' '2048x1080 (30Hz)' '2048x1080 (60Hz)' '2560x1080 (60Hz)' '3840x2160 (23.98Hz)' '3840x2160 (29.97Hz)' '3840x2160 (59.94Hz)' '4096x2160 (24Hz)' '4096x2160 (30Hz)' '4096x2160 (60Hz)' 'Custom 3'
Qualifier Key 'Output'	Qualifier Value '1' – '2'		

# OutputResolution example InterfaceName.Set('OutputResolution', '640x480 (60Hz)', {'Output': '1'})			
Command	Value	Value	Value
PowerSaveMode	'Off'	'Mode 1'	'Mode 2'
# PowerSaveMode example InterfaceName.Set('PowerSaveMode', 'Off')			
Command	Value		
PresetRecall	'1' – '16'		
# PresetRecall example InterfaceName.Set('PresetRecall', '1')			
Command	Value		
RefreshMatrix	None		
# RefreshMatrix example InterfaceName.Set('RefreshMatrix', None)			
Command	Value		
RefreshMatrixIONames	None		
# RefreshMatrixIONames example InterfaceName.Set('RefreshMatrixIONames', None)			
Command	Value	Value	
USBDevicePort ¹	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Port'	'1' – '5'		
# USBDevicePort example InterfaceName.Set('USBDevicePort', 'On', {'Port': '1'})			
Command	Value		
USBInput ¹	'0' – '3'		
# USBInput example InterfaceName.Set('USBInput', '0')			
Command	Value	Value	Value
VideoMute	'Video'	'Video & Sync'	'Off'
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# VideoMute example InterfaceName.Set('VideoMute', 'Video', {'Output': '1'})			
Command	Value		
Volume	-100 to 0 in steps of 1 dB		
# Volume example InterfaceName.Set('Volume', 0)			

¹ Only available for DTP3 CrossPoint 42 USB.

² For tie combinations of Input: 0 – 4 and Output: 1 – 3, the configured Tie Type should match the Output. For example, Output: 1 – 2 is paired with Tie Type: Audio/Video. Output: 3 is paired with Tie Type: Audio. Mismatches are not supported. Please note, it is not possible for breakaway audio.

³ When using Tie Type: Audio, Output: All is supported, but both ties and breaks only affect Output: 3.

⁴ When using Tie Type: Audio/Video, Output: All is supported, and both ties and breaks affect Output: 1 – 3, where Output: 3 is audio-only.

Status Available

For all commands except for HDCPInputAuthorization, HDCPInputStatus, Logo, OutputTieStatusName, USBDevicePort, and Volume, Update should be called only once since the command's status will be updated automatically as the device's status changes. ConnectionStatus, InputTieStatus, MatrixIOLNameStatus, OutputTieStatus, and OutputTieStatusName do not support the Update function. ConnectionStatus is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value	
AudioMute	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '3'		
# AudioMute example InterfaceName.Update('AudioMute', {'Output': '1'}) Value = InterfaceName.ReadStatus('AudioMute', {'Output': '1'}) InterfaceName.SubscribeStatus('AudioMute', None, FeedbackHandler)			
Command	Value	Value	
ConnectionStatus	'Connected'	'Disconnected'	
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command	Value	Value	Value
ExecutiveMode	'Off'	'Mode 1'	'Mode 2'
# ExecutiveMode example InterfaceName.Update('ExecutiveMode') Value = InterfaceName.ReadStatus('ExecutiveMode') InterfaceName.SubscribeStatus('ExecutiveMode', None, FeedbackHandler)			
Command	Value		
Firmware	'String'		
# Firmware example InterfaceName.Update('Firmware') Value = InterfaceName.ReadStatus('Firmware') InterfaceName.SubscribeStatus('Firmware', None, FeedbackHandler)			
Command	Value	Value	
Freeze	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# Freeze example InterfaceName.Update('Freeze', {'Output': '1'}) Value = InterfaceName.ReadStatus('Freeze', {'Output': '1'}) InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Command	Value	Value	
HDCPInputAuthorization	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Input'	'1' – '4'		
# HDCPInputAuthorization example InterfaceName.Update('HDCPInputAuthorization', {'Input': '1'}) Value = InterfaceName.ReadStatus('HDCPInputAuthorization', {'Input': '1'}) InterfaceName.SubscribeStatus('HDCPInputAuthorization', None, FeedbackHandler)			
Command	Value	Value	Value
HDCPInputStatus	'No Source Connected'	'No HDCP Content'	'HDCP Content'
Qualifier Key	Qualifier Value		
'Input'	'1' – '4'		
# HDCPInputStatus example InterfaceName.Update('HDCPInputStatus', {'Input': '1'}) Value = InterfaceName.ReadStatus('HDCPInputStatus', {'Input': '1'}) InterfaceName.SubscribeStatus('HDCPInputStatus', None, FeedbackHandler)			
Command	Value	Value	Value
HDCPOutputStatus	'No monitor connected'	'Monitor connected, not encrypted'	'Monitor connected, currently encrypted'
	'Monitor connected, no HDCP'		
Qualifier Key			
'Output'			
# HDCPOutputStatus example InterfaceName.Update('HDCPOutputStatus') Value = InterfaceName.ReadStatus('HDCPOutputStatus') InterfaceName.SubscribeStatus('HDCPOutputStatus', None, FeedbackHandler)			
Command	Value	Value	
InputSignalStatus	'Active'	'Not Active'	
Qualifier Key	Qualifier Value		
'Input'	'1' – '4'		
# InputSignalStatus example InterfaceName.Update('InputSignalStatus', {'Input': '1'}) Value = InterfaceName.ReadStatus('InputSignalStatus', {'Input': '1'}) InterfaceName.SubscribeStatus('InputSignalStatus', None, FeedbackHandler)			
Command	Value	Value	Value
InputTieStatus	'Audio'	'Audio/Video'	'Untied'
Qualifier Key	Qualifier Value		
'Input'	'1' – '4'		
Qualifier Key	Qualifier Value		
'Output'	'1' – '3'		
# InputTieStatus example Value = InterfaceName.ReadStatus('InputTieStatus', {'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('InputTieStatus', None, FeedbackHandler)			
Command	Value	Value	
Logo	'1' – '16'	'Off'	
Qualifier Key	Qualifier Value		
'Output'	'1' – '2'		
# Logo example InterfaceName.Update('Logo', {'Output': '1'}) Value = InterfaceName.ReadStatus('Logo', {'Output': '1'}) InterfaceName.SubscribeStatus('Logo', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Command MACAddress	Value 'String'		
# MACAddress example InterfaceName.Update('MACAddress') Value = InterfaceName.ReadStatus('MACAddress') InterfaceName.SubscribeStatus('MACAddress', None, FeedbackHandler)			
Command MatrixIONameStatus	Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Number'	Qualifier Value '1' – '4'		
# MatrixIONameStatus example Value = InterfaceName.ReadStatus('MatrixIONameStatus', {'Type': 'Input', 'Number': '1'}) InterfaceName.SubscribeStatus('MatrixIONameStatus', None, FeedbackHandler)			
Command OutputResolution	Value '640x480 (60Hz)'	Value '800x600 (60Hz)'	Value '1024x768 (60Hz)'
	'1280x768 (60Hz)'	'1280x800 (60Hz)'	'1280x1024 (60Hz)'
	'1360x768 (60Hz)'	'1366x768 (60Hz)'	'1440x900 (60Hz)'
	'1400x1050 (60Hz)'	'1600x900 (60Hz)'	'1680x1050 (60Hz)'
	'1600x1200 (60Hz)'	'1920x1200 (60Hz)'	'480p (59.94Hz)'
	'480p (60Hz)'	'576p (50Hz)'	'720p (25Hz)'
	'720p (29.97Hz)'	'720p (30Hz)'	'720p (50Hz)'
	'720p (59.94Hz)'	'720p (60Hz)'	'1080i (50Hz)'
	'1080i (59.94Hz)'	'1080i (60Hz)'	'1080p (23.98Hz)'
	'1080p (24Hz)'	'1080p (25Hz)'	'1080p (29.97Hz)'
	'1080p (30Hz)'	'1080p (50Hz)'	'1080p (59.94Hz)'
	'1080p (60Hz)'	'2048x1080 (23.98Hz)'	'2048x1080 (24Hz)'
	'2048x1080 (25Hz)'	'2048x1080 (29.97Hz)'	'2048x1080 (30Hz)'
	'2048x1080 (50Hz)'	'2048x1080 (59.94Hz)'	'2048x1080 (60Hz)'
	'2048x1200 (60Hz)'	'2048x1536 (60Hz)'	'2560x1080 (60Hz)'
	'2560x1440 (60Hz)'	'2560x1600 (60Hz)'	'3840x2160 (23.98Hz)'
	'3840x2160 (24Hz)'	'3840x2160 (25Hz)'	'3840x2160 (29.97Hz)'
	'3840x2160 (30Hz)'	'3840x2160 (50Hz)'	'3840x2160 (59.94Hz)'
	'3840x2160 (60Hz)'	'4096x2160 (23.98Hz)'	'4096x2160 (24Hz)'
	'4096x2160 (25Hz)'	'4096x2160 (29.97Hz)'	'4096x2160 (30Hz)'
'4096x2160 (50Hz)'	'4096x2160 (59.94Hz)'	'4096x2160 (60Hz)'	
'Custom 1'	'Custom 2'	'Custom 3'	
'Custom 4'			
Qualifier Key 'Output'	Qualifier Value '1' – '2'		
# OutputResolution example InterfaceName.Update('OutputResolution', {'Output': '1'}) Value = InterfaceName.ReadStatus('OutputResolution', {'Output': '1'}) InterfaceName.SubscribeStatus('OutputResolution', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Revision: 6/24/2026

Command OutputTieStatus	Value '0' – '4'		
Qualifier Key 'Output'	Qualifier Value '1' – '3'		
Qualifier Key 'Tie Type'	Qualifier Value 'Audio'	Qualifier Value 'Audio/Video'	
# OutputTieStatus example Value = InterfaceName.ReadStatus('OutputTieStatus', {'Output': '1', 'Tie Type': 'Audio'}) InterfaceName.SubscribeStatus('OutputTieStatus', None, FeedbackHandler)			
Command OutputTieStatusName	Value 'String'		
Qualifier Key 'Output'	Qualifier Value '1' – '2'		
Qualifier Key 'Tie Type'	Qualifier Value 'Audio'	Qualifier Value 'Audio/Video'	
# OutputTieStatusName example Value = InterfaceName.ReadStatus('OutputTieStatusName', {'Output': '1', 'Tie Type': 'Audio'}) InterfaceName.SubscribeStatus('OutputTieStatusName', None, FeedbackHandler)			
Command PowerSaveMode	Value 'Off' 'Low Power (Over Temperature)'	Value 'Mode 1'	Value 'Mode 2'
# PowerSaveMode example InterfaceName.Update('PowerSaveMode') Value = InterfaceName.ReadStatus('PowerSaveMode') InterfaceName.SubscribeStatus('PowerSaveMode', None, FeedbackHandler)			
Command SerialNumber	Value 'String'		
# SerialNumber example InterfaceName.Update('SerialNumber') Value = InterfaceName.ReadStatus('SerialNumber') InterfaceName.SubscribeStatus('SerialNumber', None, FeedbackHandler)			
Command USBDevicePort ¹	Value 'On'	Value 'Off'	
Qualifier Key 'Port'	Qualifier Value '1' – '5'		
# USBDevicePort example InterfaceName.Update('USBDevicePort', {'Port': '1'}) Value = InterfaceName.ReadStatus('USBDevicePort', {'Port': '1'}) InterfaceName.SubscribeStatus('USBDevicePort', None, FeedbackHandler)			
Command USBInput ¹	Value '0' – '3'		
# USBInput example InterfaceName.Update('USBInput') Value = InterfaceName.ReadStatus('USBInput') InterfaceName.SubscribeStatus('USBInput', None, FeedbackHandler)			
Command USBInputSignalStatus ¹	Value 'Active'	Value 'Not Active'	
Qualifier Key 'Input'	Qualifier Value '1' – '3'		
# USBInputSignalStatus example InterfaceName.Update('USBInputSignalStatus', {'Input': '1'}) Value = InterfaceName.ReadStatus('USBInputSignalStatus', {'Input': '1'}) InterfaceName.SubscribeStatus('USBInputSignalStatus', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Command USBOutputSignalStatus	Value 'Active'	Value 'Not Active'
Qualifier Key 'Output'	Qualifier Value '1' – '4'	
# USBOutputSignalStatus example InterfaceName.Update('USBOutputSignalStatus', {'Output': '1'}) Value = InterfaceName.ReadStatus('USBOutputSignalStatus', {'Output': '1'}) InterfaceName.SubscribeStatus('USBOutputSignalStatus', None, FeedbackHandler)		
Command Volume	Value -100 to 0 in steps of 1 dB	
# Volume example InterfaceName.Update('Volume') Value = InterfaceName.ReadStatus('Volume') InterfaceName.SubscribeStatus('Volume', None, FeedbackHandler)		

¹ Only available for DTP3 CrossPoint 42 USB.

Network Communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (SSH)

Default Port: 22023

Logon Credentials Supported: Yes

Default Username: admin

Multi-Connection: Yes

Capabilities:

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Audio Mute Off Output 1	1*0Z
Audio Mute Off Output 3	3*0Z
Audio Mute On Output 1	1*1Z
Audio Mute On Output 3	3*1Z
Auto Image Execute and Fill Output 1	01*1A
Auto Image Execute and Fill Output 2	02*1A
Auto Image Execute and Follow Output 1	01*2A
Auto Image Execute and Follow Output 2	02*2A
Auto Image Execute Output 1	01*0A
Auto Image Execute Output 2	02*0A
Executive Mode Mode 1	1X
Executive Mode Mode 2	2X
Executive Mode Off	0X
Freeze Off Output 1	01*0F
Freeze Off Output 2	02*0F
Freeze On Output 1	01*1F
Freeze On Output 2	02*1F
Global USB Device Port Off	wX0USBC\x0D
Global USB Device Port On	wX1USBC\x0D
Global Video Mute Off	0*B
Global Video Mute Video	1*B
Global Video Mute Video & Sync	2*B
HDCP Input Authorization Off Input 1	wE01*0HDCP\x0D
HDCP Input Authorization Off Input 4	wE04*0HDCP\x0D
HDCP Input Authorization On Input 1	wE01*1HDCP\x0D
HDCP Input Authorization On Input 4	wE04*1HDCP\x0D
Logo 1 Output 1	wE01*01LOG0\x0D
Logo 1 Output 2	wE02*01LOG0\x0D
Logo 16 Output 1	wE01*16LOG0\x0D
Logo 16 Output 2	wE02*16LOG0\x0D
Logo Off Output 1	wE01*0LOG0\x0D
Logo Off Output 2	wE02*0LOG0\x0D
Matrix IO Name Command None Type Input Number String Name String	wString,StringNI\x0D
Matrix IO Name Command None Type Output Number String Name String	wString,StringNO\x0D
Matrix Tie Command None Input 0 Output 1 Tie Type Audio/Video	0*1!
Matrix Tie Command None Input 0 Output 3 Tie Type Audio	0*3\$
Matrix Tie Command None Input 0 Output 3 Tie Type Audio/Video	0*3!
Matrix Tie Command None Input 0 Output All Tie	0*\$

Global Scriptor Module Communication Sheet

Revision: 6/24/2026

Type Audio	
Matrix Tie Command None Input 0 Output All Tie Type Audio/Video	0*!
Matrix Tie Command None Input 4 Output 1 Tie Type Audio/Video	4*1!
Matrix Tie Command None Input 4 Output 3 Tie Type Audio	4*3\$
Matrix Tie Command None Input 4 Output 3 Tie Type Audio/Video	4*3!
Matrix Tie Command None Input 4 Output All Tie Type Audio	4*\$
Matrix Tie Command None Input 4 Output All Tie Type Audio/Video	4*!
Output Resolution 1024x768 (60Hz) Output 1	w01*12RATE\x0D
Output Resolution 1024x768 (60Hz) Output 2	w02*12RATE\x0D
Output Resolution 1080i (50Hz) Output 1	w01*35RATE\x0D
Output Resolution 1080i (50Hz) Output 2	w02*35RATE\x0D
Output Resolution 1080i (59.94Hz) Output 1	w01*36RATE\x0D
Output Resolution 1080i (59.94Hz) Output 2	w02*36RATE\x0D
Output Resolution 1080i (60Hz) Output 1	w01*37RATE\x0D
Output Resolution 1080i (60Hz) Output 2	w02*37RATE\x0D
Output Resolution 1080p (23.98Hz) Output 1	w01*38RATE\x0D
Output Resolution 1080p (23.98Hz) Output 2	w02*38RATE\x0D
Output Resolution 1080p (24Hz) Output 1	w01*39RATE\x0D
Output Resolution 1080p (24Hz) Output 2	w02*39RATE\x0D
Output Resolution 1080p (25Hz) Output 1	w01*40RATE\x0D
Output Resolution 1080p (25Hz) Output 2	w02*40RATE\x0D
Output Resolution 1080p (29.97Hz) Output 1	w01*41RATE\x0D
Output Resolution 1080p (29.97Hz) Output 2	w02*41RATE\x0D
Output Resolution 1080p (30Hz) Output 1	w01*42RATE\x0D
Output Resolution 1080p (30Hz) Output 2	w02*42RATE\x0D
Output Resolution 1080p (50Hz) Output 1	w01*43RATE\x0D
Output Resolution 1080p (50Hz) Output 2	w02*43RATE\x0D
Output Resolution 1080p (59.94Hz) Output 1	w01*44RATE\x0D
Output Resolution 1080p (59.94Hz) Output 2	w02*44RATE\x0D
Output Resolution 1080p (60Hz) Output 1	w01*45RATE\x0D
Output Resolution 1080p (60Hz) Output 2	w02*45RATE\x0D
Output Resolution 1280x1024 (60Hz) Output 1	w01*15RATE\x0D
Output Resolution 1280x1024 (60Hz) Output 2	w02*15RATE\x0D
Output Resolution 1280x768 (60Hz) Output 1	w01*13RATE\x0D
Output Resolution 1280x768 (60Hz) Output 2	w02*13RATE\x0D
Output Resolution 1280x800 (60Hz) Output 1	w01*14RATE\x0D
Output Resolution 1280x800 (60Hz) Output 2	w02*14RATE\x0D
Output Resolution 1360x768 (60Hz) Output 1	w01*16RATE\x0D
Output Resolution 1360x768 (60Hz) Output 2	w02*16RATE\x0D

Global Scriptor Module Communication Sheet

Output Resolution 1366x768 (60Hz) Output 1	w01*17RATE\x0D
Output Resolution 1366x768 (60Hz) Output 2	w02*17RATE\x0D
Output Resolution 1400x1050 (60Hz) Output 1	w01*19RATE\x0D
Output Resolution 1400x1050 (60Hz) Output 2	w02*19RATE\x0D
Output Resolution 1440x900 (60Hz) Output 1	w01*18RATE\x0D
Output Resolution 1440x900 (60Hz) Output 2	w02*18RATE\x0D
Output Resolution 1600x1200 (60Hz) Output 1	w01*22RATE\x0D
Output Resolution 1600x1200 (60Hz) Output 2	w02*22RATE\x0D
Output Resolution 1600x900 (60Hz) Output 1	w01*20RATE\x0D
Output Resolution 1600x900 (60Hz) Output 2	w02*20RATE\x0D
Output Resolution 1680x1050 (60Hz) Output 1	w01*21RATE\x0D
Output Resolution 1680x1050 (60Hz) Output 2	w02*21RATE\x0D
Output Resolution 1920x1200 (60Hz) Output 1	w01*23RATE\x0D
Output Resolution 1920x1200 (60Hz) Output 2	w02*23RATE\x0D
Output Resolution 2048x1080 (23.98Hz) Output 1	w01*46RATE\x0D
Output Resolution 2048x1080 (23.98Hz) Output 2	w02*46RATE\x0D
Output Resolution 2048x1080 (24Hz) Output 1	w01*47RATE\x0D
Output Resolution 2048x1080 (24Hz) Output 2	w02*47RATE\x0D
Output Resolution 2048x1080 (25Hz) Output 1	w01*48RATE\x0D
Output Resolution 2048x1080 (25Hz) Output 2	w02*48RATE\x0D
Output Resolution 2048x1080 (29.97Hz) Output 1	w01*49RATE\x0D
Output Resolution 2048x1080 (29.97Hz) Output 2	w02*49RATE\x0D
Output Resolution 2048x1080 (30Hz) Output 1	w01*50RATE\x0D
Output Resolution 2048x1080 (30Hz) Output 2	w02*50RATE\x0D
Output Resolution 2048x1080 (50Hz) Output 1	w01*51RATE\x0D
Output Resolution 2048x1080 (50Hz) Output 2	w02*51RATE\x0D
Output Resolution 2048x1080 (59.94Hz) Output 1	w01*52RATE\x0D
Output Resolution 2048x1080 (59.94Hz) Output 2	w02*52RATE\x0D
Output Resolution 2048x1080 (60Hz) Output 1	w01*53RATE\x0D
Output Resolution 2048x1080 (60Hz) Output 2	w02*53RATE\x0D
Output Resolution 2048x1200 (60Hz) Output 1	w01*54RATE\x0D
Output Resolution 2048x1200 (60Hz) Output 2	w02*54RATE\x0D
Output Resolution 2048x1536 (60Hz) Output 1	w01*55RATE\x0D
Output Resolution 2048x1536 (60Hz) Output 2	w02*55RATE\x0D
Output Resolution 2560x1080 (60Hz) Output 1	w01*56RATE\x0D
Output Resolution 2560x1080 (60Hz) Output 2	w02*56RATE\x0D
Output Resolution 2560x1440 (60Hz) Output 1	w01*57RATE\x0D
Output Resolution 2560x1440 (60Hz) Output 2	w02*57RATE\x0D
Output Resolution 2560x1600 (60Hz) Output 1	w01*58RATE\x0D
Output Resolution 2560x1600 (60Hz) Output 2	w02*58RATE\x0D
Output Resolution 3840x2160 (23.98Hz) Output 1	w01*59RATE\x0D
Output Resolution 3840x2160 (23.98Hz) Output 2	w02*59RATE\x0D
Output Resolution 3840x2160 (24Hz) Output 1	w01*60RATE\x0D
Output Resolution 3840x2160 (24Hz) Output 2	w02*60RATE\x0D

Global Scriptor Module Communication Sheet

Output Resolution 3840x2160 (25Hz) Output 1	w01*61RATE\x0D
Output Resolution 3840x2160 (25Hz) Output 2	w02*61RATE\x0D
Output Resolution 3840x2160 (29.97Hz) Output 1	w01*62RATE\x0D
Output Resolution 3840x2160 (29.97Hz) Output 2	w02*62RATE\x0D
Output Resolution 3840x2160 (30Hz) Output 1	w01*63RATE\x0D
Output Resolution 3840x2160 (30Hz) Output 2	w02*63RATE\x0D
Output Resolution 3840x2160 (50Hz) Output 1	w01*64RATE\x0D
Output Resolution 3840x2160 (50Hz) Output 2	w02*64RATE\x0D
Output Resolution 3840x2160 (59.94Hz) Output 1	w01*65RATE\x0D
Output Resolution 3840x2160 (59.94Hz) Output 2	w02*65RATE\x0D
Output Resolution 3840x2160 (60Hz) Output 1	w01*66RATE\x0D
Output Resolution 3840x2160 (60Hz) Output 2	w02*66RATE\x0D
Output Resolution 4096x2160 (23.98Hz) Output 1	w01*69RATE\x0D
Output Resolution 4096x2160 (23.98Hz) Output 2	w02*69RATE\x0D
Output Resolution 4096x2160 (24Hz) Output 1	w01*70RATE\x0D
Output Resolution 4096x2160 (24Hz) Output 2	w02*70RATE\x0D
Output Resolution 4096x2160 (25Hz) Output 1	w01*71RATE\x0D
Output Resolution 4096x2160 (25Hz) Output 2	w02*71RATE\x0D
Output Resolution 4096x2160 (29.97Hz) Output 1	w01*72RATE\x0D
Output Resolution 4096x2160 (29.97Hz) Output 2	w02*72RATE\x0D
Output Resolution 4096x2160 (30Hz) Output 1	w01*73RATE\x0D
Output Resolution 4096x2160 (30Hz) Output 2	w02*73RATE\x0D
Output Resolution 4096x2160 (50Hz) Output 1	w01*74RATE\x0D
Output Resolution 4096x2160 (50Hz) Output 2	w02*74RATE\x0D
Output Resolution 4096x2160 (59.94Hz) Output 1	w01*75RATE\x0D
Output Resolution 4096x2160 (59.94Hz) Output 2	w02*75RATE\x0D
Output Resolution 4096x2160 (60Hz) Output 1	w01*76RATE\x0D
Output Resolution 4096x2160 (60Hz) Output 2	w02*76RATE\x0D
Output Resolution 480p (59.94Hz) Output 1	w01*24RATE\x0D
Output Resolution 480p (59.94Hz) Output 2	w02*24RATE\x0D
Output Resolution 480p (60Hz) Output 1	w01*25RATE\x0D
Output Resolution 480p (60Hz) Output 2	w02*25RATE\x0D
Output Resolution 576p (50Hz) Output 1	w01*26RATE\x0D
Output Resolution 576p (50Hz) Output 2	w02*26RATE\x0D
Output Resolution 640x480 (60Hz) Output 1	w01*10RATE\x0D
Output Resolution 640x480 (60Hz) Output 2	w02*10RATE\x0D
Output Resolution 720p (25Hz) Output 1	w01*29RATE\x0D
Output Resolution 720p (25Hz) Output 2	w02*29RATE\x0D
Output Resolution 720p (29.97Hz) Output 1	w01*30RATE\x0D
Output Resolution 720p (29.97Hz) Output 2	w02*30RATE\x0D
Output Resolution 720p (30Hz) Output 1	w01*31RATE\x0D
Output Resolution 720p (30Hz) Output 2	w02*31RATE\x0D
Output Resolution 720p (50Hz) Output 1	w01*32RATE\x0D
Output Resolution 720p (50Hz) Output 2	w02*32RATE\x0D

Global Scriptor Module Communication Sheet

Output Resolution 720p (59.94Hz) Output 1	w01*33RATE\x0D
Output Resolution 720p (59.94Hz) Output 2	w02*33RATE\x0D
Output Resolution 720p (60Hz) Output 1	w01*34RATE\x0D
Output Resolution 720p (60Hz) Output 2	w02*34RATE\x0D
Output Resolution 800x600 (60Hz) Output 1	w01*11RATE\x0D
Output Resolution 800x600 (60Hz) Output 2	w02*11RATE\x0D
Output Resolution Custom 1 Output 1	w01*201RATE\x0D
Output Resolution Custom 1 Output 2	w02*201RATE\x0D
Output Resolution Custom 2 Output 1	w01*202RATE\x0D
Output Resolution Custom 2 Output 2	w02*202RATE\x0D
Output Resolution Custom 3 Output 1	w01*203RATE\x0D
Output Resolution Custom 3 Output 2	w02*203RATE\x0D
Output Resolution Custom 4 Output 1	w01*204RATE\x0D
Output Resolution Custom 4 Output 2	w02*204RATE\x0D
Power Save Mode Mode 1	w1PSAV\x0D
Power Save Mode Mode 2	w2PSAV\x0D
Power Save Mode Off	w0PSAV\x0D
Preset Recall 1	1.
Preset Recall 16	16.
USB Device Port Off Port 1	wX1*0USBC\x0D
USB Device Port Off Port 5	wX5*0USBC\x0D
USB Device Port On Port 1	wX1*1USBC\x0D
USB Device Port On Port 5	wX5*1USBC\x0D
USB Input 0	0*^
USB Input 3	3*^
Video Mute Off Output 1	1*0B
Video Mute Off Output 2	2*0B
Video Mute Video & Sync Output 1	1*2B
Video Mute Video & Sync Output 2	2*2B
Video Mute Video Output 1	1*1B
Video Mute Video Output 2	2*1B
Volume 0	0V
Volume -100	-100V

Appendix B. Update Commands

Audio Mute Output 1	1Z
Audio Mute Output 3	3Z
Executive Mode	X
Firmware	*q
Freeze Output 1	01F
Freeze Output 2	02F
HDCP Input Authorization Input 1	wE01HDCP\x0D
HDCP Input Authorization Input 4	wE04HDCP\x0D
Input Signal Status Input 1	0LS
Input Signal Status Input 4	0LS
Logo Output 1	wE01LOGO\x0D
Logo Output 2	wE02LOGO\x0D
MAC Address	wCH\x0D
Output Resolution Output 1	w01RATE\x0D
Output Resolution Output 2	w02RATE\x0D
Power Save Mode	wPSAV\x0D
Serial Number	19i
USB Device Port Port 1	wXUSBC\x0D
USB Device Port Port 5	wXUSBC\x0D
USB Input	w0*1*3VC\x0D\x0A
USB Input Signal Status Input 1	wIUSBC\x0D
USB Input Signal Status Input 3	wIUSBC\x0D
USB Output Signal Status Output 1	wOUSBC\x0D
USB Output Signal Status Output 4	wOUSBC\x0D
Volume	V