

This document provides additional assistance with wiring your Extron IP Link® Pro Series enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link® Pro Series enabled product or the controlled device manufacturer supplied documentation.

Device Specifications

Device Type: Streaming Media
Manufacturer: 1 Beyond
Firmware Version: N/A
Model(s): Automate VX, Automate VX Plus, Automate VX Pro

Tested on the Following Software and Firmware Versions

GC (Plus, Pro) Version	3.33.0.38
IP Link Pro Control Processor Firmware	3.18.0001-b002
IP Link Pro Control Processor xi Firmware	1.13.0001-b001
IP Link Pro Control Processor Q xi Firmware	1.13.0001-b001
MediaLink Plus Controller Firmware	3.04.0000-b001
HC 400 Series Firmware	2.11.0002-b002
TLP Pro x25 and TLC Pro x26 Series Firmware	3.13.0000-b008
TLP Pro 300M Firmware	1.08.0000-b008

Version History

Driver Version	Date	Notes
1_0_11	7/21/2026	Added status to commands: Scenario, Room Configuration. Updated Scenario command: changed 'ID' parameter to value type. Added command: Home Shot Preset.
1_0_10	6/10/2026	Added Pan Tilt and Zoom commands.
1_0_9	6/2/2025	Updated driver to use HTTPS.

1_0_7	4/16/2024	Added command: Scenario.
1_0_6	1/15/2024	Added model: Automate VX Plus. Added status for command Switch Camera. Updated commands Camera Preset Recall and Switch Camera to support up to 255 cameras.
1_0_4	4/3/2023	Added commands Force Room Configuration. Updated Room Configuration command to support additional states: 5-99.
1_0_3	1/31/2023	Added commands: Wake, Sleep
1_0_2	8/31/2021	Updated Layout command to support values A – Z.
1_0_1	7/22/2019	Fixed status feedback for all commands.
1_0_0	7/16/2019	Initial Version

Driver Notes

- The “SSL Verify Mode” driver parameter (“Off” by default) must be set appropriately:
 - “On” if a certificate signed by a trusted Certificate Authority (CA) is loaded to the device.
 - “Off” if a self-signed certificate is loaded to the device.
 - For non xi /Q xi IP Link Pro control processors the “Off” setting will only work with Firmware 3.04.0001-b002 and above.
 - A self-signed certificate may already be loaded by factory default, therefore, “Off” must be used.

Driver Timings

- N/A

Control Commands & States

Auto Switch			
Value	On	Off	
Camera Preset Recall			
Camera	1 – 255		
Value	1 – 255		
Camera Preset Save			
Camera	1 – 255		
Value	1 – 255		
Force Room Configuration			
Value	1 – 99		
Home Shot Preset			
Value	None		
ISO Recording			
Value	Start	Stop	
Layout			
Value	A – Z		
Output			
Value	On	Off	
Pan Tilt			
Camera	1 – 255		
Value	Up	Up Left	Up Right
	Down	Down Left	Down Right
	Left	Right	Stop
Record			
Value	Start	Stop	
Room Configuration ¹			
Value	1 – 99		
Scenario			
Value	Number		
Sleep			
Value	None		

Stream	
Value	Start Stop
Switch Camera	
Value	1 – 255
Wake	
Value	None
Zoom	
Camera	1 – 255
Value	In Out Stop

¹ Auto Switch needs to be Off for this command to work.

Status Available

Auto Switch	
Value	On Off
Connection Status ^{RP}	
Value	Connected Disconnected
ISO Recording	
Value	Start Stop
Output	
Value	On Off
Record	
Value	Start Stop
Room Configuration ¹	
Value	1 – 99
Scenario	
Value	Number
Stream	
Value	Start Stop
Switch Camera	
Value	1 – 255

¹ Auto Switch needs to be Off for this command to work.

^{RP} Connection Status is based off of the following string: https://IP_ADDRESS:4443/api/RecordStatus

Network communication

When configuring the Ethernet driver, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet (HTTPS)
Default Port:	4443
Logon Credentials Supported:	Yes
Default Username:	admin
Default Password:	1beyond
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Driver Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device