XRComm FCS 8T8R Platform

Application Development Guide

XRComm Inc.

June 2026

XRComm FCS 8T8R Platform

Application Development Guide

Platform	XRComm FCS 8T8R Platform
Driver Version	v1.4.3
Variant	8T8R
Audience	Software Developers
Classification	Proprietary

Contents

1 Introduction

This document provides detailed guidelines for developers writing, compiling, and running custom applications that interface with the XRComm FCS 8T8R Platform.

The platform provides a header-only, zero-copy C API (`xrcomm_ip_client.h`) for POSIX applications that consume I/Q sample batches. Customer applications do not include DPDK or SPDK headers for IQ delivery; those libraries are used by the platform services. Reference documentation is available from DPDK (https://core.dpdk.org/doc/) and SPDK (https://spdk.io/doc/).

2 Compiling and Running the Hello World Examples

The platform includes an example consumer application in the `XRComm_8T8R_hello_world/` folder that demonstrates how to subscribe to and consume platform data streams.

Example Binary	Delivery Mode	Enable With	Privileges
`hello_world`	IQ samples (zero-copy shared memory)	`set-ip on`	None

2.1 Build the Hello-World Application

Navigate to the hello world folder:

```
cd XRComm_8T8R_hello_world/
```

Compile using CMake:

```
mkdir -p build && cd build
cmake ..
make
```

Or compile directly with GCC:

```
gcc -O3 -mavx2 -pthread -Wall -o hello_world hello_world.c \
    -I../XRComm_FCS_8T8R_platform/XRComm_platform_drivers/include \
    -lrt -lpthread -lm
```

Compiled binaries are placed in `bin/` (if compiled with CMake) or the folder root (if compiled with GCC).

2.2 Run the Hello-World Application

The platform driver must be running and IQ mode must be enabled before starting the application:

Terminal 1 (FlexCompute Server): Ensure `xrcomm_server` is running, then enable IQ mode:

```
python3 XRComm_platform_gRPC/client/xrcomm_grpc_client.py set-ip on
```

Terminal 2 (FlexCompute Server): Run the application:

```
./hello_world
```

The example prints a summary of batches, samples, signal power, and drops for all 8 channels:

```
[IP:hello_world_ch0] Registered slot 0 (pid 12345, port 0, ch 0)
...
[HW] All channels ready — starting receive loop
[HW] Channel summary (port 0):
  ch0: batches=15234  samples=487488  power=-18.4dBFS  mean=-18.6dBFS  dropped=0
  ch1: batches=15234  samples=487488  power=-19.1dBFS  mean=-19.2dBFS  dropped=0
  ch2: batches=15234  samples=487488  power=-18.9dBFS  mean=-19.0dBFS  dropped=0
  ch3: batches=15234  samples=487488  power=-18.7dBFS  mean=-18.8dBFS  dropped=0
```



```
[HW] Channel summary (port 1):
  ch4: batches=15234  samples=487488  power=-19.3dBFS  mean=-19.4dBFS  dropped=0
  ch5: batches=15234  samples=487488  power=-18.8dBFS  mean=-18.9dBFS  dropped=0
  ch6: batches=15234  samples=487488  power=-19.0dBFS  mean=-19.1dBFS  dropped=0
  ch7: batches=15234  samples=487488  power=-18.6dBFS  mean=-18.7dBFS  dropped=0
```

2.3 Verify the Application Is Registered

Query the registry from the **Client Machine**:

```
python3 xrcomm_grpc_client.py --host <server-ip>:50051 list-ips
```

Each of the 8 channel slots should appear active:

```
slot=0  name=hello_world_ch0  pid=12345  mode=IQ_MODE  port=0  ch=0  ring=ready  active=yes
slot=1  name=hello_world_ch1  pid=12345  mode=IQ_MODE  port=0  ch=1  ring=ready  active=yes
slot=2  name=hello_world_ch2  pid=12345  mode=IQ_MODE  port=0  ch=2  ring=ready  active=yes
slot=3  name=hello_world_ch3  pid=12345  mode=IQ_MODE  port=0  ch=3  ring=ready  active=yes
slot=4  name=hello_world_ch4  pid=12345  mode=IQ_MODE  port=1  ch=4  ring=ready  active=yes
slot=5  name=hello_world_ch5  pid=12345  mode=IQ_MODE  port=1  ch=5  ring=ready  active=yes
slot=6  name=hello_world_ch6  pid=12345  mode=IQ_MODE  port=1  ch=6  ring=ready  active=yes
slot=7  name=hello_world_ch7  pid=12345  mode=IQ_MODE  port=1  ch=7  ring=ready  active=yes
```

3 Application API Reference

Include `xrcomm_ip_client.h` (found in `XRComm_platform_drivers/include/`) in your applications. No DPDK headers are required.

3.1 Quick API Use Case: Consume One 8T8R Channel

The typical customer application opens one logical channel, waits until the platform has created the shared-memory ring, then polls batches until the platform stops:

```c
#include <stdio.h>
#include "xrcomm_ip_client.h"

int main(void) {
    xrcomm_ip_client_t client;
    if (xrcomm_ip_client_init_port_channel(&client, "my_ch0_app", 0, 0) != 0) {
        return 1;
    }
    if (xrcomm_ip_client_wait_ready(&client, 5000) != 0) {
        xrcomm_ip_client_shutdown(&client);
        return 1;
    }

    while (xrcomm_ip_client_running(&client)) {
        const xrcomm_iq_slot_t *slot = xrcomm_ip_client_poll(&client);
        if (!slot) {
            continue;
        }

        printf("port=%u channel=%u samples=%u\n",
               slot->hsp_port, slot->channel, slot->valid_sample_count);
        xrcomm_ip_client_report_spectrum(&client, 1, 0.0f);
        xrcomm_ip_client_consume(&client);
    }

    xrcomm_ip_client_shutdown(&client);
    return 0;
}
```

Run one instance per channel when you want separate per-channel processing, or follow the hello-world pattern to register all 8 channels from one process.

3.2 Connection & Lifecycle

3.2.1 `xrcomm_ip_client_init_port_channel`

```c
int xrcomm_ip_client_init_port_channel(xrcomm_ip_client_t *client,
                                       const char *name,
                                       uint32_t hsp_port,
                                       uint32_t channel);
```

8T8R: Registers the application to consume the IQ stream of a single channel of one HSP port. Arguments: client handle, application name (max 63 chars), hsp_port (0 or 1), channel (0–7). Returns 0 on success.

3.2.2 xrcomm_ip_client_wait_ready

```
int xrcomm_ip_client_wait_ready(xrcomm_ip_client_t *client, int timeout_ms);
```

Blocks the caller until the platform has created and opened the shared memory data ring for this channel. Timeout of 0 means wait indefinitely. Returns 0 when ready, -1 on timeout.

3.2.3 xrcomm_ip_client_running

```
bool xrcomm_ip_client_running(xrcomm_ip_client_t *client);
```

Returns true as long as the platform's receive loop is active. Use this as the main condition for your ingest loop.

3.2.4 xrcomm_ip_client_shutdown

```
void xrcomm_ip_client_shutdown(xrcomm_ip_client_t *client);
```

Deregisters the channel handle from the platform and releases all mapped shared memory regions.

3.3 Data Consumer Functions

3.3.1 xrcomm_ip_client_poll

```
const xrcomm_iq_slot_t* xrcomm_ip_client_poll(xrcomm_ip_client_t *client);
```

Polls the data ring for a new batch of IQ samples. Returns a read-only pointer to the batch if available, or NULL if empty or if IQ mode is off. Batch fields: - `samples[]`: Array of interleaved little-endian int16 IQ pairs - `valid_sample_count`: Count of valid samples in the batch - `hsp_port`, `channel`: Metadata indicating source port and channel

3.3.2 xrcomm_ip_client_consume

```
void xrcomm_ip_client_consume(xrcomm_ip_client_t *client);
```

Releases the current batch slot and returns it to the platform's write pool. Must be called once per successful poll.

3.4 Diagnostics

3.4.1 xrcomm_ip_client_get_dropped

```
uint64_t xrcomm_ip_client_get_dropped(xrcomm_ip_client_t *client);
```

Returns the number of batches dropped by the platform for this subscription because the application polled too slowly.

3.4.2 xrcomm_ip_client_report_spectrum

```
void xrcomm_ip_client_report_spectrum(xrcomm_ip_client_t *client,
                                      uint64_t processed,
                                      float power_dbfs);
```

Reports processing stats back to the platform, making them visible in gRPC telemetry and statistics.

