

@typemain@type@type@parent@level0@sortvalueAT&T&t@sortvalue&t@sortvalue@textAT&T&tsat&tpluralAT&T
Telephone and Telegraph Company (AT&T)rstsat&tfirstplAmerican Tele-
phone and Telegraph Companys (AT&Ts)@counterpage@useri@userii@useriii@useriv@userv@uservi@shortAT&T
Telephone and Telegraph Company@longplAmerican Telephone and Tele-
graph Companyst@nameAT&T&t@numberlistt@numberlist@numberlistat&tt@descAmerican
Telephone and Telegraph Companyt@descpluralAmerican Telephone and
Telegraph Company

Practical Implementation of an OFDM Based Active Radar System for Target Classification



Prepared by:
Rory Schram

Prepared for:
Dr Stephen Paine
Department of Electrical Engineering
University of Cape Town

Declaration

1. I know that plagiarism is wrong. Plagiarism is to use another's work and pretend that it is one's own.
2. I have used the IEEE convention for citation and referencing. Each contribution to, and quotation in, this report from the work(s) of other people has been attributed, and has been cited and referenced.
3. This report is my own work.
4. I have not allowed, and will not allow, anyone to copy my work with the intention of passing it off as their own work or part thereof.



November 6, 2024

Rory Schram

Date

Total Word Count = 20646

Acknowledgements

At the start of my engineering degree, a friend of my parents, who happens to be an engineer himself, heard that I had been accepted into the electrical engineering faculty at UCT. I asked him for any advice that he might have for me, anything that could potentially help me through the four years that lay ahead of me. He said one thing to me, ‘Make a group of close engineering friends, stick together, and you’ll get each other through’. This was some of the best advice that I have ever received. To everyone in the engineering friend group, getting to know everyone over the last few years has been one of the coolest experiences in my life. Thank you for all the memories made. I cannot wait to see what interesting things everyone gets up to in the coming years.

A special mention must be made of all the members of the radar lab on the 7th floor of the Menzies building. Thank you for welcoming me, as an undergrad student, so openly into the lab. Working with everyone in the lab over the last few weeks has been a fantastic experience, and I am truly grateful for all the enthusiastic help that has been offered to me by various members of the lab over the last few weeks.

Lastly, my family. Mum, Dad, Nic, and Mike, without your support, none of this would be possible. Mum and Dad, as I have grown older and hopefully slightly wiser, my appreciation towards your decisions to prioritise the education of us three brothers has grown exponentially. Thank you for all the support over the years, I really appreciate it.

Abstract

Every day without fail, all around the world, there are thousands of weather balloons that are launched into the atmosphere for meteorological observation and research applications. These weather balloons are all comprised of a latex balloon that is filled with helium, and a radiosonde unit that hangs below the balloon itself. This radiosonde module plays a very important role in the measurement of atmospheric conditions within which the balloon resides, as it contains the numerous electrical components that give it the ability to measure characteristics of the atmosphere and the position in which the radiosonde finds itself in, as well as transmit those readings back to a ground station.

Currently, there are only a handful of companies around the world that design, manufacture, and sell radiosonde modules. These companies essentially have a monopoly on the entire market. One of the hindrances to companies/individuals designing and manufacturing their own radiosonde modules is the complicated process of transmitting the recorded information back to a ground station. Since the companies that manufacture the radiosonde modules have closed designs on all of their components, information is not widely available as to the exact inner workings of their designs for their transmission systems, other than the broad modulation schemes. It is therefore of paramount importance that alternative transmission schemes to the schemes that are employed by the few companies that manufacture radiosondes are explored if alternative designs to the mass-manufactured models are desired.

This report outlines research into an alternative transmission system based on the [Long Range \(LoRa\)](#) communication system. While LoRa is still a proprietary communication system, it is widely available due to its popularity among hobbyist communities, as well as its expanding footprint within the [Internet of Things \(IOT\)](#) community of devices. Reasons for popularity within these communities include the long-range transmission capabilities of the communication protocol, as well as its low cost, which makes it an excellent choice for the disposable radiosonde modules that are used for atmospheric observations.

A transmission and receiver system was designed, simulated, and built, based around the LoRa transmission protocol. Tests were then performed on the system to determine the optimal LoRa parameters for the usage of the protocol in radiosonde modules. From testing and simulation data, the best bandwidth was determined to be 62.5kHz, and the best spreading factor was determined to be 11.

Contents

List of Figures

List of Tables

Acronyms

Chapter 1

Introduction

This report outlines a novel use of the [Orthogonal Frequency Division Multiplexing \(OFDM\)](#) modulation technique as the backbone of the waveform for a [Radio Detection and Ranging \(RADAR\)](#) system as an aid to object classification. Some research into OFDM and RADAR as a whole is presented, followed by the design of the transmission system and the waveform itself, and then validation of the system is outlined, finally, tests are performed to determine the realistic performance of the system as a whole at classifying objects. In this introduction chapter, some background information is presented, followed by a problem statement, objectives, system requirements, and scope and limitations.

1.1 Background

RADAR technology has unlocked the ability for humans to be able to see the world around us with a new perspective. This ability to be able to see objects and more specifically, to see information such as position and velocity about these objects has helped with the development of devices and services that are of paramount importance to society. All the current use cases of RADAR do however lack the ability to determine exactly what object is being seen by the overall RADAR system. That is where the use of the OFDM waveform in a RADAR system becomes useful.

1.2 Problem Statement

Current RADAR technology works very well when determining the distance and direction of an object, however, it does not cope well with specific object classification tasks. One of the reasons for this is that current RADAR utilize either a pulse, continuous wave, or chirp waveform, which does not allow for object detection through statistical analysis due to the simple nature of the waveform. This is a drawback of using RADAR systems, since if object classification is desired, then a combination of radar and some other technology such as cameras would have to be used which increases the cost and complexity of the system as a whole.

1.3 Objectives

The goal of this project is to build a RADAR system that can simultaneously act as a normal RADAR which can determine the distance and direction of an object, as well as classify the specific object that it is looking at when compared to other example objects. The aim is to implement an OFDM based waveform into a RADAR system that would give the flexibility to analyze the returned signal statistically and determine what exactly the object is. The goal is to make a non-realtime system, that can distinguish between three different objects.

1.4 System Requirements

Since this system is very experimental in nature, the requirements are quite broad as of writing this, at the beginning of the project **OBVIOUSLY NEED TO CHANGE THIS EVENTUALLY**. The system needs to perform the following tasks.

1. Be able to operate as a normal RADAR. This entails determining range, azimuth, and elevation.
2. Be able to classify between three separate reflectors/scatterers.

1.5 Scope and Limitations

The scope of this project has been set to not include design of RADAR hardware specifically. This is because design of RADAR hardware is a complex task that would probably encompass an entire masters project in and of itself. Therefore, the RADAR hardware portion of the project will be handled by a [Software Defined Radio \(SDR\)](#). This extrapolates the complex RADAR hardware design aspect away from the project and allows me to focus on the data collection and processing aspect of the project.

Chapter 2

Literature Review

This chapter aims to add context to the entire project by exploring the existing literature on RADAR systems, the OFDM modulation scheme, and the combination of the two within a single system in order to achieve the objective of object classification. In order to get to a level where the topic of object classification can be discussed, one must first delve into the fundamental operation of RADAR and OFDM based systems. Once one has a strong understanding of these basics, the combination of the two can be discussed in regard to object classification.

2.1 RADAR

2.1.1 Brief RADAR History

The basic idea of RADAR was experimented with in the classical electromagnetic radiation experiments of the 1880s performed by Heinrich Hertz [?]. These experiments set out to prove the previous theoretical work done by James Clerk Maxwell. Maxwell came up with a formula that described electromagnetic fields, and he hypothesized that this formula would apply to both light and radio waves since they were both examples of electromagnetic radiation, just at very different frequencies. The work done by Maxwell led to the discovery that electromagnetic waves can be reflected by metallic objects and refracted by a dielectric medium, just like light can [?]. This work did not go unnoticed, and a patent for an ‘an obstacle detector and ship navigation device’ was issued in 1904 to Christian Hülsmeyer, a German engineer [?]. Work on RADAR then slowed down due to a lack of interest from governmental authorities until the early 1930s, when the development of long-range bombers prompted the major countries of the world to develop technologies which could detect these hostile aircraft.

2.1.2 RADAR Basics

The fundamental operation of a simple single pulse RADAR system relies on three physical fundamental properties of the universe [?] which are listed below:

1. **Reflection of electromagnetic waves:** This rule describes how a radio wave will be reflected back towards a transmitter of said radio wave if the object is placed directly in front of the transmitter. This reflection indicates that the object is in front of the transmitter.
2. **Electromagnetic energy travels through air at a constant speed:** This rule describes how the electromagnetic waves transmitted by an antenna propagate through the transmission medium, usually air for our earth’s use cases, at roughly the speed of light, c . This velocity c equates to $299,792,458 \text{ m.s}^{-1}$
3. **Electromagnetic energy normally travels through space in a straight line:** This describes how the energy transmitted by an antenna in a radar system propagates through space in a

straight line. This is important because it means that the energy of the RADAR system can be directed in a specific direction by the antenna system, which means that the reflecting object's direction (azimuth and elevation) can be determined.

Using the above-mentioned physical properties, the distance, azimuth, and elevation of the object that is being looked at by the radar system can be determined.

Since RADAR utilizes the electromagnetic spectrum, there are distinct advantages concerning the use of RADAR systems [?]. The main advantage is that, unlike humans, RADAR systems can operate day and night, 24/7, over far distances, in good or bad weather. Compared to human eyes, this is much better. The above example of a RADAR system is that of a simple single pulse RADAR. In the next section I want to outline the other type of RADAR system that I might use in my OFDM system, a pulsed RADAR system.

2.2 OFDM

2.2.1 Brief OFDM History

The idea of OFDM transmission techniques has been around for many years, however, it was never implemented in communication channels until the appearance of mass market applications coincided with the availability of efficient software and electronic technologies [?]. Before OFDM however, there was [Frequency Division Multiplexing \(FDM\)](#).

2.2.1.1 FDM

FDM system innovation was built out of necessity by telegraph companies hoping to increase the amount of users that could utilize their transmission lines so as to increase profits from their systems [?]. Transmission companies needed a method to have multiple messages being sent on the same transmission line at one time. Other methods had been used such as [Time Division Multiplexing \(TDM\)](#), and [Time Division Multiple Access \(TDMA\)](#). These methods were however limited by burst speed which was itself limited by inter-symbol interference. Around the 1920s, FDM became the main carrier system for telephone companies. The first major company to deploy the system was ??.

2.2.2 OFDM Basics

[OFDM](#) is a method of data transmission that breaks information into bit chunks that are sent in parallel over multiple channels [?]. The OFDM transmission scheme builds upon FDM where multiple channels are created over a specific bandwidth, and bits of information are sent on each channel in parallel. The main difference between FDM and OFDM is therefore the orthogonality of the OFDM signal. Pictured below in figure ?? is an OFDM, and FDM based waveform. As can be seen, all the peaks of the OFDM waveform have zero interference with any other part of the signal, whereas, with the FDM waveform, the peaks have significant interference from the other channels since the channels are not spaced orthogonally in regard to each other.




Figure 2.1: OFDM and FDM Waveforms

The above figure gives a broad idea of what goes into an OFDM-based signal, however in practice, the signal used will have vastly more complexity added on concerning error correction and data formats in general. The base signal however will still revolve around the idea of orthogonal carriers.

2.3 Fresnel Zones

2.4 LoRa Theory of Operation

2.4.1 Frequency Shift Keying

2.4.2 The Chirp

2.4.3 Bandwidth

2.4.4 Spreading Factor

2.4.5 LoRa Data Packets

2.4.6 LoRa Transmission Parameters

2.4.6.1 Symbol Rate and Symbol Time

2.4.6.2 Preamble Time

2.4.6.3 Payload Time

2.4.6.4 Packet Time

2.5 Critique of Literature

Chapter 3

System Design

[?]

3.1 Requirement Analysis

3.1.1 Overall System Requirements

3.1.2 Overall System Specifications

3.2 Modules and Sub-modules

3.3 Transmission Module Component Selection

3.3.1 Microcontroller Unit

3.3.2 Sensor Module

3.3.3 LoRa Module

3.3.4 Display and Control Module

3.3.5 Power Circuitry

3.4 Receive Module Component Selection

3.4.1 The Microcontroller Unit

3.4.2 LoRa Module

3.4.3 Display and Control Module

3.5 Hardware Interface Design

3.5.1 Transmission Module Interface Design

3.5.2 Receive Module Interface Design

3.5.3 Implementation of Transmission Circuit Design

3.5.4 Implementation of Receiver Circuit Design

3.6 Software Design

3.6.1 Software Design and Implementation for Transmission Circuit

3.6.1.1 Reading GPS Data

3.6.1.2 Reading Temperature, Pressure, and Humidity Data

3.6.1.3 Calculating Altitude

3.6.1.4 Construction of Data Packet

3.6.1.5 Transmitting Data

3.6.1.6 Handling Mode Changes

3.6.2 Software Design and Implementation for Receiver Circuit

3.6.2.1 Receiver Interface with LoRa Module

3.6.2.2 Handling Mode Changes

3.7 PCB Design

Chapter 4

Validation and Simulation

[?]

4.1 Validation

4.1.1 Transmitter Validation

4.1.1.1 Power Module

4.1.1.2 Microcontroller

4.1.1.3 Sensor Modules

4.1.1.4 LoRa module and Display and Control Module

4.1.2 Receiver Validation

4.2 Simulation

Chapter 5

Methodology

[?]

5.1 Research Design and Approach

5.2 Data Collection

5.3 Shorter Range Tests

5.4 Long-Range Test

Chapter 6

Results

This section outlines the results of the experiments performed that are outlined in section ???. Discussion and analysis of results will not form part of this chapter, but rather the raw data captured will be presented for all the important tests that took place. [?]

6.1 Same Room Test

6.2 100m Test

6.3 300m Test

6.4 500m Test

6.5 20km Test

6.6 Average RSSI Values with Distance

Chapter 7

Discussion

[?]

7.1 RSSI Values with Distance

7.2 Overall Testing Performance

7.3 Determining the Optimal Packet Structure

7.4 Determining the Optimal LoRa Parameters

Chapter 8

Conclusion and Recommendations

[?]

Bibliography

- [1] M. Skolnik. Radar - detection, military, technology | britannica. [Online]. Available: <https://www.britannica.com/technology/radar/History-of-radar>
- [2] W. Christian. Physical fundamentals of the radar principle. [Online]. Available: <https://www.radartutorial.eu/01.basics/Physical%20fundamentals%20of%20the%20radar%20principle.en.html>
- [3] S. B. Weinstein, “The history of orthogonal frequency-division multiplexing.” [Online]. Available: <https://ieeexplore.ieee.org/stamp/stamp.jsp?tp=&arnumber=5307460>
- [4] G. Wright. What is orthogonal frequency-division multiplexing (OFDM)? [Online]. Available: <https://www.techtarget.com/searchnetworking/definition/orthogonal-frequency-division-multiplexing>

Chapter 9

Appendix

[?]

9.1 Full Transmitter Circuit Schematic

9.2 Full Receiver Circuit Schematic

9.3 Long Range Test Interference

9.4 GitHub Link

9.5 Ethics Clearance