

Practical Implementation of an OFDM Based Active Radar System for Target Classification



Prepared by:

Rory Schram

Prepared for:

Dr Stephen Paine

Department of Electrical Engineering

University of Cape Town

May 29, 2025

Declaration

1. I know that plagiarism is wrong. Plagiarism is to use another's work and pretend that it is one's own.
2. I have used the IEEE convention for citation and referencing. Each contribution to, and quotation in, this report from the work(s) of other people has been attributed, and has been cited and referenced.
3. This report is my own work.
4. I have not allowed, and will not allow, anyone to copy my work with the intention of passing it off as their own work or part thereof.



May 29, 2025

Rory Schram

Date

Total Word Count = 20646

Acknowledgements

At the start of my engineering degree, a friend of my parents, who happens to be an engineer himself, heard that I had been accepted into the electrical engineering faculty at UCT. I asked him for any advice that he might have for me, anything that could potentially help me through the four years that lay ahead of me. He said one thing to me, ‘Make a group of close engineering friends, stick together, and you’ll get each other through’. This was some of the best advice that I have ever received. To everyone in the engineering friend group, getting to know everyone over the last few years has been one of the coolest experiences in my life. Thank you for all the memories made. I cannot wait to see what interesting things everyone gets up to in the coming years.

A special mention must be made of all the members of the radar lab on the 7th floor of the Menzies building. Thank you for welcoming me, as an undergrad student, so openly into the lab. Working with everyone in the lab over the last few weeks has been a fantastic experience, and I am truly grateful for all the enthusiastic help that has been offered to me by various members of the lab over the last few weeks.

Lastly, my family. Mum, Dad, Nic, and Mike, without your support, none of this would be possible. Mum and Dad, as I have grown older and hopefully slightly wiser, my appreciation towards your decisions to prioritise the education of us three brothers has grown exponentially. Thank you for all the support over the years, I really appreciate it.

Abstract

Every day without fail, all around the world, there are thousands of weather balloons that are launched into the atmosphere for meteorological observation and research applications. These weather balloons are all comprised of a latex balloon that is filled with helium, and a radiosonde unit that hangs below the balloon itself. This radiosonde module plays a very important role in the measurement of atmospheric conditions within which the balloon resides, as it contains the numerous electrical components that give it the ability to measure characteristics of the atmosphere and the position in which the radiosonde finds itself in, as well as transmit those readings back to a ground station.

Currently, there are only a handful of companies around the world that design, manufacture, and sell radiosonde modules. These companies essentially have a monopoly on the entire market. One of the hindrances to companies/individuals designing and manufacturing their own radiosonde modules is the complicated process of transmitting the recorded information back to a ground station. Since the companies that manufacture the radiosonde modules have closed designs on all of their components, information is not widely available as to the exact inner workings of their designs for their transmission systems, other than the broad modulation schemes. It is therefore of paramount importance that alternative transmission schemes to the schemes that are employed by the few companies that manufacture radiosondes are explored if alternative designs to the mass-manufactured models are desired.

This report outlines research into an alternative transmission system based on the [Long Range \(LoRa\)](#) communication system. While LoRa is still a proprietary communication system, it is widely available due to its popularity among hobbyist communities, as well as its expanding footprint within the [Internet of Things \(IOT\)](#) community of devices. Reasons for popularity within these communities include the long-range transmission capabilities of the communication protocol, as well as its low cost, which makes it an excellent choice for the disposable radiosonde modules that are used for atmospheric observations.

A transmission and receiver system was designed, simulated, and built, based around the LoRa transmission protocol. Tests were then performed on the system to determine the optimal LoRa parameters for the usage of the protocol in radiosonde modules. From testing and simulation data, the best bandwidth was determined to be 62.5kHz, and the best spreading factor was determined to be 11.

Contents

List of Figures	vii
List of Tables	viii
Acronyms	ix
1 Introduction	1
1.1 Background	1
1.2 Problem Statement	1
1.3 Objectives	1
1.4 System Requirements	2
1.4.1 Hardware Requirements	2
1.5 Scope and Limitations	2
2 Literature Review	3
2.1 RADAR	3
2.1.1 History	3
2.1.2 RADAR Basics	3
2.2 OFDM	4
2.2.1 Brief OFDM History	4
2.2.1.1 FDM	4
2.2.1.2 OFDM	5
2.3 Fresnel Zones	6
2.4 LoRa Theory of Operation	6
2.4.1 Frequency Shift Keying	6
2.4.2 The Chirp	6
2.4.3 Bandwidth	6
2.4.4 Spreading Factor	6
2.4.5 LoRa Data Packets	6
2.4.6 LoRa Transmission Parameters	6
2.4.6.1 Symbol Rate and Symbol Time	6
2.4.6.2 Preamble Time	6
2.4.6.3 Payload Time	6
2.4.6.4 Packet Time	6
2.5 Critique of Literature	6
3 System Design	7
3.1 Requirement and Specification Analysis	7
3.1.1 System Requirements	7
3.1.2 System Specifications	7
3.2 Modules and Sub-modules	7

3.3	Transmission Module Component Selection	7
3.4	Receive Module Component Selection	7
3.5	Hardware Interface Design	7
3.6	Software Design	7
3.7	PCB Design	7
4	Validation and Simulation	8
4.1	Validation	8
4.1.1	Transmitter Validation	8
4.1.1.1	Power Module	8
4.1.1.2	Microcontroller	8
4.1.1.3	Sensor Modules	8
4.1.1.4	LoRa module and Display and Control Module	8
4.1.2	Receiver Validation	8
4.2	Simulation	8
5	Methodology	9
5.1	Research Design and Approach	9
5.2	Data Collection	9
5.3	Shorter Range Tests	9
5.4	Long-Range Test	9
6	Results	10
6.1	Same Room Test	10
6.2	100m Test	10
6.3	300m Test	10
6.4	500m Test	10
6.5	20km Test	10
6.6	Average RSSI Values with Distance	10
7	Discussion	11
7.1	RSSI Values with Distance	11
7.2	Overall Testing Performance	11
7.3	Determining the Optimal Packet Structure	11
7.4	Determining the Optimal LoRa Parameters	11
8	Conclusion and Recommendations	12
	Bibliography	13
9	Appendix	14
9.1	Full Transmitter Circuit Schematic	14
9.2	Full Receiver Circuit Schematic	14
9.3	Long Range Test Interference	14
9.4	GitHub Link	14
9.5	Ethics Clearance	14

List of Figures

2.1 OFDM and FDM Waveforms 5

List of Tables

Acronyms

AT&T American Telephone and Telegraph Company

FDM Frequency Division Multiplexing

IOT Internet of Things

LoRa Long Range

OFDM Orthogonal Frequency Division Multiplexing

RADAR Radio Detection and Ranging

SDR Software Defined Radio

TDM Time Division Multiplexing

TDMA Time Division Multiple Access

UCT University of Cape Town

USRP Universal Software Radio Peripheral

Chapter 1

Introduction

This report outlines the design and implementation of a single pulse classification [Radio Detection and Ranging \(RADAR\)](#) that uses an [Orthogonal Frequency Division Multiplexing \(OFDM\)](#) based signal with a flat top spectra. A literature review of RADAR and OFDM is presented, followed by the literature concerned with using OFDM signals in classification RADARs. Next, the design of the surrounding system to transmit and receive data, process the data, and analyse the results is presented. Following this, an experimental design is laid out and explained in detail. Next a simulation is performed and then the real world testing is performed. The results and comparison of the simulation and real world experiment are then discussed.

1.1 Background

RADAR technology has unlocked the ability for humans to be able to see the world around us with a new perspective. This ability to be able to see objects and more specifically, to see information such as position and velocity about these objects has helped with the development of devices and services that are of paramount importance to society. All the current use cases of RADAR do however lack the ability to determine exactly what object is being seen by the overall RADAR system. That is where the use of the OFDM waveform in a RADAR system becomes useful.

1.2 Problem Statement

Current RADAR technology works very well when determining the distance and direction of an object, however, it does not cope well with specific object classification tasks. One of the reasons for this is that current RADAR utilize either a pulse, continuous wave, or chirp waveform, which does not allow for object detection through statistical analysis due to the simple nature of the waveform. This is a drawback of using RADAR systems, since if object classification is desired, then a combination of radar and some other technology such as cameras would have to be used which increases the cost and complexity of the system as a whole.

1.3 Objectives

The goal of this project is to build a RADAR system that can simultaneously act as a normal RADAR which can determine the distance and direction of an object, as well as classify the specific object that it is looking at when compared to other example objects. The aim is to implement an OFDM based waveform into a RADAR system that would give the flexibility to analyze the returned signal statistically and determine what exactly the object is. The goal is to make a non-realtime system, that can distinguish between three different objects.

1.4 System Requirements

The RADAR project has the following requirements:

1.4.1 Hardware Requirements

The main hardware for the project should be widely available computer/scientific equipment. The availability of computer equipment is generally larger than most of the other required equipment such as the [Software Defined Radio \(SDR\)](#) equipment. The SDR equipment is much less widely available due to the high price of the equipment itself. This is fine however, since the [University of Cape Town \(UCT\)](#) has in their control multiple [Universal Software Radio Peripheral \(USRP\)](#) N210 devices designed and manufactured by Ettus research which will be perfect for my project.

test 1234

1. Be able to operate as a normal RADAR. This entails determining range, azimuth, and elevation.
2. Be able to classify between three separate reflectors/scatterers.

1.5 Scope and Limitations

The scope of this project has been set to not include design of RADAR hardware specifically. This is because design of RADAR hardware is a complex task that would probably encompass an entire masters project in and of itself. Therefore, the RADAR hardware portion of the project will be handled by a [SDR](#). This extrapolates the complex RADAR hardware design aspect away from the project and allows me to focus on the data collection and processing aspect of the project.

Chapter 2

Literature Review

The aim of this chapter, is to clarify the existing literature that surrounds the topics of [RADAR](#) and [OFDM](#). This aims to add context to the broader project, since having an understanding of current technologies involved in this project is particularly important since there are multiple complex moving parts of this project. Especially as we move towards the latter parts of the project. In order to get to a level where the topic of object classification can be discussed, one must first delve into the fundamental operation of RADAR and OFDM based systems. Once one has a strong understanding of these basics, the combination of the two can be discussed in regard to object classification. I will separate the literature review into multiple distinct and vastly different sections, with the first being RADAR.

2.1 RADAR

2.1.1 History

The fundamental idea behind RADAR systems and the technology itself were first theorized during the classical electromagnetic radiation experiments of the 1880s performed by Heinrich Hertz [1]. These experiments set out to prove the previous theoretical work achieved by James Clerk Maxwell. Maxwell came up with the formulae that described electromagnetic fields, and he hypothesized that this formula would apply to both light and radio waves since they were both examples of electromagnetic radiation just at vastly different frequencies. This has obviously since been proved, with visible light roughly falling into the 400THz to 700THz, with the electromagnetic spectrum roughly spanning the spectrum from The work done by Maxwell led to the discovery that electromagnetic waves can be reflected by metallic objects and refracted by a dielectric medium, just like light can [1]. This work did not go unnoticed and a patent for an ‘an obstacle detector and ship navigation device’ was issued in 1904 to Christian Hülsmeyer, a German engineer [1]. Work on RADAR then slowed down due to a lack of interest from governmental authorities until the early 1930s, when the development of long-range bombers prompted the major countries of the world to develop technologies which could detect these hostile aircraft.

2.1.2 RADAR Basics

The fundamental operation of a simple single pulse RADAR system relies on three physical fundamental properties of the universe [2] which are listed below:

1. **Reflection of electromagnetic waves:** This rule describes how a radio wave will be reflected back towards a transmitter of said radio wave if the object is placed directly in front of the transmitter. This reflection indicates that the object is in front of the transmitter.
2. **Electromagnetic energy travels through air at a constant speed:** This rule describes how the electromagnetic waves transmitted by an antenna propagate through the transmission

medium, usually air for our earth's use cases, at roughly the speed of light, c . This velocity c equates to $299,792,458 \text{ m.s}^{-1}$

3. **Electromagnetic energy normally travels through space in a straight line:** This describes how the energy transmitted by an antenna in a radar system propagates through space in a straight line. This is important because it means that the energy of the RADAR system can be directed in a specific direction by the antenna system, which means that the reflecting object's direction (azimuth and elevation) can be determined.

Using the above-mentioned physical properties, the distance, azimuth, and elevation of the object that is being looked at by the radar system can be determined.

Since RADAR utilizes the electromagnetic spectrum, there are distinct advantages concerning the use of RADAR systems [2]. The main advantage is that, unlike humans, RADAR systems can operate day and night, 24/7, over far distances, in good or bad weather. Compared to human eyes, this is much better. The above example of a RADAR system is that of a simple single pulse RADAR. In the next section I want to outline the other type of RADAR system that I might use in my OFDM system, a pulsed RADAR system.

2.2 OFDM

2.2.1 Brief OFDM History

The idea of OFDM transmission techniques has been around for many years, however, it was never implemented in communication channels until the appearance of mass market applications coincided with the availability of efficient software and electronic technologies [3]. Before OFDM however, there was [Frequency Division Multiplexing \(FDM\)](#).

2.2.1.1 FDM

FDM system innovation was built out of necessity by telegraph companies hoping to increase the amount of users that could utilize their transmission lines so as to increase profits from their systems [3]. Transmission companies needed a method to have multiple messages being sent on the same transmission line at one time. Other methods had been used such as [Time Division Multiplexing \(TDM\)](#), and [Time Division Multiple Access \(TDMA\)](#). These methods were however limited by burst speed which was itself limited by inter-symbol interference. Around the 1920s, FDM became the main carrier system for telephone companies. The first major company to deploy the system was [American Telephone and Telegraph Company \(AT&T\)](#). This first system used 8kHz subchannel spacing with 4kHz channel size. This form of transmission system later developed into systems that had more sub carrier channels with less subcarrier spacing. There were however some drawbacks to FDM, which are highlighted below:

1. **Waste of frequency:** Due to the large subcarrier spacing, FDM wasted a lot of precious frequency spectrum to these so-called 'guard' bands. As the frequency spectrum became more crowded throughout the years, these guards band became a liability because spectrum access became so crowded.
2. **Using different modulators for the various sub-channels:** In the old systems, each sub-channel had a separate modulator in the up-mixing process. This multiplication process became tedious once there were lots of sub-carriers.

To compensate for the waste of frequency issue, the concept of OFDM was introduced, where each subcarrier overlapped except they had non-interfering spectra [3].

2.2.1.2 OFDM

As mentioned before, OFDM is a method of data transmission that breaks information into bit chunks that are sent in parallel over multiple channels [4]. The OFDM transmission scheme builds upon FDM where multiple channels are created over a specific bandwidth, and bits of information are sent on each channel in parallel. The main difference between FDM and OFDM is therefore the orthogonality of the OFDM signal. Pictured below in figure 2.1 is an OFDM, and FDM based waveform. As can be seen, all the peaks of the OFDM waveform have zero interference with any other part of the signal, whereas, with the FDM waveform, the peaks have significant interference from the other channels since the channels are not spaced orthogonally in regard to each other.




Figure 2.1: OFDM and FDM Waveforms

The above figure gives a broad idea of what goes into an OFDM-based signal, however in practice, the signal used will have vastly more complexity added on concerning error correction and data formats in general. The base signal however will still revolve around the idea of orthogonal carriers.

2.3 Fresnel Zones

2.4 LoRa Theory of Operation

2.4.1 Frequency Shift Keying

2.4.2 The Chirp

2.4.3 Bandwidth

2.4.4 Spreading Factor

2.4.5 LoRa Data Packets

2.4.6 LoRa Transmission Parameters

2.4.6.1 Symbol Rate and Symbol Time

2.4.6.2 Preamble Time

2.4.6.3 Payload Time

2.4.6.4 Packet Time

2.5 Critique of Literature

Chapter 3

System Design

[2]

3.1 Requirement and Specification Analysis

3.1.1 System Requirements

3.1.2 System Specifications

3.2 Modules and Sub-modules

3.3 Transmission Module Component Selection

3.4 Receive Module Component Selection

3.5 Hardware Interface Design

3.6 Software Design

3.7 PCB Design

Chapter 4

Validation and Simulation

[2]

4.1 Validation

4.1.1 Transmitter Validation

4.1.1.1 Power Module

4.1.1.2 Microcontroller

4.1.1.3 Sensor Modules

4.1.1.4 LoRa module and Display and Control Module

4.1.2 Receiver Validation

4.2 Simulation

Chapter 5

Methodology

[2]

5.1 Research Design and Approach

5.2 Data Collection

5.3 Shorter Range Tests

5.4 Long-Range Test

Chapter 6

Results

This section outlines the results of the experiments performed that are outlined in section 5. Discussion and analysis of results will not form part of this chapter, but rather the raw data captured will be presented for all the important tests that took place. [2]

6.1 Same Room Test

6.2 100m Test

6.3 300m Test

6.4 500m Test

6.5 20km Test

6.6 Average RSSI Values with Distance

Chapter 7

Discussion

[2]

7.1 RSSI Values with Distance

7.2 Overall Testing Performance

7.3 Determining the Optimal Packet Structure

7.4 Determining the Optimal LoRa Parameters

Chapter 8

Conclusion and Recommendations

[2]

Bibliography

- [1] M. Skolnik. Radar - detection, military, technology | britannica. [Online]. Available: <https://www.britannica.com/technology/radar/History-of-radar>
- [2] W. Christian. Physical fundamentals of the radar principle. [Online]. Available: <https://www.radartutorial.eu/01.basics/Physical%20fundamentals%20of%20the%20radar%20principle.en.html>
- [3] S. B. Weinstein, “The history of orthogonal frequency-division multiplexing.” [Online]. Available: <https://ieeexplore.ieee.org/stamp/stamp.jsp?tp=&arnumber=5307460>
- [4] G. Wright. What is orthogonal frequency-division multiplexing (OFDM)? [Online]. Available: <https://www.techtarget.com/searchnetworking/definition/orthogonal-frequency-division-multiplexing>

Chapter 9

Appendix

[\[2\]](#)

9.1 Full Transmitter Circuit Schematic

9.2 Full Receiver Circuit Schematic

9.3 Long Range Test Interference

9.4 GitHub Link

9.5 Ethics Clearance