

Toolchain, board, broker, and project kickoff

TinyGo, a blinking board, a local broker, and your team

Dinu-Ștefan Rusu

FILS, Universitatea Politehnica București · Week 2

What this lab is for



Put code on a device

Install TinyGo, build the blink program for your board or for the simulator, flash it, and read what it prints on the serial console.

TIME

2 hours



Run your own broker

Install Mosquitto, publish and subscribe from the command line, then agree on a project idea that meets all five requirements.

SUBMIT

Branch `lab-1` in your team repository, before next lab

Bring a board if you have one. If you do not, Task III replaces Task II and is worth the same.

Where your work goes

1. One repository per team. Use the Flutter app repository from ADMD: the project extends that app.
2. Create the branch and the folder this lab writes into:

```
git checkout -b lab-1  
mkdir -p device/blink
```

3. Open a pull request from `lab-1` on the first commit. Everything you are graded on goes in its description.

Hint

Pull requests, not pushes to main. Your individual mark is read from your own commits.

Install Go and TinyGo

```
# macOS
brew install go
brew tap tinygo-org/tools && brew install tinygo

# Windows, with Scoop
scoop install go tinygo

# Debian and Ubuntu: Go from go.dev/dl, TinyGo from its releases page
sudo dpkg -i tinygo_*.deb
tinygo version
```

Install Go first: TinyGo reuses the Go standard library and the module cache. If `tinygo version` is not found, the TinyGo `bin` folder is not on your `PATH`.

TASK I

Pick a board and confirm its target

1. Pick one: a Raspberry Pi Pico, an ESP32-C3 board, or an ESP32-S3 board. With no hardware, go to Task III.

2. List what your TinyGo can build for:

```
tinygo targets
```

3. Take the target name from your board's page on the TinyGo site. The Pico is `pico`, a plain ESP32-C3 board is `esp32c3`.

DONE WHEN

- ☐ `tinygo version` prints a version.
- ☐ Your target appears in the output of `tinygo targets`.
- ☐ The target name is written in the pull request description.

Watch out

Board variants have their own targets, such as `xiao-esp32c3`. Check the board page for the exact name.

The blink program, in full

```
package main
import "machine"
import "time"
func main() {
    led := machine.LED
    led.Configure(machine.PinConfig{Mode: machine.PinOutput})
    for {
        led.Set(!led.Get())
        println("blink")
        time.Sleep(500 * time.Millisecond)
    }
}
```

Save it as `device/blink/main.go`. Use the LED pin your board page names.

Flash the board and read the console

1. Plug the board in with a data cable, not a charge-only cable.
2. Build and flash in one command:

```
tinygo flash -target=pico ./device/blink
```

3. Watch the LED, then read what the program prints:

```
tinygo monitor
```

4. Stop the monitor with Ctrl-C.

DONE WHEN

- ☐ The LED blinks about once a second.
- ☐ `tinygo monitor` prints one line per blink.
- ☐ A photo or a short video of the board is in the pull request.

No board: the same program in Wokwi

1. Open wokwi.com and start a new project on the ESP32-C3 DevKitM-1 board.
2. Add an LED and a 220 ohm resistor from the parts menu, wired to a free GPIO pin. Use that pin in the code.
3. Build the firmware on your laptop:

```
tinygo build -o blink.elf \  
-target=esp32c3 ./device/blink
```

4. Press F1, choose *Upload Firmware and Start Simulation*, and pick `blink.elf`.

DONE WHEN

- ☐ The simulated LED blinks.
- ☐ The Wokwi serial monitor prints one line per blink.
- ☐ One screenshot shows the board and the serial output.

Install the Mosquitto broker

```
# macOS  
brew install mosquitto  
  
# Debian and Ubuntu  
sudo apt install mosquitto mosquitto-clients  
  
mosquitto -v          # foreground, port 1883, one line per event
```

Hint

Mosquitto 2 and later accept local connections only until you configure a listener. In this lab that default is what you want.

Publish and subscribe from two terminals

1. Leave the broker running. In a second terminal, subscribe to a wildcard topic:

```
mosquitto_sub -h localhost -t mec/lab1/#
```

2. In a third terminal, publish to a subtopic:

```
mosquitto_pub -h localhost \  
-t mec/lab1/hello -m "1"
```

3. Publish three more messages, changing the subtopic each time.

DONE WHEN

- ☐ The subscriber prints every message the publisher sends.
- ☐ Messages from different subtopics all reach the wildcard subscription.
- ☐ The broker log lists both clients connecting.

Your team and your project idea

1. Form a team of at most three. Fill one row in the team sheet in the Teams channel: names, GitHub handles, repository URL.
2. Write the idea in the repository README: one paragraph, then one line for each of the five requirements on the next slide.
3. Show it to me during this lab. Milestone 1 is the team and the idea approved.

DONE WHEN

- ☐ The sheet row is filled and the repository URL opens.
- ☐ The README names the sensor, the transport, and the conflict rule.
- ☐ The idea is approved.

The five requirements your idea must meet

REQUIREMENT

TRUE AT THE DEFENSE

Device component

A TinyGo program on a board or in Wokwi, reading a sensor.

Device to phone

The reading arrives over MQTT or BLE and the app shows it live.

Offline-first

The app works with no network, syncs later, states its conflict rule.

One boundary

Either gRPC with a Go server, or FFI, or a platform channel.

A measured claim

One number your team measured, with the method.

All five, or the project is not approved. Pick an idea where each requirement has an obvious home.

What goes wrong, and what to do

permission denied: /dev/ttyUSB0

Your user is not in the serial port group. Add yourself to `dialout` on Debian and Ubuntu, or `uucp` on Arch, then log out and back in. Do not flash with `sudo`.

no serial ports found

The cable carries power only, or the board is not in its bootloader. Swap the cable, then hold the BOOT button while plugging the board in and release it.

unknown target or board name

The string after `-target=` is not one TinyGo knows. Copy it from `tinygo targets` or from the board's page.

When the broker refuses you

Error: Connection refused

Nothing is listening on port 1883. Start the broker in a terminal with `mosquitto -v` and leave it running while you test.

Connection refused from another machine

The default configuration binds to localhost. Add `listener 1883` and `allow_anonymous true` to `mosquitto.conf`, and open the port in the local firewall. Lab network only.

Address already in use

A broker is already running, often as a system service. Use that one, or stop the service before starting your own.

What the pull request has to contain



Proof it ran

A photo of the blinking board, or a screenshot of the Wokwi simulation, plus the serial output copied as text.



Proof it talks

The two terminals from Task IV, subscriber and publisher, with the messages visible.

ALSO IN THE DESCRIPTION

The board and the target name you used, and a link to the team sheet row.

Open the pull request now, not at the deadline. A branch with no pull request is not a submission, and an empty description is not evidence.

Push before you leave.

Branch lab-1 · blink and serial output in the PR · idea approved