Precision IoT Admin Portal

Use this guide to manage devices, control user access, approve new credential users, and handle password reset links in the live admin portal.

Admin Operations | Devices and Users | EC2 Runtime | Updated April 2026

Quick Navigation

1. What the portal is used for
2. Logging in and ending the session
3. Reading dashboard totals
4. Refreshing synced data
5. Managing devices
6. Managing users
7. Approving new email/password users
8. Troubleshooting common issues

1 Overview

The admin portal is the control surface for monitoring system totals, refreshing synced records, managing user access, and controlling device availability.

Dashboard

View totals for devices, active devices, users, and blocked users.

Devices

Restrict, allow, or delete device records from the backend.

Users

Block, unblock, edit display names, generate reset links, or delete user accounts.

Sync

Force a backend refresh when recently changed records are not visible yet.

2 Login and Access

Logging In

1. **Open the portal**
   Open the admin portal URL in a browser.
2. **Enter credentials**
   Type the admin username and password configured on the EC2 server.
3. **Open the portal**
   After successful authentication, the portal loads the Dashboard tab.

Logging Out

1. **Use logout**
   Click the logout action in the portal.
2. **Session clears**
   The browser session is cleared and the login screen is shown again.

Credential source

Portal credentials are read from environment variables on the server, not from a user table inside the UI.

3 Dashboard

The dashboard is the fastest way to see system-wide counts.

Card	Meaning
Total Devices	All known device records

Card	Meaning
Active Devices	Devices currently allowed
Total Users	All synced user records
Blocked Users	Users currently denied app access

Active Devices **Blocked Users** **Synced Records**

4 Sync Data

Use the **Sync Data** button when you want a fresh backend read immediately instead of waiting for background refresh.

1. **Click Sync Data**
   The portal starts a backend refresh request.
2. **Wait for status**
   The UI shows a temporary sync-in-progress message.
3. **Review results**
   When finished, the portal reloads dashboard totals plus the current users and devices lists.

When to use it

Use sync after a recent app sign-up, unblock action, device change, or backend reconciliation event.

5 Managing Devices

The Devices tab lists each device ID, name, location, status, last seen timestamp, and available actions.

Statuses

Active **Restricted**

Available Actions

1. **Restrict or Allow**
   Click
   Restrict
   to disable an active device, or
   Allow
   to restore a restricted device.

2. **Delete Device**
   Click
   Delete
   and confirm when the device record should be removed completely.

Delete carefully

Deleting a device is more than a temporary restriction. Use restriction for reversible access control and deletion only for permanent removal.

6 Managing Users

The Users tab lists each user ID, email, display name, authentication type, account status, last login, and row-level actions.

Field	Meaning
Auth Type	**Google** or **Email/Password**
Status	**Active** means allowed, **Blocked** means denied
Last Login	Last known sign-in time or **Never**

Actions

1. **Block or Unblock**
   Use these actions to deny or restore app access. Email/password sign-up users are initially blocked and must be unblocked before first login.

2. **Edit Display Name**
   Available for eligible email/password users. A browser prompt asks for the updated display name.

3. **Forgot Password**
   Available for eligible email/password users. The portal generates a password reset link that can be copied and shared.

4. **Delete User**
   Deletes the user from EC2-backed records. Use only for permanent account removal.

Forgot Password limitations

The reset-link action is not shown for Google users and is not shown for Gmail-address users on the password flow.

7 Email/Password Approval Flow

Non-Gmail credential users created from the mobile app require explicit admin approval before first login.

1. **User signs up in the app**
   The app creates the Firebase credential and sends the record to the backend.

2. **Backend stores the user as blocked**
   The account appears in the Users tab with blocked status by default.

3. **Admin reviews the row**
   Find the user in the Users tab and verify the email and display name.

4 **Click Unblock**

This activates the account for sign-in.

5 **User signs in**

The user can then log in with the same email and password from the app.

Expected state before approval

If the user says sign-up succeeded but login is denied, the Users tab should still show that account as
Blocked
until you click
Unblock
.

8 Troubleshooting

Login fails

Verify the admin username and password in the EC2 environment file and restart the PM2 process if credentials changed recently.

User remains blocked

Use **Sync Data**, refresh the Users tab, and verify the status actually changed from **Blocked** to **Active**.

Reset link option is missing

That action only appears for eligible non-Gmail email/password users.

Data looks stale

The portal auto-refreshes visible tab data roughly every 10 seconds, but you can still use **Sync Data** for an immediate backend refresh.

Related runbook

> See
> **change_admin_portal_password.md**
> in the workspace root for admin credential change steps.

Precision IoT Admin Portal Guide