

Precision IoT Admin Portal

Use this guide to manage devices, control user access, approve new credential users, and handle password reset links in the live admin portal.

[Admin Operations](#)[Devices and Users](#)[EC2 Runtime](#)[Updated August 2026](#)

Quick Navigation

1. What the portal is used for
2. Logging in and ending the session
3. Reading dashboard totals
4. Refreshing synced data
5. Managing devices
6. Managing users
7. Approving new email/password users
8. Troubleshooting common issues

1 Overview

The admin portal is the control surface for monitoring system totals, refreshing synced records, managing user access, and controlling device availability.

Dashboard

View totals for devices, active devices, users, and blocked users.

Devices

Restrict, allow, or delete device records from the backend.

Users

Block, unblock, edit display names, generate reset links, delete accounts, and view the devices paired

Sync

Force a backend refresh when recently changed records are not visible yet.

to each user.

2 Login and Access

Logging In

1 Open the portal

Open the admin portal URL in a browser.

2 Enter credentials

Type the admin username and password configured on the EC2 server.

3 Open the portal

After successful authentication, the portal loads the Dashboard tab.

Logging Out

1 Use logout

Click the logout action in the portal.

2 Session clears

The browser session is cleared and the login screen is shown again.

Credential source

Portal credentials are read from environment variables on the server, not from a user table inside the UI.

3 Dashboard

The dashboard is the fastest way to see system-wide counts.

Card	Meaning
Total Devices	All known device records
Active Devices	Devices currently allowed
Total Users	All synced user records
Blocked Users	Users currently denied app access

Active Devices **Blocked Users** **Synced Records**

4 Sync Data

Use the **Sync Data** button when you want a fresh backend read immediately instead of waiting for background refresh.

1 Click Sync Data

The portal starts a backend refresh request.

2 Wait for status

The UI shows a temporary sync-in-progress message.

3 Review results

When finished, the portal reloads dashboard totals plus the current users and devices lists.

When to use it

Use sync after a recent app sign-up, unblock action, device change, or backend reconciliation event.

5 Managing Devices

The Devices tab lists each device ID, name, location, status, last seen timestamp, and available actions.

Statuses

Active **Restricted**

Available Actions

1 Restrict or Allow

Click

Restrict

to disable an active device, or

Allow

to restore a restricted device.

2 Delete Device

Click

Delete

and confirm when the device record should be removed completely.

Delete carefully

Deleting a device is more than a temporary restriction. Use restriction for reversible access control and deletion only for permanent removal.

6 Managing Users

The Users tab lists each user ID, email, display name, authentication type, account status, last login, and row-level actions. Beneath every user row, the portal also shows the Raspberry Pi devices currently paired to that user.

Field	Meaning
Auth Type	Google or Email/Password
Status	Active means allowed, Blocked means denied
Last Login	Last known sign-in time or Never
Paired Devices	The devices mapped to this user, shown as badges in the row directly below the user

Paired Devices

Directly under each user, a **Paired Devices** row shows which Raspberry Pi devices are currently mapped to that user, so you can see the user-to-device relationship at a glance.

- 1

Device badges

Each paired device appears as a badge showing its device name. Hover over a badge to see its device ID, location, and the date it was paired.
- 2

Device count

A count badge (for example **2/3**) shows how many of the maximum three device slots the user has used. It turns amber when the user reaches the limit of 3.
- 3

Active vs restricted

Active devices show in blue; restricted devices show in red, so you can immediately spot a paired device that has been restricted.
- 4

No devices

Users who have not paired any device show **No devices paired**.

Active device

Restricted device

3/3 limit reached

Device pairing limit

Each user can pair at most

3 devices

. Users add devices from the mobile app by scanning the QR code shown on the Raspberry Pi; this list reflects those pairings.

Actions

1 Block or Unblock

Use these actions to deny or restore app access. Email/password sign-up users are initially blocked and must be unblocked before first login.

2 Edit Display Name

Available for eligible email/password users. A browser prompt asks for the updated display name.

3 Forgot Password

Available for eligible non-Gmail email/password users. The portal generates a password reset link that can be copied and shared.

4 Delete User

Deletes the user from EC2-backed records and Firebase-backed account management. Use only for permanent account removal.

Forgot Password limitations

The reset-link action is not shown for Google users and is not shown for Gmail-address users on the password flow.

7 Email/Password Approval Flow

Non-Gmail credential users created from the mobile app require explicit admin approval before first login.

1 User signs up in the app

The app creates the Firebase credential and sends the record to the backend.

2 Backend stores the user as blocked

The account appears in the Users tab with blocked status by default.

3 Admin reviews the row

Find the user in the Users tab and verify the email and display name.

4 Click Unblock

This activates the account for sign-in.

5 User signs in

The user can then log in with the same email and password from the app.

Expected state before approval

If the user says sign-up succeeded but login is denied, the Users tab should still show that account as

Blocked

until you click

Unblock

.

8 Troubleshooting

Login fails

Verify the admin username and password in the EC2 environment file and restart the PM2 process if credentials changed recently.

User remains blocked

Use **Sync Data**, refresh the Users tab, and verify the status actually changed from **Blocked** to **Active**.

Reset link option is missing

That action only appears for eligible non-Gmail email/password users.

Paired devices not showing for a user

The Paired Devices row reflects active device pairings. If a user recently added or removed a device, click **Sync Data** and refresh the Users tab. A user with no active pairings correctly shows **No devices paired**.

Data looks stale

The portal auto-refreshes visible tab data roughly every 10 seconds, but you can still use **Sync Data** for an immediate backend refresh.

Related runbook

See

`change_admin_portal_password.md`

in the workspace root for admin credential change steps.