This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scripter Modules, refer to the "Guide to Using Scripter Modules" document.

Device Specifications

Device Type:	Lighting Control
Manufacturer:	Chromateq
Firmware Version:	N/A
Model(s):	CQSA 512, CQSA 1024

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scripter Version
2.08.0002-b001	1.4.2

Version History

Module Version	Date	Notes
1_0_0_0	8/15/2018	Initial Version

Module Notes

- Status is not available.

Supported Classes and Examples

SerialClass

```
    InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='CQSA 512')
```

SerialOverEthernetClass

```
    InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='CQSA 512')
```

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	Value
Color	'0' – '99'		

```
# Color example
InterfaceName.Set('Color', '0')
```

Command	Value	Value	Value
ColorMode	'1' – '8'		

```
# ColorMode example
InterfaceName.Set('ColorMode', '1')
```

Command	Value	Value	Value
CurrentZone	'A'	'B'	'C'
	'D'	'E'	'F'

```
# CurrentZone example
InterfaceName.Set('CurrentZone', 'A')
```

Command	Value	Value	Value
Dimmer	'Up'	'Down'	

```
# Dimmer example
InterfaceName.Set('Dimmer', 'Up')
```

Command	Value	Value	Value
DimmerConstrained	'Up'	'Down'	
Qualifier Key	Qualifier Value		
'Dimmer value'	'0' – '9'		

```
# DimmerConstrained example
InterfaceName.Set('DimmerConstrained', 'Up', {'Dimmer value': '0'})
```

Command	Value	Value	Value
Pause	None		

```
# Pause example
InterfaceName.Set('Pause', None)
```

Command	Value	Value	Value
Play	None		

```
# Play example
InterfaceName.Set('Play', None)
```

Command	Value	Value	Value
Speed	'Up'	'Down'	

```
# Speed example
```

```
InterfaceName.Set('Speed', 'Up')
```

Command	Value	Value
SpeedConstrained	'Up'	'Down'
Qualifier Key	Qualifier Value	
'Speed value'	'0' – '9'	

```
# SpeedConstrained example
InterfaceName.Set('SpeedConstrained', 'Up', {'Speed value': '0'})
```

Command	Value
StartScene	None
Qualifier Key	Qualifier Value
'Scene'	'1' – '255'

```
# StartScene example
InterfaceName.Set('StartScene', None, {'Scene': '1'})
```

Command	Value
StopScene	None

```
# StopScene example
InterfaceName.Set('StopScene', None)
```

Cable and Adapter Requirements

Captive Screw to RJ45 Cable

Notes for the Device

Serial communication

Port Type:	RS-232	**Parity:**	None
Baud Rate:	9600	**Stop Bits:**	Two
Data Bits:	8	**Flow Control:**	None

Pin Assignments Diagram

Appendix A. Set Commands

Color 0	\x02CLR00\x03
Color 99	\x02CLR99\x03
Color Mode 1	\x02COLR1\x03
Color Mode 8	\x02COLR8\x03
Current Zone A	\x02ZONEa\x03
Current Zone B	\x02ZONEb\x03
Current Zone C	\x02ZONEc\x03
Current Zone D	\x02ZONEd\x03
Current Zone E	\x02ZONEe\x03
Current Zone F	\x02ZONEf\x03
Dimmer Constrained Down Dimmer value 0	\x02DIM-0\x03
Dimmer Constrained Down Dimmer value 9	\x02DIM-9\x03
Dimmer Constrained Up Dimmer value 0	\x02DIM+0\x03
Dimmer Constrained Up Dimmer value 9	\x02DIM+9\x03
Dimmer Down	\x02DIM--\x03
Dimmer Up	\x02DIM++\x03
Pause None	\x02PAUSE\x03
Play None	\x02PLAY0\x03
Speed Constrained Down Speed value 0	\x02SPD-0\x03
Speed Constrained Down Speed value 9	\x02SPD-9\x03
Speed Constrained Up Speed value 0	\x02SPD+0\x03
Speed Constrained Up Speed value 9	\x02SPD+9\x03
Speed Down	\x02SPD--\x03
Speed Up	\x02SPD++\x03
Start Scene None Scene 1	\x02SC001\x03
Start Scene None Scene 255	\x02SC255\x03
Stop Scene None	\x02STOP0\x03