

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Controller
Manufacturer: Ashton Bentley
Firmware Version: N/A
Model(s): abox DSP

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.1.1

Version History

Module Version	Date	Notes
1_1_0_0	1/23/2017	Removed Screen 1 Input and Screen 2 Input and added Input command. Fixed status not working if using the default Device ID.
1_0_0_0	12/2/2016	Initial Version

Module Notes

- Device ID variable must be set accordingly. Default value is '1'. Device ID ranges from '1' to '99' or 'Broadcast'. Example: InterfaceName.DeviceID = '1'
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

CodecControl	'Sleep'	'Wake'
InternalMatrix	'VC Out'	'Screen Out'
['Input']	'Aux 1'	'Aux 2'
Input	'DVI'	'HDMI' 'VGA'
['Screen']	'1'	'2'
Screen	'On'	'Off'
['Screen']	'1'	'2'
SystemInput	'HDMI Laptop' 'Aux 2'	'VGA Laptop' 'Aux 1'
SystemOff	None	

Status Available:

ConnectedDevice ¹	'Connected'	'Disconnected'
['Input']	'VGA'	'HDMI'
Input ¹	'DVI' 'No Signal'	'HDMI' 'VGA'
['Screen']	'1'	'2'
Screen ¹	'On'	'Off'
['Screen']	'1'	'2'

¹ Supports SubscribeStatus and ReadStatus only.

Cable and Adapter Requirements:

Captive Screw to Male DB9 RS-232 Serial Cable


Notes for the Device:

Serial communication:


Port Type: RS-232
Baud Rate: 9600
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Please contact manufacturer for pin diagram.



General Notes:

Appendix A. Set Commands

* Examples use a Device ID of 1.

Codec Control Sleep	Box01.COD0001\x0D\x0A
Codec Control Wake	Box01.COD0000\x0D\x0A
Input DVI Screen 1	Box01.SCRV000\x0D\x0A
Input DVI Screen 2	Box01.SCR2V00\x0D\x0A
Input HDMI Screen 1	Box01.SCRH000\x0D\x0A
Input HDMI Screen 2	Box01.SCR2H00\x0D\x0A
Input VGA Screen 1	Box01.SCRG000\x0D\x0A
Input VGA Screen 2	Box01.SCR2G00\x0D\x0A
Internal Matrix Screen Out Input Aux 1	Box01.INNA400\x0D\x0A
Internal Matrix Screen Out Input Aux 2	Box01.INNA600\x0D\x0A
Internal Matrix VC Out Input Aux 1	Box01.INNA300\x0D\x0A
Internal Matrix VC Out Input Aux 2	Box01.INNA500\x0D\x0A
Screen Off Screen 1	Box01.SCR0000\x0D\x0A
Screen Off Screen 2	Box01.SCR2100\x0D\x0A
Screen On Screen 1	Box01.SCR1000\x0D\x0A
Screen On Screen 2	Box01.SCR2000\x0D\x0A
System Input Aux 1	Box01.INNA100\x0D\x0A
System Input Aux 2	Box01.INNA200\x0D\x0A
System Input HDMI Laptop	Box01.INNL100\x0D\x0A
System Input VGA Laptop	Box01.INNL200\x0D\x0A
System Off None	Box01.OFF\x0D\x0A