

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Audio Processor
Manufacturer: Allen and Heath
Firmware Version: v1.50 or later
Model(s): QU-16, QU-32, QU-24, QU-Pac

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.03.0000-b006	2.01.0001-b001	1.1.1

Version History

Module Version	Date	Notes
1_1_3_0	12/1/2016	Initial Version

Module Notes

- N/A

Control Commands, States, and Qualifiers:

DCAFaderLevel	-45 to 10 in steps of 1		
['Midi Channel']	'1' – '16'		
['DCA']	'1' – '4'		
DCAMute	'On' 'Off'		
['Midi Channel']	'1' – '16'		
['DCA']	'1' – '4'		
FXFaderLevel	-45 to 10 in steps of 1		
['Midi Channel']	'1' – '16'		
['FX Number']	'1' – '4'		
['FX Type']	'Send' 'Return'		
FXMute	'On' 'Off'		
['Midi Channel']	'1' – '16'		
['FX Number']	'1' – '4'		
['FX Type']	'Send' 'Return'		
InputLevel	-45 to 10 in steps of 1		
['Midi Channel']	'1' – '16'		
['Input'] ¹	'1' – '16'		
['Input'] ²	'1' – '24'		
['Input'] ³	'1' – '32'		
MasterMute	'On' 'Off'		
['Midi Channel']	'1' – '16'		
MasterVolumeLevel	-45 to 10 in steps of 1		
['Midi Channel']	'1' – '16'		
MixFader	-45 to 10 in steps of 1		
['Midi Channel']	'1' – '16'		
['Mix']	'1' – '4'	'5-6'	'7-8'
	'9-10'	'LR'	'Grp1-2'
	'Grp3-4'	'Grp5-6'	'Grp7-8'
	'MTX1-2'	'MTX3-4'	
MixLevel	-45 to 10 in steps of 1		
['Midi Channel']	'1' – '16'		
['Mix']	'1' – '7'		
MixMute	'On' 'Off'		
['Midi Channel']	'1' – '16'		

['Mix']	'1' – '7'
MuteInput	'On' 'Off'
['Midi Channel']	'1' – '16'
['Input'] ¹	'1' – '16'
['Input'] ²	'1' – '24'
['Input'] ³	'1' – '32'
SceneRecall	'1' – '100'
['Midi Channel']	'1' – '16'

¹ For QU-16 model only.

² For QU-24 model only.

³ For QU-32 and QU-Pac models only.

Status Available:

N/A

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type: Ethernet

Default Port: 51325

Logon Credentials No

Supported:

Multi-Connection No

Capabilities:

Port Changeability: No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

* The examples use the following values for the qualifiers

Midi Channel: '16'

DCA: '4'

FX Number: '3'

Input: '1'

Mix: '2'

DCAFaderLevel -45	\xbfc\x13\xfb\x17\xbf\x06\x11\xbf&\x07
DCAFaderLevel 10	\xbfc\x13\xfb\x17\xbf\x06\x7f\xbf&\x07
DCAMute On	\x9fg\x13\x7f\x13\x00
DCAMute Off	\x9fg\x13?\x13\x00
FXFaderLevel Send -45	\xbfc\x02\xfb\x17\xbf\x06\x11\xbf&\x07
FXFaderLevel Send 10	\xbfc\x02\xfb\x17\xbf\x06\x7f\xbf&\x07
FXFaderLevel Return -45	\xbfc\n\xfb\x17\xbf\x06\x11\xbf&\x07
FXFaderLevel Return 10	\xbfc\n\xfb\x17\xbf\x06\x7f\xbf&\x07
FXMute Send On	\x9fg\x02\x7f\x02\x00
FXMute Send Off	\x9fg\x02?\x02\x00
FXMute Return On	\x9fg\n\x7f\n\x00
FXMute Return Off	\x9fg\n?\n\x00
InputLevel -45	\xbfc \xfb\x17\xbf\x06\x11\xbf&\x07
InputLevel 10	\xbfc \xfb\x17\xbf\x06\x7f\xbf&\x07
MasterMute On	\x9fg\x7f\x9fg\x00
MasterMute Off	\x9fg?\x9fg\x00
MasterVolumeLevel -45	\xbfcg\xfb\x17\xbf\x06\x11\xbf&\x07
MasterVolumeLevel 10	\xbfcg\xfb\x17\xbf\x06\x7f\xbf&\x07
MixFader -45	\xbfca\xfb\x17\xbf\x06\x11\xbf&\x07
MixFader 10	\xbfca\xfb\x17\xbf\x06\x7f\xbf&\x07
MixLevel -45	\xbfca\xfb \xbf\x06\x11\xbf&\x01
MixLevel 10	\xbfca\xfb \xbf\x06\x7f\xbf&\x01
MixMute On	\xbfca\xfbU\xbf\x06\x01\xbf&\x01
MixMute Off	\xbfca\xfbU\xbf\x06\x00\xbf&\x01
MuteInput On	\x9f \x7f\x9f \x00
MuteInput Off	\x9f ?\x9f \x00
SceneRecall 1	\xbf\x00\x00\xbf \x00\xcf\x00
SceneRecall 100	\xbf\x00\x00\xbf \x00\xcf