

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Other
Manufacturer: Alpha American
Firmware Version: N/A
Model(s): 7160C, 7080C, 7120C, 7200C

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.05.0000-b007	2.01.0002-b005	1.3.0

Version History

Module Version	Date	Notes
1_0_0_0	5/25/2017	Initial Version

Module Notes

- DeviceID variable must be set accordingly. Default value is 'Broadcast'. Device ID ranges from '1' – '255' and 'Broadcast'. Example: InterfaceName.DeviceID = '1'

Read TEXT File commands:

- Read TEXT File Recall
 - This command recalls a saved TEXT file from defined File Label.
- Read TEXT File String
 - This shows the string (TEXT file) that a defined File Label contains.
- Read TEXT File Update
 - This command updates Read TEXT File String with value for a defined File Label.

Write TEXT File commands:

- Write TEXT File Command
 - This command saves TEXT File to defined File Label and sends it to the device.

File Label Parameter Table:

Refer to this table to define which File Label number to use. These are the valid File Labels the device supports.

Note: 17 is denoted as Priority TEXT.

20H - sp	1	30H - "0"	17	40H - "00"	33	50H - "P"	49	60H - ""	65	70H - "p"	81
21H - "I"	2	31H - "1"	18	41H - "A"	34	51H - "Q"	50	61H - "a"	66	71H - "q"	82
22H - ""	3	32H - "2"	19	42H - "B"	35	52H - "R"	51	62H - "b"	67	72H - "r"	83
23H - "F"	4	33H - "3"	20	43H - "C"	36	53H - "S"	52	63H - "c"	68	73H - "s"	84
24H - "S"	5	34H - "4"	21	44H - "D"	37	54H - "T"	53	64H - "d"	69	74H - "t"	85
25H - "%"	6	35H - "5"	22	45H - "E"	38	55H - "U"	54	65H - "e"	70	75H - "u"	86
26H - "&"	7	36H - "6"	23	46H - "F"	39	56H - "V"	55	66H - "f"	71	76H - "v"	87
27H - ""	8	37H - "7"	24	47H - "G"	40	57H - "W"	56	67H - "g"	72	77H - "w"	88
28H - "I"	9	38H - "8"	25	48H - "H"	41	58H - "X"	57	68H - "h"	73	78H - "x"	89
29H - "J"	10	39H - "9"	26	49H - "I"	42	59H - "Y"	58	69H - "i"	74	79H - "y"	90
2AH - ""	11	3AH - "A"	27	4AH - "J"	43	5AH - "Z"	59	6AH - "j"	75	7AH - "z"	91
2BH - "+"	12	3BH - "B"	28	4BH - "K"	44	5BH - "I"	60	6BH - "k"	76	7BH - "i"	92
2CH - "I"	13	3CH - "<"	29	4CH - "L"	45	5CH - "Y"	61	6CH - "l"	77	7CH - "l"	93
2DH - "I"	14	3DH - "="	30	4DH - "M"	46	5DH - "J"	62	6DH - "m"	78	7DH - "j"	94
2EH - "I"	15	3EH - ">"	31	4EH - "N"	47	5EH - "F"	63	6EH - "n"	79	7EH - 1/2 sp	95
2FH - "I"	16	3FH - "7"	32	4FH - "O"	48	5FH - "I"	64	6FH - "o"	80	7FH - reserved	96

Control Commands, States, and Qualifiers:

ReadTEXTFileRecall	'1' – '16'	'18' – '95'	'Priority TEXT'
ReadTEXTFileUpdate	'1' – '16'	'18' – '95'	'Priority TEXT'
WriteTEXTFileCommand ¹	'String'		
['File Label']	'1' – '16'	'18' – '95'	'Priority TEXT'
['Position']	'Middle' 'Fill'	'Top' 'None'	'Bottom'
['Effect']	'Rotate' 'Roll Up' 'Roll Right' 'Wipe Right' 'Twinkle' 'Interlock' 'Wipe In' 'Switch' 'Starburst'	'Hold' 'Roll Down' 'Wipe Up' 'Scroll' 'Sparkle' 'Roll In' 'Wipe Out' 'Slide' 'None'	'Flash' 'Roll Left' 'Wipe Left' 'Automode' 'Snow' 'Roll Out' 'Wipe Down' 'Spray'
['Color']	'Red' 'Dim Red' 'Orange' 'Autocolor'	'Green' 'Dim Green' 'Yellow' 'None'	'Amber' 'Brown' 'Color Mix'
['Speed']	'Slowest' 'Faster'	'Slow' 'Fastest'	'Fast' 'None'

¹ The Position, Effect, Color, and Speed qualifiers must be all set to something other than 'None' for these qualifiers to be useful. If any of them are set to 'None', then the other qualifiers are automatically set to 'None'.

Status Available:

ReadTEXTFileString ¹	'String'		
['File Label']	'1' – '16'	'18' – '95'	'Priority TEXT'

¹ Supports SubscribeStatus and ReadStatus only. This status will get updated by a Set('ReadTEXTFileUpdate', value) command.

Cable and Adapter Requirements:

Captive Screw to RJ-11 Serial Cable.

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	3	RxD
RxD	←	4	TxD
GND		1	GND



General Notes:

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	23
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Requires Alpha Ethernet Adapter for Ethernet control to work.

Appendix A. Set Commands

- Commands assume a Device ID of 'Broadcast'.

Read TEXT File Recall 1	\x00\x00\x00\x00\x00\x01100\x02A testString\x04
Read TEXT File Recall 16	\x00\x00\x00\x00\x00\x01100\x02A/testString\x04
Read TEXT File Recall 18	\x00\x00\x00\x00\x00\x01100\x02A1testString\x04
Read TEXT File Recall 95	\x00\x00\x00\x00\x00\x01100\x02A~testString\x04
Read TEXT File Recall Priority TEXT	\x00\x00\x00\x00\x00\x01100\x02A0testString\x04
Read TEXT File Update 1	\x00\x00\x00\x00\x00\x01100\x02B \x04
Read TEXT File Update 16	\x00\x00\x00\x00\x00\x01100\x02B/\x04
Read TEXT File Update 18	\x00\x00\x00\x00\x00\x01100\x02B1\x04
Read TEXT File Update 95	\x00\x00\x00\x00\x00\x01100\x02B~\x04
Read TEXT File Update Priority TEXT	\x00\x00\x00\x00\x00\x01100\x02B0\x04
Write TEXT File Command testString File Label 19 Position Fill Effect Roll Right Color Color Mix Speed Faster	\x00\x00\x00\x00\x00\x01100\x02A2\x1b0h\x1cB\x18testString\x04
Write TEXT File Command testString File Label 83 Position Bottom Effect Roll Up Color Yellow Speed Fastest	\x00\x00\x00\x00\x00\x01100\x02Ar\x1b&e\x1c8\x19testString\x04
Write TEXT File Command testString File Label 1 Position Middle Effect Hold Color Color Mix Speed None	\x00\x00\x00\x00\x00\x01100\x02A testString\x04
Write TEXT File Command testString File Label 37 Position None Effect Snow Color Amber Speed None	\x00\x00\x00\x00\x00\x01100\x02ADtestString\x04
Write TEXT File Command testString File Label 78 Position Fill Effect Roll Left Color Green Speed Fast	\x00\x00\x00\x00\x00\x01100\x02Am\x1b0g\x1c2\x17testString\x04