
This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Video Projector
Manufacturer: Appotronics
Firmware Version: N/A
Model(s): AL-UH420, AL-UH450, AL-UH455, AL-FX520, AL-FW520, AL-FH520, AL-FX540, AL-FW540, AL-FH540

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.01.0000-b010	2.1.0

Version History

Module Version	Date	Notes
1_0_2_0	12/10/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='AL-UH420')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='AL-UH420')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command BlankScreen	Value 'On'	Value 'Off'	
# BlankScreen example InterfaceName.Set('BlankScreen', 'On')			
Command Input	Value 'HDMI 1' 'AV' 'S-Video'	Value 'HDMI 2' 'DVI'	Value 'PC' 'HDBaseT'
# Input example InterfaceName.Set('Input', 'HDMI 1')			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
ConnectionStatus	'Connected'	'Disconnected'
# ConnectionStatus examples Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	Value
Power	'On'	'Off'
# Power examples InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)		

Cable and Adapter Requirements

Please consult manufacturer for Cable and Adapter Requirements.

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None

Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Please contact manufacturer for Pin Assignments Diagram

Appendix A. Set Commands

Blank Screen Off	Z\x00\x00\x00#\x00\x00\x00\x00\x00\x00\x00\x00Z
Blank Screen On	Z\x00\x00\x00#\x00\x00\x01\x00\x00\x00\x00\x00\x00Z
Input AV	Z\x00\x00\x00\x04\x00\x00\x00\x05\x00\x00\x00\x00\x00Z
Input DVI	Z\x00\x00\x00\x04\x00\x00\x00\x07\x00\x00\x00\x00\x00Z
Input HDBaseT	Z\x00\x00\x00\x04\x00\x00\x00\x08\x00\x00\x00\x00\x00Z
Input HDMI 1	Z\x00\x00\x00\x04\x00\x00\x00\x01\x00\x00\x00\x00\x00Z
Input HDMI 2	Z\x00\x00\x00\x04\x00\x00\x00\x02\x00\x00\x00\x00\x00Z
Input PC	Z\x00\x00\x00\x04\x00\x00\x00\x03\x00\x00\x00\x00\x00Z
Input S-Video	Z\x00\x00\x00\x04\x00\x00\x00\x06\x00\x00\x00\x00\x00Z
Power Off	Z\x00\x00\x00\x03\x00\x00\x00\x00\x00\x00\x00\x00\x00Z
Power On	Z\x00\x00\x00\x03\x00\x00\x00\x01\x00\x00\x00\x00\x00Z

Appendix B. Update Commands

Power	Z\x00\x00\x00f\x00\x00\x00\x00\x00\x00\x00\x00\x00Z
--------------	---