

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Camera
Manufacturer: Arrive EyePoint
Firmware Version: N/A
Model(s): AEP-3030

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.04.0001-b002	2.3.1

Version History

Module Version	Date	Notes
1_0_0_0	3/4/2020	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- DeviceID variable must be set accordingly. Default value is '1'. DeviceID ranges from 1 to 7.
Example: `InterfaceName.DeviceID = '1'`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='AEP-3030')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='AEP-3030')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AutoExposure	Value 'Automatic Exposure Mode' 'Iris Priority Mode'	Value 'Manual Control Mode' 'Bright Mode'	Value 'Shutter Priority Mode'
# AutoExposure example InterfaceName.Set('AutoExposure', 'Automatic Exposure Mode')			
Command AutoFocus	Value 'Auto'	Value 'Manual'	
# AutoFocus example InterfaceName.Set('AutoFocus', 'Auto')			
Command BacklightMode	Value 'On'	Value 'Off'	
# BacklightMode example InterfaceName.Set('BacklightMode', 'On')			
Command Focus	Value 'Near'	Value 'Far'	Value 'Stop'
Qualifier Key 'Focus Speed'	Qualifier Value 0 to 7 in steps of 1		
# Focus example InterfaceName.Set('Focus', 'Near', {'Focus Speed': 7})			
Command Gain	Value 'Up'	Value 'Down'	Value 'Reset'
# Gain example InterfaceName.Set('Gain', 'Up')			
Command Iris	Value 'Up'	Value 'Down'	Value 'Reset'
# Iris example InterfaceName.Set('Iris', 'Up')			
Command PanTilt	Value 'Up' 'Right' 'Down Left'	Value 'Down' 'Up Left' 'Down Right'	Value 'Left' 'Up Right' 'Stop'
Qualifier Key 'Pan Speed'	Qualifier Value 1 to 63 in steps of 1		
Qualifier Key 'Tilt Speed'	Qualifier Value 1 to 63 in steps of 1		
# PanTilt example InterfaceName.Set('PanTilt', 'Up', {'Pan Speed': 63, 'Tilt Speed': 63})			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PresetRecall	Value '1' – '64'		
# PresetRecall example			

InterfaceName.Set('PresetRecall', '1')			
Command PresetSave	Value '1' – '64'		
# PresetSave example InterfaceName.Set('PresetSave', '1')			
Command Shutter	Value 'Up'	Value 'Down'	Value 'Reset'
# Shutter example InterfaceName.Set('Shutter', 'Up')			
Command Zoom	Value 'Tele'	Value 'Wide'	Value 'Stop'
Qualifier Key 'Zoom Speed'	Qualifier Value 0 to 7 in steps of 1		
# Zoom example InterfaceName.Set('Zoom', 'Tele', {'Zoom Speed': 7})			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
FeedbackHandler)
```

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AutoExposure	Value 'Automatic Exposure Mode' 'Iris Priority Mode'	Value 'Manual Control Mode' 'Bright Mode'	Value 'Shutter Priority Mode'
# AutoExposure example InterfaceName.Update('AutoExposure') Value = InterfaceName.ReadStatus('AutoExposure') InterfaceName.SubscribeStatus('AutoExposure', None, FeedbackHandler)			
Command AutoFocus	Value 'Auto'	Value 'Manual'	
# AutoFocus example InterfaceName.Update('AutoFocus') Value = InterfaceName.ReadStatus('AutoFocus') InterfaceName.SubscribeStatus('AutoFocus', None, FeedbackHandler)			
Command BacklightMode	Value 'On'	Value 'Off'	
# BacklightMode example InterfaceName.Update('BacklightMode') Value = InterfaceName.ReadStatus('BacklightMode') InterfaceName.SubscribeStatus('BacklightMode', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			

Cable and Adapter Requirements

Captive Screw to Male Mini 8-Pin Din RS232 Cable

Notes for the Device

The following DIP-switch settings must be properly configured for the driver to work:


- SW2, DIP-1 → Off
- SW2, DIP-2 → Off
- SW2, DIP-3 → Off

Serial communication


Port Type: RS-232
Baud Rate: 9600
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	5	RxD
RxD	←	3	TxD
GND	→	4	GND



Appendix A. Set Commands

Auto Exposure Automatic Exposure Mode	\x01\x01\x049\x00\xff
Auto Exposure Bright Mode	\x01\x01\x049\x0D\xff
Auto Exposure Iris Priority Mode	\x01\x01\x049\x0B\xff
Auto Exposure Manual Control Mode	\x01\x01\x049\x03\xff
Auto Exposure Shutter Priority Mode	\x01\x01\x049\x0A\xff
Auto Focus Auto	\x01\x01\x048\x02\xff
Auto Focus Manual	\x01\x01\x048\x03\xff
Backlight Mode Off	\x01\x01\x043\x03\xff
Backlight Mode On	\x01\x01\x043\x02\xff
Focus Far Focus Speed 0	\x01\x01\x04\x080\xff
Focus Far Focus Speed 7	\x01\x01\x04\x087\xff
Focus Near Focus Speed 0	\x01\x01\x04\x08 \xff
Focus Near Focus Speed 7	\x01\x01\x04\x08' \xff
Focus Stop Focus Speed 0	\x01\x01\x04\x08\x00\xff
Focus Stop Focus Speed 7	\x01\x01\x04\x08\x00\xff
Gain Down	\x01\x01\x04\x0C\x03\xff
Gain Reset	\x01\x01\x04\x0C\x00\xff
Gain Up	\x01\x01\x04\x0C\x02\xff
Iris Down	\x01\x01\x04\x0B\x03\xff
Iris Reset	\x01\x01\x04\x0B\x00\xff
Iris Up	\x01\x01\x04\x0B\x02\xff
Pan Tilt Down Left Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x02\xff
Pan Tilt Down Left Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x01\x02\xff
Pan Tilt Down Left Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x01\x02\xff
Pan Tilt Down Left Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x01\x02\xff
Pan Tilt Down Right Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x02\x02\xff
Pan Tilt Down Right Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x02\x02\xff
Pan Tilt Down Right Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x02\x02\xff
Pan Tilt Down Right Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x02\x02\xff
Pan Tilt Down Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x03\x02\xff
Pan Tilt Down Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x03\x02\xff
Pan Tilt Down Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x03\x02\xff
Pan Tilt Down Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x03\x02\xff
Pan Tilt Left Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x01\x03\xff
Pan Tilt Left Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x01\x03\xff
Pan Tilt Left Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x01\x03\xff
Pan Tilt Right Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x02\x03\xff
Pan Tilt Right Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x02\x03\xff
Pan Tilt Right Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x02\x03\xff
Pan Tilt Right Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x02\x03\xff
Pan Tilt Stop Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x03\x03\xff

Pan Tilt Stop Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x03\x03\xFF
Pan Tilt Stop Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x03\x03\xFF
Pan Tilt Stop Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x03\x03\xFF
Pan Tilt Up Left Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x01\xFF
Pan Tilt Up Left Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x01\x01\xFF
Pan Tilt Up Left Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x01\x01\xFF
Pan Tilt Up Left Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x01\x01\xFF
Pan Tilt Up Right Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x02\x01\xFF
Pan Tilt Up Right Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x02\x01\xFF
Pan Tilt Up Right Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x02\x01\xFF
Pan Tilt Up Right Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x02\x01\xFF
Pan Tilt Up Tilt Speed 1 Pan Speed 1	\x01\x01\x06\x01\x01\x01\x03\x01\xFF
Pan Tilt Up Tilt Speed 1 Pan Speed 63	\x01\x01\x06\x01?\x01\x03\x01\xFF
Pan Tilt Up Tilt Speed 63 Pan Speed 1	\x01\x01\x06\x01\x01?\x03\x01\xFF
Pan Tilt Up Tilt Speed 63 Pan Speed 63	\x01\x01\x06\x01??\x03\x01\xFF
Power Off	\x01\x01\x04\x00\x03\xFF
Power On	\x01\x01\x04\x00\x02\xFF
Preset Recall 1	\x01\x01\x04?\x02\x00\xFF
Preset Recall 64	\x01\x01\x04?\x02?\xFF
Preset Save 1	\x01\x01\x04?\x01\x00\xFF
Preset Save 64	\x01\x01\x04?\x01?\xFF
Shutter Down	\x01\x01\x04\x0A\x03\xFF
Shutter Reset	\x01\x01\x04\x0A\x00\xFF
Shutter Up	\x01\x01\x04\x0A\x02\xFF
Zoom Stop Zoom Speed 0	\x01\x01\x04\x07\x00\xFF
Zoom Stop Zoom Speed 7	\x01\x01\x04\x07\x00\xFF
Zoom Tele Zoom Speed 0	\x01\x01\x04\x07 \xFF
Zoom Tele Zoom Speed 7	\x01\x01\x04\x07' \xFF
Zoom Wide Zoom Speed 0	\x01\x01\x04\x070\xFF
Zoom Wide Zoom Speed 7	\x01\x01\x04\x077\xFF

Appendix B. Update Commands

Auto Exposure	\x01\x09\x049\xFF
Auto Focus	\x01\x09\x048\xFF
Backlight Mode	\x01\x09\x043\xFF
Power	\x01\x09\x04\x00\xFF