

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Scaler
Manufacturer: Atlona
Firmware Version: N/A
Model(s): AT-HD-SC-500

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_0_1_0	2/23/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5

Control Commands, States, and Qualifiers:

AspectRatio	'Full'	'16:9'	'16:10'
	'4:3'	'Keep Ratio'	
AudioMute	'On'	'Off'	
AudioOutput	'On'	'Off'	
['Input']	'HDMI'	'Analog'	
AudioSource	'Auto'	'Digital'	'Analog'
['HDMI']	'1' – '2'		
AutoImage ¹	None		
HDCPMode	'Compliant'	'Non-Complaint'	
['HDMI']	'1' – '2'		
Input	'HDMI 1'	'HDMI 2'	'VGA'
OnScreenDisplayMenu	'On'	'Off'	'Auto'
OutputVolume	-80 to 0 in steps of 1		

¹ This command works only when VGA input is selected.

Status Available:

AudioMute	'On'	'Off'	
AudioOutput	'On'	'Off'	
['Input']	'HDMI'	'Analog'	
ConnectionStatus	'Connected'	'Disconnected'	
HDCPMode	'Compliant'	'Non-Complaint'	
['HDMI']	'1' – '2'		
Input	'HDMI 1'	'HDMI 2'	'VGA'
OnScreenDisplayMenu	'On'	'Off'	'Auto'
OutputVolume	-80 to 0 in steps of 1		

Cable and Adapter Requirements:

Captive Screw to Captive Screw Cable.


Notes for the Device:

Serial communication:


Port Type: RS-232
Baud Rate: 115200
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Signal
TxD	↘	TxD
RxD	↙	RxD
GND	—	GND



General Notes:

Network communication:

When configuring the Ethernet module, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet
Default Port:	23
Logon Credentials Supported:	Yes
Multi-Connection Capabilities:	Undetermined
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

Aspect Ratio 16:10	Aspect 2\x0D
Aspect Ratio 16:9	Aspect 1\x0D
Aspect Ratio 4:3	Aspect 3\x0D
Aspect Ratio Full	Aspect 0\x0D
Aspect Ratio Keep Ratio	Aspect 4\x0D
Audio Mute Off	VOUTMute1 off\x0D
Audio Mute On	VOUTMute1 on\x0D
Audio Output Off Input Analog	LRAUD off\x0D
Audio Output Off Input HDMI	HDMIAUD off\x0D
Audio Output On Input Analog	LRAUD on\x0D
Audio Output On Input HDMI	HDMIAUD on\x0D
Audio Source Analog HDMI 1	AudioScr1 ana\x0D
Audio Source Analog HDMI 2	AudioScr2 ana\x0D
Audio Source Auto HDMI 1	AudioScr1 auto\x0D
Audio Source Auto HDMI 2	AudioScr2 auto\x0D
Audio Source Digital HDMI 1	AudioScr1 dig\x0D
Audio Source Digital HDMI 2	AudioScr2 dig\x0D
Auto Image None	VGAAuto\x0D
HDCP Mode Compliant HDMI 1	HDCPSet1 on\x0D
HDCP Mode Compliant HDMI 2	HDCPSet2 on\x0D
HDCP Mode Non-Complaint HDMI 1	HDCPSet1 off\x0D
HDCP Mode Non-Complaint HDMI 2	HDCPSet2 off\x0D
Input HDMI 1	Input HDMI 1\x0D
Input HDMI 2	Input HDMI 2\x0D
Input VGA	Input VGA\x0D
On Screen Display Menu Auto	INFOOSD auto\x0D
On Screen Display Menu Off	INFOOSD off\x0D
On Screen Display Menu On	INFOOSD on\x0D
Output Volume 0	VOUT1 0\x0D
Output Volume -80	VOUT1 -80\x0D

Appendix B. Query Commands

Audio Mute	VOUTMute1 sta\x0D
Audio Output Input Analog	LRAUD sta\x0D
Audio Output Input HDMI	HDMIAUD sta\x0D
HDCP Mode HDMI 1	HDCPSet1 sta\x0D
HDCP Mode HDMI 2	HDCPSet2 sta\x0D
Input	Input sta\x0D
On Screen Display Menu	INFOOSD sta\x0D