

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Audio Processor
Manufacturer: Audio Technica
Firmware Version: N/A
Model(s): AT-MX862

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_0_0_0	2/22/2017	Initial Version

Module Notes

- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

ExecutiveMode	'On'	'Off'
InputGain	0 to 31 in steps of 1	
['Channel']	'1' – '8'	
InputMute	'On'	'Off'
['Channel']	'1' – '8'	
Mode	'A'	'B' 'C'
	'D'	'Mic'
OutputLevel	0 to 31 in steps of 1	
['Channel']	'1' – '8'	
OutputMute	'On'	'Off'
['Channel']	'1' – '8'	
PhantomPower	'On'	'Off'
['Channel']	'1' – '8'	
Scene	'0' – '19'	

Status Available:

N/A

Cable and Adapter Requirements:

Contact Manufacturer for Cable and Adapter Requirements.

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 38400


Data Bits: 8

Parity: None

Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Contact Manufacturer for Pin Assignments Diagram

General Notes:

Appendix A. Set Commands

Executive Mode Off	\xAAU\x00\x05\x00\x00\x00\x01DS\x017\x001U\xAA
Executive Mode On	\xAAU\x00\x05\x00\x00\x00\x01DS\x017\x010U\xAA
Input Gain 0 Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x09\x00_U\xAA
Input Gain 31 Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x09\x1F@U\xAA
Input Gain 0 Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x10\x00XU\xAA
Input Gain 31 Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x10\x1F9U\xAA
Input Mute Off Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x19\x00OU\xAA
Input Mute On Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x19\x01NU\xAA
Input Mute Off Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01 \x00HU\xAA
Input Mute On Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01 \x01GU\xAA
Input Mute Off Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x19\x00OU\xAA
Input Mute Off Channel 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1A\x00NU\xAA
Input Mute Off Channel 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1B\x00MU\xAA
Input Mute Off Channel 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1C\x00LU\xAA
Input Mute Off Channel 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1D\x00KU\xAA
Input Mute Off Channel 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1E\x00JU\xAA
Input Mute Off Channel 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1F\x00IU\xAA
Input Mute Off Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01 \x00HU\xAA
Input Mute On Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x19\x01NU\xAA
Input Mute On Channel 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1A\x01MU\xAA
Input Mute On Channel 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1B\x01LU\xAA
Input Mute On Channel 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1C\x01KU\xAA
Input Mute On Channel 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1D\x01JU\xAA
Input Mute On Channel 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1E\x01IU\xAA
Input Mute On Channel 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x01\x1F\x01HU\xAA
Input Mute On Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01 \x01GU\xAA
Mode A	\xAAU\x00\x05\x00\x00\x00\x01DS\x011\x016U\xAA
Mode B	\xAAU\x00\x05\x00\x00\x00\x01DS\x011\x025U\xAA
Mode C	\xAAU\x00\x05\x00\x00\x00\x01DS\x011\x034U\xAA
Mode D	\xAAU\x00\x05\x00\x00\x00\x01DS\x011\x043U\xAA
Mode Mic	\xAAU\x00\x05\x00\x00\x00\x01DS\x011\x007U\xAA
Output Level 0 Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01!\x00GU\xAA
Output Level 31 Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01!\x1F(U\xAA
Output Level 0 Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01(\x00@U\xAA
Output Level 31 Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01(\x1F!U\xAA
Output Mute Off Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01)\x00?U\xAA
Output Mute Off Channel 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x01*\x00>U\xAA
Output Mute Off Channel 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x01+\x00=U\xAA
Output Mute Off Channel 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x01'\x00<U\xAA
Output Mute Off Channel 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x01-\x00;U\xAA
Output Mute Off Channel 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x01.\x00:U\xAA
Output Mute Off Channel 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x01/\x009U\xAA
Output Mute Off Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x010\x008U\xAA
Output Mute On Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x01)\x01>U\xAA
Output Mute On Channel 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x01*\x01=U\xAA

Output Mute On Channel 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x01+\x01<U\xAA
Output Mute On Channel 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x01'\x01;U\xAA
Output Mute On Channel 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x01-\x01;U\xAA
Output Mute On Channel 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x01.\x019U\xAA
Output Mute On Channel 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x01/\x018U\xAA
Output Mute On Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x010\x017U\xAA
Phantom Power Off Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x018\x000U\xAA
Phantom Power Off Channel 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x019\x00/U\xAA
Phantom Power Off Channel 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x01:\x00.U\xAA
Phantom Power Off Channel 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x01;\x00-U\xAA
Phantom Power Off Channel 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x01<\x00'U\xAA
Phantom Power Off Channel 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x01=\x00+U\xAA
Phantom Power Off Channel 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x01>\x00*U\xAA
Phantom Power Off Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01?\x00)U\xAA
Phantom Power On Channel 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x018\x01/U\xAA
Phantom Power On Channel 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x019\x01.U\xAA
Phantom Power On Channel 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x01:\x01-U\xAA
Phantom Power On Channel 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x01;\x01'U\xAA
Phantom Power On Channel 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x01<\x01+U\xAA
Phantom Power On Channel 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x01=\x01*U\xAA
Phantom Power On Channel 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x01>\x01)U\xAA
Phantom Power On Channel 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x01?\x01(U\xAA
Scene 0	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x006U\xAA
Scene 1	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x015U\xAA
Scene 10	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x0A'U\xAA
Scene 11	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x0B+U\xAA
Scene 12	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x0C*U\xAA
Scene 13	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x0D)U\xAA
Scene 14	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x0E(U\xAA
Scene 15	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x0F'U\xAA
Scene 16	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x10&U\xAA
Scene 17	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x11%U\xAA
Scene 18	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x12\$U\xAA
Scene 19	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x13#U\xAA
Scene 2	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x024U\xAA
Scene 3	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x033U\xAA
Scene 4	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x042U\xAA
Scene 5	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x051U\xAA
Scene 6	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x060U\xAA
Scene 7	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x07/U\xAA
Scene 8	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x08.U\xAA
Scene 9	\xAAU\x00\x05\x00\x00\x00\x01DS\x012\x09-U\xAA