

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Switcher
Manufacturer: Analog Way
Firmware Version: N/A
Model(s): ASC3204-4K, ASC1602-4K, ASC4806-4K, ASC16LE-4K, ASC32LE-4K, ASC48LE-4K

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.11.0000-b007	2.7.0

Version History

Module Version	Date	Notes
1_2_0	10/26/2020	Fixed Master Preset Recall: - Removed 'Screen' parameter for Master Preset Recall. - Added Master Preset Load Enable. Added Master Preset Recall notes to communication sheet.
1_1_1_0	5/20/2020	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Class and Example

EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 10600, Model='ASC3204-4K')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command CurrentPlug	Value 'Analog HD15' 'SDI'	Value 'Analog DVI' 'HDMI'	Value 'DVI' 'Display Port'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Input'	Qualifier Value '1' – '12'		
# CurrentPlug example InterfaceName.Set('CurrentPlug', 'Analog HD15', {'Device': 'Master', 'Input': '1'})			
Command GPIMode	Value 'Normal'	Value 'Take'	
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# GPIMode example InterfaceName.Set('GPIMode', 'Normal', {'Device': 'Master'})			
Command GPITakeScreen	Value '1' – '8'		
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# GPITakeScreen example InterfaceName.Set('GPITakeScreen', '1', {'Device': 'Master'})			
Command GPOMode	Value 'Free'	Value 'Tally before transition'	Value 'Tally after transition'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Output'	Qualifier Value '1' – '5'		
# GPOMode example InterfaceName.Set('GPOMode', 'Free', {'Device': 'Master', 'Output': '1'})			
Command InputAutoSet	Value None		
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Input'	Qualifier Value '1' – '12'		
# InputAutoSet example InterfaceName.Set('InputAutoSet', None, {'Device': 'Master', 'Input': '1'})			
Command InputFreeze	Value 'On'	Value 'Off'	
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Input'	Qualifier Value '1' – '12'		
# InputFreeze example InterfaceName.Set('InputFreeze', 'On', {'Device': 'Master', 'Input': '1'})			

Command LayerInput	Value 'No Input' 'Input 3 of Master Device' 'Input 6 of Master Device' 'Input 9 of Master Device' 'Input 12 of Master Device' 'Input 3 of Slave Device' 'Input 6 of Slave Device' 'Input 9 of Slave Device' 'Input 12 of Slave Device' 'Frame 3 of Master Device' 'Frame 2 of Slave Device' 'Logo 1 of Master Device' 'Logo 4 of Master Device' 'Logo 3 of Slave Device'	Value 'Input 1 of Master Device' 'Input 4 of Master Device' 'Input 7 of Master Device' 'Input 10 of Master Device' 'Input 1 of Slave Device' 'Input 4 of Slave Device' 'Input 7 of Slave Device' 'Input 10 of Slave Device' 'Frame 1 of Master Device' 'Frame 4 of Master Device' 'Frame 3 of Slave Device' 'Logo 2 of Master Device' 'Logo 1 of Slave Device' 'Logo 4 of Slave Device'	Value 'Input 2 of Master Device' 'Input 5 of Master Device' 'Input 8 of Master Device' 'Input 11 of Master Device' 'Input 2 of Slave Device' 'Input 5 of Slave Device' 'Input 8 of Slave Device' 'Input 11 of Slave Device' 'Frame 2 of Master Device' 'Frame 1 of Slave Device' 'Frame 4 of Slave Device' 'Logo 3 of Master Device' 'Logo 2 of Slave Device' 'Color (or Black) fill of PiP'
Qualifier Key 'Layers'	Qualifier Value 'A' 'D'	Qualifier Value 'B' 'E'	Qualifier Value 'C' 'F'
Qualifier Key 'Preset Mode'	Qualifier Value 'Main'	Qualifier Value 'Preview'	
Qualifier Key 'Screen'	Qualifier Value '1' – '8'		
# LayerInput example InterfaceName.Set('LayerInput', 'No Input', {'Layers': 'A', 'Preset Mode': 'Main', 'Screen': '1'})			
Command MasterPresetDestinationType	Value 'Program'	Value 'Preview'	
# MasterPresetDestinationType example InterfaceName.Set('MasterPresetDestinationType', 'Program')			
Command MasterPresetLoadEnable	Value None		
Qualifier Key 'Screen'	Qualifier Value '1' – '8'		
# MasterPresetSave example InterfaceName.Set('MasterPresetSave', None, {'Save Mode': 'No Save Operation'})			
Command MasterPresetOriginMemoryNumber	Value '1' – '144'		

# MasterPresetOriginMemoryNumber example InterfaceName.Set('MasterPresetOriginMemoryNumber', '1')			
Command MasterPresetRecall ¹	Value None		
Qualifier Key 'Screen'	Qualifier Value '1' – '8'		
# MasterPresetRecall example InterfaceName.Set('MasterPresetRecall', None, {'Screen': '1'})			
Command MasterPresetReset	Value None		
# MasterPresetReset example InterfaceName.Set('MasterPresetReset', None)			
Command MasterPresetSave	Value None		
Qualifier Key 'Save Mode'	Qualifier Value 'No Save Operation'	Qualifier Value 'Selected by User'	Qualifier Value 'Auto Allocated by Device'
# MasterPresetSave example InterfaceName.Set('MasterPresetSave', None, {'Save Mode': 'No Save Operation'})			
Command MonitoringFullscreenEnable	Value 'Mosaic'	Value 'Fullscreen'	
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# MonitoringFullscreenEnable example InterfaceName.Set('MonitoringFullscreenEnable', 'Mosaic', {'Device': 'Master'})			
Command NativeBackground	Value '1' – '8'	Value 'No Native Background'	
Qualifier Key 'Screen'	Qualifier Value '1' – '8'		
Qualifier Key 'Preset Mode'	Qualifier Value 'Program'	Qualifier Value 'Preview'	
# NativeBackground example InterfaceName.Set('NativeBackground', '1', {'Screen': '1', 'Preset Mode': 'Program'})			
Command PresetLoad	Value None		
# PresetLoad example InterfaceName.Set('PresetLoad', None)			
Command PresetLoadandTake	Value None		
# PresetLoadandTake example InterfaceName.Set('PresetLoadandTake', None)			
Command PresetRecallDestinationScreen	Value '1' – '8'		
# PresetRecallDestinationScreen example InterfaceName.Set('PresetRecallDestinationScreen', '1')			
Command PresetRecallDestinationType	Value 'Program'	Value 'Preview'	
# PresetRecallDestinationType example InterfaceName.Set('PresetRecallDestinationType', 'Program')			
Command PresetRecallFilterCategory	Value 'Include'	Value 'Exclude'	

Qualifier Key 'Type'	Qualifier Value 'Source' 'Crop' 'Effects' 'Flying Curve' 'All'	Qualifier Value 'Position' 'Border' 'Timing' 'Native Background'	Qualifier Value 'Transparency' 'Transitions' 'Speed' 'Mask'
# PresetRecallFilterCategory example InterfaceName.Set('PresetRecallFilterCategory', 'Include', {'Type': 'Source'})			
Command PresetRecallOriginMemoryNumber	Value '1' – '144'		
# PresetRecallOriginMemoryNumber example InterfaceName.Set('PresetRecallOriginMemoryNumber', '1')			
Command PresetRecallScale	Value 'Enable automatic resizing'	Value 'Disable automatic resizing'	
# PresetRecallScale example InterfaceName.Set('PresetRecallScale', 'Enable automatic resizing')			
Command PresetReset	Value None		
# PresetReset example InterfaceName.Set('PresetReset', None)			
Command PresetSave	Value None		
# PresetSave example InterfaceName.Set('PresetSave', None)			
Command Reboot	Value None		
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# Reboot example InterfaceName.Set('Reboot', None, {'Device': 'Master'})			
Command Shutdown	Value 'Idle'	Value 'Shutdown of device'	Value 'Shutdown of device and Enable Wake On Lan'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# Shutdown example InterfaceName.Set('Shutdown', 'Idle', {'Device': 'Master'})			

¹ The following commands need to be sent before sending Master Preset Recall (in that order):

1. Preset Recall Filter Category
2. Preset Recall Scale
3. Preset Recall Original Memory Number
4. Preset Recall Destination Type

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command FirmwareVersionMasterDevice	Value 'String'	
# FirmwareVersionMasterDevice example InterfaceName.Update('FirmwareVersionMasterDevice') Value = InterfaceName.ReadStatus('FirmwareVersionMasterDevice') InterfaceName.SubscribeStatus('FirmwareVersionMasterDevice', None, FeedbackHandler)		
Command HDCPStatusIn	Value 'Enabled'	Value 'Disabled'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'
Qualifier Key 'Input'	Qualifier Value '1' – '12'	
Qualifier Key 'Input Type'	Qualifier Value 'Analog' 'SDI'	Qualifier Value 'DVI-A' 'HDMI' 'DVI-D' 'DisplayPort'
# HDCPStatusIn example InterfaceName.Update('HDCPStatusIn', {'Device': 'Master', 'Input': '1', 'Input Type': 'Analog'}) Value = InterfaceName.ReadStatus('HDCPStatusIn', {'Device': 'Master', 'Input': '1', 'Input Type': 'Analog'}) InterfaceName.SubscribeStatus('HDCPStatusIn', None, FeedbackHandler)		
Command HDCPStatusOut	Value 'Enabled'	Value 'Disabled'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'
Qualifier Key 'Output'	Qualifier Value '1' – '4'	
# HDCPStatusOut example InterfaceName.Update('HDCPStatusOut', {'Device': 'Master', 'Output': '1'}) Value = InterfaceName.ReadStatus('HDCPStatusOut', {'Device': 'Master', 'Output': '1'}) InterfaceName.SubscribeStatus('HDCPStatusOut', None, FeedbackHandler)		
Command	Value	Value

MasterPresetDestinationType	'Program'		'Preview'
# MasterPresetDestinationType example InterfaceName.Update('MasterPresetDestinationType') Value = InterfaceName.ReadStatus('MasterPresetDestinationType') InterfaceName.SubscribeStatus('MasterPresetDestinationType', None, FeedbackHandler)			
Command MasterPresetOriginMemoryNumber	Value '1' – '144'		
# MasterPresetOriginMemoryNumber example InterfaceName.Update('MasterPresetOriginMemoryNumber') Value = InterfaceName.ReadStatus('MasterPresetOriginMemoryNumber') InterfaceName.SubscribeStatus('MasterPresetOriginMemoryNumber', None, FeedbackHandler)			
Command PresetRecallDestinationScreen	Value '1' – '8'		
# PresetRecallDestinationScreen example InterfaceName.Update('PresetRecallDestinationScreen') Value = InterfaceName.ReadStatus('PresetRecallDestinationScreen') InterfaceName.SubscribeStatus('PresetRecallDestinationScreen', None, FeedbackHandler)			
Command PresetRecallDestinationType	Value 'Program'	Value 'Preview'	
# PresetRecallDestinationType example InterfaceName.Update('PresetRecallDestinationType') Value = InterfaceName.ReadStatus('PresetRecallDestinationType') InterfaceName.SubscribeStatus('PresetRecallDestinationType', None, FeedbackHandler)			
Command PresetRecallFilterCategory	Value 'Include'	Value 'Exclude'	
Qualifier Key 'Type'	Qualifier Value 'Source' 'Crop' 'Effects' 'Flying Curve' 'All'	Qualifier Value 'Position' 'Border' 'Timing' 'Native Background'	Qualifier Value 'Transparency' 'Transitions' 'Speed' 'Mask'
# PresetRecallFilterCategory example InterfaceName.Update('PresetRecallFilterCategory', {'Type': 'Source'}) Value = InterfaceName.ReadStatus('PresetRecallFilterCategory', {'Type': 'Source'}) InterfaceName.SubscribeStatus('PresetRecallFilterCategory', None, FeedbackHandler)			
Command PresetRecallOriginMemoryNumber	Value '1' – '144'		
# PresetRecallOriginMemoryNumber example InterfaceName.Update('PresetRecallOriginMemoryNumber') Value = InterfaceName.ReadStatus('PresetRecallOriginMemoryNumber') InterfaceName.SubscribeStatus('PresetRecallOriginMemoryNumber', None, FeedbackHandler)			
Command PresetRecallScale	Value 'Enable automatic resizing'	Value 'Disable automatic resizing'	
# PresetRecallScale example InterfaceName.Update('PresetRecallScale') Value = InterfaceName.ReadStatus('PresetRecallScale') InterfaceName.SubscribeStatus('PresetRecallScale', None, FeedbackHandler)			

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scripter ethernet interface.

Port Type:	Ethernet
Default Port:	10600
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Yes (Max:5)
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Current Plug Analog DVI Device Master Input 1	0,1INplg\x0A
Current Plug Analog DVI Device Master Input 12	11,1INplg\x0A
Current Plug Analog DVI Device Slave Input 1	12,1INplg\x0A
Current Plug Analog DVI Device Slave Input 12	23,1INplg\x0A
Current Plug Analog HD15 Device Master Input 1	0,0INplg\x0A
Current Plug Analog HD15 Device Master Input 12	11,0INplg\x0A
Current Plug Analog HD15 Device Slave Input 1	12,0INplg\x0A
Current Plug Analog HD15 Device Slave Input 12	23,0INplg\x0A
Current Plug Display Port Device Master Input 1	0,5INplg\x0A
Current Plug Display Port Device Master Input 12	11,5INplg\x0A
Current Plug Display Port Device Slave Input 1	12,5INplg\x0A
Current Plug Display Port Device Slave Input 12	23,5INplg\x0A
Current Plug DVI Device Master Input 1	0,2INplg\x0A
Current Plug DVI Device Master Input 12	11,2INplg\x0A
Current Plug DVI Device Slave Input 1	12,2INplg\x0A
Current Plug DVI Device Slave Input 12	23,2INplg\x0A
Current Plug HDMI Device Master Input 1	0,4INplg\x0A
Current Plug HDMI Device Master Input 12	11,4INplg\x0A
Current Plug HDMI Device Slave Input 1	12,4INplg\x0A
Current Plug HDMI Device Slave Input 12	23,4INplg\x0A
Current Plug SDI Device Master Input 1	0,3INplg\x0A
Current Plug SDI Device Master Input 12	11,3INplg\x0A
Current Plug SDI Device Slave Input 1	12,3INplg\x0A
Current Plug SDI Device Slave Input 12	23,3INplg\x0A
GPI Mode Normal Device Master	0,0GPimo\x0A
GPI Mode Normal Device Slave	1,0GPimo\x0A
GPI Mode Take Device Master	0,1GPimo\x0A
GPI Mode Take Device Slave	1,1GPimo\x0A
GPIO Take Screen 1 Device Master	0,0,GPits\x0A
GPIO Take Screen 1 Device Slave	1,0,GPits\x0A
GPIO Take Screen 8 Device Master	0,7,GPits\x0A
GPIO Take Screen 8 Device Slave	1,7,GPits\x0A
GPO Mode Free Device Master Output 1	0,0GPomo\x0A
GPO Mode Free Device Master Output 5	4,0GPomo\x0A
GPO Mode Free Device Slave Output 1	5,0GPomo\x0A
GPO Mode Free Device Slave Output 5	9,0GPomo\x0A
GPO Mode Tally after transition Device Master Output 1	0,2GPomo\x0A
GPO Mode Tally after transition Device Master Output 5	4,2GPomo\x0A
GPO Mode Tally after transition Device Slave Output 1	5,2GPomo\x0A
GPO Mode Tally after transition Device Slave Output	9,2GPomo\x0A

Global Scriptor Module Communication Sheet

5	
GPO Mode Tally before transition Device Master Output 1	0,1GPomo\x0A
GPO Mode Tally before transition Device Master Output 5	4,1GPomo\x0A
GPO Mode Tally before transition Device Slave Output 1	5,1GPomo\x0A
GPO Mode Tally before transition Device Slave Output 5	9,1GPomo\x0A
Input Auto Set None Device Master Input 1	0,INasi\x0A
Input Auto Set None Device Master Input 12	11,INasi\x0A
Input Auto Set None Device Slave Input 1	12,INasi\x0A
Input Auto Set None Device Slave Input 12	23,INasi\x0A
Input Freeze Off Device Master Input 1	0,0INfrz\x0A
Input Freeze Off Device Master Input 12	11,0INfrz\x0A
Input Freeze Off Device Slave Input 1	12,0INfrz\x0A
Input Freeze Off Device Slave Input 12	23,0INfrz\x0A
Input Freeze On Device Master Input 1	0,1INfrz\x0A
Input Freeze On Device Master Input 12	11,1INfrz\x0A
Input Freeze On Device Slave Input 1	12,1INfrz\x0A
Input Freeze On Device Slave Input 12	23,1INfrz\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers A Screen 1	0,0,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers A Screen 8	7,0,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers B Screen 1	0,0,1,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers B Screen 8	7,0,1,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers C Screen 1	0,0,2,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers C Screen 8	7,0,2,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers D Screen 1	0,0,3,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers D Screen 8	7,0,3,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers E Screen 1	0,0,4,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers E Screen 8	7,0,4,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers F Screen 1	0,0,5,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Main Layers F Screen 8	7,0,5,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode	0,1,0,41SPPEi\x0A

Global Scriptor Module Communication Sheet

Preview Layers A Screen 1	
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers A Screen 8	7,1,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers B Screen 1	0,1,1,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers B Screen 8	7,1,1,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers C Screen 1	0,1,2,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers C Screen 8	7,1,2,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers D Screen 1	0,1,3,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers D Screen 8	7,1,3,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers E Screen 1	0,1,4,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers E Screen 8	7,1,4,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers F Screen 1	0,1,5,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Preset Mode Preview Layers F Screen 8	7,1,5,41SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,25SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Frame 1 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,25SPPEi\x0A
Layer Input Frame 1 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,25SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,29SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers F Screen 8	
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,29SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,26SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Frame 2 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,26SPPEi\x0A
Layer Input Frame 2 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,26SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode	0,0,5,30SPPEi\x0A

Global Scriptor Module Communication Sheet

Main Layers F Screen 1	
Layer Input Frame 2 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,30SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,27SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Frame 3 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,27SPPEi\x0A
Layer Input Frame 3 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,27SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode	7,0,4,31SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers E Screen 8	
Layer Input Frame 3 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,31SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,28SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Frame 4 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,28SPPEi\x0A
Layer Input Frame 4 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,28SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode	0,0,4,32SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers E Screen 1	
Layer Input Frame 4 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,32SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,1SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 1 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,1SPPEi\x0A
Layer Input Input 1 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,1SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode	7,0,3,13SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers D Screen 8	
Layer Input Input 1 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,13SPPEi\x0A
Layer Input Input 1 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,13SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,10SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 10 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,10SPPEi\x0A
Layer Input Input 10 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,10SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode	0,0,3,22SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers D Screen 1	
Layer Input Input 10 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,22SPPEi\x0A
Layer Input Input 10 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,22SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,11SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 11 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,11SPPEi\x0A
Layer Input Input 11 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,11SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode	7,0,2,23SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers C Screen 8	
Layer Input Input 11 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,23SPPEi\x0A
Layer Input Input 11 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,23SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,12SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 12 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,12SPPEi\x0A
Layer Input Input 12 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,12SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode	0,0,2,24SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers C Screen 1	
Layer Input Input 12 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,24SPPEi\x0A
Layer Input Input 12 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,24SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,2SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 2 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,2SPPEi\x0A
Layer Input Input 2 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,2SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode	7,0,1,14SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers B Screen 8	
Layer Input Input 2 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,14SPPEi\x0A
Layer Input Input 2 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,14SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,3SPPEi\x0A

Global Scriptor Module Communication Sheet

Layer Input Input 3 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,3SPPEi\x0A
Layer Input Input 3 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,3SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode	0,0,1,15SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers B Screen 1	
Layer Input Input 3 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,15SPPEi\x0A
Layer Input Input 3 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,15SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,4SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 4 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,4SPPEi\x0A
Layer Input Input 4 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,4SPPEi\x0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,16SPPEi\x0A
Layer Input Input 4 of Slave Device Preset Mode	7,0,0,16SPPEi\x0A

Global Scripter Module Communication Sheet

Main Layers A Screen 8	
Layer Input Input 4 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,16SPPEi\X0A
Layer Input Input 4 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,16SPPEi\X0A
Layer Input Input 5 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,5SPPEi\X0A

Global Scripter Module Communication Sheet

Layer Input Input 5 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,5SPPEi\x0A
Layer Input Input 5 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,5SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode	0,0,0,17SPPEi\x0A

Global Scriptor Module Communication Sheet

Main Layers A Screen 1	
Layer Input Input 5 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,17SPPEi\x0A
Layer Input Input 5 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,17SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 6 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,6SPPEi\x0A
Layer Input Input 6 of Master Device Preset Mode	7,1,5,6SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers F Screen 8	
Layer Input Input 6 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,18SPPEi\x0A
Layer Input Input 6 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,18SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 6 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,18SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,7SPPEi\x0A
Layer Input Input 7 of Master Device Preset Mode	0,1,5,7SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers F Screen 1	
Layer Input Input 7 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,7SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,19SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 7 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,19SPPEi\x0A
Layer Input Input 7 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,19SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode	7,1,4,8SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers E Screen 8	
Layer Input Input 8 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,8SPPEi\x0A
Layer Input Input 8 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,8SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,20SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 8 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,20SPPEi\x0A
Layer Input Input 8 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,20SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode	0,1,4,9SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers E Screen 1	
Layer Input Input 9 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,9SPPEi\x0A
Layer Input Input 9 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,9SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,21SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 9 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,21SPPEi\x0A
Layer Input Input 9 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,21SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode	7,1,3,33SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers D Screen 8	
Layer Input Logo 1 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,33SPPEi\x0A
Layer Input Logo 1 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,33SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,37SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Logo 1 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,37SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode	0,1,3,34SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers D Screen 1	
Layer Input Logo 2 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,34SPPEi\x0A
Layer Input Logo 2 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,34SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,38SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Logo 2 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,38SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers C Screen 1	0,1,2,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode	7,1,2,35SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers C Screen 8	
Layer Input Logo 3 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,35SPPEi\x0A
Layer Input Logo 3 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,35SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,39SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Logo 3 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,39SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers A Screen 1	0,0,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers A Screen 8	7,0,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers B Screen 1	0,0,1,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers B Screen 8	7,0,1,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers C Screen 1	0,0,2,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers C Screen 8	7,0,2,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers D Screen 1	0,0,3,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers D Screen 8	7,0,3,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers E Screen 1	0,0,4,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers E Screen 8	7,0,4,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers F Screen 1	0,0,5,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Main Layers F Screen 8	7,0,5,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers A Screen 1	0,1,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers A Screen 8	7,1,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers B Screen 1	0,1,1,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers B Screen 8	7,1,1,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode	0,1,2,36SPPEi\x0A

Global Scripter Module Communication Sheet

Preview Layers C Screen 1	
Layer Input Logo 4 of Master Device Preset Mode Preview Layers C Screen 8	7,1,2,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers D Screen 1	0,1,3,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers D Screen 8	7,1,3,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers E Screen 1	0,1,4,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers E Screen 8	7,1,4,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers F Screen 1	0,1,5,36SPPEi\x0A
Layer Input Logo 4 of Master Device Preset Mode Preview Layers F Screen 8	7,1,5,36SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers A Screen 1	0,0,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers A Screen 8	7,0,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers B Screen 1	0,0,1,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers B Screen 8	7,0,1,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers C Screen 1	0,0,2,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers C Screen 8	7,0,2,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers D Screen 1	0,0,3,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers D Screen 8	7,0,3,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers E Screen 1	0,0,4,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers E Screen 8	7,0,4,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers F Screen 1	0,0,5,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Main Layers F Screen 8	7,0,5,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers A Screen 1	0,1,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers A Screen 8	7,1,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers B Screen 1	0,1,1,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers B Screen 8	7,1,1,40SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Logo 4 of Slave Device Preset Mode Preview Layers C Screen 1	0,1,2,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers C Screen 8	7,1,2,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers D Screen 1	0,1,3,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers D Screen 8	7,1,3,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers E Screen 1	0,1,4,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers E Screen 8	7,1,4,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers F Screen 1	0,1,5,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Preset Mode Preview Layers F Screen 8	7,1,5,40SPPEi\x0A
Layer Input No Input Preset Mode Main Layers A Screen 1	0,0,0,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers A Screen 8	7,0,0,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers B Screen 1	0,0,1,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers B Screen 8	7,0,1,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers C Screen 1	0,0,2,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers C Screen 8	7,0,2,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers D Screen 1	0,0,3,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers D Screen 8	7,0,3,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers E Screen 1	0,0,4,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers E Screen 8	7,0,4,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers F Screen 1	0,0,5,0SPPEi\x0A
Layer Input No Input Preset Mode Main Layers F Screen 8	7,0,5,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers A Screen 1	0,1,0,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers A Screen 8	7,1,0,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers B Screen 1	0,1,1,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers B Screen 8	7,1,1,0SPPEi\x0A

Global Scripter Module Communication Sheet

Screen 8	
Layer Input No Input Preset Mode Preview Layers C Screen 1	0,1,2,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers C Screen 8	7,1,2,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers D Screen 1	0,1,3,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers D Screen 8	7,1,3,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers E Screen 1	0,1,4,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers E Screen 8	7,1,4,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers F Screen 1	0,1,5,0SPPEi\x0A
Layer Input No Input Preset Mode Preview Layers F Screen 8	7,1,5,0SPPEi\x0A
Master Preset Destination Type Preview	1PSprf\x0A
Master Preset Destination Type Program	0PSprf\x0A
Master Preset Origin Memory Number 1	0PSmet\x0A
Master Preset Origin Memory Number 144	143PSmet\x0A
Master Preset Recall None Screen 1	0,1PSose\x0A
Master Preset Recall None Screen 8	7,1PSose\x0A
Master Preset Reset None	1PSres\x0A
Master Preset Save None Save Mode Auto Allocated by Device	2PSsav\x0A
Master Preset Save None Save Mode No Save Operation	0PSsav\x0A
Master Preset Save None Save Mode Selected by User	1PSsav\x0A
Monitoring Fullscreen Enable Fullscreen Device Master	0,1MLfen\x0A
Monitoring Fullscreen Enable Fullscreen Device Slave	1,1MLfen\x0A
Monitoring Fullscreen Enable Mosaic Device Master	0,0MLfen\x0A
Monitoring Fullscreen Enable Mosaic Device Slave	1,0MLfen\x0A
Native Background 1 Preset Mode Preview Screen 1	0,1,1SPPNi\x0A
Native Background 1 Preset Mode Preview Screen 8	7,1,1SPPNi\x0A
Native Background 1 Preset Mode Program Screen 1	0,0,1SPPNi\x0A
Native Background 1 Preset Mode Program Screen 8	7,0,1SPPNi\x0A
Native Background 8 Preset Mode Preview Screen 1	0,1,8SPPNi\x0A
Native Background 8 Preset Mode Preview Screen 8	7,1,8SPPNi\x0A
Native Background 8 Preset Mode Program Screen 1	0,0,8SPPNi\x0A
Native Background 8 Preset Mode Program Screen 8	7,0,8SPPNi\x0A
Native Background No Native Background Preset Mode Preview Screen 1	0,1,0SPPNi\x0A
Native Background No Native Background Preset	7,1,0SPPNi\x0A

Global Scripter Module Communication Sheet

Mode Preview Screen 8	
Native Background No Native Background Preset Mode Program Screen 1	0,0,0SPPNi\x0A
Native Background No Native Background Preset Mode Program Screen 8	7,0,0SPPNi\x0A
Preset Load and Take None	1PMlot\x0A
Preset Load None	1PMloa\x0A
Preset Recall Destination Screen 1	0PMscf\x0A
Preset Recall Destination Screen 8	7PMscf\x0A
Preset Recall Destination Type Preview	1PMprf\x0A
Preset Recall Destination Type Program	0PMprf\x0A
Preset Recall Filter Category Exclude Type All	0PMcat\x0A
Preset Recall Filter Category Include Type All	4095PMcat\x0A
Preset Recall Origin Memory Number 1	0PMmet\x0A
Preset Recall Origin Memory Number 144	143PMmet\x0A
Preset Recall Scale Disable automatic resizing	0PMlse\x0A
Preset Recall Scale Enable automatic resizing	1PMlse\x0A
Preset Reset None	1PMres\x0A
Preset Save None	1PMsav\x0A
Reboot None Device Master	0,1PCreb\x0A
Reboot None Device Slave	1,1PCreb\x0A
Shutdown Idle Device Master	0,0PCsht\x0A
Shutdown Idle Device Slave	1,0PCsht\x0A
Shutdown Shutdown of device and Enable Wake On Lan Device Master	0,2PCsht\x0A
Shutdown Shutdown of device and Enable Wake On Lan Device Slave	1,2PCsht\x0A
Shutdown Shutdown of device Device Master	0,1PCsht\x0A
Shutdown Shutdown of device Device Slave	1,1PCsht\x0A

Appendix B. Update Commands

Firmware Version Master Device	0,VEupd\x0A
HDCP Status In Input Type Analog Device Master Input 1	0,0,IShdc\x0A
HDCP Status In Input Type Analog Device Master Input 12	11,0,IShdc\x0A
HDCP Status In Input Type Analog Device Slave Input 1	12,0,IShdc\x0A
HDCP Status In Input Type Analog Device Slave Input 12	23,0,IShdc\x0A
HDCP Status In Input Type DisplayPort Device Master Input 1	0,5,IShdc\x0A
HDCP Status In Input Type DisplayPort Device Master Input 12	11,5,IShdc\x0A
HDCP Status In Input Type DisplayPort Device Slave Input 1	12,5,IShdc\x0A
HDCP Status In Input Type DisplayPort Device Slave Input 12	23,5,IShdc\x0A
HDCP Status In Input Type DVI-A Device Master Input 1	0,1,IShdc\x0A
HDCP Status In Input Type DVI-A Device Master Input 12	11,1,IShdc\x0A
HDCP Status In Input Type DVI-A Device Slave Input 1	12,1,IShdc\x0A
HDCP Status In Input Type DVI-A Device Slave Input 12	23,1,IShdc\x0A
HDCP Status In Input Type DVI-D Device Master Input 1	0,2,IShdc\x0A
HDCP Status In Input Type DVI-D Device Master Input 12	11,2,IShdc\x0A
HDCP Status In Input Type DVI-D Device Slave Input 1	12,2,IShdc\x0A
HDCP Status In Input Type DVI-D Device Slave Input 12	23,2,IShdc\x0A
HDCP Status In Input Type HDMI Device Master Input 1	0,4,IShdc\x0A
HDCP Status In Input Type HDMI Device Master Input 12	11,4,IShdc\x0A
HDCP Status In Input Type HDMI Device Slave Input 1	12,4,IShdc\x0A
HDCP Status In Input Type HDMI Device Slave Input 12	23,4,IShdc\x0A
HDCP Status In Input Type SDI Device Master Input 1	0,3,IShdc\x0A
HDCP Status In Input Type SDI Device Master Input 12	11,3,IShdc\x0A
HDCP Status In Input Type SDI Device Slave Input 1	12,3,IShdc\x0A

Global Scriptor Module Communication Sheet

HDCP Status In Input Type SDI Device Slave Input 12	23,3,IShdc\x0A
HDCP Status Out Device Master Output 1	0,0Uihc\x0A
HDCP Status Out Device Master Output 4	3,0Uihc\x0A
HDCP Status Out Device Slave Output 1	4,0Uihc\x0A
HDCP Status Out Device Slave Output 4	7,0Uihc\x0A
Master Preset Destination Type	PSprf\x0A
Master Preset Origin Memory Number	PSmet\x0A
Preset Recall Destination Type	PMprf\x0A
Preset Recall Filter Category Type All	PMcat\x0A
Preset Recall Filter Category Type Border	PMcat\x0A
Preset Recall Filter Category Type Crop	PMcat\x0A
Preset Recall Filter Category Type Effects	PMcat\x0A
Preset Recall Filter Category Type Flying Curve	PMcat\x0A
Preset Recall Filter Category Type Mask	PMcat\x0A
Preset Recall Filter Category Type Native Background	PMcat\x0A
Preset Recall Filter Category Type Position	PMcat\x0A
Preset Recall Filter Category Type Source	PMcat\x0A
Preset Recall Filter Category Type Speed	PMcat\x0A
Preset Recall Filter Category Type Timing	PMcat\x0A
Preset Recall Filter Category Type Transitions	PMcat\x0A
Preset Recall Filter Category Type Transparency	PMcat\x0A
Preset Recall Origin Memory Number	PMmet\x0A
Preset Recall Scale	PMlse\x0A

