
This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Video Processor
Manufacturer: Analog Way
Firmware Version: N/A
Model(s): ASC48LE-4K

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.04.0002-b003	2.3.1

Version History

Module Version	Date	Notes
1_0_0_0	12/5/2019	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Class and Example

EthernetClass

<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 10600, Model='ASC48LE-4K')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command CurrentPlug	Value 'Analog HD15' 'SDI'	Value 'Analog DVI' 'HDMI'	Value 'DVI' 'Display Port'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Input'	Qualifier Value '1' – '12'		
# CurrentPlug example InterfaceName.Set('CurrentPlug', 'Analog HD15', {'Device': 'Master', 'Input': '1'})			
Command GPIMode	Value 'Normal'	Value 'Take'	
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# GPIMode example InterfaceName.Set('GPIMode', 'Normal', {'Device': 'Master'})			
Command GPITakeScreen	Value '1' – '8'		
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# GPITakeScreen example InterfaceName.Set('GPITakeScreen', '1', {'Device': 'Master'})			
Command GPOMode	Value 'Free'	Value 'Tally before transition'	Value 'Tally after transition'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Output'	Qualifier Value '1' – '5'		
# GPOMode example InterfaceName.Set('GPOMode', 'Free', {'Device': 'Master', 'Output': '1'})			
Command InputAutoSet	Value None		
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Input'	Qualifier Value '1' – '12'		
# InputAutoSet example InterfaceName.Set('InputAutoSet', None, {'Device': 'Master', 'Input': '1'})			
Command InputFreeze	Value 'On'	Value 'Off'	
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
Qualifier Key 'Input'	Qualifier Value '1' – '12'		
# InputFreeze example InterfaceName.Set('InputFreeze', 'On', {'Device': 'Master', 'Input': '1'})			

Global Scripter Module Communication Sheet

Command LayerInput	Value	Value	Value
	'No Input'	'Input 1 of Master Device'	'Input 2 of Master Device'
	'Input 3 of Master Device'	'Input 4 of Master Device'	'Input 5 of Master Device'
	'Input 6 of Master Device'	'Input 7 of Master Device'	'Input 8 of Master Device'
	'Input 9 of Master Device'	'Input 10 of Master Device'	'Input 11 of Master Device'
	'Input 12 of Master Device'	'Input 1 of Slave Device'	'Input 2 of Slave Device'
	'Input 3 of Slave Device'	'Input 4 of Slave Device'	'Input 5 of Slave Device'
	'Input 6 of Slave Device'	'Input 7 of Slave Device'	'Input 8 of Slave Device'
	'Input 9 of Slave Device'	'Input 10 of Slave Device'	'Input 11 of Slave Device'
	'Input 12 of Slave Device'	'Frame 1 of Master Device'	'Frame 2 of Master Device'
	'Frame 3 of Master Device'	'Frame 4 of Master Device'	'Frame 1 of Slave Device'
	'Frame 2 of Slave Device'	'Frame 3 of Slave Device'	'Frame 4 of Slave Device'
	'Logo 1 of Master Device'	'Logo 2 of Master Device'	'Logo 3 of Master Device'
	'Logo 4 of Master Device'	'Logo 1 of Slave Device'	'Logo 2 of Slave Device'
	'Logo 3 of Slave Device'	'Logo 4 of Slave Device'	'Color (or Black) fill of PiP'
Qualifier Key 'Screen'	Qualifier Value '1' – '8'		
Qualifier Key 'Preset Mode'	Qualifier Value 'Main'	Qualifier Value 'Preview'	
Qualifier Key 'Layer'	Qualifier Value '1' – '24'		
# LayerInput example InterfaceName.Set('LayerInput', 'No Input', {'Screen': '1', 'Preset Mode': 'Main', 'Layer': '1'})			
Command MasterPresetMode	Value 'Program'	Value 'Preview'	
# MasterPresetMode example InterfaceName.Set('MasterPresetMode', 'Program')			
Command MasterPresetOriginMemoryNumber	Value '1' – '144'		
# MasterPresetOriginMemoryNumber example InterfaceName.Set('MasterPresetOriginMemoryNumber', '1')			
Command MasterPresetRecall	Value None		
Qualifier Key 'Screen'	Qualifier Value '1' – '8'		
# MasterPresetRecall example InterfaceName.Set('MasterPresetRecall', None, {'Screen': '1'})			

Global Scripter Module Communication Sheet

Revision: 12/5/2019

Command	Value		
MasterPresetReset	None		
# MasterPresetReset example InterfaceName.Set('MasterPresetReset', None)			
Command	Value		
MasterPresetSave	None		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Save Mode'	'No Save Operation'	'Selected by User'	'Auto Allocated by Device'
# MasterPresetSave example InterfaceName.Set('MasterPresetSave', None, {'Save Mode': 'No Save Operation'})			
Command	Value	Value	
MonitoringFullscreen	'Mosaic'	'Fullscreen'	
Qualifier Key	Qualifier Value	Qualifier Value	
'Device'	'Master'	'Slave'	
# MonitoringFullscreen example InterfaceName.Set('MonitoringFullscreen', 'Mosaic', {'Device': 'Master'})			
Command	Value	Value	
NativeBackground	'1' – '8'	None	
Qualifier Key	Qualifier Value	Qualifier Value	
'Preset Mode'	'Program'	'Preview'	
Qualifier Key	Qualifier Value		
'Screen'	'1' – '8'		
# NativeBackground example InterfaceName.Set('NativeBackground', '1', {'Preset Mode': 'Program', 'Screen': '1'})			
Command	Value	Value	
PresetFilterCategory	'Include'	'Exclude'	
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Type'	'Source'	'Position'	'Transparency'
	'Crop'	'Border'	'Transitions'
	'Effects'	'Timing'	'Speed'
	'Flying Curve'	'Native Background'	'Mask'
	'All'		
# PresetFilterCategory example InterfaceName.Set('PresetFilterCategory', 'Include', {'Type': 'Source'})			
Command	Value		
PresetLoad	None		
# PresetLoad example InterfaceName.Set('PresetLoad', None)			
Command	Value		
PresetLoadandTake	None		
# PresetLoadandTake example InterfaceName.Set('PresetLoadandTake', None)			
Command	Value	Value	
PresetMode	'Program'	'Preview'	
# PresetMode example InterfaceName.Set('PresetMode', 'Program')			
Command	Value		
PresetOriginMemoryNumber	'1' – '144'		
# PresetOriginMemoryNumber example InterfaceName.Set('PresetOriginMemoryNumber', '1')			
Command	Value	Value	

Global Scripter Module Communication Sheet

PresetRecallScale	'Enable automatic resizing'	'Disable automatic resizing'	
# PresetRecallScale example InterfaceName.Set('PresetRecallScale', 'Enable automatic resizing')			
Command PresetRecallScreen	Value '1' – '8'		
# PresetRecallScreen example InterfaceName.Set('PresetRecallScreen', '1')			
Command PresetReset	Value None		
# PresetReset example InterfaceName.Set('PresetReset', None)			
Command PresetSave	Value None		
# PresetSave example InterfaceName.Set('PresetSave', None)			
Command Reboot	Value None		
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# Reboot example InterfaceName.Set('Reboot', None, {'Device': 'Master'})			
Command Shutdown	Value 'Idle'	Value 'Shutdown of device'	Value 'Shutdown of device and Enable Wake On Lan'
Qualifier Key 'Device'	Qualifier Value 'Master'	Qualifier Value 'Slave'	
# Shutdown example InterfaceName.Set('Shutdown', 'Idle', {'Device': 'Master'})			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
ConnectionStatus	'Connected'	'Disconnected'
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	
Firmware	'String'	
# Firmware example InterfaceName.Update('Firmware') Value = InterfaceName.ReadStatus('Firmware') InterfaceName.SubscribeStatus('Firmware', None, FeedbackHandler)		
Command	Value	Value
HDCPInputStatus	'Enabled'	'Disabled'
Qualifier Key	Qualifier Value	Qualifier Value
'Device'	'Master'	'Slave'
Qualifier Key	Qualifier Value	
'Input'	'1' – '12'	
Qualifier Key	Qualifier Value	Qualifier Value
'Input Type'	'Analog'	'DVI-A'
	'SDI'	'HDMI'
		'DVI-D'
		'DisplayPort'
# HDCPInputStatus example InterfaceName.Update('HDCPInputStatus', {'Device': 'Master', 'Input': '1', 'Input Type': 'Analog'}) Value = InterfaceName.ReadStatus('HDCPInputStatus', {'Device': 'Master', 'Input': '1', 'Input Type': 'Analog'}) InterfaceName.SubscribeStatus('HDCPInputStatus', None, FeedbackHandler)		
Command	Value	Value
HDCPOutputStatus	'Enabled'	'Disabled'
Qualifier Key	Qualifier Value	Qualifier Value
'Device'	'Master'	'Slave'
Qualifier Key	Qualifier Value	
'Output'	'1' – '4'	
# HDCPOutputStatus example InterfaceName.Update('HDCPOutputStatus', {'Device': 'Master', 'Output': '1'}) Value = InterfaceName.ReadStatus('HDCPOutputStatus', {'Device': 'Master', 'Output': '1'}) InterfaceName.SubscribeStatus('HDCPOutputStatus', None, FeedbackHandler)		
Command	Value	Value
MasterPresetMode	'Program'	'Preview'

# MasterPresetMode example InterfaceName.Update('MasterPresetMode') Value = InterfaceName.ReadStatus('MasterPresetMode') InterfaceName.SubscribeStatus('MasterPresetMode', None, FeedbackHandler)			
Command MasterPresetOriginMemoryNumber	Value '1' – '144'		
# MasterPresetOriginMemoryNumber example InterfaceName.Update('MasterPresetOriginMemoryNumber') Value = InterfaceName.ReadStatus('MasterPresetOriginMemoryNumber') InterfaceName.SubscribeStatus('MasterPresetOriginMemoryNumber', None, FeedbackHandler)			
Command PresetFilterCategory ¹	Value 'Include'	Value 'Exclude'	
Qualifier Key 'Type'	Qualifier Value 'Source' 'Crop' 'Effects' 'Flying Curve' 'All'	Qualifier Value 'Position' 'Border' 'Timing' 'Native Background'	Qualifier Value 'Transparency' 'Transitions' 'Speed' 'Mask'
# PresetFilterCategory example InterfaceName.Update('PresetFilterCategory') Value = InterfaceName.ReadStatus('PresetFilterCategory', {'Type': 'Source'}) InterfaceName.SubscribeStatus('PresetFilterCategory', None, FeedbackHandler)			
Command PresetMode	Value 'Program'	Value 'Preview'	
# PresetMode example InterfaceName.Update('PresetMode') Value = InterfaceName.ReadStatus('PresetMode') InterfaceName.SubscribeStatus('PresetMode', None, FeedbackHandler)			
Command PresetOriginMemoryNumber	Value '1' – '144'		
# PresetOriginMemoryNumber example InterfaceName.Update('PresetOriginMemoryNumber') Value = InterfaceName.ReadStatus('PresetOriginMemoryNumber') InterfaceName.SubscribeStatus('PresetOriginMemoryNumber', None, FeedbackHandler)			
Command PresetRecallScale	Value 'Enable automatic resizing'	Value 'Disable automatic resizing'	
# PresetRecallScale example InterfaceName.Update('PresetRecallScale') Value = InterfaceName.ReadStatus('PresetRecallScale') InterfaceName.SubscribeStatus('PresetRecallScale', None, FeedbackHandler)			
Command PresetRecallScreen	Value '1' – '8'		
# PresetRecallScreen example InterfaceName.Update('PresetRecallScreen') Value = InterfaceName.ReadStatus('PresetRecallScreen') InterfaceName.SubscribeStatus('PresetRecallScreen', None, FeedbackHandler)			

¹ Qualifier parameters is not required when calling the Update method with this command because the response returns statuses for all qualifier states.

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type:	Ethernet
Default Port:	10600
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Yes (Max: 5)
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Current Plug Analog DVI Device Master Input 1	0,1INplg\x0A
Current Plug Analog DVI Device Master Input 12	11,1INplg\x0A
Current Plug Analog DVI Device Slave Input 1	12,1INplg\x0A
Current Plug Analog DVI Device Slave Input 12	23,1INplg\x0A
Current Plug Analog HD15 Device Master Input 1	0,0INplg\x0A
Current Plug Analog HD15 Device Master Input 12	11,0INplg\x0A
Current Plug Analog HD15 Device Slave Input 1	12,0INplg\x0A
Current Plug Analog HD15 Device Slave Input 12	23,0INplg\x0A
Current Plug Display Port Device Master Input 1	0,5INplg\x0A
Current Plug Display Port Device Master Input 12	11,5INplg\x0A
Current Plug Display Port Device Slave Input 1	12,5INplg\x0A
Current Plug Display Port Device Slave Input 12	23,5INplg\x0A
Current Plug DVI Device Master Input 1	0,2INplg\x0A
Current Plug DVI Device Master Input 12	11,2INplg\x0A
Current Plug DVI Device Slave Input 1	12,2INplg\x0A
Current Plug DVI Device Slave Input 12	23,2INplg\x0A
Current Plug HDMI Device Master Input 1	0,4INplg\x0A
Current Plug HDMI Device Master Input 12	11,4INplg\x0A
Current Plug HDMI Device Slave Input 1	12,4INplg\x0A
Current Plug HDMI Device Slave Input 12	23,4INplg\x0A
Current Plug SDI Device Master Input 1	0,3INplg\x0A
Current Plug SDI Device Master Input 12	11,3INplg\x0A
Current Plug SDI Device Slave Input 1	12,3INplg\x0A
Current Plug SDI Device Slave Input 12	23,3INplg\x0A
GPI Mode Normal Device Master	0,0GPimo\x0A
GPI Mode Normal Device Slave	1,0GPimo\x0A
GPI Mode Take Device Master	0,1GPimo\x0A
GPI Mode Take Device Slave	1,1GPimo\x0A
GPIO Take Screen 1 Device Master	0,0GPits\x0A
GPIO Take Screen 1 Device Slave	1,0GPits\x0A
GPIO Take Screen 8 Device Master	0,7GPits\x0A
GPIO Take Screen 8 Device Slave	1,7GPits\x0A
GPO Mode Free Device Master Output 1	0,0GPomo\x0A
GPO Mode Free Device Master Output 5	4,0GPomo\x0A
GPO Mode Free Device Slave Output 1	5,0GPomo\x0A
GPO Mode Free Device Slave Output 5	9,0GPomo\x0A
GPO Mode Tally after transition Device Master Output 1	0,2GPomo\x0A
GPO Mode Tally after transition Device Master Output 5	4,2GPomo\x0A
GPO Mode Tally after transition Device Slave Output 1	5,2GPomo\x0A
GPO Mode Tally after transition Device Slave Output	9,2GPomo\x0A

Global Scripter Module Communication Sheet

5	
GPO Mode Tally before transition Device Master Output 1	0,1GPomo\x0A
GPO Mode Tally before transition Device Master Output 5	4,1GPomo\x0A
GPO Mode Tally before transition Device Slave Output 1	5,1GPomo\x0A
GPO Mode Tally before transition Device Slave Output 5	9,1GPomo\x0A
Input Auto Set None Device Master Input 1	0INasi\x0A
Input Auto Set None Device Master Input 12	11INasi\x0A
Input Auto Set None Device Slave Input 1	12INasi\x0A
Input Auto Set None Device Slave Input 12	23INasi\x0A
Input Freeze Off Device Master Input 1	0,0INfrz\x0A
Input Freeze Off Device Master Input 12	11,0INfrz\x0A
Input Freeze Off Device Slave Input 1	12,0INfrz\x0A
Input Freeze Off Device Slave Input 12	23,0INfrz\x0A
Input Freeze On Device Master Input 1	0,1INfrz\x0A
Input Freeze On Device Master Input 12	11,1INfrz\x0A
Input Freeze On Device Slave Input 1	12,1INfrz\x0A
Input Freeze On Device Slave Input 12	23,1INfrz\x0A
Layer Input Color (or Black) fill of PiP Screen 1 Preset Mode Main Layer 1	0,0,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 1 Preset Mode Main Layer 24	0,0,23,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 1 Preset Mode Preview Layer 1	0,1,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 1 Preset Mode Preview Layer 24	0,1,23,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 8 Preset Mode Main Layer 1	7,0,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 8 Preset Mode Main Layer 24	7,0,23,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 8 Preset Mode Preview Layer 1	7,1,0,41SPPEi\x0A
Layer Input Color (or Black) fill of PiP Screen 8 Preset Mode Preview Layer 24	7,1,23,41SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,25SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,25SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 8	7,0,0,25SPPEi\x0A

Global Scripter Module Communication Sheet

Preset Mode Main Layer 1	
Layer Input Frame 1 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,25SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,25SPPEi\x0A
Layer Input Frame 1 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,25SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,29SPPEi\x0A
Layer Input Frame 1 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,29SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,26SPPEi\x0A
Layer Input Frame 2 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,26SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,30SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Frame 2 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,30SPPEi\x0A
Layer Input Frame 2 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,30SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,27SPPEi\x0A
Layer Input Frame 3 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,27SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,31SPPEi\x0A
Layer Input Frame 3 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,31SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,28SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,28SPPEi\x0A

Global Scripter Module Communication Sheet

Preset Mode Preview Layer 24	
Layer Input Frame 4 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,28SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,28SPPEi\x0A
Layer Input Frame 4 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,28SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,32SPPEi\x0A
Layer Input Frame 4 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,32SPPEi\x0A
Layer Input Input 1 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,1SPPEi\x0A
Layer Input Input 1 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,1SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,13SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,13SPPEi\x0A

Global Scripter Module Communication Sheet

Revision: 12/5/2019

Layer Input Input 1 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,13SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,13SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,13SPPEi\x0A
Layer Input Input 1 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,13SPPEi\x0A
Layer Input Input 10 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,10SPPEi\x0A
Layer Input Input 10 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,10SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,22SPPEi\x0A
Layer Input Input 10 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,22SPPEi\x0A
Layer Input Input 11 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,11SPPEi\x0A
Layer Input Input 11 of Master Device Screen 1	0,1,0,11SPPEi\x0A

Global Scripter Module Communication Sheet

Preset Mode Preview Layer 1	
Layer Input Input 11 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,11SPPEi\x0A
Layer Input Input 11 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,11SPPEi\x0A
Layer Input Input 11 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,11SPPEi\x0A
Layer Input Input 11 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,11SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,23SPPEi\x0A
Layer Input Input 11 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,23SPPEi\x0A
Layer Input Input 12 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,12SPPEi\x0A
Layer Input Input 12 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,12SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,24SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 12 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,24SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,24SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,24SPPEi\x0A
Layer Input Input 12 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,24SPPEi\x0A
Layer Input Input 2 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,2SPPEi\x0A
Layer Input Input 2 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,2SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,14SPPEi\x0A
Layer Input Input 2 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,14SPPEi\x0A
Layer Input Input 3 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Screen 1 Preset	0,0,23,3SPPEi\x0A

Global Scripter Module Communication Sheet

Mode Main Layer 24	
Layer Input Input 3 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,3SPPEi\x0A
Layer Input Input 3 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,3SPPEi\x0A
Layer Input Input 3 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,3SPPEi\x0A
Layer Input Input 3 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,3SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,15SPPEi\x0A
Layer Input Input 3 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,15SPPEi\x0A
Layer Input Input 4 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,4SPPEi\x0A
Layer Input Input 4 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,4SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,16SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 4 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,16SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,16SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,16SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,16SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,16SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,16SPPEi\x0A
Layer Input Input 4 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,16SPPEi\x0A
Layer Input Input 5 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,5SPPEi\x0A
Layer Input Input 5 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,5SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,17SPPEi\x0A
Layer Input Input 5 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,17SPPEi\x0A
Layer Input Input 6 of Master Device Screen 1 Preset	0,0,0,6SPPEi\x0A

Global Scriptor Module Communication Sheet

Mode Main Layer 1	
Layer Input Input 6 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,6SPPEi\x0A
Layer Input Input 6 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,6SPPEi\x0A
Layer Input Input 6 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,6SPPEi\x0A
Layer Input Input 6 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,6SPPEi\x0A
Layer Input Input 6 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,6SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,18SPPEi\x0A
Layer Input Input 6 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,18SPPEi\x0A
Layer Input Input 7 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,7SPPEi\x0A
Layer Input Input 7 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,7SPPEi\x0A

Global Scripter Module Communication Sheet

Layer Input Input 7 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,19SPPEi\x0A
Layer Input Input 7 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,19SPPEi\x0A
Layer Input Input 8 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,8SPPEi\x0A
Layer Input Input 8 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,8SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,20SPPEi\x0A
Layer Input Input 8 of Slave Device Screen 8 Preset	7,1,23,20SPPEi\x0A

Global Scripter Module Communication Sheet

Mode Preview Layer 24	
Layer Input Input 9 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,9SPPEi\x0A
Layer Input Input 9 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,9SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,21SPPEi\x0A
Layer Input Input 9 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,21SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,33SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,33SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,33SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,33SPPEi\x0A
Layer Input Logo 1 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,33SPPEi\x0A

Global Scripter Module Communication Sheet

Revision: 12/5/2019

Layer Input Logo 1 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,33SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,37SPPEi\x0A
Layer Input Logo 1 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,37SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,34SPPEi\x0A
Layer Input Logo 2 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,34SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,38SPPEi\x0A
Layer Input Logo 2 of Slave Device Screen 8 Preset	7,1,0,38SPPEi\x0A

Global Scripter Module Communication Sheet

Mode Preview Layer 1	
Layer Input Logo 2 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,38SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,35SPPEi\x0A
Layer Input Logo 3 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,35SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,39SPPEi\x0A
Layer Input Logo 3 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,39SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 1 Preset Mode Main Layer 1	0,0,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 1 Preset Mode Main Layer 24	0,0,23,36SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 1 Preset Mode Preview Layer 1	0,1,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 1 Preset Mode Preview Layer 24	0,1,23,36SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 8 Preset Mode Main Layer 1	7,0,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 8 Preset Mode Main Layer 24	7,0,23,36SPPEi\x0A

Global Scripter Module Communication Sheet

Revision: 12/5/2019

Layer Input Logo 4 of Master Device Screen 8 Preset Mode Preview Layer 1	7,1,0,36SPPEi\x0A
Layer Input Logo 4 of Master Device Screen 8 Preset Mode Preview Layer 24	7,1,23,36SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 1 Preset Mode Main Layer 1	0,0,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 1 Preset Mode Main Layer 24	0,0,23,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 1 Preset Mode Preview Layer 1	0,1,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 1 Preset Mode Preview Layer 24	0,1,23,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 8 Preset Mode Main Layer 1	7,0,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 8 Preset Mode Main Layer 24	7,0,23,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 8 Preset Mode Preview Layer 1	7,1,0,40SPPEi\x0A
Layer Input Logo 4 of Slave Device Screen 8 Preset Mode Preview Layer 24	7,1,23,40SPPEi\x0A
Layer Input No Input Screen 1 Preset Mode Main Layer 1	0,0,0,0SPPEi\x0A
Layer Input No Input Screen 1 Preset Mode Main Layer 24	0,0,23,0SPPEi\x0A
Layer Input No Input Screen 1 Preset Mode Preview Layer 1	0,1,0,0SPPEi\x0A
Layer Input No Input Screen 1 Preset Mode Preview Layer 24	0,1,23,0SPPEi\x0A
Layer Input No Input Screen 8 Preset Mode Main Layer 1	7,0,0,0SPPEi\x0A
Layer Input No Input Screen 8 Preset Mode Main Layer 24	7,0,23,0SPPEi\x0A
Layer Input No Input Screen 8 Preset Mode Preview Layer 1	7,1,0,0SPPEi\x0A
Layer Input No Input Screen 8 Preset Mode Preview Layer 24	7,1,23,0SPPEi\x0A
Master Preset Mode Preview	1PSprf\x0A
Master Preset Mode Program	0PSprf\x0A
Master Preset Origin Memory Number 1	0PSmet\x0A
Master Preset Origin Memory Number 144	143PSmet\x0A
Master Preset Recall None Screen 1	0,1PSose\x0A
Master Preset Recall None Screen 8	7,1PSose\x0A
Master Preset Reset None	1PSres\x0A
Master Preset Save None Save Mode Auto Allocated by Device	2PSsav\x0A
Master Preset Save None Save Mode No Save	0PSsav\x0A

Global Scriptor Module Communication Sheet

Operation	
Master Preset Save None Save Mode Selected by User	1PSsav\x0A
Monitoring Fullscreen Fullscreen Device Master	0,1MLfen\x0A
Monitoring Fullscreen Fullscreen Device Slave	1,1MLfen\x0A
Monitoring Fullscreen Mosaic Device Master	0,0MLfen\x0A
Monitoring Fullscreen Mosaic Device Slave	1,0MLfen\x0A
Native Background 1 Preset Mode Preview Screen 1	0,1,2SPPNi\x0A
Native Background 1 Preset Mode Preview Screen 8	7,1,2SPPNi\x0A
Native Background 1 Preset Mode Program Screen 1	0,0,2SPPNi\x0A
Native Background 1 Preset Mode Program Screen 8	7,0,2SPPNi\x0A
Native Background 8 Preset Mode Preview Screen 1	0,1,9SPPNi\x0A
Native Background 8 Preset Mode Preview Screen 8	7,1,9SPPNi\x0A
Native Background 8 Preset Mode Program Screen 1	0,0,9SPPNi\x0A
Native Background 8 Preset Mode Program Screen 8	7,0,9SPPNi\x0A
Native Background None Preset Mode Preview Screen 1	0,1,1SPPNi\x0A
Native Background None Preset Mode Preview Screen 8	7,1,1SPPNi\x0A
Native Background None Preset Mode Program Screen 1	0,0,1SPPNi\x0A
Native Background None Preset Mode Program Screen 8	7,0,1SPPNi\x0A
Preset Filter Category Exclude Type All	0PMcat\x0A
Preset Filter Category Include Type All	4095PMcat\x0A
Preset Load and Take None	1PMlot\x0A
Preset Load None	1PMloa\x0A
Preset Mode Preview	1PMprf\x0A
Preset Mode Program	0PMprf\x0A
Preset Origin Memory Number 1	0PMmet\x0A
Preset Origin Memory Number 144	143PMmet\x0A
Preset Recall Scale Disable automatic resizing	0PMlse\x0A
Preset Recall Scale Enable automatic resizing	1PMlse\x0A
Preset Recall Screen 1	0PMscf\x0A
Preset Recall Screen 8	7PMscf\x0A
Preset Reset None	1PMres\x0A
Preset Save None	1PMsav\x0A
Reboot None Device Master	0,1PCreb\x0A
Reboot None Device Slave	1,1PCreb\x0A
Shutdown Idle Device Master	0,0PCsht\x0A
Shutdown Idle Device Slave	1,0PCsht\x0A
Shutdown Shutdown of device and Enable Wake On Lan Device Master	0,2PCsht\x0A
Shutdown Shutdown of device and Enable Wake On Lan Device Slave	1,2PCsht\x0A

Global Scriptor Module Communication Sheet

Shutdown Shutdown of device Device Master	0,1PCsht\x0A
Shutdown Shutdown of device Device Slave	1,1PCsht\x0A

Appendix B. Update Commands

Firmware	0,VEupd\x0A
HDCP Input Status Device Master Input 1 Input Type Analog	0,0,IShdc\x0A
HDCP Input Status Device Master Input 1 Input Type DisplayPort	0,5,IShdc\x0A
HDCP Input Status Device Master Input 1 Input Type DVI-A	0,1,IShdc\x0A
HDCP Input Status Device Master Input 1 Input Type DVI-D	0,2,IShdc\x0A
HDCP Input Status Device Master Input 1 Input Type HDMI	0,4,IShdc\x0A
HDCP Input Status Device Master Input 1 Input Type SDI	0,3,IShdc\x0A
HDCP Input Status Device Master Input 12 Input Type Analog	11,0,IShdc\x0A
HDCP Input Status Device Master Input 12 Input Type DisplayPort	11,5,IShdc\x0A
HDCP Input Status Device Master Input 12 Input Type DVI-A	11,1,IShdc\x0A
HDCP Input Status Device Master Input 12 Input Type DVI-D	11,2,IShdc\x0A
HDCP Input Status Device Master Input 12 Input Type HDMI	11,4,IShdc\x0A
HDCP Input Status Device Master Input 12 Input Type SDI	11,3,IShdc\x0A
HDCP Input Status Device Slave Input 1 Input Type Analog	12,0,IShdc\x0A
HDCP Input Status Device Slave Input 1 Input Type DisplayPort	12,5,IShdc\x0A
HDCP Input Status Device Slave Input 1 Input Type DVI-A	12,1,IShdc\x0A
HDCP Input Status Device Slave Input 1 Input Type DVI-D	12,2,IShdc\x0A
HDCP Input Status Device Slave Input 1 Input Type HDMI	12,4,IShdc\x0A
HDCP Input Status Device Slave Input 1 Input Type SDI	12,3,IShdc\x0A
HDCP Input Status Device Slave Input 12 Input Type Analog	23,0,IShdc\x0A
HDCP Input Status Device Slave Input 12 Input Type DisplayPort	23,5,IShdc\x0A
HDCP Input Status Device Slave Input 12 Input Type DVI-A	23,1,IShdc\x0A
HDCP Input Status Device Slave Input 12 Input Type DVI-D	23,2,IShdc\x0A

Global Scripter Module Communication Sheet

HDCP Input Status Device Slave Input 12 Input Type HDMI	23,4,IShdc\x0A
HDCP Input Status Device Slave Input 12 Input Type SDI	23,3,IShdc\x0A
HDCP Output Status Device Master Output 1	0,0Uihc\x0A
HDCP Output Status Device Master Output 4	3,0Uihc\x0A
HDCP Output Status Device Slave Output 1	4,0Uihc\x0A
HDCP Output Status Device Slave Output 4	7,0Uihc\x0A
Master Preset Mode	PSprf\x0A
Master Preset Origin Memory Number	PSmet\x0A
Preset Filter Category	PMcat\x0A
Preset Mode	PMprf\x0A
Preset Origin Memory Number	PMmet\x0A
Preset Recall Scale	PMlse\x0A
Preset Recall Screen	PMscf\x0A