

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Display
 Manufacturer: Barco
 Firmware Version: N/A
 Model(s): MDSC-2224 LED, MDSC-2226 LED, MDSC-2232 DDI, MDSC-2242 LED, MDSC-2224 DDI, MDSC-2224 DOI, MDSC-2224 MNA, MDSC-2232 MNA, MDSC-2226 DDI, MDSC-2226 MNA, MDSC-2242 MNA

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2.7

Version History

Module Version	Date	Notes
1_0_1_0	2/9/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

ExecutiveMode	'On'	'Off'	
Input	'SDI' ³ 'S-Video' 'Component' 'DVI 1' ¹	'DVI' ⁴ 'Autosearch' 'SDI 1' ¹ 'DVI 2' ¹	'DisplayPort' 'RGB' 'SDI 2' ¹ 'Nexxis' ²
LoadProfile	'Factory' 'User 2'	'X-Ray' 'User 3'	'User 1'
PIPInputLED/DOI	'SDI' ³ 'S-Video' 'Component' 'DVI 1' ¹	'DVI' ⁴ 'Autosearch' 'SDI 1' ¹ 'DVI 2' ¹	'DisplayPort' 'RGB' 'SDI 2' ¹ 'Nexxis' ²
PIPLayout	'Off' 'Side By Side'	'Large' 'Side By Side Tall'	'Small' 'Side By Side Fill'
PIPSwap	None		
PowerSavingMode	'On'	'Off'	

¹ Only available on DDI models

² Only available on MNA models

³ Not available on MDSC-2224 MNA, MDSC-2242 MNA or DDI models

⁴ Not available on DDI models

Status Available:

Backlight	'On'	'Off'	'Sensor not working'
ConnectionStatus	'Connected'	'Disconnected'	
ExecutiveMode	'On'	'Off'	
InputLED/DOI	'SDI' ³ 'S-Video' 'Component' 'DVI 1' ¹	'DVI' ⁴ 'Autosearch' 'SDI 1' ¹ 'DVI 2' ¹	'DisplayPort' 'RGB' 'SDI 2' ¹ 'Nexxis' ²
LoadProfile	'Factory' 'User 2'	'X-Ray' 'User 3'	'User 1'
OperationHours	0 – 99999		
PIPInputLED/DOI	'SDI' ³ 'S-Video' 'Component' 'DVI 1' ¹	'DVI' ⁴ 'Autosearch' 'SDI 1' ¹ 'DVI 2' ¹	'DisplayPort' 'RGB' 'SDI 2' ¹ 'Nexxis' ²
PIPLayout	'Off' 'Side By Side'	'Large' 'Side By Side Tall'	'Small' 'Side By Side Fill'
PowerSavingMode	'On'	'Off'	
ReleaseInfo	'String'		
SerialNumber	'String'		
SignalStatus	'Present and valid signal'	'Not present or bad signal'	
['Input']	'Main'	'Secondary'	

¹ Only available on DDI models

² Only available on MNA models

³ Not available on MDSC-2224 MNA, MDSC-2242 MNA or DDI models

⁴ Not available on DDI models

Cable and Adapter Requirements:

Please contact manufacturer for cable requirements.

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None

Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Please contact manufacturer for pin diagram.

General Notes:

Appendix A. Set Commands

Executive Mode Off	&&KEY'0;
Executive Mode On	&&KEY'1;
Input Autosearch	&&INP'0;
Input Component	&&INP'8;
Input DisplayPort	&&INP'10;
Input DVI	&&INP'3;
Input DVI 1	&&INP'3;
Input DVI 2	&&INP'4;
Input Nexxis	&&INP'11;
Input RGB	&&INP'7;
Input SDI	&&INP'9;
Input SDI 1	&&INP'9;
Input SDI 2	&&INP'4;
Input S-Video	&&INP'6;
Load Profile Factory	&&PRO'0;
Load Profile User 1	&&PRO'2;
Load Profile User 2	&&PRO'3;
Load Profile User 3	&&PRO'4;
Load Profile X-Ray	&&PRO'1;
PIP Input Autosearch	&&PIPI'0;
PIP Input Component	&&PIPI'8;
PIP Input DisplayPort	&&PIPI'10;
PIP Input DVI	&&PIPI'3;
PIP Input DVI 1	&&PIPI'3;
PIP Input DVI 2	&&PIPI'4;
PIP Input Nexxis	&&PIPI'11;
PIP Input RGB	&&PIPI'7;
PIP Input SDI	&&PIPI'9;
PIP Input SDI 1	&&PIPI'9;
PIP Input SDI 2	&&PIPI'4;
PIP Input S-Video	&&PIPI'6;
PIP Layout Large	&&PIPL'1;
PIP Layout Off	&&PIPL'0;
PIP Layout Side By Side	&&PIPL'3;
PIP Layout Side By Side Fill	&&PIPL'5;
PIP Layout Side By Side Tall	&&PIPL'4;
PIP Layout Small	&&PIPL'2;
PIP Swap None	&&PIPT;
Power Saving Mode Off	&&DPMS'0;
Power Saving Mode On	&&DPMS'1;

Appendix B. Query Commands

Backlight	\x1Bps?
Executive Mode	&&RV'KEY;
Input	&&RV'INP;
Load Profile	&&RV'PRO;
Operation Hours	\x1Bh?
PIP Input	&&RV'PIPI;
PIP Layout	&&RV'PIPL;
Power Saving Mode	&&RV'DPMS;
Release Info	\x1BR?
Serial Number	\x1BSN?