

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Other
Manufacturer: Barco
Firmware Version: N/A
Model(s): E2

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_2_0_0	12/22/2016	Initial Version

Module Notes

- Certain commands work for certain TCP ports only. See the command table for more information.

Control Commands, States, and Qualifiers:

Cut ¹	None
['Destination Manager']	'1' – '100'
['Screen Destination']	'1' – '16'
Preset ²	1 – 1000
['Action']	'Save' 'Recall' 'Recall and Auto Transition'
RoutingVideoSource ¹	None
['Layer']	'1' – '64'
['Screen Destination']	'1' – '16'
['Destination Manager']	'1' – '100'
['Source']	'1' – '100'

¹ For TCP port 9876 only.² For TCP port 9878 only.**Status Available:**

N/A

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	9878 or 9876
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

* GUID is a randomly generated UUID.

Cut Destination Manager 1 Screen Destination 1	<System id="0" GUID="2acd7ac4-b127-48ae-a39b-41885e4e3d00"><DestMgr id="0"><ScreenDestCol id="0"><ScreenDest id="0"><Transition id="0"><Cut></Cut></Transition></ScreenDest></ScreenDestCol></DestMgr></System>
Cut Destination Manager 100 Screen Destination 16	<System id="0" GUID="085641f8-3e43-4f58-bbfb-133b2a61cb37"><DestMgr id="99"><ScreenDestCol id="0"><ScreenDest id="15"><Transition id="0"><Cut></Cut></Transition></ScreenDest></ScreenDestCol></DestMgr></System>
Preset 1 Action Recall	PRESET -r 1.0\x0D\x0A
Preset 1 Action Recall and Auto Transition	PRESET -a 1.0\x0D\x0A
Preset 1 Action Save	PRESET -s 1.0\x0D\x0A
Preset 1000 Action Recall	PRESET -r 1000.0\x0D\x0A
Preset 1000 Action Recall and Auto Transition	PRESET -a 1000.0\x0D\x0A
Preset 1000 Action Save	PRESET -s 1000.0\x0D\x0A
Routing Video Source Layer 1 Screen Destination 1 Destination Manager 1 Source 1	<System id="0" GUID="e3eeadd5-3b49-4b12-ab92-ea7108c475f1"><DestMgr id="0"><ScreenDestCol id="0"><ScreenDest id="0"><LayerCollection id="0"><Layer id="0"><SrcIdx>0</SrcIdx></Layer></LayerCollection></ScreenDest></ScreenDestCol></DestMgr></System>
Routing Video Source Layer 64 Screen Destination 16 Destination Manager 100 Source 100	<System id="0" GUID="2a3e4e80-6a49-4902-9919-ed2085a3f8b8"><DestMgr id="99"><ScreenDestCol id="0"><ScreenDest id="15"><LayerCollection id="0"><Layer id="63"><SrcIdx>99</SrcIdx></Layer></LayerCollection></ScreenDest></ScreenDestCol></DestMgr></System>