

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Barco
Firmware Version: N/A
Model(s): F22

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_0_0_0	3/21/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5
- **Device requires a 5 second delay in Update commands after receiving 20 commands. Module would not allow Updates for 5 seconds after 20 commands had been sent out.

Control Commands, States, and Qualifiers:

AspectRatio	'1:1'	'Fill All'	'Fill Aspect Ratio'
	'Fill 16:9'	'Fill 4:3'	'Letterbox 16:9'
	'Letterbox St 16:9'	'Anamorphic Lens'	
AutoImage	None		
EcoMode	'On'	'Off'	
Focus	'In'	'Out'	
['Speed']	'Slow'	'Medium'	'Fast'
Freeze	'On'	'Off'	
Input	'HDMI'	'DVI'	'S-Video'
	'Composite'	'YPbPr'	'VGA'
MenuNavigation	'Menu'	'Up'	'Down'
	'Left'	'Right'	'OK'
OnScreenDisplay	'Off'	'Warnings Only'	'On'
PictureMute	'On'	'Off'	
Power	'On'	'Off'	
Shutter	'On'	'Off'	
Zoom	'In'	'Out'	
['Speed']	'Slow'	'Medium'	'Fast'

Status Available:

AspectRatio	'1:1'	'Fill All'	'Fill Aspect Ratio'
	'Fill 16:9'	'Fill 4:3'	'Letterbox 16:9'
	'Letterbox St 16:9'	'Anamorphic Lens'	
ConnectionStatus	'Connected'	'Disconnected'	
EcoMode	'On'	'Off'	
Freeze	'On'	'Off'	
Input	'HDMI'	'DVI'	'S-Video'
	'Composite'	'YPbPr'	'VGA'
LampStatus	'Broken'	'Warming Up'	'On'
	'Off'	'Cooling Down'	'Not Present'
LampUsage	Hours		
OnScreenDisplay	'Off'	'Warnings Only'	'On'
OperationHours	Hours		
PictureMute	'On'	'Off'	
Power	'On'	'Off'	'Warming Up'
	'Cooling Down'		

Cable and Adapter Requirements:

Captive Screw to Male DB9 RS-232 Serial Cable


Notes for the Device:

Serial communication:


Port Type: RS-232
Baud Rate: 19200
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



General Notes:

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	1025
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

Aspect Ratio 1:1	:SABS0\x0D
Aspect Ratio Anamorphic Lens	:SABS11\x0D
Aspect Ratio Fill 16:9	:SABS3\x0D
Aspect Ratio Fill 4:3	:SABS4\x0D
Aspect Ratio Fill All	:SABS1\x0D
Aspect Ratio Fill Aspect Ratio	:SABS2\x0D
Aspect Ratio Letterbox 16:9	:SABS9\x0D
Aspect Ratio Letterbox St 16:9	:SABS10\x0D
Auto Image None	:AUTO\x0D
Eco Mode Off	:ECOM0\x0D
Eco Mode On	:ECOM1\x0D
Focus In Speed Fast	:FOIN3\x0D
Focus In Speed Medium	:FOIN2\x0D
Focus In Speed Slow	:FOIN1\x0D
Focus Out Speed Fast	:FOUT3\x0D
Focus Out Speed Medium	:FOUT2\x0D
Focus Out Speed Slow	:FOUT1\x0D
Freeze Off	:FRZE0\x0D
Freeze On	:FRZE1\x0D
Input Composite	:IABS5\x0D
Input DVI	:IABS2\x0D
Input HDMI	:IABS8\x0D
Input S-Video	:IABS4\x0D
Input VGA	:IABS0\x0D
Input YPbPr	:IABS6\x0D
Menu Navigation Down	:NVDW\x0D
Menu Navigation Left	:NVLF\x0D
Menu Navigation Menu	:MENU\x0D
Menu Navigation OK	:NVOK\x0D
Menu Navigation Right	:NVRH\x0D
Menu Navigation Up	:NVUP\x0D
On Screen Display Off	:OSDC0\x0D
On Screen Display On	:OSDC2\x0D
On Screen Display Warnings Only	:OSDC1\x0D
Picture Mute Off	:PMUT0\x0D
Picture Mute On	:PMUT1\x0D
Power Off	:POWR0\x0D
Power On	:POWR1\x0D
Shutter Off	:SHUT1\x0D
Shutter On	:SHUT0\x0D
Zoom In Speed Fast	:ZOIN3\x0D
Zoom In Speed Medium	:ZOIN2\x0D
Zoom In Speed Slow	:ZOIN1\x0D
Zoom Out Speed Fast	:ZOUT3\x0D
Zoom Out Speed Medium	:ZOUT2\x0D

Appendix B. Query Commands

Aspect Ratio	:SABS?\x0D
Eco Mode	:ECOM?\x0D
Freeze	:FRZE?\x0D
Input	:IABS?\x0D
Lamp Status	:LST1?\x0D
Lamp Usage	:LTR1?\x0D
On Screen Display	:OSDC?\x0D
Operation Hours	:UTOT?\x0D
Picture Mute	:PMUT?\x0D