

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Display
Manufacturer: BenQ
Firmware Version: N/A
Model(s): ST550K, ST650K, ST430K

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.03.0000-b006	2.01.0000-b003	1.1.1

Version History

Module Version	Date	Notes
1_0_1_0	10/24/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5

Control Commands, States, and Qualifiers:

AspectRatio	'Full'	'4:3'	'Film'
	'Subtitle'	'PC Mode'	
AudioMute ¹	'Toggle'		
AutoImage			
ButtonandIRControl	'Enable'	'Disable'	
Freeze	None		
Input	'VGA'	'HDMI 1'	'HDMI 2'
	'HDMI 3'	'AV'	'YPbPr'
	'Android'		
Power	'On'	'Off'	
Volume	'Up'	'Down'	

¹ Only applicable for VGA input.

Status Available:

AspectRatio	'Full'	'4:3'	'Film'
	'Subtitle'	'PC Mode'	
AudioMute	'On'	'Off'	
ButtonandIRControl	'Enable'	'Disable'	
ConnectionStatus	'Connected'	'Disconnected'	
Input	'VGA'	'HDMI 1'	'HDMI 2'
	'HDMI 3'	'AV'	'YPbPr'
	'Android'		
VolumeStatus	0 – 100		

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	4660
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Undetermined

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device: