

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: BenQ
Firmware Version: N/A
Model(s): SH963

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.02.0000-b012	2.01.0000-b003	1.1.0

Version History

Module Version	Date	Notes
1_0_0_0	8/26/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- ConnectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.ConnectionCounter = 5

Control Commands, States, and Qualifiers:

AspectRatio	'Anamorphic'	'4:3'	'Letterbox'
	'Wide'	'Real'	
AudioMute	'On'	'Off'	
AutoImage	None		
Freeze	'On'	'Off'	
Input	'HDMI 1'	'Component'	'Composite'
	'Network'	'USB Reader'	'USB Display'
	'HDMI 2'	'Computer 1'	'Computer 2'
LampMode	'Normal'	'Eco'	'Smart Eco'
	'Dual Brightest'	'Dual Reliable'	'Single Alternative'
	'Single Alternative Eco'		
MenuNavigation	'Up'	'Down'	'Left'
	'Right'	'Enter'	'Menu On'
	'Menu Off'		
Power	'On'	'Off'	
VideoMute	'On'	'Off'	
Volume	'Up'	'Down'	

Status Available:

AspectRatio	'Anamorphic' 'Wide'	'4:3' 'Real'	'Letterbox'
AudioMute	'On'	'Off'	
ConnectionStatus	'Connected'	'Disconnected'	
Freeze	'On'	'Off'	
Input	'HDMI 1' 'Network' 'HDMI 2'	'Component' 'USB Reader' 'Computer 1'	'Composite' 'USB Display' 'Computer 2'
LampMode	'Normal' 'Dual Brightest' 'Single Alternative Eco'	'Eco' 'Dual Reliable'	'Smart Eco' 'Single Alternative'
LampUsage	Hours		
['Lamp']	'1' – '2'		
Power	'On'	'Off'	
VideoMute	'On'	'Off'	
VolumeStatus	0 to 10 in step of 1		


Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable


Notes for the Device:**Serial communication:**

Port Type: RS-232
Baud Rate: 115200
Data Bits: 8

Parity: None
Stop Bits: 1
Flow Control: None

Pin Assignments Diagram:

Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND

**General Notes:**