

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Lighting Control
Manufacturer: bluecog
Firmware Version: N/A
Model(s): RS2DMX-G2

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
2.08.0002-b001	1.4.2

Version History

Module Version	Date	Notes
1_0_0_0	7/10/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='RS2DMX-G2')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='RS2DMX-G2')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command RecallPreset	Value '1' – '8'
Qualifier Key 'Fade Time'	Qualifier Value 0 to 255 in steps of 1
# RecallPreset example InterfaceName.Set('RecallPreset', '1', {'Fade Time': 255})	
Command SavePreset	Value '1' – '8'
# SavePreset example InterfaceName.Set('SavePreset', '1')	
Command SetChannel	Value 0 – 255
Qualifier Key 'Channel'	Qualifier Value 1 to 512 in steps of 1
Qualifier Key 'Fade Time'	Qualifier Value 0 to 255 in steps of 1
# SetChannel example InterfaceName.Set('SetChannel', 255, {'Channel': 512, 'Fade Time': 255})	

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
ConnectionStatus	'Connected'	'Disconnected'
# ConnectionStatus examples Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	
FirmwareVersion	'String'	
# ConnectionStatus examples InterfaceName.Update('FirmwareVersion') Value = InterfaceName.ReadStatus('FirmwareVersion') InterfaceName.SubscribeStatus('FirmwareVersion', None, FeedbackHandler)		

Cable and Adapter Requirements

Captive Screw to Male DB9 RS-232 Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None

Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



Appendix A. Set Commands

Recall Preset 1 Fade Time 0	rc11f000\x0D
Recall Preset 8 Fade Time 0	rc18f000\x0D
Recall Preset 1 Fade Time 255	rc11f255\x0D
Recall Preset 8 Fade Time 255	rc18f255\x0D
Save Preset 1	str1\x0D
Save Preset 8	str8\x0D
Set Channel 0 Channel 1 Fade Time 0	001@000F000\x0D
Set Channel 255 Channel 1 Fade Time 0	001@255F000\x0D
Set Channel 0 Channel 1 Fade Time 255	001@000F255\x0D
Set Channel 255 Channel 1 Fade Time 255	001@255F255\x0D
Set Channel 0 Channel 512 Fade Time 0	512@000F000\x0D
Set Channel 255 Channel 512 Fade Time 0	512@255F000\x0D
Set Channel 0 Channel 512 Fade Time 255	512@000F255\x0D
Set Channel 255 Channel 512 Fade Time 255	512@255F255\x0D

Appendix B. Update Commands

Firmware Version	ver\x0D
------------------	---------