

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Canon
Firmware Version: N/A
Model(s): SX80 Mark II, SX80 Mark II D, SX800

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.01.0000-b004	2.01.0000-b003	1.0.5

Version History

Module Version	Date	Notes
1_0_2_1	2/5/2016	Update module standards
1_0_2_0	2/5/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- ConnectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.ConnectionCounter = 5

Control Commands, States, and Qualifiers:

AspectRatio	'Auto'	'4:3'	'16:9'
	'True'	'Zoom'	
AudioMute	'On'	'Off'	
AutoImage ¹	None		
ExecutiveMode	'Main'	'Remote'	'Off'
Freeze	'On'	'Off'	
Image	'Standard'	'Presentation'	'sRGB'
	'Movie'	'Photo' ²	'DICOM'
Input	'RGB 1' ³	'RGB 2' ³	'DVI'
	'Video' ³	'S-Video'	'Component' ³
	'HDMI'	'USB Port'	
LampMode	'Normal'	'Silent'	
MenuNavigation	'Menu'	'Up'	'Down'
	'Left'	'Right'	'Enter'
Mode	'Local'	'Remote'	
Power	'On'	'Off'	
VideoMute	'On'	'Off'	
Volume	0 to 20 in steps of 1		

¹ Only works on RGB 2 input.² Only works on SX80 Mark II D.³ Only works on SX80 Mark II and SX80 Mark II D.


Status Available:

AspectRatio	'Auto'	'4:3'	'16:9'
	'True'	'Zoom'	
AudioMute	'On'	'Off'	
ConnectionStatus	'Connected'	'Disconnected'	
DeviceStatus	'Normal'	'Temperature Error'	'Lamp Error'
	'Lamp Cover Error'	'Cooling Fan Error'	'Power Supply Error'
	'AK Error'	'ASC Error'	'AF Error'
	'Zoom Error'	'Focus Error'	
ExecutiveMode	'Main'	'Remote'	'Off'
Freeze	'On'	'Off'	
Image	'Standard'	'Presentation'	'sRGB'
	'Movie'	'Photo' ¹	'DICOM'
Input	'RGB 1' ²	'RGB 2' ²	'DVI'
	'Video' ²	'S-Video'	'Component' ²
	'HDMI'	'USB Port'	
LampMode	'Normal'	'Silent'	
LampUsage	Hours		
Mode	'Local'	'Remote'	
Power	'On'	'Off'	'Warming'
	'Cooling'		
SignalStatus	'No Signal'	'Signal Displaying'	'Processing'
VideoMute	'On'	'Off'	
Volume	0 to 20 in steps of 1		


¹ Only works on SX80 Mark II D.² Only works on SX80 Mark II and SX80 Mark II D.

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:**Serial communication:****Port Type:** RS-232**Baud Rate:** 19200**Data Bits:** 8**Parity:** None**Stop Bits:** Two**Flow Control:** None**Pin Assignments Diagram**

Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND

**RS232 DB9 Male
Projector****General Notes:**

Network communication:

When configuring the Ethernet module, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet
Default Port:	33336
Logon Credentials Supported:	No
Multi-Connection Capabilities:	No
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device: