

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Casio
Firmware Version: N/A
Model(s): XJ-UT310WN

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.02.0001-b002	2.01.0001-b001	1.1.1

Version History

Module Version	Date	Notes
1_0_0_0	9/26/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- ConnectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.ConnectionCounter = 5

Control Commands, States, and Qualifiers:


AspectRatio	'Normal'	'16:9'	'4:3'
	'Letter Box'	'Full'	'True'
	'4:3 (Forced)'		
AudioMute	'On'	'Off'	
ColorMode	'Graphics'	'Theater'	'Standard'
	'Blackboard'	'Natural'	
Freeze	'On'	'Off'	
Input	'Computer 1'	'Component 1'	'Video'
	'USB Display'	'Auto 1'	'HDMI'
	'S-Video'	'Computer 2'	'Component 2'
	'Network'	'Auto 2'	'File Viewer'
	'USB Tool'		
MenuNavigation	'Up'	'Down'	'Left'
	'Right'	'Enter'	'Esc'
	'Menu'		
Power	'On'	'Off'	
VideoMute	'On'	'Off'	
Volume	0 to 30 in steps of 1		

Status Available:


AspectRatio	'Normal' 'Letter Box' '4:3 (Forced)'	'16:9' 'Full'	'4:3' 'True'
AudioMute	'On'	'Off'	
ColorMode	'Graphics' 'Blackboard'	'Theater' 'Natural'	'Standard'
ConnectionStatus	'Connected'	'Disconnected'	
DeviceStatus	'Normal' 'Light Error'	'Fan Error' 'Other Error'	'Temperature Error'
Freeze	'On'	'Off'	
Input	'Computer 1' 'USB Display' 'S-Video' 'Network' 'USB Tool'	'Component 1' 'Auto 1' 'Computer 2' 'Auto 2'	'Video' 'HDMI' 'Component 2' 'File Viewer'
LampUsage	Hours		
Power	'On'	'Off'	
VideoMute	'On'	'Off'	
Volume	0 to 30 in steps of 1		

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:**Serial communication:****Port Type:** RS-232**Baud Rate:** 19200**Data Bits:** 8**Parity:** None**Stop Bits:** One**Flow Control:** None**Pin Assignments Diagram**

Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	—	5	GND

**General Notes:**