

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Cable Box
Manufacturer: Cabletime
Firmware Version: N/A
Model(s): MediaStar 780, MediaStar 780-HD, MediaStar 780-HD-PoE, MediaStar 780-SD,
MediaStar 780-SD-PoE

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	1/16/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

Channel	'Up'	'Down'	
Keypad	'0' – '9'		
MenuNavigation	'Up' 'OK'	'Down' 'Menu'	'Quit'
Mute	'On'	'Off'	
Playback	'Play' 'Skip Back'	'Pause' 'Next Item'	'Skip Forward' 'Previous Item'
Power	'On'	'Off'	
Volume	0 to 16 in steps of 1		

Status Available:

BackgroundStatus	String
ChannelStatus	String
ConnectionStatus	'Connected' 'Disconnected'
ForegroundStatus	String
Mute	'On' 'Off'
Volume	0 to 16 in steps of 1

Cable and Adapter Requirements:

Contact manufacturer for cable requirements

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None

Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Contact manufacturer for pin out diagram.

General Notes:

Appendix A. Set Commands

Channel Down	channeldown,passwd=test_password\x0A
Channel Up	channelup,passwd=test_password\x0A
Keypad 0	ircontrol, key=0,passwd=test_password\x0A
Keypad 1	ircontrol, key=1,passwd=test_password\x0A
Keypad 2	ircontrol, key=2,passwd=test_password\x0A
Keypad 3	ircontrol, key=3,passwd=test_password\x0A
Keypad 4	ircontrol, key=4,passwd=test_password\x0A
Keypad 5	ircontrol, key=5,passwd=test_password\x0A
Keypad 6	ircontrol, key=6,passwd=test_password\x0A
Keypad 7	ircontrol, key=7,passwd=test_password\x0A
Keypad 8	ircontrol, key=8,passwd=test_password\x0A
Keypad 9	ircontrol, key=9,passwd=test_password\x0A
Menu Navigation Down	ircontrol, key=DOWN,passwd=test_password\x0A
Menu Navigation Menu	ircontrol, key=MENU,passwd=test_password\x0A
Menu Navigation OK	ircontrol, key=OK,passwd=test_password\x0A
Menu Navigation Quit	ircontrol, key=QUIT,passwd=test_password\x0A
Menu Navigation Up	ircontrol, key=UP,passwd=test_password\x0A
Mute Off	mute, muted=0,passwd=test_password\x0A
Mute On	mute, muted=1,passwd=test_password\x0A
Playback Next Item	playbackcontrol, test_password, passwd=test_password\x0A
Playback Pause	playbackcontrol, test_password, passwd=test_password\x0A
Playback Play	playbackcontrol, test_password, passwd=test_password\x0A
Playback Previous Item	playbackcontrol, test_password, passwd=test_password\x0A
Playback Skip Back	playbackcontrol, test_password, passwd=test_password\x0A
Playback Skip Forward	playbackcontrol, test_password, passwd=test_password\x0A
Power Off	displaycontrol, enable=0\x0A
Power On	displaycontrol, enable=1\x0A

Appendix B. Query Commands

Background Status	getcurrentmedia,passwd=test_password\x0A
Channel Status	getchannel,passwd=test_password\x0A
Foreground Status	getcurrentmedia,passwd=test_password\x0A
Mute	getmute,passwd=test_password\x0A