

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Signal Processor
Manufacturer: Christie
Firmware Version: N/A
Model(s): Phoenix

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_0_1_0	3/2/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5
- If login credentials are required, deviceUsername and devicePassword must be set accordingly. Default username and default password are both 'admin'.
Example: InterfaceName.deviceUsername = 'admin'
InterfaceName.devicePassword = 'admin'
- Wall ID, Source ID, Layer ID and Preset ID parameters are the numerical IDs assigned within the device
- X Position parameter in the Layer Add command is the position of the New Layer relative to the left edge of the wall (in pixels)

- Y Position parameter in the Layer Add command is the position of the New Layer relative to the top edge of the wall (in pixels)
- Offset parameter for the Layer Move – Horizontal Moves the Layer in number of pixels from the current position of the Layer. A Negative number of pixels shifts the layer to the right while a positive number of pixels shifts the layer to left)
- Offset parameter for the Layer Move – Vertical Moves the Layer in number of pixels from the current position of the Layer. A Negative number of pixels shifts the layer up while a positive number of pixels shifts the layer down)
- Audio Source -1 denotes a Removal of all audio sources from the Wall ID specified

Control Commands, States, and Qualifiers:

AudioSource	None
['Wall ID']	0 to 32767 in steps of 1
['Source ID']	-1 – 32767 in steps of 1
LayerAdd	None
['Wall ID']	0 to 32767 in steps of 1
['Source ID']	0 to 32767 in steps of 1
['X Position']	-32768 to 32767 in steps of 1 pixel
['Y Position']	-32768 to 32767 in steps of 1 pixel
['Width']	-32768 to 32767 in steps of 1 pixel
LayerMoveHorizontal	None
['Layer ID']	0 to 32767 in steps of 1
['Offset']	-32768 to 32767 in steps of 1 pixel
LayerMoveVertical	None
['Layer ID']	0 to 32767 in steps of 1
['Offset']	-32768 to 32767 in steps of 1 pixel
LayerRemove	None
['Layer ID']	0 to 32767 in steps of 1
RecallLayout	None
['Preset ID']	0 to 32767 in steps of 1
ResetSource	None
['Source ID']	0 to 32767 in steps of 1
Restart	None


Status Available:

ConnectionStatus	'Connected' 'Disconnected'
HeartBeat ¹	None


¹ Supports Update only. Used only to trigger ConnectionStatus.

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:**Serial communication:****Port Type:** RS-232**Baud Rate:** 9600**Data Bits:** 8**Parity:** None**Stop Bits:** One**Flow Control:** None**Pin Assignments Diagram**

Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND

**General Notes:**

Network communication:

When configuring the Ethernet module, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet
Default Port:	11135
Logon Credentials Supported:	Yes
Default Username:	admin
Default Password:	admin
Multi-Connection Capabilities:	Yes
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

Audio Source None Wall ID 0 Source ID -1	SetAudioSource 0 -1\x0D
Audio Source None Wall ID 0 Source ID 32767	SetAudioSource 0 32767\x0D
Audio Source None Wall ID 32767 Source ID -1	SetAudioSource 32767 -1\x0D
Audio Source None Wall ID 32767 Source ID 32767	SetAudioSource 32767 32767\x0D
Layer Add None Wall ID 0 Source ID 0 X Position -32768 Y Position -32768 Width -32768	LayerAdd 0 0 -32768 -32768 -32768\x0D
Layer Add None Wall ID 0 Source ID 0 X Position -32768 Y Position -32768 Width 32767	LayerAdd 0 0 -32768 -32768 32767\x0D
Layer Add None Wall ID 0 Source ID 0 X Position -32768 Y Position 32767 Width -32768	LayerAdd 0 0 -32768 32767 -32768\x0D
Layer Add None Wall ID 0 Source ID 0 X Position -32768 Y Position 32767 Width 32767	LayerAdd 0 0 -32768 32767 32767\x0D
Layer Add None Wall ID 0 Source ID 0 X Position 32767 Y Position -32768 Width -32768	LayerAdd 0 0 32767 -32768 -32768\x0D
Layer Add None Wall ID 0 Source ID 0 X Position 32767 Y Position -32768 Width 32767	LayerAdd 0 0 32767 -32768 32767\x0D
Layer Add None Wall ID 0 Source ID 0 X Position 32767 Y Position 32767 Width -32768	LayerAdd 0 0 32767 32767 -32768\x0D
Layer Add None Wall ID 0 Source ID 0 X Position 32767 Y Position 32767 Width 32767	LayerAdd 0 0 32767 32767 32767\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position -32768 Y Position -32768 Width -32768	LayerAdd 0 32767 -32768 -32768 -32768\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position -32768 Y Position -32768 Width 32767	LayerAdd 0 32767 -32768 -32768 32767\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position -32768 Y Position 32767 Width -32768	LayerAdd 0 32767 -32768 32767 -32768\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position -32768 Y Position 32767 Width 32767	LayerAdd 0 32767 -32768 32767 32767\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position 32767 Y Position -32768 Width -32768	LayerAdd 0 32767 32767 -32768 -32768\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position 32767 Y Position -32768 Width 32767	LayerAdd 0 32767 32767 -32768 32767\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position 32767 Y Position 32767 Width -32768	LayerAdd 0 32767 32767 32767 -32768\x0D
Layer Add None Wall ID 0 Source ID 32767 X Position 32767 Y Position 32767 Width 32767	LayerAdd 0 32767 32767 32767 32767\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position -32768 Y Position -32768 Width -32768	LayerAdd 32767 0 -32768 -32768 -32768\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position -32768 Y Position -32768 Width 32767	LayerAdd 32767 0 -32768 -32768 32767\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position -32768 Y Position 32767 Width -32768	LayerAdd 32767 0 -32768 32767 -32768\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position -32768 Y Position 32767 Width 32767	LayerAdd 32767 0 -32768 32767 32767\x0D

Layer Add None Wall ID 32767 Source ID 0 X Position 32767 Y Position -32768 Width -32768	LayerAdd 32767 0 32767 -32768 - 32768\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position 32767 Y Position -32768 Width 32767	LayerAdd 32767 0 32767 -32768 32767\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position 32767 Y Position 32767 Width -32768	LayerAdd 32767 0 32767 32767 - 32768\x0D
Layer Add None Wall ID 32767 Source ID 0 X Position 32767 Y Position 32767 Width 32767	LayerAdd 32767 0 32767 32767 32767\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position -32768 Y Position -32768 Width -32768	LayerAdd 32767 32767 -32768 -32768 - 32768\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position -32768 Y Position -32768 Width 32767	LayerAdd 32767 32767 -32768 -32768 32767\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position -32768 Y Position 32767 Width -32768	LayerAdd 32767 32767 -32768 32767 - 32768\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position -32768 Y Position 32767 Width 32767	LayerAdd 32767 32767 -32768 32767 32767\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position 32767 Y Position -32768 Width -32768	LayerAdd 32767 32767 32767 -32768 - 32768\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position 32767 Y Position -32768 Width 32767	LayerAdd 32767 32767 32767 -32768 32767\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position 32767 Y Position 32767 Width -32768	LayerAdd 32767 32767 32767 32767 - 32768\x0D
Layer Add None Wall ID 32767 Source ID 32767 X Position 32767 Y Position 32767 Width 32767	LayerAdd 32767 32767 32767 32767 32767\x0D
Layer Move - Horizontal None Layer ID 0 Offset -32768	LayerMove 1 H -32768 0 0\x0D
Layer Move - Horizontal None Layer ID 0 Offset 32767	LayerMove 1 H 32767 0 0\x0D
Layer Move - Horizontal None Layer ID 32767 Offset -32768	LayerMove 1 H -32768 0 32767\x0D
Layer Move - Horizontal None Layer ID 32767 Offset 32767	LayerMove 1 H 32767 0 32767\x0D
Layer Move - Vertical None Layer ID 0 Offset - 32768	LayerMove 1 V 0 -32768 0\x0D
Layer Move - Vertical None Layer ID 0 Offset 32767	LayerMove 1 V 0 32767 0\x0D
Layer Move - Vertical None Layer ID 32767 Offset -32768	LayerMove 1 V 0 -32768 32767\x0D
Layer Move - Vertical None Layer ID 32767 Offset 32767	LayerMove 1 V 0 32767 32767\x0D
Layer Remove None Layer ID 0	LayerRemove 0\x0D

Layer Remove None Layer ID 32767	LayerRemove 32767\x0D
Recall Layout None Preset ID 0	LayoutRecall 0\x0D
Recall Layout None Preset ID 32767	LayoutRecall 32767\x0D
Reset Source None Source ID 0	ResetSource 0\x0D
Reset Source None Source ID 32767	ResetSource 32767\x0D
Restart None	Restart\x0D

Appendix B. Query Commands

HeartBeat	GetWall 1\x0D
-----------	---------------