

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Christie
Firmware Version: N/A
Model(s): DWU1052, DWU1052Q, DHD1052

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_1_0	1/3/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

AspectRatio	'Normal'	'4:3'	'16:9'
	'16:10'	'14:9'	'Native'
AutoImage	None		
AVMute	'On'	'Off'	
ClosedCaption	'On'	'Off'	
ClosedCaptionChannel	'1' – '4'		
ClosedCaptionMode	'Captions'	'Text'	
ExecutiveMode	'On'	'Off'	
Freeze	'On'	'Off'	
Input	'Computer'	'Video'	'DVI-D'
	'HDMI 1'	'HDMI 2'	'SDI'
	'LAN'	'HDBaseT'	
LampMode	'Normal'	'Eco'	
Power	'On'	'Off'	
VideoMute	'On'	'Off'	

Status Available:

AspectRatio	'Normal' '16:10'	'4:3' '14:9'	'16:9' 'Native'
AVMute	'On'	'Off'	
ClosedCaption	'On'	'Off'	
ClosedCaptionChannel	'1' – '4'		
ClosedCaptionMode	'Captions'	'Text'	
ConnectionStatus	'Connected'	'Disconnected'	
DeviceStatus	'Normal' 'Lamp Error' 'Cold Error' 'Lens Shift Error' 'Humidity Error' 'Other Error'	'Cover Error' 'Temp Error' 'Filter Error' 'Lamp 1 Warning' 'Color Wheel Error'	'Fan Error' 'Air Flow Error' 'Shutter Failure' 'Lamp 2 Warning' 'Dynamic Iris Error'
ExecutiveMode	'On'	'Off'	
FilterUsage	Hours		
Freeze	'On'	'Off'	
Input	'Computer' 'HDMI 1' 'LAN'	'Video' 'HDMI 2' 'HDBaseT'	'DVI-D' 'SDI'
LampMode	'Normal'	'Eco'	
LampUsage	Hours		
Power	'On'	'Off'	'Cooling Down'
VideoMute	'On'	'Off'	

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable


Notes for the Device:

Serial communication:


Port Type: RS-232
Baud Rate: 19200
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



General Notes:

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type: Ethernet

Default Port: 23

Logon Credentials Supported: Yes

Multi-Connection Capabilities: No

Port Changeability: No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

Aspect Ratio 14:9	\xBE\xEF\x03\x06\x00\xCE\xD6\x01\x00\x08 \x09\x00
Aspect Ratio 16:10	\xBE\xEF\x03\x06\x00>\xD6\x01\x00\x08 \x0A\x00
Aspect Ratio 16:9	\xBE\xEF\x03\x06\x00\x0E\xD1\x01\x00\x08 \x01\x00
Aspect Ratio 4:3	\xBE\xEF\x03\x06\x00\x9E\xD0\x01\x00\x08 \x00\x00
Aspect Ratio Native	\xBE\xEF\x03\x06\x00^\xD7\x01\x00\x08 \x08\x00
Aspect Ratio Normal	\xBE\xEF\x03\x06\x00^\xDD\x01\x00\x08 \x10\x00
Auto Image None	\xBE\xEF\x03\x06\x00\x91\xD0\x06\x00\x0A \x00\x00
AV Mute Off	\xBE\xEF\x03\x06\x00\xFB\xD8\x01\x00 0\x00\x00
AV Mute On	\xBE\xEF\x03\x06\x00k\xD9\x01\x00 0\x01\x00
Closed Caption Channel 1	\xBE\xEF\x03\x06\x00\xD2b\x01\x00\x027\x01\x00
Closed Caption Channel 2	\xBE\xEF\x03\x06\x00"b\x01\x00\x027\x02\x00
Closed Caption Channel 3	\xBE\xEF\x03\x06\x00\xB2c\x01\x00\x027\x03\x00
Closed Caption Channel 4	\xBE\xEF\x03\x06\x00\x82a\x01\x00\x027\x04\x00
Closed Caption Mode Captions	\xBE\xEF\x03\x06\x00\x06c\x01\x00\x017\x00\x00
Closed Caption Mode Text	\xBE\xEF\x03\x06\x00\x96b\x01\x00\x017\x01\x00
Closed Caption Off	\xBE\xEF\x03\x06\x00\xFAB\x01\x00\x007\x00\x00
Closed Caption On	\xBE\xEF\x03\x06\x00jc\x01\x00\x007\x01\x00
Executive Mode Off	\xBE\xEF\x03\x06\x00\xAB\xEE\x01\x00\xC00\x00\x00
Executive Mode On	\xBE\xEF\x03\x06\x00;\xEF\x01\x00\xC00\x01\x00
Freeze Off	\xBE\xEF\x03\x06\x00\x13\xD3\x01\x00\x020\x01\x00
Freeze On	\xBE\xEF\x03\x06\x00\x13\xD3\x01\x00\x020\x01\x00
Input Computer	\xBE\xEF\x03\x06\x00\xFE\xD2\x01\x00\x00 \x00\x00
Input DVI-D	\xBE\xEF\x03\x06\x00\xAE\xD4\x01\x00\x00 \x09\x00
Input HDBaseT	\xBE\xEF\x03\x06\x00\xAE\xDE\x01\x00\x00 \x11\x00
Input HDMI 1	\xBE\xEF\x03\x06\x00\x0E\xD2\x01\x00\x00 \x03\x00
Input HDMI 2	\xBE\xEF\x03\x06\x00n\xD6\x01\x00\x00 \x0D\x00
Input LAN	\xBE\xEF\x03\x06\x00\xCE\xD5\x01\x00\x00 \x0B\x00
Input SDI	\xBE\xEF\x03\x06\x00^\xDE\x01\x00\x00 \x12\x00
Input Video	\xBE\xEF\x03\x06\x00n\xD3\x01\x00\x00 \x01\x00
Lamp Mode Eco	\xBE\xEF\x03\x06\x00\xAB"\x01\x00\x003\x01\x00
Lamp Mode Normal	\xBE\xEF\x03\x06\x00;#\x01\x00\x003\x00\x00
Power Off	\xBE\xEF\x03\x06\x00*\xD3\x01\x00\x00` \x00\x00
Power On	\xBE\xEF\x03\x06\x00\xBA\xD2\x01\x00\x00` \x01\x00
Video Mute Off	\xBE\xEF\x03\x06\x00\xFB\xD8\x01\x00 0\x00\x00
Video Mute On	\xBE\xEF\x03\x06\x00k\xD9\x01\x00 0\x01\x00

Appendix B. Query Commands

Aspect Ratio	\xBE\xEF\x03\x06\x00\xAD\xD0\x02\x00\x08 \x00\x00
AV Mute	\xBE\xEF\x03\x06\x00\xC8\xD8\x02\x00 0\x00\x00
Closed Caption	\xBE\xEF\x03\x06\x00\xC9b\x02\x00\x007\x00\x00
Closed Caption Channel	\xBE\xEF\x03\x06\x00qc\x02\x00\x027\x00\x00
Closed Caption Mode	\xBE\xEF\x03\x06\x005c\x02\x00\x017\x00\x00

Global Scripter Module Communication Sheet

Device Status	\xBE\xEF\x03\x06\x00\xD9\xD8\x02\x00 \x00\x00
Executive Mode	\xBE\xEF\x03\x06\x00\x08\xEF\x02\x00\xC00\x00\x00
Filter Usage	\xBE\xEF\x03\x06\x00\xC2\xF0\x02\x00\xA0\x10\x00\x00
Freeze	\xBE\xEF\x03\x06\x00\xB0\xD2\x02\x00\x020\x00\x00
Input	\xBE\xEF\x03\x06\x00\xCD\xD2\x02\x00\x00 \x00\x00
Lamp Mode	\xBE\xEF\x03\x06\x00\x08#\x02\x00\x003\x00\x00
Lamp Usage	\xBE\xEF\x03\x06\x00\xC2\xFF\x02\x00\x90\x10\x00\x00
Power	\xBE\xEF\x03\x06\x00\x19\xD3\x02\x00\x00`\x00\x00
Video Mute	\xBE\xEF\x03\x06\x00\xC8\xD8\x02\x00 0\x00\x00