

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Video Projector
Manufacturer: Christie
Firmware Version: N/A
Model(s): DHD555-GS, DWX555-GS, DWU555-GS

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.03.0000-b006	2.3.0

Version History

Module Version	Date	Notes
1_0_1_0	6/6/2019	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='DHD555-GS')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='DHD555-GS')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 3002, Model='DHD555-GS')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AspectRatio	Value 'Auto' 'LetterBox' 'Full Height'	Value 'Native' 'Full Size'	Value '4:3' 'Full Width'
# AspectRatio example InterfaceName.Set('AspectRatio', 'Auto')			
Command AutoImage	Value 'None'		
Qualifier Key 'Mode'	Qualifier Value 'Normal'	Qualifier Value 'Wide'	
# AutoImage example InterfaceName.Set('AutoImage', None, {'Mode': 'Normal'})			
Command ClosedCaption	Value 'Off'	Value 'CC1'	Value 'CC2'
# ClosedCaption example InterfaceName.Set('ClosedCaption', 'Off')			
Command Freeze	Value 'On'	Value 'Off'	
# Freeze example InterfaceName.Set('Freeze', 'On')			
Command Input	Value 'VGA' 'DisplayPort' 'Composite'	Value 'HDMI' 'Component' 'Mini USB'	Value 'DVI-D' 'S-Video'
# Input example InterfaceName.Set('Input', 'VGA')			
Command Keypad	Value '0' – '9'		
# Keypad example InterfaceName.Set('Keypad', '0')			
Command LampMode	Value 'Constant Power (Default)'	Value 'Constant Intensity'	Value 'Eco'
# LampMode example InterfaceName.Set('LampMode', 'Constant Power (Default)')			
Command MenuNavigation	Value 'Menu' 'Right' 'Enter'	Value 'Up' 'Left'	Value 'Down' 'Exit'
# MenuNavigation example InterfaceName.Set('MenuNavigation', 'Menu')			
Command OnScreenDisplay	Value 'On'	Value 'Off'	
# OnScreenDisplay example InterfaceName.Set('OnScreenDisplay', 'On')			

Global Scripter Module Communication Sheet

Command PIPInput	Value 'VGA' 'DisplayPort' 'Composite'	Value 'HDMI' 'Component' 'Mini USB'	Value 'DVI-D' 'S-Video'
# PIPInput example InterfaceName.Set('PIPInput', 'VGA')			
Command PIPMode	Value 'On'	Value 'Off'	
# PIPMode example InterfaceName.Set('PIPMode', 'On')			
Command PIPPosition	Value 'Left Vertical Center' 'Bottom Center' 'Top Left'	Value 'Top Center' 'Bottom Right' 'Top Right'	Value 'Right Vertical Center' 'Bottom Left'
# PIPPosition example InterfaceName.Set('PIPPosition', 'Left Vertical Center')			
Command PIPSize	Value 'Small'	Value 'Medium'	Value 'Large'
# PIPSize example InterfaceName.Set('PIPSize', 'Small')			
Command PIPSwap	Value 'None'		
# PIPSwap example InterfaceName.Set('PIPSwap', None)			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command VideoMute	Value 'On'	Value 'Off'	
# VideoMute example InterfaceName.Set('VideoMute', 'On')			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AspectRatio	Value 'Auto' 'LetterBox' 'Full Height'	Value 'Native' 'Full Size'	Value '4:3' 'Full Width'
# AspectRatio example InterfaceName.Update('AspectRatio') Value = InterfaceName.ReadStatus('AspectRatio') InterfaceName.SubscribeStatus('AspectRatio', None, FeedbackHandler)			
Command ClosedCaption	Value 'Off'	Value 'CC1'	Value 'CC2'
# ClosedCaption example InterfaceName.Update('ClosedCaption') Value = InterfaceName.ReadStatus('ClosedCaption') InterfaceName.SubscribeStatus('ClosedCaption', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command Freeze	Value 'On'	Value 'Off'	
# Freeze example InterfaceName.Update('Freeze') Value = InterfaceName.ReadStatus('Freeze') InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)			
Command Input	Value 'VGA' 'DisplayPort' 'Composite'	Value 'HDMI' 'Component' 'Mini USB'	Value 'DVI-D' 'S-Video'
# Input example InterfaceName.Update('Input') Value = InterfaceName.ReadStatus('Input') InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)			
Command LampMode	Value 'Constant Power (Default)'	Value 'Constant Intensity'	Value 'Eco'
# LampMode example InterfaceName.Update('LampMode') Value = InterfaceName.ReadStatus('LampMode') InterfaceName.SubscribeStatus('LampMode', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Revision: 6/6/2019

Command OnScreenDisplay	Value 'On'	Value 'Off'	
# OnScreenDisplay example InterfaceName.Update('OnScreenDisplay') Value = InterfaceName.ReadStatus('OnScreenDisplay') InterfaceName.SubscribeStatus('OnScreenDisplay', None, FeedbackHandler)			
Command PIPInput	Value 'VGA' 'DisplayPort' 'Composite'	Value 'HDMI' 'Component' 'Mini USB'	Value 'DVI-D' 'S-Video'
# PIPInput example InterfaceName.Update('PIPInput') Value = InterfaceName.ReadStatus('PIPInput') InterfaceName.SubscribeStatus('PIPInput', None, FeedbackHandler)			
Command PIPMode	Value 'On'	Value 'Off'	
# PIPMode example InterfaceName.Update('PIPMode') Value = InterfaceName.ReadStatus('PIPMode') InterfaceName.SubscribeStatus('PIPMode', None, FeedbackHandler)			
Command PIPPosition	Value 'Left Vertical Center' 'Bottom Center' 'Top Left'	Value 'Top Center' 'Bottom Right' 'Top Right'	Value 'Right Vertical Center' 'Bottom Left'
# PIPPosition example InterfaceName.Update('PIPPosition') Value = InterfaceName.ReadStatus('PIPPosition') InterfaceName.SubscribeStatus('PIPPosition', None, FeedbackHandler)			
Command PIPSize	Value 'Small'	Value 'Medium'	Value 'Large'
# PIPSize example InterfaceName.Update('PIPSize') Value = InterfaceName.ReadStatus('PIPSize') InterfaceName.SubscribeStatus('PIPSize', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command VideoMute	Value 'On'	Value 'Off'	
# VideoMute example InterfaceName.Update('VideoMute') Value = InterfaceName.ReadStatus('VideoMute') InterfaceName.SubscribeStatus('VideoMute', None, FeedbackHandler)			

Cable and Adapter Requirements

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 115200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND		5	GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type:	Ethernet
Default Port:	3002
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Aspect Ratio 4:3	(SZP 2)
Aspect Ratio Auto	(SZP 0)
Aspect Ratio Full Height	(SZP 6)
Aspect Ratio Full Size	(SZP 4)
Aspect Ratio Full Width	(SZP 5)
Aspect Ratio LetterBox	(SZP 3)
Aspect Ratio Native	(SZP 1)
Auto Image None Mode Normal	(AIM 0)
Auto Image None Mode Wide	(AIM 1)
Closed Caption CC1	(CLC 1)
Closed Caption CC2	(CLC 2)
Closed Caption Off	(CLC 0)
Freeze Off	(FRZ 0)
Freeze On	(FRZ 1)
Input Component	(SIN+MAIN 7)
Input Composite	(SIN+MAIN 9)
Input DisplayPort	(SIN+MAIN 6)
Input DVI-D	(SIN+MAIN 5)
Input HDMI	(SIN+MAIN 4)
Input Mini USB	(SIN+MAIN 12)
Input S-Video	(SIN+MAIN 8)
Input VGA	(SIN+MAIN 1)
Keypad 0	(KEY 36)
Keypad 9	(KEY 34)
Lamp Mode Constant Intensity	(LPM 1)
Lamp Mode Constant Power (Default)	(LPM 0)
Lamp Mode Eco	(LPM 3)
Menu Navigation Down	(KEY 42)
Menu Navigation Enter	(KEY 40)
Menu Navigation Exit	(KEY 20)
Menu Navigation Left	(KEY 39)
Menu Navigation Menu	(KEY 19)
Menu Navigation Right	(KEY 41)
Menu Navigation Up	(KEY 38)
On Screen Display Off	(OSD 0)
On Screen Display On	(OSD 1)
PIP Input Component	(SIN+PIP 7)
PIP Input Composite	(SIN+PIP 9)
PIP Input DisplayPort	(SIN+PIP 6)
PIP Input DVI-D	(SIN+PIP 5)
PIP Input HDMI	(SIN+PIP 4)
PIP Input Mini USB	(SIN+PIP 12)

Global Scriptor Module Communication Sheet

Revision: 6/6/2019

PIP Input S-Video	(SIN+PIP 8)
PIP Input VGA	(SIN+PIP 1)
PIP Mode Off	(PIP 0)
PIP Mode On	(PIP 1)
PIP Position Bottom Center	(PPP 3)
PIP Position Bottom Left	(PPP 5)
PIP Position Bottom Right	(PPP 4)
PIP Position Left Vertical Center	(PPP 0)
PIP Position Right Vertical Center	(PPP 2)
PIP Position Top Center	(PPP 1)
PIP Position Top Left	(PPP 6)
PIP Position Top Right	(PPP 7)
PIP Size Large	(PHS 2)
PIP Size Medium	(PHS 1)
PIP Size Small	(PHS 0)
PIP Swap None	(PPS)
Power Off	(PWR 0)
Power On	(PWR 1)
Video Mute Off	(SHU 0)
Video Mute On	(SHU 1)

Appendix B. Update Commands

Aspect Ratio	(SZP ?)
Closed Caption	(CLC ?)
Freeze	(FRZ ?)
Input	(SIN+MAIN ?)
Lamp Mode	(LPM ?)
On Screen Display	(OSD ?)
PIP Input	(SIN+PIP ?)
PIP Mode	(PIP ?)
PIP Position	(PPP ?)
PIP Size	(PHS ?)
Power	(PWR ?)
Video Mute	(SHU ?)