

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Display
Manufacturer: Christie
Firmware Version: N/A
Model(s): FHQ981-L

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	1/20/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

AutoImage	None		
Input	'VGA' 'HDMI 2' 'OPS-HDMI'	'DP' 'HDMI 3' 'OPS-DP'	'HDMI 1' 'HDMI 4'
InputResolution	'1024x768' '1366x768'	'1280x768' '1400x1050'	'1360x768' '1680x1050'
MenuNavigation	'Up' 'Right'	'Down' 'Select'	'Left' 'Menu'
MultiWindowMode	'Off'	'PBP'	'Quadrant'
Mute	'On'	'Off'	
PictureMode	'Standard'	'Dynamic'	'User'
Power	'On'	'Off'	
Volume	0 to 100 in steps of 1		
WindowInput	'DP' 'HDMI 3' 'OPS-DP'	'HDMI 1' 'HDMI 4'	'HDMI 2' 'OPS-HDMI'
['Window']	'1' – '4'		
WindowMode	'Window 1' 'Window 4'	'Window 2'	'Window 3'

Status Available:

ConnectionStatus	'Connected'	'Disconnected'	
Input	'VGA'	'DP'	'HDMI 1'
	'HDMI 2'	'HDMI 3'	'HDMI 4'
	'OPS-HDMI'	'OPS-DP'	
InputResolution	'1024x768'	'1280x768'	'1360x768'
	'1366x768'	'1400x1050'	'1680x1050'
MultiWindowMode	'Off'	'PBP'	'Quadrant'
Mute	'On'	'Off'	
PictureMode	'Standard'	'Dynamic'	'User'
Volume	0 to 100 in steps of 1		
WindowInput	'DP'	'HDMI 1'	'HDMI 2'
	'HDMI 3'	'HDMI 4'	'OPS-HDMI'
	'OPS-DP'		
['Window']	'1' – '4'		
WindowMode	'Window 1'	'Window 2'	'Window 3'
	'Window 4'		

Cable and Adapter Requirements:

Captive Screw to 3.5mm Stereo Serial Cable

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
RxD	←	1	TxD
TxD	→	2	RxD
GND	→	3	GND



General Notes:

Appendix A. Set Commands

Auto Image None	K:ALLRAT.
Input DP	K:ALLSH1.
Input HDMI 1	K:ALLSH2.
Input HDMI 2	K:ALLSH3.
Input HDMI 3	K:ALLSH4.
Input HDMI 4	K:ALLSH5.
Input OPS-DP	K:ALLSH7.
Input OPS-HDMI	K:ALLSH6.
Input Resolution 1024x768	K:ALLIR0.
Input Resolution 1280x768	K:ALLIR1.
Input Resolution 1360x768	K:ALLIR2.
Input Resolution 1366x768	K:ALLIR3.
Input Resolution 1400x1050	K:ALLIR4.
Input Resolution 1680x1050	K:ALLIR5.
Input VGA	K:ALLSPC.
Menu Navigation Down	K:ALLRDN.
Menu Navigation Left	K:ALLRLT.
Menu Navigation Menu	K:ALLRMN.
Menu Navigation Right	K:ALLRRT.
Menu Navigation Select	K:ALLREN.
Menu Navigation Up	K:ALLRUP.
Multi Window Mode Off	K:ALLWM0.
Multi Window Mode PBP	K:ALLWM1.
Multi Window Mode Quadrant	K:ALLWM2.
Mute Off	K:ALLMOF.
Mute On	K:ALLMON.
Picture Mode Dynamic	K:ALLPM1.
Picture Mode Standard	K:ALLPMO.
Picture Mode User	K:ALLPM2.
Power Off	K:ALLPOF.
Power On	K:ALLPON.
Volume 0	K:ALLVOL000.
Volume 100	K:ALLVOL100.
Window Input DP Window 1	K:ALLW10.
Window Input DP Window 2	K:ALLW20.
Window Input DP Window 3	K:ALLW30.
Window Input DP Window 4	K:ALLW40.
Window Input HDMI 1 Window 1	K:ALLW11.
Window Input HDMI 1 Window 2	K:ALLW21.
Window Input HDMI 1 Window 3	K:ALLW31.
Window Input HDMI 1 Window 4	K:ALLW41.
Window Input HDMI 2 Window 1	K:ALLW12.
Window Input HDMI 2 Window 2	K:ALLW22.
Window Input HDMI 2 Window 3	K:ALLW32.
Window Input HDMI 2 Window 4	K:ALLW42.
Window Input HDMI 3 Window 1	K:ALLW13.

Window Input HDMI 3 Window 2	K:ALLW23.
Window Input HDMI 3 Window 3	K:ALLW33.
Window Input HDMI 3 Window 4	K:ALLW43.
Window Input HDMI 4 Window 1	K:ALLW14.
Window Input HDMI 4 Window 2	K:ALLW24.
Window Input HDMI 4 Window 3	K:ALLW34.
Window Input HDMI 4 Window 4	K:ALLW44.
Window Input OPS-DP Window 1	K:ALLW16.
Window Input OPS-DP Window 2	K:ALLW26.
Window Input OPS-DP Window 3	K:ALLW36.
Window Input OPS-DP Window 4	K:ALLW46.
Window Input OPS-HDMI Window 1	K:ALLW15.
Window Input OPS-HDMI Window 2	K:ALLW25.
Window Input OPS-HDMI Window 3	K:ALLW35.
Window Input OPS-HDMI Window 4	K:ALLW45.
Window Mode Window 1	K:ALLWN1.
Window Mode Window 2	K:ALLWN2.
Window Mode Window 3	K:ALLWN3.
Window Mode Window 4	K:ALLWN4.

Appendix B. Query Commands

Input	K:ALLSRC?
Input Resolution	K:ALLIRT?
Multi Window Mode	K:ALLWMT?
Mute	K:ALLMUT?
Picture Mode	K:ALLPMT?
Volume	K:ALLVOL?
Window Input Window 1	K:ALLW1S?
Window Input Window 2	K:ALLW2S?
Window Input Window 3	K:ALLW3S?
Window Input Window 4	K:ALLW4S?
Window Mode	K:ALLWIN?