

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Christie
Firmware Version: N/A
Model(s): Roadie 4k45

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.06.0000-b010	2.01.0002-b005	1.4.0

Version History

Module Version	Date	Notes
1_0_0_0	7/12/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='ModelName')

Control Commands, States, and Qualifiers:

AutoImage	None		
Channel	'Four-Port (slot 1,2)'	'Four-Port (slot 3,4)'	'Four-Port (slot 1,2,3,4)'
	'Two-Port (slot 1,2)'	'Two-Port (slot 3,4)'	'One-Port (slot 1)'
	'One-Port (slot 2)'	'One-Port (slot 3)'	'One-Port (slot 4)'
Freeze	'On'	'Off'	
LampMode	'Constant Power'	'Constant Intensity'	
Power	'On'	'Off'	
VideoMute	'On'	'Off'	

Status Available:

Channel	'Four-Port (slot 1,2)'	'Four-Port (slot 3,4)'	'Four-Port (slot 1,2,3,4)'
	'Two-Port (slot 1,2)'	'Two-Port (slot 3,4)'	'One-Port (slot 1)'
	'One-Port (slot 2)'	'One-Port (slot 3)'	'One-Port (slot 4)'
ConnectionStatus	'Connected' 'Disconnected'		
LampUsage	Hours		
['Lamp']	'1' – '3'		
Power	'On'	'Off'	'Warming Up'
	'Cooling Down'		
VideoMute	'On' 'Off'		

Cable and Adapter Requirements:

Captive Screw to Male DB9 RS-232 Serial Cable


Notes for the Device:

Serial communication:

Port Type: RS-232
Baud Rate: 115200
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



General Notes:

Appendix A. Set Commands

Auto Image None	(ASU)
Channel Four-Port (slot 1,2)	(CHA 1)
Channel Four-Port (slot 1,2,3,4)	(CHA 3)
Channel Four-Port (slot 3,4)	(CHA 2)
Channel One-Port (slot 1)	(CHA 21)
Channel One-Port (slot 2)	(CHA 22)
Channel One-Port (slot 3)	(CHA 23)
Channel One-Port (slot 4)	(CHA 24)
Channel Two-Port (slot 1,2)	(CHA 11)
Channel Two-Port (slot 3,4)	(CHA 12)
Freeze Off	(FRZ 0)
Freeze On	(FRZ 1)
Lamp Mode Constant Intensity	(LPM 1)
Lamp Mode Constant Power	(LPM 0)
Power Off	(PWR 0)
Power On	(PWR 1)
Video Mute Off	(SHU 0)
Video Mute On	(SHU 1)

Appendix B. Query Commands

Channel	(CHA?L)
Lamp Usage Lamp 1	(HIS?)
Lamp Usage Lamp 3	(HIS?)
Power	(PWR?)
Video Mute	(SHU?)

*Lamp Usage 1 – 3 share the same Update command string