

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Other
 Manufacturer: Clipsal
 Firmware Version: N/A
 Model(s): BM2600-DALI

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
2.06.0002-b002	1.4.1

Version History

Module Version	Date	Notes
1_0_0_0	1/4/2018	Initial Version

Module Notes

- ControllerID variable must be set accordingly. Default value is '1'. Controller ID ranges from '0' to '254'.
- Default value is '0'

Example: InterfaceName.ControllerID = '1'

Supported Classes and Examples

EthernetClass
InterfaceName = ModuleName.EthernetClass('192.168.254.254', 1235, Model='BM2600-DALI')

Set Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command DimLevel	Value 'Up'	Value 'Down'
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'	
# DimLevel example InterfaceName.Set('DimLevel', 'Up', {'Group Address': '1'})		
Command Scene	Value '0' – '15'	
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'	
# Scene example InterfaceName.Set('Scene', '0', {'Group Address': '1'})		
Command SequenceStep1	Value '1' – '32'	
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'	
# SequenceStep1 example InterfaceName.Set('SequenceStep1', '1', {'Group Address': '1'})		
Command SequenceStep2	Value '1' – '32'	
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'	
# SequenceStep2 example InterfaceName.Set('SequenceStep2', '1', {'Group Address': '1'})		
Command SequenceStep3	Value '1' – '32'	
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'	
# SequenceStep3 example InterfaceName.Set('SequenceStep3', '1', {'Group Address': '1'})		
Command SequenceStep4	Value '1' – '32'	
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'	

# SequenceStep4 example InterfaceName.Set('SequenceStep4', '1', {'Group Address': '1'})	
Command SequenceStep5	Value '1' – '32'
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'
# SequenceStep5 example InterfaceName.Set('SequenceStep5', '1', {'Group Address': '1'})	
Command SequenceStep6	Value '1' – '32'
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'
# SequenceStep6 example InterfaceName.Set('SequenceStep6', '1', {'Group Address': '1'})	
Command SequenceStep7	Value '1' – '32'
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'
# SequenceStep7 example InterfaceName.Set('SequenceStep7', '1', {'Group Address': '1'})	
Command SequenceStep8	Value '1' – '32'
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'
# SequenceStep8 example InterfaceName.Set('SequenceStep8', '1', {'Group Address': '1'})	
Command SwitchLight	Value 'On' Value 'Off'
Qualifier Key 'Group Address'	Qualifier Value '1' – '128'
# SwitchLight example InterfaceName.Set('SwitchLight', 'On', {'Group Address': '1'})	

Status Available: N/A

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scripter ethernet interface

Port Type:	Ethernet
Default Port:	1235
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Dim Level Down Group Address 1	\$001015007001800200*
Dim Level Up Group Address 1	\$001015007001800100*
Dim Level Down Group Address 128	\$001015007080800200*
Dim Level Up Group Address 128	\$001015007080800100*
Scene 0 Group Address 1	\$001015007001801000*
Scene 15 Group Address 1	\$001015007001801F00*
Scene 0 Group Address 128	\$001015007080801000*
Scene 15 Group Address 128	\$001015007080801F00*
Sequence Step 1 1 Group Address 1	\$001015007001820000*
Sequence Step 1 32 Group Address 1	\$001015007001821F00*
Sequence Step 1 1 Group Address 128	\$001015007080820000*
Sequence Step 1 32 Group Address 128	\$001015007080821F00*
Sequence Step 2 1 Group Address 1	\$001015007001822000*
Sequence Step 2 32 Group Address 1	\$001015007001823F00*
Sequence Step 2 1 Group Address 128	\$001015007080822000*
Sequence Step 2 32 Group Address 128	\$001015007080823F00*
Sequence Step 3 1 Group Address 1	\$001015007001824000*
Sequence Step 3 32 Group Address 1	\$001015007001825F00*
Sequence Step 3 1 Group Address 128	\$001015007080824000*
Sequence Step 3 32 Group Address 128	\$001015007080825F00*
Sequence Step 4 1 Group Address 1	\$001015007001826000*
Sequence Step 4 32 Group Address 1	\$001015007001827F00*
Sequence Step 4 1 Group Address 128	\$001015007080826000*
Sequence Step 4 32 Group Address 128	\$001015007080827F00*
Sequence Step 5 1 Group Address 1	\$001015007001828000*
Sequence Step 5 32 Group Address 1	\$001015007001829F00*
Sequence Step 5 1 Group Address 128	\$001015007080828000*
Sequence Step 5 32 Group Address 128	\$001015007080829F00*
Sequence Step 6 1 Group Address 1	\$00101500700182A000*
Sequence Step 6 32 Group Address 1	\$00101500700182BF00*
Sequence Step 6 1 Group Address 128	\$00101500708082A000*
Sequence Step 6 32 Group Address 128	\$00101500708082BF00*
Sequence Step 7 1 Group Address 1	\$00101500700182C000*
Sequence Step 7 32 Group Address 1	\$00101500700182DF00*
Sequence Step 7 1 Group Address 128	\$00101500708082C000*
Sequence Step 7 32 Group Address 128	\$00101500708082DF00*

Global Scripter Module Communication Sheet

Sequence Step 8 1 Group Address 1	\$00101500700182E000*
Sequence Step 8 32 Group Address 1	\$00101500700182FF00*
Sequence Step 8 1 Group Address 128	\$00101500708082E000*
Sequence Step 8 32 Group Address 128	\$00101500708082FF00*
Switch Light Off Group Address 1	\$001015007001800000*
Switch Light On Group Address 1	\$001015007001800500*
Switch Light Off Group Address 128	\$001015007080800000*
Switch Light On Group Address 128	\$001015007080800500*