

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Audio Processor
Manufacturer: ClearOne
Firmware Version: 4.3.0.16
Model(s): Converge Pro SR 1212, Converge Pro 840T, Converge Pro 880TA, Converge Pro 880,
Converge Pro SR 1212A, Converge Pro 880T, Converge Pro 8i, Converge Pro TH20,
Converge Pro VH20, Beamforming Mic Array

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.1.0

Version History

Module Version	Date	Notes
1_3_8_0	2/2/2017	Fixed status for VoIP Transmit/Receive Mutes and Gains. Fixed VoIP commands for Converge Pro VH20.
1_3_7_0	9/14/2016	Driver update.
1_3_6_0	2/16/2016	Initial Version.

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'.
- ConnectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.ConnectionCounter = 5.
- If login credentials are required, devicePassword and dievceUsername variables must be set accordingly. Default values for devicePassword and dievceUsername are 'converge' and 'clearone' respectively. For example: InterfaceName.devicePassword = 'converge'.
- DeviceID variable must be set to the ID used on the device. Default value is '0'.
- The value ranges from '0' – '9' and 'A' and 'B'. Converge Pro TH20 and Converge Pro VH20 models also support DeviceID from 'C' – 'F'. Example. InterfaceName.DeviceID = '0'.
- Not all commands are available for all models.

Phonebook Commands:

- These commands apply only to Converge Pro 840T, 880T, 880TA, TH20 and VH20 models.
- Phonebook Entry: Displays the name and number of a phonebook entry for the given Index in the format name: number (Ex: ExtronS3 : 8006339876).
- Phonebook Entry Speed Dial Value: Displays the speed dial value of a phonebook entry for the given Index.
- Phonebook Navigation: Scrolls up and down the entries that appear in Phonebook Entry indexes.
- Phonebook Refresh: Updates all Phonebook Entry indexes with the latest entry from the device.

Control Commands, States, and Qualifiers:

AmplifierOutputGain	-65 to 20 in steps of 0.1		
['Amplifier Output']	'1' – '4'		
AmplifierOutputMute	'On'	'Off'	'Toggle'
['Amplifier Output']	'1' – '4'		
AutoAnswer	'On'	'Off'	'Toggle'
BeamformingMicArrayGain	-65 to 20 in steps of 0.1		
BeamformingMicArrayMute	'On'	'Off'	'Toggle'
ClearEffect	'On'	'Off'	'Toggle'
DTMF	'0' – '9' '*'	'#'	'*'
FaderGain	-65 to 20 in steps of 0.1		
['Fader']	'1' – '4'		
FaderMute	'On'	'Off'	'Toggle'
['Fader']	'1' – '4'		
GPIOStatus	'High'	'Low'	
['Pin']	'2' '8' '14'	'4' '10' '16'	'6' '12' '22'
['Port']	'A'	'B'	
Hook	'Off' 'Flash'	'On' 'Dial'	'Toggle' 'Redial'
['Number']¹	'String'		
InputGain	-65 to 20 in steps of 0.1		
['Input']	'1' – '12'		
InputMute	'On'	'Off'	'Toggle'
['Input']	'1' – '12'		
LineInputGain	-65 to 20 in steps of 0.1		
['Line Input']	'1' – '2'		
LineInputMute	'Off'	'On'	'Toggle'
['Line Input']	'1' – '2'		
Macro	1 – 255		
Matrix	'Crosspoint off'	'Crosspoint on'	'Toggle'

	'Non-Gated'	'Gated'	'Pre-AEC'
['Source']	'1' – '12'	'A' – 'Z'	
['Source Group']	'Inputs' 'Line Inputs'	'Mics' 'Fader'	'Processing' 'Expansion Bus'
['Destination']	'1' – '12'	'A' – 'Z'	
['Destination Group']	'Outputs' 'Fader'	'Processing' 'Virtual Reference'	'Expansion Bus'
MatrixLevel	-60 to 12 in steps of 0.1		
['Source']	'1' – '12'	'A' – 'Z'	
['Source Group']	'Inputs' 'Line Inputs'	'Mics' 'Expansion Bus'	'Processing'
['Destination']	'1' – '12'	'A' – 'Z'	
['Destination Group']	'Outputs' 'Amplifier Output'	'Processing' 'PA Virtual Reference'	'Expansion Bus'
MicGain	-65 to 20 in steps of 0.1		
['Mic']	'1' – '8'		
MicMute	'On'	'Off'	'Toggle'
['Mic']	'1' – '8'		
OutputGain	-65 to 20 in steps of 0.1		
['Output']	'1' – '12'		
OutputMute	'On'	'Off'	'Toggle'
['Output']	'1' – '2'		
PhoneReceiveGain	-65 to 20 in steps of 0.1		
PhoneReceiveMute	'On'	'Off'	'Toggle'
PhoneTransmitGain	-65 to 20 in steps of 0.1		
PhoneTransmitMute	'On'	'Off'	'Toggle'
PhonebookAddEntryCommand	'String'		
['Speed Dial']	'None'	'1' – '20'	
PhonebookDeleteEntryCommand	'String'		
PhonebookNavigation	'Up'	'Down'	
['Step']	'1' – '10'		
PhonebookRefresh	None		
Preset	'Off'	'Execute On'	'Execute Off'
['Preset Number']	'1' – '32'		

ProcessingChannelGain	-65 to 20 in steps of 0.1		
['Processing Channel']	'A' – 'H'		
ProcessingChannelMute	'On'	'Off'	'Toggle'
['Processing Channel']	'A' – 'H'		
RingerEnable	'Off'	'On'	'Toggle'
SafetyMute	'On'	'Off'	
SpeedDial	'1' – '20'		
VoIPReceiveGain	-65 to 20 in steps of 0.1		
VoIPReceiveMute	'On'	'Off'	'Toggle'
VoIPTransmitGain	-65 to 20 in steps of 0.1		
VoIPTransmitMute	'On'	'Off'	'Toggle'

¹ Required only for the Dial command.

Status Available:

AmplifierOutputGain	-65 to 20 in steps of 0.1		
['Amplifier Output']	'1' – '4'		
AmplifierOutputMute	'On'	'Off'	
['Amplifier Output']	'1' – '4'		
AutoAnswer	'On'	'Off'	
BeamformingMicArrayGain	-65 to 20 in steps of 0.1		
BeamformingMicArrayMute	'On'	'Off'	
CallerID	'String'		
ClearEffect	'On'	'Off'	
ConnectionStatus	'Connected'	'Disconnected'	
FaderGain	-65 to 20 in steps of 0.1		
['Fader']	'1' – '4'		
FaderMute	'On'	'Off'	
['Fader']	'1' – '4'		
GPIOStatus	'High'	'Low'	
['Pin']	'2'	'4'	'6'
	'8'	'10'	'12'
	'14'	'16'	'22'
['Port']	'A'	'B'	
Hook	'Off'	'On'	'Ringing'
InputGain	-65 to 20 in steps of 0.1		
['Input']	'1' – '12'		
InputMute	'On'	'Off'	
['Input']	'1' – '12'		
LineInputGain	-65 to 20 in steps of 0.1		
['Line Input']	'1' – '2'		
LineInputMute	'Off'	'On'	
['Line Input']	'1' – '2'		
Macro	1 – 255		
Matrix	'Crosspoint off'	'Crosspoint on'	'Non-Gated'
	'Gated'	'Pre-AEC'	'Routing Prohibited'
['Source']	'1' – '12'	'A' – 'Z'	

Global Scriptor Module Communication Sheet

['Source Group']	'Inputs' 'Line Inputs'	'Mics' 'Fader'	'Processing' 'Expansion Bus'
['Destination']	'1' – '12'	'A' – 'Z'	
['Destination Group']	'Outputs' 'Fader'	'Processing' 'Virtual Reference'	'Expansion Bus'
MatrixLevel	-60 to 12 in steps of 0.1		
['Source']	'1' – '12'	'A' – 'Z'	
['Source Group']	'Inputs' 'Line Inputs'	'Mics' 'Expansion Bus'	'Processing'
['Destination']	'1' – '12'	'A' – 'Z'	
['Destination Group']	'Outputs' 'Amplifier Output'	'Processing' 'PA Virtual Reference'	'Expansion Bus'
MicGain	-65 to 20 in steps of 0.1		
['Mic']	'1' – '8'		
MicMute	'On'	'Off'	
['Mic']	'1' – '8'		
OutputGain	-65 to 20 in steps of 0.1		
['Output']	'1' – '12'		
OutputMute	'On'	'Off'	
['Output']	'1' – '2'		
PhoneReceiveGain	-65 to 20 in steps of 0.1		
PhoneReceiveMute	'On'	'Off'	
PhoneTransmitGain	-65 to 20 in steps of 0.1		
PhoneTransmitMute	'On'	'Off'	
PhonebookCount	0 – 20		
PhonebookEntry	'String'		
['Index']	'1' – '20'		
PhonebookEntrySpeedDialValue	'1' – '20'	'N/A'	
['Index']	'1' – '20'		
Preset	'Off'	'Execute On'	
['Preset Number']	'1' – '32'		
ProcessingChannelGain	-65 to 20 in steps of 0.1		
['Processing Channel']	'A' – 'H'		
ProcessingChannelMute	'On'	'Off'	

Global Scripter Module Communication Sheet

['Processing Channel']	'A' – 'H'	
RingerEnable	'Off'	'On'
SafetyMute	'On'	'Off'
VoIPReceiveGain	-65 to 20 in steps of 0.1	
VoIPReceiveMute	'On'	'Off'
VoIPTransmitGain	-65 to 20 in steps of 0.1	
VoIPTransmitMute	'On'	'Off'

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:


- Devices have different numbers of inputs, outputs, faders, microphones and processing. Please refer to owner manual.
- If using this module with any Extron Electronics product with only 3-wire serial control, the ClearOne device flow control must be disabled. The ClearOne device settings can be configured using the manufacturer's control software.

Serial communication:


Port Type: RS-232
Baud Rate: 57600
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND



General Notes:

Network communication:

When configuring the Ethernet module, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet
Default Port:	23
Logon Credentials Supported:	Yes
Default Username:	Clearone
Default Password:	Converge
Multi-Connection Capabilities:	Yes
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

* Examples assume a Device ID of 0

* The letter after # will change depending on the model

* VoIP commands are for Converge Pro VH20

Amplifier Output Gain 20 #D0 GAIN 1 J 20.0 A\x0D
Amplifier Output 1

Amplifier Output Gain 20 #D0 GAIN 2 J 20.0 A\x0D
Amplifier Output 2

Amplifier Output Gain 20 #D0 GAIN 3 J 20.0 A\x0D
Amplifier Output 3

Amplifier Output Gain 20 #D0 GAIN 4 J 20.0 A\x0D
Amplifier Output 4

Amplifier Output Gain -65 #D0 GAIN 1 J -65.0 A\x0D
Amplifier Output 1

Amplifier Output Gain -65 #D0 GAIN 2 J -65.0 A\x0D
Amplifier Output 2

Amplifier Output Gain -65 #D0 GAIN 3 J -65.0 A\x0D
Amplifier Output 3

Amplifier Output Gain -65 #D0 GAIN 4 J -65.0 A\x0D
Amplifier Output 4

Amplifier Output Mute Off #D0 MUTE 1 J 0\x0D
Amplifier Output 1

Amplifier Output Mute Off #D0 MUTE 2 J 0\x0D
Amplifier Output 2

Amplifier Output Mute Off #D0 MUTE 3 J 0\x0D
Amplifier Output 3

Amplifier Output Mute Off #D0 MUTE 4 J 0\x0D
Amplifier Output 4

Amplifier Output Mute On #D0 MUTE 1 J 1\x0D
Amplifier Output 1

Amplifier Output Mute On #D0 MUTE 2 J 1\x0D
Amplifier Output 2

Amplifier Output Mute On #D0 MUTE 3 J 1\x0D
Amplifier Output 3

Amplifier Output Mute On Amplifier Output 4	#D0 MUTE 4 J 1\x0D
Amplifier Output Mute Toggle Amplifier Output 1	#D0 MUTE 1 J 2\x0D
Amplifier Output Mute Toggle Amplifier Output 2	#D0 MUTE 2 J 2\x0D
Amplifier Output Mute Toggle Amplifier Output 3	#D0 MUTE 3 J 2\x0D
Amplifier Output Mute Toggle Amplifier Output 4	#D0 MUTE 4 J 2\x0D
Auto Answer Off	#D0 AA 1 0\x0D
Auto Answer On	#D0 AA 1 1\x0D
Auto Answer Toggle	#D0 AA 1 2\x0D
Auto Answer Off (VoIP)	#E0 XAA 1 Z 0\x0D
Auto Answer On (VoIP)	#E0 XAA 1 Z 1\x0D
Auto Answer Toggle (VoIP)	#E0 XAA 1 Z 2\x0D
Beamforming Mic Array Mute Toggle	#D0 MUTE 1 V 2\x0D
Clear Effect Off	#D0 CLEAREFFECT 1 0\x0D
Clear Effect On	#D0 CLEAREFFECT 1 1\x0D
Clear Effect Toggle	#D0 CLEAREFFECT 1 2\x0D
DTMF # (VoIP)	#E0 XDIAL 1 Z #\x0D
DTMF * (VoIP)	#E0 XDIAL 1 Z *\x0D
DTMF , (VoIP)	#E0 XDIAL 1 Z ,\x0D
DTMF 0 (VoIP)	#E0 XDIAL 1 Z 0\x0D
DTMF 1 (VoIP)	#E0 XDIAL 1 Z 1\x0D
DTMF 2 (VoIP)	#E0 XDIAL 1 Z 2\x0D
DTMF 3 (VoIP)	#E0 XDIAL 1 Z 3\x0D
DTMF 4 (VoIP)	#E0 XDIAL 1 Z 4\x0D
DTMF 5 (VoIP)	#E0 XDIAL 1 Z 5\x0D
DTMF 6 (VoIP)	#E0 XDIAL 1 Z 6\x0D

DTMF 7 (VoIP)	#E0 XDIAL 1 Z 7\x0D
DTMF 8 (VoIP)	#E0 XDIAL 1 Z 8\x0D
DTMF 9 (VoIP)	#E0 XDIAL 1 Z 9\x0D
DTMF #	#D0 DIAL 1 #\x0D
DTMF *	#D0 DIAL 1 *\x0D
DTMF ,	#D0 DIAL 1 ,\x0D
DTMF 0	#D0 DIAL 1 0\x0D
DTMF 1	#D0 DIAL 1 1\x0D
DTMF 2	#D0 DIAL 1 2\x0D
DTMF 3	#D0 DIAL 1 3\x0D
DTMF 4	#D0 DIAL 1 4\x0D
DTMF 5	#D0 DIAL 1 5\x0D
DTMF 6	#D0 DIAL 1 6\x0D
DTMF 7	#D0 DIAL 1 7\x0D
DTMF 8	#D0 DIAL 1 8\x0D
DTMF 9	#D0 DIAL 1 9\x0D
Fader Gain 20 Fader 1	#D0 GAIN 1 F 20.0 A\x0D
Fader Gain 20 Fader 2	#D0 GAIN 2 F 20.0 A\x0D
Fader Gain 20 Fader 3	#D0 GAIN 3 F 20.0 A\x0D
Fader Gain 20 Fader 4	#D0 GAIN 4 F 20.0 A\x0D
Fader Gain -65 Fader 1	#D0 GAIN 1 F -65.0 A\x0D
Fader Gain -65 Fader 2	#D0 GAIN 2 F -65.0 A\x0D
Fader Gain -65 Fader 3	#D0 GAIN 3 F -65.0 A\x0D
Fader Gain -65 Fader 4	#D0 GAIN 4 F -65.0 A\x0D
Fader Mute Off Fader 1	#D0 MUTE 1 F 0\x0D
Fader Mute Off Fader 2	#D0 MUTE 2 F 0\x0D
Fader Mute Off Fader 3	#D0 MUTE 3 F 0\x0D
Fader Mute Off Fader 4	#D0 MUTE 4 F 0\x0D
Fader Mute On Fader 1	#D0 MUTE 1 F 1\x0D

Fader Mute On Fader 2	#D0 MUTE 2 F 1\x0D
Fader Mute On Fader 3	#D0 MUTE 3 F 1\x0D
Fader Mute On Fader 4	#D0 MUTE 4 F 1\x0D
Fader Mute Toggle Fader 1	#D0 MUTE 1 F 2\x0D
Fader Mute Toggle Fader 2	#D0 MUTE 2 F 2\x0D
Fader Mute Toggle Fader 3	#D0 MUTE 3 F 2\x0D
Fader Mute Toggle Fader 4	#D0 MUTE 4 F 2\x0D
GPIO Status High Pin 2 Port A	#D0 GPIOSTATUS 2 1 0\x0D
GPIO Status High Pin 4 Port A	#D0 GPIOSTATUS 4 1 0\x0D
GPIO Status Low Pin 2 Port A	#D0 GPIOSTATUS 2 1 1\x0D
GPIO Status Low Pin 4 Port A	#D0 GPIOSTATUS 4 1 1\x0D
Hook Dial 8006339876	#D0 DIAL 1 8006339876\x0D
Hook Flash	#D0 HOOK 1\x0D
Hook Off	#D0 TE 1 1\x0D
Hook On	#D0 TE 1 0\x0D
Hook Redial	#D0 REDIAL 1\x0D
Hook Toggle	#D0 TE 1 2\x0D
Hook Dial 8006339876 (VoIP)	#E0 XDIAL 1 Z 8006339876\x0D
Hook Flash (VoIP)	#E0 XHOOK 1 Z\x0D
Hook Off (VoIP)	#E0 XTE 1 Z 1\x0D
Hook On (VoIP)	#E0 XTE 1 Z 0\x0D
Hook Redial (VoIP)	#E0 XREDIAL 1 Z\x0D
Hook Toggle (VoIP)	#E0 XTE 1 Z 2\x0D
Input Gain 20 Input 1	#D0 GAIN 1 I 20.0 A\x0D
Input Gain 20 Input 10	#D0 GAIN 10 I 20.0 A\x0D
Input Gain 20 Input 11	#D0 GAIN 11 I 20.0 A\x0D
Input Gain 20 Input 12	#D0 GAIN 12 I 20.0 A\x0D
Input Gain 20 Input 2	#D0 GAIN 2 I 20.0 A\x0D
Input Gain 20 Input 3	#D0 GAIN 3 I 20.0 A\x0D

Input Gain 20 Input 4	#D0 GAIN 4 I 20.0 A\x0D
Input Gain 20 Input 5	#D0 GAIN 5 I 20.0 A\x0D
Input Gain 20 Input 6	#D0 GAIN 6 I 20.0 A\x0D
Input Gain 20 Input 7	#D0 GAIN 7 I 20.0 A\x0D
Input Gain 20 Input 8	#D0 GAIN 8 I 20.0 A\x0D
Input Gain 20 Input 9	#D0 GAIN 9 I 20.0 A\x0D
Input Gain -65 Input 1	#D0 GAIN 1 I -65.0 A\x0D
Input Gain -65 Input 10	#D0 GAIN 10 I -65.0 A\x0D
Input Gain -65 Input 11	#D0 GAIN 11 I -65.0 A\x0D
Input Gain -65 Input 12	#D0 GAIN 12 I -65.0 A\x0D
Input Gain -65 Input 2	#D0 GAIN 2 I -65.0 A\x0D
Input Gain -65 Input 3	#D0 GAIN 3 I -65.0 A\x0D
Input Gain -65 Input 4	#D0 GAIN 4 I -65.0 A\x0D
Input Gain -65 Input 5	#D0 GAIN 5 I -65.0 A\x0D
Input Gain -65 Input 6	#D0 GAIN 6 I -65.0 A\x0D
Input Gain -65 Input 7	#D0 GAIN 7 I -65.0 A\x0D
Input Gain -65 Input 8	#D0 GAIN 8 I -65.0 A\x0D
Input Gain -65 Input 9	#D0 GAIN 9 I -65.0 A\x0D
Input Mute Off Input 1	#D0 MUTE 1 I 0\x0D
Input Mute Off Input 10	#D0 MUTE 10 I 0\x0D
Input Mute Off Input 11	#D0 MUTE 11 I 0\x0D
Input Mute Off Input 12	#D0 MUTE 12 I 0\x0D
Input Mute Off Input 2	#D0 MUTE 2 I 0\x0D
Input Mute Off Input 3	#D0 MUTE 3 I 0\x0D
Input Mute Off Input 4	#D0 MUTE 4 I 0\x0D
Input Mute Off Input 5	#D0 MUTE 5 I 0\x0D
Input Mute Off Input 6	#D0 MUTE 6 I 0\x0D
Input Mute Off Input 7	#D0 MUTE 7 I 0\x0D
Input Mute Off Input 8	#D0 MUTE 8 I 0\x0D

Input Mute Off Input 9	#D0 MUTE 9 I 0\x0D
Input Mute On Input 1	#D0 MUTE 1 I 1\x0D
Input Mute On Input 10	#D0 MUTE 10 I 1\x0D
Input Mute On Input 11	#D0 MUTE 11 I 1\x0D
Input Mute On Input 12	#D0 MUTE 12 I 1\x0D
Input Mute On Input 2	#D0 MUTE 2 I 1\x0D
Input Mute On Input 3	#D0 MUTE 3 I 1\x0D
Input Mute On Input 4	#D0 MUTE 4 I 1\x0D
Input Mute On Input 5	#D0 MUTE 5 I 1\x0D
Input Mute On Input 6	#D0 MUTE 6 I 1\x0D
Input Mute On Input 7	#D0 MUTE 7 I 1\x0D
Input Mute On Input 8	#D0 MUTE 8 I 1\x0D
Input Mute On Input 9	#D0 MUTE 9 I 1\x0D
Input Mute Toggle Input 1	#D0 MUTE 1 I 2\x0D
Input Mute Toggle Input 10	#D0 MUTE 10 I 2\x0D
Input Mute Toggle Input 11	#D0 MUTE 11 I 2\x0D
Input Mute Toggle Input 12	#D0 MUTE 12 I 2\x0D
Input Mute Toggle Input 2	#D0 MUTE 2 I 2\x0D
Input Mute Toggle Input 3	#D0 MUTE 3 I 2\x0D
Input Mute Toggle Input 4	#D0 MUTE 4 I 2\x0D
Input Mute Toggle Input 5	#D0 MUTE 5 I 2\x0D
Input Mute Toggle Input 6	#D0 MUTE 6 I 2\x0D
Input Mute Toggle Input 7	#D0 MUTE 7 I 2\x0D
Input Mute Toggle Input 8	#D0 MUTE 8 I 2\x0D
Input Mute Toggle Input 9	#D0 MUTE 9 I 2\x0D
Macro 1	#D0 MACRO 1\x0D
Macro 255	#D0 MACRO 255\x0D
Matrix Crosspoint off Source 1 Source Group Inputs	#D0 MTRX 1 I 1 O 0\x0D

Destination 1 Destination
Group Outputs

Matrix Crosspoint off Source #D0 MTRX Z E Z B 0\x0D
Z Source Group Expansion
Bus Destination Z Destination
Group Virtual Reference

Matrix Crosspoint on Source 1 #D0 MTRX 1 I 1 O 1\x0D
Source Group Inputs
Destination 1 Destination
Group Outputs

Matrix Crosspoint on Source Z #D0 MTRX Z E Z B 1\x0D
Source Group Expansion Bus
Destination Z Destination
Group Virtual Reference

Matrix Gated Source 1 Source #D0 MTRX 1 I 1 O 4\x0D
Group Inputs Destination 1
Destination Group Outputs

Matrix Gated Source Z Source #D0 MTRX Z E Z B 4\x0D
Group Expansion Bus
Destination Z Destination
Group Virtual Reference

Matrix Non-Gated Source 1 #D0 MTRX 1 I 1 O 3\x0D
Source Group Inputs
Destination 1 Destination
Group Outputs

Matrix Non-Gated Source Z #D0 MTRX Z E Z B 3\x0D
Source Group Expansion Bus
Destination Z Destination
Group Virtual Reference

Matrix Pre-AEC Source 1 #D0 MTRX 1 I 1 O 5\x0D
Source Group Inputs
Destination 1 Destination
Group Outputs

Matrix Pre-AEC Source Z #D0 MTRX Z E Z B 5\x0D
Source Group Expansion Bus
Destination Z Destination
Group Virtual Reference

Matrix Toggle Source 1 Source #D0 MTRX 1 I 1 O 2\x0D
Group Inputs Destination 1
Destination Group Outputs

Matrix Toggle Source Z	#D0 MTRX Z E Z B 2\x0D
Source Group Expansion Bus	
Destination Z Destination	
Group Virtual Reference	
Mic Gain 20 Mic 1	#D0 GAIN 1 M 20.0 A\x0D
Mic Gain 20 Mic 2	#D0 GAIN 2 M 20.0 A\x0D
Mic Gain 20 Mic 3	#D0 GAIN 3 M 20.0 A\x0D
Mic Gain 20 Mic 4	#D0 GAIN 4 M 20.0 A\x0D
Mic Gain 20 Mic 5	#D0 GAIN 5 M 20.0 A\x0D
Mic Gain 20 Mic 6	#D0 GAIN 6 M 20.0 A\x0D
Mic Gain 20 Mic 7	#D0 GAIN 7 M 20.0 A\x0D
Mic Gain 20 Mic 8	#D0 GAIN 8 M 20.0 A\x0D
Mic Gain -65 Mic 1	#D0 GAIN 1 M -65.0 A\x0D
Mic Gain -65 Mic 2	#D0 GAIN 2 M -65.0 A\x0D
Mic Gain -65 Mic 3	#D0 GAIN 3 M -65.0 A\x0D
Mic Gain -65 Mic 4	#D0 GAIN 4 M -65.0 A\x0D
Mic Gain -65 Mic 5	#D0 GAIN 5 M -65.0 A\x0D
Mic Gain -65 Mic 6	#D0 GAIN 6 M -65.0 A\x0D
Mic Gain -65 Mic 7	#D0 GAIN 7 M -65.0 A\x0D
Mic Gain -65 Mic 8	#D0 GAIN 8 M -65.0 A\x0D
Mic Mute Off Mic 1	#D0 MUTE 1 M 0\x0D
Mic Mute Off Mic 2	#D0 MUTE 2 M 0\x0D
Mic Mute Off Mic 3	#D0 MUTE 3 M 0\x0D
Mic Mute Off Mic 4	#D0 MUTE 4 M 0\x0D
Mic Mute Off Mic 5	#D0 MUTE 5 M 0\x0D
Mic Mute Off Mic 6	#D0 MUTE 6 M 0\x0D
Mic Mute Off Mic 7	#D0 MUTE 7 M 0\x0D
Mic Mute Off Mic 8	#D0 MUTE 8 M 0\x0D
Mic Mute On Mic 1	#D0 MUTE 1 M 1\x0D
Mic Mute On Mic 2	#D0 MUTE 2 M 1\x0D

Mic Mute On Mic 3	#D0 MUTE 3 M 1\x0D
Mic Mute On Mic 4	#D0 MUTE 4 M 1\x0D
Mic Mute On Mic 5	#D0 MUTE 5 M 1\x0D
Mic Mute On Mic 6	#D0 MUTE 6 M 1\x0D
Mic Mute On Mic 7	#D0 MUTE 7 M 1\x0D
Mic Mute On Mic 8	#D0 MUTE 8 M 1\x0D
Mic Mute Toggle Mic 1	#D0 MUTE 1 M 2\x0D
Mic Mute Toggle Mic 2	#D0 MUTE 2 M 2\x0D
Mic Mute Toggle Mic 3	#D0 MUTE 3 M 2\x0D
Mic Mute Toggle Mic 4	#D0 MUTE 4 M 2\x0D
Mic Mute Toggle Mic 5	#D0 MUTE 5 M 2\x0D
Mic Mute Toggle Mic 6	#D0 MUTE 6 M 2\x0D
Mic Mute Toggle Mic 7	#D0 MUTE 7 M 2\x0D
Mic Mute Toggle Mic 8	#D0 MUTE 8 M 2\x0D
Output Gain 20 Output 1	#D0 GAIN 1 O 20.0 A\x0D
Output Gain 20 Output 10	#D0 GAIN 10 O 20.0 A\x0D
Output Gain 20 Output 11	#D0 GAIN 11 O 20.0 A\x0D
Output Gain 20 Output 12	#D0 GAIN 12 O 20.0 A\x0D
Output Gain 20 Output 2	#D0 GAIN 2 O 20.0 A\x0D
Output Gain 20 Output 3	#D0 GAIN 3 O 20.0 A\x0D
Output Gain 20 Output 4	#D0 GAIN 4 O 20.0 A\x0D
Output Gain 20 Output 5	#D0 GAIN 5 O 20.0 A\x0D
Output Gain 20 Output 6	#D0 GAIN 6 O 20.0 A\x0D
Output Gain 20 Output 7	#D0 GAIN 7 O 20.0 A\x0D
Output Gain 20 Output 8	#D0 GAIN 8 O 20.0 A\x0D
Output Gain 20 Output 9	#D0 GAIN 9 O 20.0 A\x0D
Output Gain -65 Output 1	#D0 GAIN 1 O -65.0 A\x0D
Output Gain -65 Output 10	#D0 GAIN 10 O -65.0 A\x0D
Output Gain -65 Output 11	#D0 GAIN 11 O -65.0 A\x0D

Output Gain -65 Output 12	#D0 GAIN 12 O -65.0 A\x0D
Output Gain -65 Output 2	#D0 GAIN 2 O -65.0 A\x0D
Output Gain -65 Output 3	#D0 GAIN 3 O -65.0 A\x0D
Output Gain -65 Output 4	#D0 GAIN 4 O -65.0 A\x0D
Output Gain -65 Output 5	#D0 GAIN 5 O -65.0 A\x0D
Output Gain -65 Output 6	#D0 GAIN 6 O -65.0 A\x0D
Output Gain -65 Output 7	#D0 GAIN 7 O -65.0 A\x0D
Output Gain -65 Output 8	#D0 GAIN 8 O -65.0 A\x0D
Output Gain -65 Output 9	#D0 GAIN 9 O -65.0 A\x0D
Output Mute Off Output 1	#D0 MUTE 1 O 0\x0D
Output Mute Off Output 2	#D0 MUTE 2 O 0\x0D
Output Mute On Output 1	#D0 MUTE 1 O 1\x0D
Output Mute On Output 2	#D0 MUTE 2 O 1\x0D
Output Mute Toggle Output 1	#D0 MUTE 1 O 2\x0D
Output Mute Toggle Output 2	#D0 MUTE 2 O 2\x0D
Phone Receive Mute Off	#D0 MUTE 1 R 0\x0D
Phone Receive Mute On	#D0 MUTE 1 R 1\x0D
Phone Receive Mute Toggle	#D0 MUTE 1 R 2\x0D
Phone Transmit Mute Off	#D0 MUTE 1 T 0\x0D
Phone Transmit Mute On	#D0 MUTE 1 T 1\x0D
Phone Transmit Mute Toggle	#D0 MUTE 1 T 2\x0D
Phonebook Add Entry Command entryToAdd Speed Dial 1	#D0 PHONEBOOKADD 1 entryToAdd\x0D
Phonebook Add Entry Command entryToAdd Speed Dial 20	#D0 PHONEBOOKADD 20 entryToAdd\x0D
Phonebook Delete Entry Command entryToDelete	#D0 PHONEBOOKDEL entryToDelete\x0D
Phonebook Refresh None	#D0 PHONEBOOKREAD 0\x0D#D0 PHONEBOOKREAD 1\x0D#D0 PHONEBOOKREAD 2\x0D#D0 PHONEBOOKREAD 3\x0D#D0 PHONEBOOKREAD 4\x0D#D0 PHONEBOOKREAD 5\x0D#D0

	PHONEBOOKREAD 6\x0D#D0 PHONEBOOKREAD 7\x0D#D0 PHONEBOOKREAD 8\x0D#D0 PHONEBOOKREAD 9\x0D#D0 PHONEBOOKREAD 10\x0D#D0 PHONEBOOKREAD 11\x0D#D0 PHONEBOOKREAD 12\x0D#D0 PHONEBOOKREAD 13\x0D#D0 PHONEBOOKREAD 14\x0D#D0 PHONEBOOKREAD 15\x0D#D0 PHONEBOOKREAD 16\x0D#D0 PHONEBOOKREAD 17\x0D#D0 PHONEBOOKREAD 18\x0D#D0 PHONEBOOKREAD 19\x0D
Preset Execute Off Preset Number 1	#D0 PRESET 1 2\x0D
Preset Execute Off Preset Number 10	#D0 PRESET 10 2\x0D
Preset Execute Off Preset Number 11	#D0 PRESET 11 2\x0D
Preset Execute Off Preset Number 12	#D0 PRESET 12 2\x0D
Preset Execute Off Preset Number 13	#D0 PRESET 13 2\x0D
Preset Execute Off Preset Number 14	#D0 PRESET 14 2\x0D
Preset Execute Off Preset Number 15	#D0 PRESET 15 2\x0D
Preset Execute Off Preset Number 16	#D0 PRESET 16 2\x0D
Preset Execute Off Preset Number 17	#D0 PRESET 17 2\x0D
Preset Execute Off Preset Number 18	#D0 PRESET 18 2\x0D
Preset Execute Off Preset Number 19	#D0 PRESET 19 2\x0D
Preset Execute Off Preset Number 2	#D0 PRESET 2 2\x0D
Preset Execute Off Preset Number 20	#D0 PRESET 20 2\x0D
Preset Execute Off Preset Number 21	#D0 PRESET 21 2\x0D
Preset Execute Off Preset Number 22	#D0 PRESET 22 2\x0D

Preset Execute Off Preset Number 23	#D0 PRESET 23 2\x0D
Preset Execute Off Preset Number 24	#D0 PRESET 24 2\x0D
Preset Execute Off Preset Number 25	#D0 PRESET 25 2\x0D
Preset Execute Off Preset Number 26	#D0 PRESET 26 2\x0D
Preset Execute Off Preset Number 27	#D0 PRESET 27 2\x0D
Preset Execute Off Preset Number 28	#D0 PRESET 28 2\x0D
Preset Execute Off Preset Number 29	#D0 PRESET 29 2\x0D
Preset Execute Off Preset Number 3	#D0 PRESET 3 2\x0D
Preset Execute Off Preset Number 30	#D0 PRESET 30 2\x0D
Preset Execute Off Preset Number 31	#D0 PRESET 31 2\x0D
Preset Execute Off Preset Number 32	#D0 PRESET 32 2\x0D
Preset Execute Off Preset Number 4	#D0 PRESET 4 2\x0D
Preset Execute Off Preset Number 5	#D0 PRESET 5 2\x0D
Preset Execute Off Preset Number 6	#D0 PRESET 6 2\x0D
Preset Execute Off Preset Number 7	#D0 PRESET 7 2\x0D
Preset Execute Off Preset Number 8	#D0 PRESET 8 2\x0D
Preset Execute Off Preset Number 9	#D0 PRESET 9 2\x0D
Preset Execute On Preset Number 1	#D0 PRESET 1 1\x0D

Preset Execute On Preset Number 10	#D0 PRESET 10 1\x0D
Preset Execute On Preset Number 11	#D0 PRESET 11 1\x0D
Preset Execute On Preset Number 12	#D0 PRESET 12 1\x0D
Preset Execute On Preset Number 13	#D0 PRESET 13 1\x0D
Preset Execute On Preset Number 14	#D0 PRESET 14 1\x0D
Preset Execute On Preset Number 15	#D0 PRESET 15 1\x0D
Preset Execute On Preset Number 16	#D0 PRESET 16 1\x0D
Preset Execute On Preset Number 17	#D0 PRESET 17 1\x0D
Preset Execute On Preset Number 18	#D0 PRESET 18 1\x0D
Preset Execute On Preset Number 19	#D0 PRESET 19 1\x0D
Preset Execute On Preset Number 2	#D0 PRESET 2 1\x0D
Preset Execute On Preset Number 20	#D0 PRESET 20 1\x0D
Preset Execute On Preset Number 21	#D0 PRESET 21 1\x0D
Preset Execute On Preset Number 22	#D0 PRESET 22 1\x0D
Preset Execute On Preset Number 23	#D0 PRESET 23 1\x0D
Preset Execute On Preset Number 24	#D0 PRESET 24 1\x0D
Preset Execute On Preset Number 25	#D0 PRESET 25 1\x0D
Preset Execute On Preset Number 26	#D0 PRESET 26 1\x0D

Preset Execute On Preset Number 27	#D0 PRESET 27 1\x0D
Preset Execute On Preset Number 28	#D0 PRESET 28 1\x0D
Preset Execute On Preset Number 29	#D0 PRESET 29 1\x0D
Preset Execute On Preset Number 3	#D0 PRESET 3 1\x0D
Preset Execute On Preset Number 30	#D0 PRESET 30 1\x0D
Preset Execute On Preset Number 31	#D0 PRESET 31 1\x0D
Preset Execute On Preset Number 32	#D0 PRESET 32 1\x0D
Preset Execute On Preset Number 4	#D0 PRESET 4 1\x0D
Preset Execute On Preset Number 5	#D0 PRESET 5 1\x0D
Preset Execute On Preset Number 6	#D0 PRESET 6 1\x0D
Preset Execute On Preset Number 7	#D0 PRESET 7 1\x0D
Preset Execute On Preset Number 8	#D0 PRESET 8 1\x0D
Preset Execute On Preset Number 9	#D0 PRESET 9 1\x0D
Preset Off Preset Number 1	#D0 PRESET 1 0\x0D
Preset Off Preset Number 10	#D0 PRESET 10 0\x0D
Preset Off Preset Number 11	#D0 PRESET 11 0\x0D
Preset Off Preset Number 12	#D0 PRESET 12 0\x0D
Preset Off Preset Number 13	#D0 PRESET 13 0\x0D
Preset Off Preset Number 14	#D0 PRESET 14 0\x0D
Preset Off Preset Number 15	#D0 PRESET 15 0\x0D
Preset Off Preset Number 16	#D0 PRESET 16 0\x0D

Preset Off Preset Number 17	#D0 PRESET 17 0\x0D
Preset Off Preset Number 18	#D0 PRESET 18 0\x0D
Preset Off Preset Number 19	#D0 PRESET 19 0\x0D
Preset Off Preset Number 2	#D0 PRESET 2 0\x0D
Preset Off Preset Number 20	#D0 PRESET 20 0\x0D
Preset Off Preset Number 21	#D0 PRESET 21 0\x0D
Preset Off Preset Number 22	#D0 PRESET 22 0\x0D
Preset Off Preset Number 23	#D0 PRESET 23 0\x0D
Preset Off Preset Number 24	#D0 PRESET 24 0\x0D
Preset Off Preset Number 25	#D0 PRESET 25 0\x0D
Preset Off Preset Number 26	#D0 PRESET 26 0\x0D
Preset Off Preset Number 27	#D0 PRESET 27 0\x0D
Preset Off Preset Number 28	#D0 PRESET 28 0\x0D
Preset Off Preset Number 29	#D0 PRESET 29 0\x0D
Preset Off Preset Number 3	#D0 PRESET 3 0\x0D
Preset Off Preset Number 30	#D0 PRESET 30 0\x0D
Preset Off Preset Number 31	#D0 PRESET 31 0\x0D
Preset Off Preset Number 32	#D0 PRESET 32 0\x0D
Preset Off Preset Number 4	#D0 PRESET 4 0\x0D
Preset Off Preset Number 5	#D0 PRESET 5 0\x0D
Preset Off Preset Number 6	#D0 PRESET 6 0\x0D
Preset Off Preset Number 7	#D0 PRESET 7 0\x0D
Preset Off Preset Number 8	#D0 PRESET 8 0\x0D
Preset Off Preset Number 9	#D0 PRESET 9 0\x0D
Processing Channel Gain 20 Processing Channel A	#D0 GAIN A P 20.0 A\x0D
Processing Channel Gain 20 Processing Channel B	#D0 GAIN B P 20.0 A\x0D
Processing Channel Gain 20 Processing Channel C	#D0 GAIN C P 20.0 A\x0D

Processing Channel Gain 20 Processing Channel D	#D0 GAIN D P 20.0 A\x0D
Processing Channel Gain 20 Processing Channel E	#D0 GAIN E P 20.0 A\x0D
Processing Channel Gain 20 Processing Channel F	#D0 GAIN F P 20.0 A\x0D
Processing Channel Gain 20 Processing Channel G	#D0 GAIN G P 20.0 A\x0D
Processing Channel Gain 20 Processing Channel H	#D0 GAIN H P 20.0 A\x0D
Processing Channel Gain -65 Processing Channel A	#D0 GAIN A P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel B	#D0 GAIN B P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel C	#D0 GAIN C P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel D	#D0 GAIN D P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel E	#D0 GAIN E P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel F	#D0 GAIN F P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel G	#D0 GAIN G P -65.0 A\x0D
Processing Channel Gain -65 Processing Channel H	#D0 GAIN H P -65.0 A\x0D
Processing Channel Mute Off Processing Channel A	#D0 MUTE A P 0\x0D
Processing Channel Mute Off Processing Channel B	#D0 MUTE B P 0\x0D
Processing Channel Mute Off Processing Channel C	#D0 MUTE C P 0\x0D
Processing Channel Mute Off Processing Channel D	#D0 MUTE D P 0\x0D
Processing Channel Mute Off Processing Channel E	#D0 MUTE E P 0\x0D

Processing Channel Mute Off Processing Channel F	#D0 MUTE F P 0\x0D
Processing Channel Mute Off Processing Channel G	#D0 MUTE G P 0\x0D
Processing Channel Mute Off Processing Channel H	#D0 MUTE H P 0\x0D
Processing Channel Mute On Processing Channel A	#D0 MUTE A P 1\x0D
Processing Channel Mute On Processing Channel B	#D0 MUTE B P 1\x0D
Processing Channel Mute On Processing Channel C	#D0 MUTE C P 1\x0D
Processing Channel Mute On Processing Channel D	#D0 MUTE D P 1\x0D
Processing Channel Mute On Processing Channel E	#D0 MUTE E P 1\x0D
Processing Channel Mute On Processing Channel F	#D0 MUTE F P 1\x0D
Processing Channel Mute On Processing Channel G	#D0 MUTE G P 1\x0D
Processing Channel Mute On Processing Channel H	#D0 MUTE H P 1\x0D
Processing Channel Mute Toggle Processing Channel A	#D0 MUTE A P 2\x0D
Processing Channel Mute Toggle Processing Channel B	#D0 MUTE B P 2\x0D
Processing Channel Mute Toggle Processing Channel C	#D0 MUTE C P 2\x0D
Processing Channel Mute Toggle Processing Channel D	#D0 MUTE D P 2\x0D
Processing Channel Mute Toggle Processing Channel E	#D0 MUTE E P 2\x0D
Processing Channel Mute Toggle Processing Channel F	#D0 MUTE F P 2\x0D
Processing Channel Mute Toggle Processing Channel G	#D0 MUTE G P 2\x0D

Processing Channel Mute	#D0 MUTE H P 2\x0D
Toggle Processing Channel H	
Ringer Enable Off	#D0 RINGEREN 1 0\x0D
Ringer Enable On	#D0 RINGEREN 1 1\x0D
Ringer Enable Toggle	#D0 RINGEREN 1 2\x0D
Safety Mute Off	#D0 SFTYMUTE 0\x0D
Safety Mute On	#D0 SFTYMUTE 1\x0D
Speed Dial 1 (VoIP)	#E0 XSPEEDDIAL 1 Z 1\x0D
Speed Dial 10 (VoIP)	#E0 XSPEEDDIAL 1 Z 10\x0D
Speed Dial 11	#D0 SPEEDDIAL 1 11\x0D
Speed Dial 12	#D0 SPEEDDIAL 1 12\x0D
Speed Dial 13	#D0 SPEEDDIAL 1 13\x0D
Speed Dial 14	#D0 SPEEDDIAL 1 14\x0D
Speed Dial 15	#D0 SPEEDDIAL 1 15\x0D
Speed Dial 16	#D0 SPEEDDIAL 1 16\x0D
Speed Dial 17	#D0 SPEEDDIAL 1 17\x0D
Speed Dial 18	#D0 SPEEDDIAL 1 18\x0D
Speed Dial 19	#D0 SPEEDDIAL 1 19\x0D
Speed Dial 2	#D0 SPEEDDIAL 1 2\x0D
Speed Dial 20	#D0 SPEEDDIAL 1 20\x0D
Speed Dial 3	#D0 SPEEDDIAL 1 3\x0D
Speed Dial 4	#D0 SPEEDDIAL 1 4\x0D
Speed Dial 5	#D0 SPEEDDIAL 1 5\x0D
Speed Dial 6	#D0 SPEEDDIAL 1 6\x0D
Speed Dial 7	#D0 SPEEDDIAL 1 7\x0D
Speed Dial 8	#D0 SPEEDDIAL 1 8\x0D
Speed Dial 9	#D0 SPEEDDIAL 1 9\x0D
VoIP Receive Mute Off	#D0 MUTE 1 Z 0\x0D
VoIP Receive Mute On	#D0 MUTE 1 Z 1\x0D
VoIP Receive Mute Toggle	#D0 MUTE 1 Z 2\x0D

VoIP Transmit Mute Off	#D0 MUTE 1 K 0\x0D
VoIP Transmit Mute On	#D0 MUTE 1 K 1\x0D
VoIP Transmit Mute Toggle	#D0 MUTE 1 K 2\x0D

Appendix B. Query Commands

* Examples assume a Device ID of 0

* The letter after # will change depending on the model

* VoIP commands are for Converge Pro VH20

Amplifier Output Gain Amplifier Output 1	#D0 GAIN 1 J\x0D
Amplifier Output Gain Amplifier Output 2	#D0 GAIN 2 J\x0D
Amplifier Output Gain Amplifier Output 3	#D0 GAIN 3 J\x0D
Amplifier Output Gain Amplifier Output 4	#D0 GAIN 4 J\x0D
Amplifier Output Mute Amplifier Output 1	#D0 MUTE 1 J\x0D
Amplifier Output Mute Amplifier Output 2	#D0 MUTE 2 J\x0D
Amplifier Output Mute Amplifier Output 3	#D0 MUTE 3 J\x0D
Amplifier Output Mute Amplifier Output 4	#D0 MUTE 4 J\x0D
Auto Answer	#D0 AA 1\x0D
Auto Answer (VoIP)	#E0 XAA 1 Z\x0D
Beamforming Mic Array Gain	#D0 GAIN 1 V\x0D
Beamforming Mic Array Mute	#D0 MUTE 1 V\x0D
Clear Effect	#D0 CLEAREFFECT 1\x0D
Fader Gain Fader 1	#D0 GAIN 1 F\x0D
Fader Gain Fader 2	#D0 GAIN 2 F\x0D
Fader Gain Fader 3	#D0 GAIN 3 F\x0D
Fader Gain Fader 4	#D0 GAIN 4 F\x0D
Fader Mute Fader 1	#D0 MUTE 1 F\x0D
Fader Mute Fader 2	#D0 MUTE 2 F\x0D
Fader Mute Fader 3	#D0 MUTE 3 F\x0D
Fader Mute Fader 4	#D0 MUTE 4 F\x0D

Gate Status Mic 1	#D0 GATE\x0D
Gate Status Mic 2	#D0 GATE\x0D
Gate Status Mic 3	#D0 GATE\x0D
Gate Status Mic 4	#D0 GATE\x0D
Gate Status Mic 5	#D0 GATE\x0D
Gate Status Mic 6	#D0 GATE\x0D
Gate Status Mic 7	#D0 GATE\x0D
Gate Status Mic 8	#D0 GATE\x0D
GPIO Status 2 A	#D0 GPIOSTATUS 2 1\x0D
GPIO Status 4 A	#D0 GPIOSTATUS 4 1\x0D
Hook	#D0 TE 1\x0D
Hook (VoIP)	#E0 XTE 1 Z\x0D
Input Gain Input 1	#D0 GAIN 1 I\x0D
Input Gain Input 10	#D0 GAIN 10 I\x0D
Input Gain Input 11	#D0 GAIN 11 I\x0D
Input Gain Input 12	#D0 GAIN 12 I\x0D
Input Gain Input 2	#D0 GAIN 2 I\x0D
Input Gain Input 3	#D0 GAIN 3 I\x0D
Input Gain Input 4	#D0 GAIN 4 I\x0D
Input Gain Input 5	#D0 GAIN 5 I\x0D
Input Gain Input 6	#D0 GAIN 6 I\x0D
Input Gain Input 7	#D0 GAIN 7 I\x0D
Input Gain Input 8	#D0 GAIN 8 I\x0D
Input Gain Input 9	#D0 GAIN 9 I\x0D
Input Mute Input 1	#D0 MUTE 1 I\x0D
Input Mute Input 10	#D0 MUTE 10 I\x0D
Input Mute Input 11	#D0 MUTE 11 I\x0D
Input Mute Input 12	#D0 MUTE 12 I\x0D
Input Mute Input 2	#D0 MUTE 2 I\x0D

Input Mute Input 3	#D0 MUTE 3 I\x0D
Input Mute Input 4	#D0 MUTE 4 I\x0D
Input Mute Input 5	#D0 MUTE 5 I\x0D
Input Mute Input 6	#D0 MUTE 6 I\x0D
Input Mute Input 7	#D0 MUTE 7 I\x0D
Input Mute Input 8	#D0 MUTE 8 I\x0D
Input Mute Input 9	#D0 MUTE 9 I\x0D
Macro	#D0 MACRO\x0D
Mic Gain Mic 1	#D0 GAIN 1 M\x0D
Mic Gain Mic 2	#D0 GAIN 2 M\x0D
Mic Gain Mic 3	#D0 GAIN 3 M\x0D
Mic Gain Mic 4	#D0 GAIN 4 M\x0D
Mic Gain Mic 5	#D0 GAIN 5 M\x0D
Mic Gain Mic 6	#D0 GAIN 6 M\x0D
Mic Gain Mic 7	#D0 GAIN 7 M\x0D
Mic Gain Mic 8	#D0 GAIN 8 M\x0D
Mic Mute Mic 1	#D0 MUTE 1 M\x0D
Mic Mute Mic 2	#D0 MUTE 2 M\x0D
Mic Mute Mic 3	#D0 MUTE 3 M\x0D
Mic Mute Mic 4	#D0 MUTE 4 M\x0D
Mic Mute Mic 5	#D0 MUTE 5 M\x0D
Mic Mute Mic 6	#D0 MUTE 6 M\x0D
Mic Mute Mic 7	#D0 MUTE 7 M\x0D
Mic Mute Mic 8	#D0 MUTE 8 M\x0D
Output Gain Output 1	#D0 GAIN 1 O\x0D
Output Gain Output 10	#D0 GAIN 10 O\x0D
Output Gain Output 11	#D0 GAIN 11 O\x0D
Output Gain Output 12	#D0 GAIN 12 O\x0D
Output Gain Output 2	#D0 GAIN 2 O\x0D

Output Gain Output 3	#D0 GAIN 3 O\x0D
Output Gain Output 4	#D0 GAIN 4 O\x0D
Output Gain Output 5	#D0 GAIN 5 O\x0D
Output Gain Output 6	#D0 GAIN 6 O\x0D
Output Gain Output 7	#D0 GAIN 7 O\x0D
Output Gain Output 8	#D0 GAIN 8 O\x0D
Output Gain Output 9	#D0 GAIN 9 O\x0D
Output Mute Output 1	#D0 MUTE 1 O\x0D
Output Mute Output 2	#D0 MUTE 2 O\x0D
Phone Receive Gain	#D0 GAIN 1 R\x0D
Phone Receive Mute	#D0 MUTE 1 R\x0D
Phone Transmit Gain	#D0 GAIN 1 T\x0D
Phone Transmit Mute	#D0 MUTE 1 T\x0D
Phonebook Count	#D0 PHONEBOOKCNT\x0D
Preset Preset Number 1	#D0 PRESET 1\x0D
Preset Preset Number 10	#D0 PRESET 10\x0D
Preset Preset Number 11	#D0 PRESET 11\x0D
Preset Preset Number 12	#D0 PRESET 12\x0D
Preset Preset Number 13	#D0 PRESET 13\x0D
Preset Preset Number 14	#D0 PRESET 14\x0D
Preset Preset Number 15	#D0 PRESET 15\x0D
Preset Preset Number 16	#D0 PRESET 16\x0D
Preset Preset Number 17	#D0 PRESET 17\x0D
Preset Preset Number 18	#D0 PRESET 18\x0D
Preset Preset Number 19	#D0 PRESET 19\x0D
Preset Preset Number 2	#D0 PRESET 2\x0D
Preset Preset Number 20	#D0 PRESET 20\x0D
Preset Preset Number 21	#D0 PRESET 21\x0D
Preset Preset Number 22	#D0 PRESET 22\x0D

Preset Preset Number 23	#D0 PRESET 23\x0D
Preset Preset Number 24	#D0 PRESET 24\x0D
Preset Preset Number 25	#D0 PRESET 25\x0D
Preset Preset Number 26	#D0 PRESET 26\x0D
Preset Preset Number 27	#D0 PRESET 27\x0D
Preset Preset Number 28	#D0 PRESET 28\x0D
Preset Preset Number 29	#D0 PRESET 29\x0D
Preset Preset Number 3	#D0 PRESET 3\x0D
Preset Preset Number 30	#D0 PRESET 30\x0D
Preset Preset Number 31	#D0 PRESET 31\x0D
Preset Preset Number 32	#D0 PRESET 32\x0D
Preset Preset Number 4	#D0 PRESET 4\x0D
Preset Preset Number 5	#D0 PRESET 5\x0D
Preset Preset Number 6	#D0 PRESET 6\x0D
Preset Preset Number 7	#D0 PRESET 7\x0D
Preset Preset Number 8	#D0 PRESET 8\x0D
Preset Preset Number 9	#D0 PRESET 9\x0D
Processing Channel Gain Processing Channel A	#D0 GAIN A P\x0D
Processing Channel Gain Processing Channel B	#D0 GAIN B P\x0D
Processing Channel Gain Processing Channel C	#D0 GAIN C P\x0D
Processing Channel Gain Processing Channel D	#D0 GAIN D P\x0D
Processing Channel Gain Processing Channel E	#D0 GAIN E P\x0D
Processing Channel Gain Processing Channel F	#D0 GAIN F P\x0D
Processing Channel Gain Processing Channel G	#D0 GAIN G P\x0D
Processing Channel Gain Processing Channel H	#D0 GAIN H P\x0D
Processing Channel Mute Processing Channel A	#D0 MUTE A P\x0D
Processing Channel Mute Processing Channel B	#D0 MUTE B P\x0D
Processing Channel Mute Processing Channel C	#D0 MUTE C P\x0D
Processing Channel Mute Processing Channel D	#D0 MUTE D P\x0D

Processing Channel Mute Processing Channel E	#D0 MUTE E P\x0D
Processing Channel Mute Processing Channel F	#D0 MUTE F P\x0D
Processing Channel Mute Processing Channel G	#D0 MUTE G P\x0D
Processing Channel Mute Processing Channel H	#D0 MUTE H P\x0D
Ringer Enable	#D0 RINGEREN 1\x0D
Safety Mute	#D0 SFTYMUTE\x0D
VoIP Receive Gain	#D0 GAIN 1 Z\x0D
VoIP Receive Mute	#D0 MUTE 1 Z\x0D
VoIP Transmit Gain	#D0 GAIN 1 K\x0D
VoIP Transmit Mute	#D0 MUTE 1 K\x0D