

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Video Processor
Manufacturer: Colorlight
Firmware Version: N/A
Model(s): S6F

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.14.0000-b007	2.13.0

Version History

Module Version	Date	Notes
1_0_1_0	12/3/2021	Added status and DeviceID module parameter.
1_0_0_0	10/14/2019	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- DeviceID variable must be set accordingly. Default value is 0. DeviceID ranges from 0 to 65535 where 65535 corresponds to Broadcast.
Example: `InterfaceName.DeviceID = 0`

Supported Class and Example

EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 9099, Model='S6F')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	
Blank	'On'	'Off'	
# Blank example InterfaceName.Set('Blank', 'On')			
Command	Value		
Brightness	0 to 100 in steps of 1		
# Brightness example InterfaceName.Set('Brightness', 100)			
Command	Value		
ColorTemperature	2000 to 10000 in steps of 1		
# ColorTemperature example InterfaceName.Set('ColorTemperature', 10000)			
Command	Value	Value	
Freeze	'On'	'Off'	
# Freeze example InterfaceName.Set('Freeze', 'On')			
Command	Value	Value	
Input	'DVI'	'HDMI'	
# Input example InterfaceName.Set('Input', 'DVI')			
Command	Value	Value	
SwitchInputManually	'Enable'	'Disable'	
# SwitchInputManually example InterfaceName.Set('SwitchInputManually', 'Enable')			
Command	Value	Value	Value
TestPattern	'Normal'	'Red'	'Green'
	'Blue'	'White'	'Vertical Line'
	'Horizontal Line'	'Left Diagonal'	'Right Diagonal'
	'Gradient of Red'	'Gradient of Green'	'Gradient of Blue'
	'Gradient of White'	'Black'	
# TestPattern example InterfaceName.Set('TestPattern', 'Normal')			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus, Brightness, ColorTemperature, Freeze, Input, and SwitchInputManually do not support the Update function. ConnectionStatus is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
Blank	'On'	'Off'
# Blank example InterfaceName.Update('Blank') Value = InterfaceName.ReadStatus('Blank') InterfaceName.SubscribeStatus('Blank', None, FeedbackHandler)		
Command	Value	
Brightness ¹	0 to 100 in steps of 1	
# Brightness example Value = InterfaceName.ReadStatus('Brightness') InterfaceName.SubscribeStatus('Brightness', None, FeedbackHandler)		
Command	Value	
ColorTemperature ¹	2000 to 10000 in steps of 1	
# ColorTemperature example Value = InterfaceName.ReadStatus('ColorTemperature') InterfaceName.SubscribeStatus('ColorTemperature', None, FeedbackHandler)		
Command	Value	Value
ConnectionStatus ¹	'Connected'	'Disconnected'
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	Value
Freeze ¹	'On'	'Off'
# Freeze example Value = InterfaceName.ReadStatus('Freeze') InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)		
Command	Value	Value
Input ¹	'DVI'	'HDMI'
# Input example Value = InterfaceName.ReadStatus('Input') InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)		
Command	Value	Value
SwitchInputManually ¹	'Enable'	'Disable'
# SwitchInputManually example Value = InterfaceName.ReadStatus('SwitchInputManually') InterfaceName.SubscribeStatus('SwitchInputManually', None, FeedbackHandler)		

¹ For this status to update, the Blank Update must be called

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (UDP)

Device Listen Port: 9099

Logon Credentials Supported: No

Multi-Connection Capabilities: Undetermined

Port Changeability: Yes

Ethernet Module Configuration Description

- Please refer to user manual for settings and changes to the network communication.
- When using multiple UDP modules within the same program each module should have a unique 'Reply on Port' number due to the nature of UDP communication. If you have a module with a fixed 'Reply on Port' number, only one instance of the module can be used within the program.

Notes for the Device

Appendix A. Set Commands

Blank Off	\x11\x00\x11\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x01
Blank On	\x11\x00\x11\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00
Brightness 0	!\x00\x14\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x00\x00
Brightness 100	!\x00\x14\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x00\x00
Color Temperature 10000	"\x00\x12\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x10'
Color Temperature 2000	"\x00\x12\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\xD0\x07
Freeze Off	\x12\x00\x11\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x00
Freeze On	\x12\x00\x11\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x01
Input DVI	3\x00\x12\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x01
Input HDMI	3\x00\x12\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x10
Switch Input Manually Disable	\x8B\x00\x11\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x00
Switch Input Manually Enable	\x8B\x00\x11\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x01
Test Pattern Black	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x0E\x00
Test Pattern Blue	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x03\x00
Test Pattern Gradient of Blue	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x0C\x00
Test Pattern Gradient of Green	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x0B\x00
Test Pattern Gradient of Red	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x0A\x00
Test Pattern Gradient of White	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x0D\x00
Test Pattern Green	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x02\x00
Test Pattern Horizontal Line	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x06\x00
Test Pattern Left Diagonal	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x07\x00
Test Pattern Normal	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x00\x00
Test Pattern Red	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x01\x00
Test Pattern Right Diagonal	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x09\x00
Test Pattern Vertical Line	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x05\x00
Test Pattern White	2\x00\x17\x00\x00\x00\x00\x00\x00\xFF\x00\x00\x00\x00\x00\x00\x00\x04\x00

Appendix B. Update Commands

Blank	\x01\x00\x11\x00\x00\x00\x00\x00\xff\x00\x00\x00\x00\x01\x00\x16
--------------	--