

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Camera
Manufacturer: Cisco
Firmware Version: N/A
Model(s): PrecisionHD 720p, PrecisionHD 1080p 4X, PrecisionHD 1080p 12X

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.02.0000-b012	2.01.0000-b003	1.1.0

Version History

Module Version	Date	Notes
1_1_0_0	9/13/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- ConnectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.ConnectionCounter = 5
- DeviceID variable must be set to ID of the camera. Default value is 1. Example: InterfaceName.DeviceID = 1

Control Commands, States, and Qualifiers:

AutoFocus	'Auto'	'Manual'	
BacklightCompensation	'On'	'Off'	
Focus ^{2,3}	'Near'	'Far'	'Stop'
FocuswithSpeed ¹	'Near'	'Far'	'Stop'
['Focus Speed']	0 to 7 in steps of 1		
IRReceiver	'On'	'Off'	
PanTiltwithSpeed ¹	'Up'	'Down'	'Left'
	'Right'	'Up Left'	'Up Right'
	'Down Left'	'Down Right'	'Stop'
['Pan Speed']	1 to 10 in steps of 1		
['Tilt Speed']	1 to 10 in steps of 1		
PanTilt ²	'Up'	'Down'	'Left'
	'Right'	'Up Left'	'Up Right'
	'Down Left'	'Down Right'	'Stop'
PanTiltDirect	'None'		
['Pan Position']	-90 to 90 in steps of 1		
['Tilt Position']	-25 to 15 in steps of 1		
Power	'On'	'Off'	
ResetPanTilt ²	None		
ZoomwithSpeed ¹	'Wide'	'Tele'	'Stop'
['Zoom Speed']	0 to 7 in steps of 1		
Zoom	'Wide'	'Tele'	'Stop'

¹ Only available for Model PrecisionHD 720p, PrecisionHD 1080p 12X

² Only available for Model PrecisionHD 1080p 4X

³ Auto Focus must be set to 'Manual'

Status Available:

AutoFocus	'Auto'	'Manual'
BacklightCompensation	'On'	'Off'
ConnectionStatus	'Connected'	'Disconnected'
PanPosition	-90 to 90 in steps of 1	
Power	'On'	'Off'
TiltPosition	-25 to 15 Degrees	

Cable and Adapter Requirements:

Captive Screw to RJ-45 jack cable.

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	3	RxD
RxD	←	6	TxD
GND	→	2, 7	GND



General Notes: