

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Scaler
 Manufacturer: Contemporary Research
 Firmware Version: N/A
 Model(s): QMOD-SDI 2

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.09.0000-b009	2.5.0

Version History

Module Version	Date	Notes
1_0_0_0	7/23/2020	Initial Version

Module Notes

- Status is not supported

Supported Class and Example

EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 23, Model='QMOD-SDI 2')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	
AspectRatio	'4:3'	'16:9'	
Qualifier Key	Qualifier Value	Qualifier Value	
'Program'	'A'	'B'	
# AspectRatio example InterfaceName.Set('AspectRatio', '4:3', {'Program': 'A'})			
Command	Value	Value	Value
AudioInput	None	'Analog 1'	'Analog 2'
	'SPDIF 1'	'SPDIF 2'	'SDI 1 - P1'
	'SDI 1 - P2'	'SDI 1 - P3'	'SDI 1 - P4'
	'SDI 1 - P5'	'SDI 1 - P6'	'SDI 1 - P7'
	'SDI 1 - P8'	'SDI 2 - P1'	'SDI 2 - P2'
	'SDI 2 - P3'	'SDI 2 - P4'	'SDI 2 - P5'
	'SDI 2 - P6'	'SDI 2 - P7'	'SDI 2 - P8'
Qualifier Key	Qualifier Value	Qualifier Value	
'Program'	'A'	'B'	
Qualifier Key	Qualifier Value		
'Input'	'1' – '2'		
# AudioInput example InterfaceName.Set('AudioInput', None, {'Program': 'A', 'Input': '1'})			
Command	Value	Value	
AutoResolution	'On'	'Off'	
Qualifier Key	Qualifier Value	Qualifier Value	
'Program'	'A'	'B'	
# AutoResolution example InterfaceName.Set('AutoResolution', 'On', {'Program': 'A'})			
Command	Value	Value	
BitrateMode	'Constant'	'Variable'	
Qualifier Key	Qualifier Value	Qualifier Value	
'Program'	'A'	'B'	
# BitrateMode example InterfaceName.Set('BitrateMode', 'Constant', {'Program': 'A'})			
Command	Value		
Channel	'2' – '135'		
# Channel example InterfaceName.Set('Channel', '2')			
Command	Value	Value	Value
ClosedCaption	'Video 1'	'Video 2'	'SDI 1'
	'SDI 2'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Program'	'A'	'B'	
# ClosedCaption example InterfaceName.Set('ClosedCaption', 'Video 1', {'Program': 'A'})			
Command	Value	Value	Value

Input	'SDI 1' 'Video 2'	'SDI 2' None ¹	'Video 1'
Qualifier Key 'Program'	Qualifier Value 'A'	Qualifier Value 'B'	
# Input example InterfaceName.Set('Input', 'SDI 1', {'Program': 'A'})			
Command OutputResolution	Value '1080i' '480i'	Value '720p'	Value '480p'
Qualifier Key 'Program'	Qualifier Value 'A'	Qualifier Value 'B'	
# OutputResolution example InterfaceName.Set('OutputResolution', '1080i', {'Program': 'A'})			
Command ProgramChannel	Value None		
Qualifier Key 'Program'	Qualifier Value 'A'	Qualifier Value 'B'	
Qualifier Key 'Major'	Qualifier Value 0 to 9999 in steps of 1		
Qualifier Key 'Minor'	Qualifier Value 0 to 999 in steps of 1		
# ProgramChannel example InterfaceName.Set('ProgramChannel', None, {'Program': 'A', 'Major': 9999, 'Minor': 999})			
Command VideoBitrate	Value 4 to 20 in steps of 0.5		
Qualifier Key 'Program'	Qualifier Value 'A'	Qualifier Value 'B'	
# VideoBitrate example InterfaceName.Set('VideoBitrate', 20, {'Program': 'A'})			

¹ Only available for Program B.

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type:	Ethernet
Default Port:	23
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Aspect Ratio 16:9 Program A	>1ar=1\x0D\x0A
Aspect Ratio 16:9 Program B	>2ar=1\x0D\x0A
Aspect Ratio 4:3 Program A	>1ar=0\x0D\x0A
Aspect Ratio 4:3 Program B	>2ar=0\x0D\x0A
Audio Input Analog 1 Input 1 Program A	>1fa=1\x0D\x0A
Audio Input Analog 1 Input 1 Program B	>2fa=1\x0D\x0A
Audio Input Analog 1 Input 2 Program A	>1fd=1\x0D\x0A
Audio Input Analog 1 Input 2 Program B	>2fd=1\x0D\x0A
Audio Input Analog 2 Input 1 Program A	>1fa=2\x0D\x0A
Audio Input Analog 2 Input 1 Program B	>2fa=2\x0D\x0A
Audio Input Analog 2 Input 2 Program A	>1fd=2\x0D\x0A
Audio Input Analog 2 Input 2 Program B	>2fd=2\x0D\x0A
Audio Input None Input 1 Program A	>1fa=0\x0D\x0A
Audio Input None Input 1 Program B	>2fa=0\x0D\x0A
Audio Input None Input 2 Program A	>1fd=0\x0D\x0A
Audio Input None Input 2 Program B	>2fd=0\x0D\x0A
Audio Input SDI 1 - P1 Input 1 Program A	>1fa=9\x0D\x0A
Audio Input SDI 1 - P1 Input 1 Program B	>2fa=9\x0D\x0A
Audio Input SDI 1 - P1 Input 2 Program A	>1fd=9\x0D\x0A
Audio Input SDI 1 - P1 Input 2 Program B	>2fd=9\x0D\x0A
Audio Input SDI 1 - P2 Input 1 Program A	>1fa=10\x0D\x0A
Audio Input SDI 1 - P2 Input 1 Program B	>2fa=10\x0D\x0A
Audio Input SDI 1 - P2 Input 2 Program A	>1fd=10\x0D\x0A
Audio Input SDI 1 - P2 Input 2 Program B	>2fd=10\x0D\x0A
Audio Input SDI 1 - P3 Input 1 Program A	>1fa=11\x0D\x0A
Audio Input SDI 1 - P3 Input 1 Program B	>2fa=11\x0D\x0A
Audio Input SDI 1 - P3 Input 2 Program A	>1fd=11\x0D\x0A
Audio Input SDI 1 - P3 Input 2 Program B	>2fd=11\x0D\x0A
Audio Input SDI 1 - P4 Input 1 Program A	>1fa=12\x0D\x0A
Audio Input SDI 1 - P4 Input 1 Program B	>2fa=12\x0D\x0A
Audio Input SDI 1 - P4 Input 2 Program A	>1fd=12\x0D\x0A
Audio Input SDI 1 - P4 Input 2 Program B	>2fd=12\x0D\x0A
Audio Input SDI 1 - P5 Input 1 Program A	>1fa=13\x0D\x0A
Audio Input SDI 1 - P5 Input 1 Program B	>2fa=13\x0D\x0A
Audio Input SDI 1 - P5 Input 2 Program A	>1fd=13\x0D\x0A
Audio Input SDI 1 - P5 Input 2 Program B	>2fd=13\x0D\x0A
Audio Input SDI 1 - P6 Input 1 Program A	>1fa=14\x0D\x0A
Audio Input SDI 1 - P6 Input 1 Program B	>2fa=14\x0D\x0A
Audio Input SDI 1 - P6 Input 2 Program A	>1fd=14\x0D\x0A
Audio Input SDI 1 - P6 Input 2 Program B	>2fd=14\x0D\x0A
Audio Input SDI 1 - P7 Input 1 Program A	>1fa=15\x0D\x0A
Audio Input SDI 1 - P7 Input 1 Program B	>2fa=15\x0D\x0A

Global Scripter Module Communication Sheet

Audio Input SDI 1 - P7 Input 2 Program A	>1fd=15\x0D\x0A
Audio Input SDI 1 - P7 Input 2 Program B	>2fd=15\x0D\x0A
Audio Input SDI 1 - P8 Input 1 Program A	>1fa=16\x0D\x0A
Audio Input SDI 1 - P8 Input 1 Program B	>2fa=16\x0D\x0A
Audio Input SDI 1 - P8 Input 2 Program A	>1fd=16\x0D\x0A
Audio Input SDI 1 - P8 Input 2 Program B	>2fd=16\x0D\x0A
Audio Input SDI 2 - P1 Input 1 Program A	>1fa=17\x0D\x0A
Audio Input SDI 2 - P1 Input 1 Program B	>2fa=17\x0D\x0A
Audio Input SDI 2 - P1 Input 2 Program A	>1fd=17\x0D\x0A
Audio Input SDI 2 - P1 Input 2 Program B	>2fd=17\x0D\x0A
Audio Input SDI 2 - P2 Input 1 Program A	>1fa=18\x0D\x0A
Audio Input SDI 2 - P2 Input 1 Program B	>2fa=18\x0D\x0A
Audio Input SDI 2 - P2 Input 2 Program A	>1fd=18\x0D\x0A
Audio Input SDI 2 - P2 Input 2 Program B	>2fd=18\x0D\x0A
Audio Input SDI 2 - P3 Input 1 Program A	>1fa=19\x0D\x0A
Audio Input SDI 2 - P3 Input 1 Program B	>2fa=19\x0D\x0A
Audio Input SDI 2 - P3 Input 2 Program A	>1fd=19\x0D\x0A
Audio Input SDI 2 - P3 Input 2 Program B	>2fd=19\x0D\x0A
Audio Input SDI 2 - P4 Input 1 Program A	>1fa=20\x0D\x0A
Audio Input SDI 2 - P4 Input 1 Program B	>2fa=20\x0D\x0A
Audio Input SDI 2 - P4 Input 2 Program A	>1fd=20\x0D\x0A
Audio Input SDI 2 - P4 Input 2 Program B	>2fd=20\x0D\x0A
Audio Input SDI 2 - P5 Input 1 Program A	>1fa=21\x0D\x0A
Audio Input SDI 2 - P5 Input 1 Program B	>2fa=21\x0D\x0A
Audio Input SDI 2 - P5 Input 2 Program A	>1fd=21\x0D\x0A
Audio Input SDI 2 - P5 Input 2 Program B	>2fd=21\x0D\x0A
Audio Input SDI 2 - P6 Input 1 Program A	>1fa=22\x0D\x0A
Audio Input SDI 2 - P6 Input 1 Program B	>2fa=22\x0D\x0A
Audio Input SDI 2 - P6 Input 2 Program A	>1fd=22\x0D\x0A
Audio Input SDI 2 - P6 Input 2 Program B	>2fd=22\x0D\x0A
Audio Input SDI 2 - P7 Input 1 Program A	>1fa=23\x0D\x0A
Audio Input SDI 2 - P7 Input 1 Program B	>2fa=23\x0D\x0A
Audio Input SDI 2 - P7 Input 2 Program A	>1fd=23\x0D\x0A
Audio Input SDI 2 - P7 Input 2 Program B	>2fd=23\x0D\x0A
Audio Input SDI 2 - P8 Input 1 Program A	>1fa=24\x0D\x0A
Audio Input SDI 2 - P8 Input 1 Program B	>2fa=24\x0D\x0A
Audio Input SDI 2 - P8 Input 2 Program A	>1fd=24\x0D\x0A
Audio Input SDI 2 - P8 Input 2 Program B	>2fd=24\x0D\x0A
Audio Input SPDIF 1 Input 1 Program A	>1fa=3\x0D\x0A
Audio Input SPDIF 1 Input 1 Program B	>2fa=3\x0D\x0A
Audio Input SPDIF 1 Input 2 Program A	>1fd=3\x0D\x0A
Audio Input SPDIF 1 Input 2 Program B	>2fd=3\x0D\x0A
Audio Input SPDIF 2 Input 1 Program A	>1fa=4\x0D\x0A
Audio Input SPDIF 2 Input 1 Program B	>2fa=4\x0D\x0A

Global Scriptor Module Communication Sheet

Audio Input SPDIF 2 Input 2 Program A	>1fd=4\x0D\x0A
Audio Input SPDIF 2 Input 2 Program B	>2fd=4\x0D\x0A
Auto Resolution Off Program A	>1xa=0\x0D\x0A
Auto Resolution Off Program B	>2xa=0\x0D\x0A
Auto Resolution On Program A	>1xa=1\x0D\x0A
Auto Resolution On Program B	>2xa=1\x0D\x0A
Bitrate Mode Constant Program A	>1bm=0\x0D\x0A
Bitrate Mode Constant Program B	>2bm=0\x0D\x0A
Bitrate Mode Variable Program A	>1bm=1\x0D\x0A
Bitrate Mode Variable Program B	>2bm=1\x0D\x0A
Channel 135	>tc=135\x0D\x0A
Channel 2	>tc=2\x0D\x0A
Closed Caption SDI 1 Program A	>1cc=9\x0D\x0A
Closed Caption SDI 1 Program B	>2cc=9\x0D\x0A
Closed Caption SDI 2 Program A	>1cc=10\x0D\x0A
Closed Caption SDI 2 Program B	>2cc=10\x0D\x0A
Closed Caption Video 1 Program A	>1cc=3\x0D\x0A
Closed Caption Video 1 Program B	>2cc=3\x0D\x0A
Closed Caption Video 2 Program A	>1cc=4\x0D\x0A
Closed Caption Video 2 Program B	>2cc=4\x0D\x0A
Input None Program B	>2x9=0\x0D\x0A
Input SDI 1 Program A	>1x9=9\x0D\x0A
Input SDI 1 Program B	>2x9=9\x0D\x0A
Input SDI 2 Program A	>1x9=10\x0D\x0A
Input SDI 2 Program B	>2x9=10\x0D\x0A
Input Video 1 Program A	>1x9=3\x0D\x0A
Input Video 1 Program B	>2x9=3\x0D\x0A
Input Video 2 Program A	>1x9=4\x0D\x0A
Input Video 2 Program B	>2x9=4\x0D\x0A
Output Resolution 1080i Program A	>1x8=0\x0D\x0A
Output Resolution 1080i Program B	>2x8=0\x0D\x0A
Output Resolution 480i Program A	>1x8=3\x0D\x0A
Output Resolution 480i Program B	>2x8=3\x0D\x0A
Output Resolution 480p Program A	>1x8=2\x0D\x0A
Output Resolution 480p Program B	>2x8=2\x0D\x0A
Output Resolution 720p Program A	>1x8=1\x0D\x0A
Output Resolution 720p Program B	>2x8=1\x0D\x0A
Program Channel None Major 0 Minor 0 Program A	>1ta=0\x0D\x0A>1ti=0\x0D\x0A
Program Channel None Major 0 Minor 0 Program B	>2ta=0\x0D\x0A>2ti=0\x0D\x0A
Program Channel None Major 0 Minor 999 Program A	>1ta=0\x0D\x0A>1ti=999\x0D\x0A
Program Channel None Major 0 Minor 999 Program B	>2ta=0\x0D\x0A>2ti=999\x0D\x0A
Program Channel None Major 9999 Minor 0 Program A	>1ta=9999\x0D\x0A>1ti=0\x0D\x0A

Global Scriptor Module Communication Sheet

Program Channel None Major 9999 Minor 0 Program B	>2ta=9999\x0D\x0A>2ti=0\x0D\x0A
Program Channel None Major 9999 Minor 999 Program A	>1ta=9999\x0D\x0A>1ti=999\x0D\x0A
Program Channel None Major 9999 Minor 999 Program B	>2ta=9999\x0D\x0A>2ti=999\x0D\x0A
Video Bitrate 20 Program A	>1f4=20.0\x0D\x0A
Video Bitrate 20 Program B	>2f4=20.0\x0D\x0A
Video Bitrate 4 Program A	>1f4=4.0\x0D\x0A
Video Bitrate 4 Program B	>2f4=4.0\x0D\x0A