

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Camera
Manufacturer: Marshall
Firmware Version: N/A
Model(s): CV620, CV620-IP, CV620-NDI, CV620-NDIW, CV620-IPW

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.03.0000-b006	2.3.0

Version History

Module Version	Date	Notes
1_1_0_0	6/18/2019	Added models CV620-IPW, CV620-NDI and CV620-NDIW. Changed Ethernet control to UDP.
1_0_2_0	3/14/2019	Added model CV620-IP and Ethernet control
1_0_1_0	1/7/2019	Updated module to Rev. B1. Added RS-422 notes. Fixed WhiteBalance and Resolution commands.
1_0_0_0	12/28/2006	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- If login credentials are required, devicePassword and deviceUsername must be set accordingly.
Example: `InterfaceName.devicePassword = 'extron'`
- Serial communication only, DeviceID variable must be set accordingly. Default value is '1'. DeviceID ranges from '1' to '7'.
Example: `InterfaceName.DeviceID = '1'`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='CV620')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='CV620')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 52381, Model='CV620')</code>

Control Commands (Serial)

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	Value
Aperture	'Reset'	'Up'	'Down'
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# Aperture example InterfaceName.Set('Aperture', 'Reset', {'Device ID': '1'})			
Command	Value	Value	Value
AutoExposure	'Full Auto'	'Manual'	'Shutter Priority'
	'Iris Priority'	'White Board' ²	'Smooth Auto' ²
	'Bright'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# AutoExposure example InterfaceName.Set('AutoExposure', 'Full Auto', {'Device ID': '1'})			
Command	Value	Value	Value
AutoFocusMode ¹	'Normal'	'Interval'	'Zoom Trigger'
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# AutoFocusMode example InterfaceName.Set('AutoFocusMode', 'Normal', {'Device ID': '1'})			
Command	Value	Value	
DigitalZoom ¹	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# DigitalZoom example InterfaceName.Set('DigitalZoom', 'On', {'Device ID': '1'})			
Command	Value	Value	Value
Focus	'Near'	'Far'	'Stop'
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
Qualifier Key	Qualifier Value		
'Speed'	'0' – '7'		
# Focus example InterfaceName.Set('Focus', 'Near', {'Device ID': '1', 'Speed': '0'})			
Command	Value	Value	Value
FocusMode	'Auto'	'Manual'	'Auto/Manual'
	'One Push Trigger'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# FocusMode example InterfaceName.Set('FocusMode', 'Auto', {'Device ID': '1'})			

Global Scriptor Module Communication Sheet

Command	Value		
Freeze	'On' 'Off'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# Freeze example InterfaceName.Set('Freeze', 'On', {'Device ID': '1'})			
Command	Value		
Gain	'None'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
Qualifier Key	Qualifier Value		
'Position 1'	'0' – '15'		
Qualifier Key	Qualifier Value		
'Position 2'	'0' – '15'		
# Gain example InterfaceName.Set('Gain', None, {'Device ID': '1', 'Position 1': '0', 'Position 2': '0'})			
Command	Value		Value
IRReceive	'On' 'Off'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# IRReceive example InterfaceName.Set('IRReceive', 'On', {'Device ID': '1'})			
Command	Value		Value
Iris	'Reset' 'Up' 'Down'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# Iris example InterfaceName.Set('Iris', 'Reset', {'Device ID': '1'})			
Command	Value		Value
Mute	'On' 'Off'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# Mute example InterfaceName.Set('Mute', 'On', {'Device ID': '1'})			
Command	Value		Value
PanTilt	'Up' 'Down' 'Left' 'Right' 'Up Left' 'Up Right' 'Down Left' 'Down Right' 'Stop'		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
Qualifier Key	Qualifier Value		
'Pan Speed'	'1' – '24'		
Qualifier Key	Qualifier Value		
'Tilt Speed'	'1' – '24'		
# PanTilt example InterfaceName.Set('PanTilt', 'Up', {'Device ID': '1', 'Pan Speed': '1', 'Tilt Speed': '1'})			
Command	Value		
PanTiltHome	None		
Qualifier Key	Qualifier Value		
'Device ID'	'1' – '7'		
# PanTiltHome example InterfaceName.Set('PanTiltHome', None, {'Device ID': '1'})			

Command PanTiltReset	Value None		
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# PanTiltReset example InterfaceName.Set('PanTiltReset', None, {'Device ID': '1'})			
Command PictureEffect	Value 'Off'	Value 'Neg Art'	Value 'B&W'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# PictureEffect example InterfaceName.Set('PictureEffect', 'Off', {'Device ID': '1'})			
Command Power	Value 'On'	Value 'Off'	
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Power example InterfaceName.Set('Power', 'On', {'Device ID': '1'})			
Command PresetRecall	Value '0' – '127'		
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# PresetRecall example InterfaceName.Set('PresetRecall', '0', {'Device ID': '1'})			
Command PresetReset	Value '0' – '127'		
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# PresetReset example InterfaceName.Set('PresetReset', '0', {'Device ID': '1'})			
Command PresetSave	Value '0' – '127'		
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# PresetSave example InterfaceName.Set('PresetSave', '0', {'Device ID': '1'})			
Command Resolution	Value '1080p-60Hz' '1080p-30Hz' '1080i-60Hz' '720p-60Hz' '720p-30Hz' ¹	Value '1080p-59.94Hz' '1080p-29.97Hz' '1080i-59.94Hz' '720p-59.94Hz' '720p-25Hz' ¹	Value '1080p-50Hz' '1080p-25Hz' '1080i-50Hz' '720p-50Hz' '720p-29.97Hz' ¹
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Resolution example InterfaceName.Set('Resolution', '1080p-60Hz', {'Device ID': '1'})			
Command Shutter	Value 'Reset'	Value 'Up'	Value 'Down'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Shutter example InterfaceName.Set('Shutter', 'Reset', {'Device ID': '1'})			

Global Scriptor Module Communication Sheet

Command WhiteBalance	Value 'Auto' 'One Push' 'Sodium Lamp' '5000K' ² 'Wide Auto' ² 'Sodium Lamp Auto'	Value 'Indoor' 'ATW' '3000K' ² '6500K' ² 'One Push Trigger' 'Sodium Lamp Outdoor Auto'	Value 'Outdoor' 'Manual' '4300K' ² '8000K' ² 'Outdoor Auto'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# WhiteBalance example InterfaceName.Set('WhiteBalance', 'Auto', {'Device ID': '1'})			
Command Zoom	Value 'In'	Value 'Out'	Value 'Stop'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
Qualifier Key 'Speed'	Qualifier Value '0' – '7'		
# Zoom example InterfaceName.Set('Zoom', 'In', {'Device ID': '1', 'Speed': '0'})			

¹ Only available for CV620.

² Only available for CV620-IP, CV620-IPW, CV620-NDI, CV620-NDIW.

Status Available (Serial)

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AutoExposure	Value 'Full Auto' 'Iris Priority' 'Bright'	Value 'Manual' 'White Board'	Value 'Shutter Priority' 'Smooth Auto' ²
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# AutoExposure example InterfaceName.Update('AutoExposure', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('AutoExposure', {'Device ID': '1'}) InterfaceName.SubscribeStatus('AutoExposure', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command DigitalZoom ¹	Value 'On'	Value 'Off'	
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# DigitalZoom example InterfaceName.Update('DigitalZoom', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('DigitalZoom', {'Device ID': '1'}) InterfaceName.SubscribeStatus('DigitalZoom', None, FeedbackHandler)			
Command FocusMode	Value 'Auto' 'One Push Trigger'	Value 'Manual'	Value 'Auto/Manual'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# FocusMode example InterfaceName.Update('FocusMode', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('FocusMode', {'Device ID': '1'}) InterfaceName.SubscribeStatus('FocusMode', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Command Freeze	Value 'On'	Value 'Off'	
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Freeze example InterfaceName.Update('Freeze', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('Freeze', {'Device ID': '1'}) InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)			
Command IRReceive	Value 'On'	Value 'Off'	
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# IRReceive example InterfaceName.Update('IRReceive', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('IRReceive', {'Device ID': '1'}) InterfaceName.SubscribeStatus('IRReceive', None, FeedbackHandler)			
Command Mute	Value 'On'	Value 'Off'	
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Mute example InterfaceName.Update('Mute', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('Mute', {'Device ID': '1'}) InterfaceName.SubscribeStatus('Mute', None, FeedbackHandler)			
Command PictureEffect	Value 'Off'	Value 'Neg Art'	Value 'B&W'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# PictureEffect example InterfaceName.Update('PictureEffect', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('PictureEffect', {'Device ID': '1'}) InterfaceName.SubscribeStatus('PictureEffect', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Power example InterfaceName.Update('Power', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('Power', {'Device ID': '1'}) InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command Resolution	Value '1080p-60Hz' '1080p-30Hz' '1080i-60Hz' '720p-60Hz' '720p-30Hz' ¹	Value '1080p-59.94Hz' '1080p-29.97Hz' '1080i-59.94Hz' '720p-59.94Hz' '720p-25Hz' ¹	Value '1080p-50Hz' '1080p-25Hz' '1080i-50Hz' '720p-50Hz' '720p-29.97Hz' ¹
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
# Resolution example InterfaceName.Update('Resolution', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('Resolution', {'Device ID': '1'}) InterfaceName.SubscribeStatus('Resolution', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Command WhiteBalance	Value 'Auto' 'One Push' 'Sodium Lamp' '5000K' ² 'Wide Auto' ² 'Sodium Lamp Auto'	Value 'Indoor' 'ATW' '3000K' ² '6500K' ² 'One Push Trigger' 'Sodium Lamp Outdoor Auto'	Value 'Outdoor' 'Manual' '4300K' ² '8000K' ² 'Outdoor Auto'
Qualifier Key 'Device ID'	Qualifier Value '1' – '7'		
<pre># WhiteBalance example InterfaceName.Update('WhiteBalance', {'Device ID': '1'}) Value = InterfaceName.ReadStatus('WhiteBalance', {'Device ID': '1'}) InterfaceName.SubscribeStatus('WhiteBalance', None, FeedbackHandler)</pre>			

¹ Only available for CV620.

² Only available for CV620-IP, CV620-IPW, CV620-NDI, CV620-NDIW.

Control Commands (Ethernet)

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	Value
Aperture	'Reset'	'Up'	'Down'
# Aperture example InterfaceName.Set('Aperture', 'Reset')			
Command	Value	Value	Value
AutoExposure	'Full Auto'	'Manual'	'Shutter Priority'
	'Iris Priority'	'White Board'	'Smooth Auto'
# AutoExposure example InterfaceName.Set('AutoExposure', 'Full Auto')			
Command	Value	Value	Value
Focus	'Near'	'Far'	'Stop'
Qualifier Key	Qualifier Value		
'Speed'	'0' – '7'		
# Focus example InterfaceName.Set('Focus', 'Near', {'Speed': '0'})			
Command	Value	Value	Value
FocusMode	'Auto'	'Manual'	'Auto/Manual'
	'One Push Trigger'		
# FocusMode example InterfaceName.Set('FocusMode', 'Auto')			
Command	Value	Value	
Freeze	'On'	'Off'	
# Freeze example InterfaceName.Set('Freeze', 'On')			
Command	Value		
Gain	None		
Qualifier Key	Qualifier Value		
'Position 1'	'0' – '15'		
Qualifier Key	Qualifier Value		
'Position 2'	'0' – '15'		
# Gain example InterfaceName.Set('Gain', None, {'Position 1': '0', 'Position 2': '0'})			
Command	Value	Value	
IRReceive	'On'	'Off'	
# IRReceive example InterfaceName.Set('IRReceive', 'On')			
Command	Value	Value	Value
Iris	'Reset'	'Up'	'Down'
# Iris example InterfaceName.Set('Iris', 'Reset')			
Command	Value	Value	
Mute	'On'	'Off'	
# Mute example InterfaceName.Set('Mute', 'On')			

Global Scripter Module Communication Sheet

Command PanTilt	Value 'Up' 'Right' 'Down Left'	Value 'Down' 'Up Left' 'Down Right'	Value 'Left' 'Up Right' 'Stop'
Qualifier Key 'Pan Speed'	Qualifier Value '1' – '24'		
Qualifier Key 'Tilt Speed'	Qualifier Value '1' – '24'		
# PanTilt example InterfaceName.Set('PanTilt', 'Up', {'Pan Speed': '1', 'Tilt Speed': '1'})			
Command PanTiltHome	Value None		
# PanTiltHome example InterfaceName.Set('PanTiltHome', None)			
Command PanTiltReset	Value None		
# PanTiltReset example InterfaceName.Set('PanTiltReset', None)			
Command PictureEffect	Value 'Off'	Value 'Neg Art'	Value 'B&W'
# PictureEffect example InterfaceName.Set('PictureEffect', 'Off')			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PresetRecall	Value '0' – '127'		
# PresetRecall example InterfaceName.Set('PresetRecall', '0')			
Command PresetReset	Value '0' – '127'		
# PresetReset example InterfaceName.Set('PresetReset', '0')			
Command PresetSave	Value '0' – '127'		
# PresetSave example InterfaceName.Set('PresetSave', '0')			
Command Resolution	Value '1080p-60Hz' '1080p-30Hz' '1080i-60Hz' '720p-60Hz'	Value '1080p-59.94Hz' '1080p-29.97Hz' '1080i-59.94Hz' '720p-59.94Hz'	Value '1080p-50Hz' '1080p-25Hz' '1080i-50Hz' '720p-50Hz'
# Resolution example InterfaceName.Set('Resolution', '1080p-60Hz')			
Command Shutter	Value 'Reset'	Value 'Up'	Value 'Down'
# Shutter example InterfaceName.Set('Shutter', 'Reset')			

Global Scriptor Module Communication Sheet

Command WhiteBalance	Value	Value	Value
	'Auto'	'Indoor'	'Outdoor'
	'One Push'	'ATW'	'Manual'
	'Sodium Lamp'	'3000K'	'4300K'
	'5000K'	'6500K'	'8000K'
	'Wide Auto'	'One Push Trigger'	
# WhiteBalance example InterfaceName.Set('WhiteBalance', 'Auto')			
Command Zoom	Value	Value	Value
	'In'	'Out'	'Stop'
Qualifier Key 'Speed'	Qualifier Value '0' – '7'		
# Zoom example InterfaceName.Set('Zoom', 'In', {'Speed': '0'})			

Status Available (Ethernet)

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})  
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})  
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},  
FeedbackHandler)
```

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)  
Value = InterfaceName.ReadStatus(Command)  
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)  
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AutoExposure	Value 'Full Auto' 'Iris Priority'	Value 'Manual' 'White Board'	Value 'Shutter Priority' 'Smooth Auto'
# AutoExposure example InterfaceName.Update('AutoExposure') Value = InterfaceName.ReadStatus('AutoExposure') InterfaceName.SubscribeStatus('AutoExposure', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command FocusMode	Value 'Auto' 'One Push Trigger'	Value 'Manual'	Value 'Auto/Manual'
# FocusMode example InterfaceName.Update('FocusMode') Value = InterfaceName.ReadStatus('FocusMode') InterfaceName.SubscribeStatus('FocusMode', None, FeedbackHandler)			
Command Freeze	Value 'On'	Value 'Off'	
# Freeze example InterfaceName.Update('Freeze') Value = InterfaceName.ReadStatus('Freeze') InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)			
Command IRReceive	Value 'On'	Value 'Off'	
# IRReceive example InterfaceName.Update('IRReceive') Value = InterfaceName.ReadStatus('IRReceive') InterfaceName.SubscribeStatus('IRReceive', None, FeedbackHandler)			
Command Mute	Value 'On'	Value 'Off'	
# Mute example InterfaceName.Update('Mute') Value = InterfaceName.ReadStatus('Mute') InterfaceName.SubscribeStatus('Mute', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Command PictureEffect	Value 'Off'	Value 'Neg Art'	Value 'B&W'
# PictureEffect example InterfaceName.Update('PictureEffect') Value = InterfaceName.ReadStatus('PictureEffect') InterfaceName.SubscribeStatus('PictureEffect', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command Resolution	Value '1080p-60Hz' '1080p-30Hz' '1080i-60Hz' '720p-60Hz'	Value '1080p-59.94Hz' '1080p-29.97Hz' '1080i-59.94Hz' '720p-59.94Hz'	Value '1080p-50Hz' '1080p-25Hz' '1080i-50Hz' '720p-50Hz'
# Resolution example InterfaceName.Update('Resolution') Value = InterfaceName.ReadStatus('Resolution') InterfaceName.SubscribeStatus('Resolution', None, FeedbackHandler)			
Command WhiteBalance	Value 'Auto' 'One Push' 'Sodium Lamp' '5000K' 'Wide Auto'	Value 'Indoor' 'ATW' '3000K' '6500K' 'One Push Trigger'	Value 'Outdoor' 'Manual' '4300K' '8000K'
# WhiteBalance example InterfaceName.Update('WhiteBalance') Value = InterfaceName.ReadStatus('WhiteBalance') InterfaceName.SubscribeStatus('WhiteBalance', None, FeedbackHandler)			

Cable and Adapter Requirements

For RS-232: Captive Screw to 8-Pin DIN

For RS-422: Captive Screw to Captive Screw

Notes for the Device

- For RS-232: Set “DIP 1” switch of “System Switch” setting to the “Off” position
- For RS-422: Set “DIP 1” switch of “System Switch” setting to the “On” position
- The baud rate is selected using “DIP 3” switch of “System Switch” setting. “Off” position is 9600 and “On” is 38400

Serial communication

Port Type: RS-232, Serial_RS422

Baud Rate: 9600

Data Bits: 8


Parity: None

Stop Bits: One


Flow Control: None

Pin Assignments Diagram


For RS-232:




Signal	Main Cable	Pin	Signal
TxD	→	5	RxD
RxD	←	3	TxD
GND	→	4	GND



For RS-422:



Device Label	Signal	Main Cable	Pin	Signal
TxD	Tx-	→	6	RxD IN-
RxD	Rx-	←	8	TxD IN-
GND	GND	→	5	GND
RTS	Tx+	→	7	RxD IN+
CTS	Rx+	←	9	TxD IN+



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type:	Ethernet
Device Listen Port:	52381
Device Reply Port:	52381
Logon Credentials Supported:	Yes
Default Username:	
Default Password:	
Multi-Connection Capabilities:	Undetermined
Listen Port Changeability:	No
Listen Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

- Please refer to user manual for settings and changes to the network communication. The Camera's VISCA setting must be changed from the default "Serial" to "IP" for Ethernet control to function.
- When using multiple UDP drivers within the same configuration each driver should have a unique 'Reply on Port' number due to the nature of UDP communication. If you have a driver with a fixed 'Reply on Port' number, only one instance of the driver can be used within the configuration.

Notes for the Device

Appendix A. Set Commands (Serial)

Aperture Down	\x81\x01\x04\x02\x03\xff
Aperture Down Device ID 1	\x81\x01\x04\x02\x03\xff
Aperture Down Device ID 7	\x81\x01\x04\x02\x03\xff
Aperture Reset	\x81\x01\x04\x02\x00\xff
Aperture Reset Device ID 1	\x81\x01\x04\x02\x00\xff
Aperture Reset Device ID 7	\x81\x01\x04\x02\x00\xff
Aperture Up	\x81\x01\x04\x02\x02\xff
Aperture Up Device ID 1	\x81\x01\x04\x02\x02\xff
Aperture Up Device ID 7	\x81\x01\x04\x02\x02\xff
Auto Focus Mode Interval Device ID 1	\x81\x01\x04W\x01\xff
Auto Focus Mode Interval Device ID 7	\x81\x01\x04W\x01\xff
Auto Focus Mode Normal Device ID 1	\x81\x01\x04W\x00\xff
Auto Focus Mode Normal Device ID 7	\x81\x01\x04W\x00\xff
Auto Focus Mode Zoom Trigger Device ID 1	\x81\x01\x04W\x02\xff
Auto Focus Mode Zoom Trigger Device ID 7	\x81\x01\x04W\x02\xff
Digital Zoom Off Device ID 1	\x81\x01\x04\x06\x03\xff
Digital Zoom Off Device ID 7	\x81\x01\x04\x06\x03\xff
Digital Zoom On Device ID 1	\x81\x01\x04\x06\x02\xff
Digital Zoom On Device ID 7	\x81\x01\x04\x06\x02\xff
Focus Far Device ID 1 Speed 0	\x81\x01\x04\x08 \xff
Focus Far Device ID 1 Speed 7	\x81\x01\x04\x08' \xff
Focus Far Device ID 7 Speed 0	\x81\x01\x04\x08 \xff
Focus Far Device ID 7 Speed 7	\x81\x01\x04\x08' \xff
Focus Far Speed 0	\x81\x01\x04\x08 \xff
Focus Far Speed 7	\x81\x01\x04\x08' \xff
Focus Mode Auto	\x81\x01\x048\x02\xff
Focus Mode Auto Device ID 1	\x81\x01\x048\x02\xff
Focus Mode Auto Device ID 7	\x81\x01\x048\x02\xff
Focus Mode Auto/Manual	\x81\x01\x048\x10\xff
Focus Mode Auto/Manual Device ID 1	\x81\x01\x048\x10\xff
Focus Mode Auto/Manual Device ID 7	\x81\x01\x048\x10\xff
Focus Mode Manual	\x81\x01\x048\x03\xff
Focus Mode Manual Device ID 1	\x81\x01\x048\x03\xff
Focus Mode Manual Device ID 7	\x81\x01\x048\x03\xff
Focus Mode One Push Trigger	\x81\x01\x04\x18\x01\xff
Focus Mode One Push Trigger Device ID 1	\x81\x01\x04\x18\x01\xff
Focus Mode One Push Trigger Device ID 7	\x81\x01\x04\x18\x01\xff
Focus Near Device ID 1 Speed 0	\x81\x01\x04\x080\xff
Focus Near Device ID 1 Speed 7	\x81\x01\x04\x087\xff
Focus Near Device ID 7 Speed 0	\x81\x01\x04\x080\xff
Focus Near Device ID 7 Speed 7	\x81\x01\x04\x087\xff
Focus Near Speed 0	\x81\x01\x04\x080\xff

Global Scriptor Module Communication Sheet

Focus Near Speed 7	\x81\x01\x04\x087\xff
Focus Stop Device ID 1 Speed 0	\x81\x01\x04\x08\x00\xff
Focus Stop Device ID 1 Speed 7	\x81\x01\x04\x08\x00\xff
Focus Stop Device ID 7 Speed 0	\x81\x01\x04\x08\x00\xff
Focus Stop Device ID 7 Speed 7	\x81\x01\x04\x08\x00\xff
Focus Stop Speed 0	\x81\x01\x04\x08\x00\xff
Focus Stop Speed 7	\x81\x01\x04\x08\x00\xff
Freeze Off	\x81\x01\x04b\x03\xff
Freeze Off Device ID 1	\x81\x01\x04b\x03\xff
Freeze Off Device ID 7	\x81\x01\x04b\x03\xff
Freeze On	\x81\x01\x04b\x02\xff
Freeze On Device ID 1	\x81\x01\x04b\x02\xff
Freeze On Device ID 7	\x81\x01\x04b\x02\xff
Gain None Device ID 1 Position 1 0 Position 2 0	\x81\x01\x04L\x00\x00\x00\xff
Gain None Device ID 1 Position 1 0 Position 2 15	\x81\x01\x04L\x00\x00\x00\x0F\xff
Gain None Device ID 1 Position 1 15 Position 2 0	\x81\x01\x04L\x00\x00\x0F\x00\xff
Gain None Device ID 1 Position 1 15 Position 2 15	\x81\x01\x04L\x00\x00\x0F\x0F\xff
Gain None Device ID 7 Position 1 0 Position 2 0	\x81\x01\x04L\x00\x00\x00\xff
Gain None Device ID 7 Position 1 0 Position 2 15	\x81\x01\x04L\x00\x00\x00\x0F\xff
Gain None Device ID 7 Position 1 15 Position 2 0	\x81\x01\x04L\x00\x00\x0F\x00\xff
Gain None Device ID 7 Position 1 15 Position 2 15	\x81\x01\x04L\x00\x00\x0F\x0F\xff
Gain None Position 1 0 Position 2 0	\x81\x01\x04L\x00\x00\x00\xff
Gain None Position 1 0 Position 2 15	\x81\x01\x04L\x00\x00\x00\x0F\xff
Gain None Position 1 15 Position 2 0	\x81\x01\x04L\x00\x00\x0F\x00\xff
Gain None Position 1 15 Position 2 15	\x81\x01\x04L\x00\x00\x0F\x0F\xff
IR Receive Off	\x81\x01\x06\x08\x03\xff
IR Receive Off Device ID 1	\x81\x01\x06\x08\x03\xff
IR Receive Off Device ID 7	\x81\x01\x06\x08\x03\xff
IR Receive On	\x81\x01\x06\x08\x02\xff
IR Receive On Device ID 1	\x81\x01\x06\x08\x02\xff
IR Receive On Device ID 7	\x81\x01\x06\x08\x02\xff
Iris Down	\x81\x01\x04\x0B\x03\xff
Iris Down Device ID 1	\x81\x01\x04\x0B\x03\xff
Iris Down Device ID 7	\x81\x01\x04\x0B\x03\xff
Iris Reset	\x81\x01\x04\x0B\x00\xff
Iris Reset Device ID 1	\x81\x01\x04\x0B\x00\xff
Iris Reset Device ID 7	\x81\x01\x04\x0B\x00\xff
Iris Up	\x81\x01\x04\x0B\x02\xff
Iris Up Device ID 1	\x81\x01\x04\x0B\x02\xff
Iris Up Device ID 7	\x81\x01\x04\x0B\x02\xff
Mute Off	\x81\x01\x04u\x03\xff
Mute Off Device ID 1	\x81\x01\x04u\x03\xff
Mute Off Device ID 7	\x81\x01\x04u\x03\xff
Mute On	\x81\x01\x04u\x02\xff

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Mute On Device ID 1	\x81\x01\x04u\x02\xff
Mute On Device ID 7	\x81\x01\x04u\x02\xff
Pan Tilt Down Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x02\xff
Pan Tilt Down Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x02\xff
Pan Tilt Down Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x02\xff
Pan Tilt Down Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x02\xff
Pan Tilt Down Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x02\xff
Pan Tilt Down Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x02\xff
Pan Tilt Down Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x02\xff
Pan Tilt Down Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x02\xff
Pan Tilt Down Left Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\xff
Pan Tilt Down Left Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x02\xff
Pan Tilt Down Left Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x02\xff
Pan Tilt Down Left Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x02\xff
Pan Tilt Down Left Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\xff
Pan Tilt Down Left Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x02\xff
Pan Tilt Down Left Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x02\xff
Pan Tilt Down Left Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x02\xff
Pan Tilt Down Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\xff
Pan Tilt Down Left Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x02\xff
Pan Tilt Down Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x02\xff
Pan Tilt Down Left Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x02\xff
Pan Tilt Down Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x02\xff
Pan Tilt Down Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x02\xff
Pan Tilt Down Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x02\xff
Pan Tilt Down Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x02\xff
Pan Tilt Down Right Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x02\xff
Pan Tilt Down Right Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x02\xff
Pan Tilt Down Right Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x02\xff
Pan Tilt Down Right Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x02\xff
Pan Tilt Down Right Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x02\xff

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Pan Tilt Down Right Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x02\xff
Pan Tilt Down Right Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x02\xff
Pan Tilt Down Right Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x02\xff
Pan Tilt Down Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x02\xff
Pan Tilt Down Right Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x02\xff
Pan Tilt Down Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x02\xff
Pan Tilt Down Right Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x02\xff
Pan Tilt Home None	\x81\x01\x06\x04\xff
Pan Tilt Home None Device ID 1	\x81\x01\x06\x04\xff
Pan Tilt Home None Device ID 7	\x81\x01\x06\x04\xff
Pan Tilt Left Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x03\xff
Pan Tilt Left Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x03\xff
Pan Tilt Left Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x03\xff
Pan Tilt Left Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x03\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\x03\xff
Pan Tilt Reset None	\x81\x01\x06\x05\xff
Pan Tilt Reset None Device ID 1	\x81\x01\x06\x05\xff
Pan Tilt Reset None Device ID 7	\x81\x01\x06\x05\xff
Pan Tilt Right Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Right Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x03\xff
Pan Tilt Right Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x03\xff
Pan Tilt Right Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x03\xff
Pan Tilt Right Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Right Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x03\xff
Pan Tilt Right Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x03\xff
Pan Tilt Right Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x03\xff
Pan Tilt Stop Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff
Pan Tilt Stop Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x03\xff
Pan Tilt Stop Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x03\xff
Pan Tilt Stop Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x03\xff
Pan Tilt Stop Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xff

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Pan Tilt Stop Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x03\xFF
Pan Tilt Stop Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x03\xFF
Pan Tilt Stop Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x03\xFF
Pan Tilt Stop Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x03\xFF
Pan Tilt Stop Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x03\xFF
Pan Tilt Stop Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x03\xFF
Pan Tilt Stop Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x03\xFF
Pan Tilt Up Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x01\xFF
Pan Tilt Up Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x01\xFF
Pan Tilt Up Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x01\xFF
Pan Tilt Up Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x01\xFF
Pan Tilt Up Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\x01\xFF
Pan Tilt Up Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\x01\xFF
Pan Tilt Up Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\x01\xFF
Pan Tilt Up Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\x01\xFF
Pan Tilt Up Left Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x01\xFF
Pan Tilt Up Left Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\xFF
Pan Tilt Up Left Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\xFF
Pan Tilt Up Left Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\xFF
Pan Tilt Up Left Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x01\xFF
Pan Tilt Up Left Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\xFF
Pan Tilt Up Left Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\xFF
Pan Tilt Up Left Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\xFF
Pan Tilt Up Left Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x01\xFF
Pan Tilt Up Left Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x01\xFF
Pan Tilt Up Left Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x01\xFF
Pan Tilt Up Left Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x01\xFF
Pan Tilt Up Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x03\xFF
Pan Tilt Up Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x03\xFF
Pan Tilt Up Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x03\xFF
Pan Tilt Up Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x03\xFF
Pan Tilt Up Right Device ID 1 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\xFF
Pan Tilt Up Right Device ID 1 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\xFF
Pan Tilt Up Right Device ID 1 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\xFF
Pan Tilt Up Right Device ID 1 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\xFF

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Pan Tilt Up Right Device ID 7 Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x01\xff
Pan Tilt Up Right Device ID 7 Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x01\xff
Pan Tilt Up Right Device ID 7 Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x01\xff
Pan Tilt Up Right Device ID 7 Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 1	\x81\x01\x06\x01\x01\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 1 Tilt Speed 24	\x81\x01\x06\x01\x01\x18\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 1	\x81\x01\x06\x01\x18\x01\x02\x01\xff
Pan Tilt Up Right Pan Speed 24 Tilt Speed 24	\x81\x01\x06\x01\x18\x18\x02\x01\xff
Picture Effect B&W	\x81\x01\x04c\x04\xff
Picture Effect B&W Device ID 1	\x81\x01\x04c\x04\xff
Picture Effect B&W Device ID 7	\x81\x01\x04c\x04\xff
Picture Effect Neg Art	\x81\x01\x04c\x02\xff
Picture Effect Neg Art Device ID 1	\x81\x01\x04c\x02\xff
Picture Effect Neg Art Device ID 7	\x81\x01\x04c\x02\xff
Picture Effect Off	\x81\x01\x04c\x00\xff
Picture Effect Off Device ID 1	\x81\x01\x04c\x00\xff
Picture Effect Off Device ID 7	\x81\x01\x04c\x00\xff
Power Off	\x81\x01\x04\x00\x03\xff
Power Off Device ID 1	\x81\x01\x04\x00\x03\xff
Power Off Device ID 7	\x81\x01\x04\x00\x03\xff
Power On	\x81\x01\x04\x00\x02\xff
Power On Device ID 1	\x81\x01\x04\x00\x02\xff
Power On Device ID 7	\x81\x01\x04\x00\x02\xff
Preset Recall 0	\x81\x01\x04?\x02\x00\xff
Preset Recall 0 Device ID 1	\x81\x01\x04?\x02\x00\xff
Preset Recall 0 Device ID 7	\x81\x01\x04?\x02\x00\xff
Preset Recall 127	\x81\x01\x04?\x02\x7f\xff
Preset Recall 127 Device ID 1	\x81\x01\x04?\x02\x7f\xff
Preset Recall 127 Device ID 7	\x81\x01\x04?\x02\x7f\xff
Preset Reset 0	\x81\x01\x04?\x00\x00\xff
Preset Reset 0 Device ID 1	\x81\x01\x04?\x00\x00\xff
Preset Reset 0 Device ID 7	\x81\x01\x04?\x00\x00\xff
Preset Reset 127	\x81\x01\x04?\x00\x7f\xff
Preset Reset 127 Device ID 1	\x81\x01\x04?\x00\x7f\xff
Preset Reset 127 Device ID 7	\x81\x01\x04?\x00\x7f\xff
Preset Save 0	\x81\x01\x04?\x01\x00\xff
Preset Save 0 Device ID 1	\x81\x01\x04?\x01\x00\xff
Preset Save 0 Device ID 7	\x81\x01\x04?\x01\x00\xff
Preset Save 127	\x81\x01\x04?\x01\x7f\xff
Preset Save 127 Device ID 1	\x81\x01\x04?\x01\x7f\xff
Preset Save 127 Device ID 7	\x81\x01\x04?\x01\x7f\xff

Global Scriptor Module Communication Sheet

Shutter Down	\x81\x01\x04\x0A\x03\xff
Shutter Down Device ID 1	\x81\x01\x04\x0A\x03\xff
Shutter Down Device ID 7	\x81\x01\x04\x0A\x03\xff
Shutter Reset	\x81\x01\x04\x0A\x00\xff
Shutter Reset Device ID 1	\x81\x01\x04\x0A\x00\xff
Shutter Reset Device ID 7	\x81\x01\x04\x0A\x00\xff
Shutter Up	\x81\x01\x04\x0A\x02\xff
Shutter Up Device ID 1	\x81\x01\x04\x0A\x02\xff
Shutter Up Device ID 7	\x81\x01\x04\x0A\x02\xff
White Balance One Push Trigger	\x81\x01\x04\x10\x05\xff
White Balance One Push Trigger Device ID 1	\x81\x01\x04\x10\x05\xff
White Balance One Push Trigger Device ID 7	\x81\x01\x04\x10\x05\xff
Zoom In Device ID 1 Speed 0	\x81\x01\x04\x07 \xff
Zoom In Device ID 1 Speed 7	\x81\x01\x04\x07' \xff
Zoom In Device ID 7 Speed 0	\x81\x01\x04\x07 \xff
Zoom In Device ID 7 Speed 7	\x81\x01\x04\x07' \xff
Zoom In Speed 0	\x81\x01\x04\x07 \xff
Zoom In Speed 7	\x81\x01\x04\x07' \xff
Zoom Out Device ID 1 Speed 0	\x81\x01\x04\x070\xff
Zoom Out Device ID 1 Speed 7	\x81\x01\x04\x077\xff
Zoom Out Device ID 7 Speed 0	\x81\x01\x04\x070\xff
Zoom Out Device ID 7 Speed 7	\x81\x01\x04\x077\xff
Zoom Out Speed 0	\x81\x01\x04\x070\xff
Zoom Out Speed 7	\x81\x01\x04\x077\xff
Zoom Stop Device ID 1 Speed 0	\x81\x01\x04\x07\x00\xff
Zoom Stop Device ID 1 Speed 7	\x81\x01\x04\x07\x00\xff
Zoom Stop Device ID 7 Speed 0	\x81\x01\x04\x07\x00\xff
Zoom Stop Device ID 7 Speed 7	\x81\x01\x04\x07\x00\xff
Zoom Stop Speed 0	\x81\x01\x04\x07\x00\xff
Zoom Stop Speed 7	\x81\x01\x04\x07\x00\xff

Appendix B. Update Commands (Serial)

Auto Exposure	\x81\x09\x049\xff
Auto Exposure Device ID 1	\x81\x09\x049\xff
Auto Exposure Device ID 7	\x81\x09\x049\xff
Digital Zoom Device ID 1	\x81\x09\x04\x06\xff
Digital Zoom Device ID 7	\x81\x09\x04\x06\xff
Focus Mode	\x81\x09\x048\xff
Focus Mode Device ID 1	\x81\x09\x048\xff
Focus Mode Device ID 7	\x81\x09\x048\xff
Freeze	\x81\x09\x04b\xff
Freeze Device ID 1	\x81\x09\x04b\xff
Freeze Device ID 7	\x81\x09\x04b\xff
IR Receive	\x81\x09\x06\x08\xff
IR Receive Device ID 1	\x81\x09\x06\x08\xff
IR Receive Device ID 7	\x81\x09\x06\x08\xff
Mute	\x81\x09\x04u\xff
Mute Device ID 1	\x81\x09\x04u\xff
Mute Device ID 7	\x81\x09\x04u\xff
Picture Effect	\x81\x09\x04c\xff
Picture Effect Device ID 1	\x81\x09\x04c\xff
Picture Effect Device ID 7	\x81\x09\x04c\xff
Power and Connection	\x81\x09\x04\x00\xff
Resolution	\x81\x09\x06#\xff
Resolution Device ID 1	\x81\x09\x06#\xff
Resolution Device ID 7	\x81\x09\x06#\xff
White Balance	\x81\x09\x045\xff
White Balance Device ID 1	\x81\x09\x045\xff
White Balance Device ID 7	\x81\x09\x045\xff

Appendix C. Set Commands(Ethernet)

Aperture Down	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x02\x03\xFF
Aperture Reset	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x02\x00\xFF
Aperture Up	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x02\x02\xFF
Auto Exposure Full Auto	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x049\x00\xFF
Auto Exposure Iris Priority	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x049\x0B\xFF
Auto Exposure Manual	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x049\x03\xFF
Auto Exposure Shutter Priority	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x049\x0A\xFF
Auto Exposure Smooth Auto	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x049'\xFF
Auto Exposure White Board	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x049_\xFF
Focus Far Speed 0	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x08\xFF
Focus Far Speed 7	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x08'\xFF
Focus Mode Auto	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x048\x02\xFF
Focus Mode Auto/Manual	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x048\x10\xFF
Focus Mode Manual	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x048\x03\xFF
Focus Mode One Push Trigger	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x18\x01\xFF
Focus Near	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x080\xFF

Global Scriptor Module Communication Sheet

Speed 0	
Focus Near Speed 7	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x087\xFF
Focus Stop Speed 0	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x08\x00\xFF
Focus Stop Speed 7	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x08\x00\xFF
Freeze Off	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04b\x03\xFF
Freeze On	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04b\x02\xFF
Gain None Position 1 0 Position 2 0	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04L\x00\x00\x00\x00\xFF
Gain None Position 1 0 Position 2 15	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04L\x00\x00\x00\x0F\xFF
Gain None Position 1 15 Position 2 0	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04L\x00\x00\x0F\x00\xFF
Gain None Position 1 15 Position 2 15	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04L\x00\x00\x0F\x0F\xFF
IR Receive Off	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x08\x03\xFF
IR Receive On	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x08\x02\xFF
Iris Down	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x0B\x03\xFF
Iris Reset	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x0B\x00\xFF
Iris Up	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x0B\x02\xFF
Mute Off	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04u\x03\xFF
Mute On	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04u\x02\xFF
Pan Tilt Down Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x01\x02\xFF
Pan Tilt Down Left Pan Speed 1 Tilt	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x01\x02\xFF

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Speed 24	
Pan Tilt Down Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x02\xFF
Pan Tilt Down Left Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x01\x02\xFF
Pan Tilt Down Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x02\xFF
Pan Tilt Down Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x03\x02\xFF
Pan Tilt Down Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x02\xFF
Pan Tilt Down Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x03\x02\xFF
Pan Tilt Down Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x02\xFF
Pan Tilt Down Right Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x02\x02\xFF
Pan Tilt Down Right Pan Speed 24 Tilt Speed	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x02\xFF

Global Scriptor Module Communication Sheet

1	
Pan Tilt Down Right Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x02\x02\xff
Pan Tilt Home None	\x01\x00\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x04\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x01\x03\xff
Pan Tilt Left Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x03\xff
Pan Tilt Left Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x01\x03\xff
Pan Tilt Reset None	\x01\x00\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x05\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x03\xff
Pan Tilt Right Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x02\x03\xff
Pan Tilt Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x03\xff

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Pan Tilt Right Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x02\x03\xFF
Pan Tilt Stop Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x03\xFF
Pan Tilt Stop Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x03\x03\xFF
Pan Tilt Stop Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x03\xFF
Pan Tilt Stop Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x03\x03\xFF
Pan Tilt Up Left Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x01\xFF
Pan Tilt Up Left Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x01\x01\xFF
Pan Tilt Up Left Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x01\x01\xFF
Pan Tilt Up Left Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x01\x01\xFF
Pan Tilt Up Pan Speed 1 Tilt	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x03\x01\xFF

Global Scripter Module Communication Sheet

Revision: 6/18/2019

Speed 1	
Pan Tilt Up Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x03\x01\xFF
Pan Tilt Up Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x03\x01\xFF
Pan Tilt Up Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x03\x01\xFF
Pan Tilt Up Right Pan Speed 1 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x01\x02\x01\xFF
Pan Tilt Up Right Pan Speed 1 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x01\x18\x02\x01\xFF
Pan Tilt Up Right Pan Speed 24 Tilt Speed 1	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x01\x02\x01\xFF
Pan Tilt Up Right Pan Speed 24 Tilt Speed 24	\x01\x00\x00\x09\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x06\x01\x18\x18\x02\x01\xFF
Picture Effect B&W	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04c\x04\xFF
Picture Effect Neg Art	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04c\x02\xFF
Picture Effect Off	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04c\x00\xFF
Power Off	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x00\x03\xFF
Power On	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x00\x02\xFF
Preset Recall 0	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04?\x02\x00\xFF
Preset Recall 127	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04?\x02\x7F\xFF

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Preset Reset 0	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04?\x00\x00\xff
Preset Reset 127	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04?\x00\x07\xff
Preset Save 0	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04?\x01\x00\xff
Preset Save 127	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04?\x01\x07\xff
Resolution 1080i-50Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x08\xff
Resolution 1080i- 59.94Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x07\xff
Resolution 1080i-60Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x06\xff
Resolution 1080p- 25Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x05\xff
Resolution 1080p- 29.97Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x04\xff
Resolution 1080p- 30Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x03\xff
Resolution 1080p- 50Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x02\xff
Resolution 1080p- 59.94Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x01\xff
Resolution 1080p- 60Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x00\xff
Resolution 720p-50Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x0B\xff
Resolution 720p- 59.94Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x0A\xff
Resolution 720p-60Hz	\x01\x00\x00\x07\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x065\x00\x09\xff
Shutter Down	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x0A\x03\xff
Shutter Reset	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x0A\x00\xff
Shutter Up	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x0A\x02\xff
White Balance	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x07\xff

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

3000K	
White Balance 4300K	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x08\xFF
White Balance 5000K	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x09\xFF
White Balance 6500K	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x0A\xFF
White Balance 8000K	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x0B\xFF
White Balance ATW	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x04\xFF
White Balance Auto	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x00\xFF
White Balance Indoor	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x01\xFF
White Balance Manual	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x05\xFF
White Balance One Push	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x03\xFF
White Balance One Push Trigger	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x10\x05\xFF
White Balance Outdoor	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x02\xFF
White Balance Sodium Lamp	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x06\xFF
White Balance Wide Auto	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x045\x0C\xFF
Zoom In Speed 0	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x07\xFF
Zoom In Speed 7	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x07'\xFF
Zoom Out Speed 0	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x070\xFF

Global Scriptor Module Communication Sheet

Revision: 6/18/2019

Zoom Out Speed 7	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x077\xFF
Zoom Stop Speed 0	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x07\x00\xFF
Zoom Stop Speed 7	\x01\x00\x00\x06\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x01\x04\x07\x00\xFF

Appendix D. Update Commands (Ethernet)

Auto Exposure	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x049\xFF
Focus Mode	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x048\xFF
Freeze	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x04b\xFF
IR Receive	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x06\x08\xFF
Mute	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x04u\xFF
Picture Effect	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x04c\xFF
Power	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x04\x00\xFF
Resolution	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x06#\xFF
White Balance	\x01\x10\x00\x05\x02\x00\x00\x01\x00\x00\x00\x00\x01\x00\x00\x00\x01\x81\x09\x045\xFF