
Course Instructor: **Nishat Tasnim**
Course: **CSE103 (Structured Programming)**

Lab: **03**

Topics Today

1. Switch case statement
2. While loop
3. Do..while loop

Problem 1

In this problem you will develop a calculator which can do Addition, Subtraction, Multiplication, Division and Modulo (Remainder). Use switch-case statements.

Sample Input	Sample Output
4 + 7	11
7 % 3	1

Problem 2

Write a C program to print numbers from 1 to 20.

Problem 3

Write a C program to Program to add numbers until the user enters zero.

Problem 4

User will input a number and you have to generate the multiplication table of that number.

Input	Output
3	3 x 0 = 0
	3 x 1 = 3
	3 x 2 = 6
	3 x 3 = 9
	3 x 4 = 12
	3 x 5 = 15
	3 x 6 = 18
	3 x 7 = 21
	3 x 8 = 24
	3 x 9 = 27
	3 x 10 = 30

Problem 5

Write a program to print odd numbers between 1 and 50 in reverse order.

Problem 6

Write a C program that takes an integer from the user and calculates the number of digits.

Sample Input	Sample Output
Test Data : 2319	The number of digit is: 4

Problem 7

Write a C program to C Program to Reverse a Number.

Sample Input	Sample Output
Enter an integer: 2345	Reversed number = 5432

Problem 8

Print Hello World 10 times along with the serial number and skip the 7th Hello World. Your program would only print a total of 9 'Hello world's along with the serial number.

Sample Output
1 Hello World
2 Hello World
3 Hello World
4 Hello World
5 Hello World
6 Hello World
8 Hello World
9 Hello World
10 Hello World