

SUBSTATION B - BAY L1 - CABLE AND TERMINATION SCHEDULE (AS BUILT)

Circuit: CT 52-L1 core 1, protection Revision C 2025-02-12 Rev C: BF-50 replaced

#	From (device:terminal)	To (device:terminal)	Function
1	CT52L1-A:X2	TB-L1:1	CT secondary, phase A
2	TB-L1:1	TS-L1:1	to test switch
3	TS-L1:2	L1-21:Z01	relay current in
4	TS-L1:2	BF50-L1:A1	BF current in
5	L1-21:Z02	TB-L1:10	to star point
6	BF50-L1:A2	TB-L1:10	to star point
7	CT52L1-B:X2	TB-L1:4	CT secondary, phase B
8	TB-L1:4	TS-L1:3	to test switch
9	TS-L1:4	L1-21:Z03	relay current in
10	TS-L1:4	BF50-L1:B1	BF current in
11	L1-21:Z04	TB-L1:10	to star point
12	BF50-L1:B2	TB-L1:10	to star point
13	CT52L1-C:X2	TB-L1:7	CT secondary, phase C
14	TB-L1:7	TS-L1:5	to test switch
15	TS-L1:6	L1-21:Z05	relay current in
16	TS-L1:6	BF50-L1:C1	BF current in
17	L1-21:Z06	TB-L1:10	to star point
18	BF50-L1:C2	TB-L1:10	to star point
19	CT52L1-A:X4 / B:X4 / C:X4	TB-L1:10	CT common (star point)
20	TB-L1:10	earth bar E1	single earth of CT circuit

Terminations verified against cable cores at the panel. Drawing references: AC schematic B-E-33xx, CT details B-E-22xx.

SUBSTATION B - BAY L2 - CABLE AND TERMINATION SCHEDULE (AS BUILT)

Circuit: CT 52-L2 core 1, protection Revision B 2023-04-11

#	From (device:terminal)	To (device:terminal)	Function
1	CT52L2-A:X2	TB-L2:1	CT secondary, phase A
2	TB-L2:1	TS-L2:1	to test switch
3	TS-L2:2	L2-21:Z01	relay current in
4	L2-21:Z02	BF50-L2:A1	relay out to BF in
5	BF50-L2:A2	TB-L2:10	to star point
6	CT52L2-B:X2	TB-L2:4	CT secondary, phase B
7	TB-L2:4	TS-L2:3	to test switch
8	TS-L2:4	L2-21:Z03	relay current in
9	L2-21:Z04	BF50-L2:B1	relay out to BF in
10	BF50-L2:B2	TB-L2:10	to star point
11	CT52L2-C:X2	TB-L2:7	CT secondary, phase C
12	TB-L2:7	TS-L2:5	to test switch
13	TS-L2:6	L2-21:Z05	relay current in
14	L2-21:Z06	BF50-L2:C1	relay out to BF in
15	BF50-L2:C2	TB-L2:10	to star point
16	CT52L2-A:X4 / B:X4 / C:X4	TB-L2:10	CT common (star point)
17	TB-L2:10	earth bar E1	single earth of CT circuit

Terminations verified against cable cores at the panel. Drawing references: AC schematic B-E-33xx, CT details B-E-22xx.

SUBSTATION B - BAY T1 - CABLE AND TERMINATION SCHEDULE (AS BUILT)

Circuit: CT 52-T1 core 1, protection Revision B 2023-04-11

#	From (device:terminal)	To (device:terminal)	Function
1	CT52T1-A:X2	TB-T1:1	CT secondary, phase A
2	TB-T1:1	TS-T1:1	to test switch
3	TS-T1:2	87T:I1	differential in
4	87T:I2	TB-T1:10	to star point
5	CT52T1-B:X2	TB-T1:4	CT secondary, phase B
6	TB-T1:4	TS-T1:3	to test switch
7	TS-T1:4	87T:I3	differential in
8	87T:I4	TB-T1:10	to star point
9	CT52T1-C:X2	TB-T1:7	CT secondary, phase C
10	TB-T1:7	TS-T1:5	to test switch
11	TS-T1:6	87T:I5	differential in
12	87T:I6	TB-T1:10	to star point
13	CT52T1-A:X5 / B:X5 / C:X5	TB-T1:10	CT common (star point)
14	TB-T1:10	earth bar E1	single earth of CT circuit

Terminations verified against cable cores at the panel. Drawing references: AC schematic B-E-33xx, CT details B-E-22xx.