

# OpenWrt 24.10.8 + COMFAST CF-WA350 ) (

## ✓ GPIO Pins ) (

|          |                                                                                   | GPIO    |             | Trigger   |
|----------|-----------------------------------------------------------------------------------|---------|-------------|-----------|
| LAN      |  | GPIO 21 | ACTIVE_LOW  | switch0   |
| WAN      |  | GPIO 7  | ACTIVE_LOW  | switch0   |
| WLAN2G   |  | GPIO 8  | ACTIVE_LOW  | phy0radio |
| Reset    | -                                                                                 | GPIO 2  | ACTIVE_LOW  | -         |
| Watchdog | -                                                                                 | GPIO 6  | ACTIVE_HIGH | toggle    |



### 1. OpenWrt 24.10.8

```
cd /home/ha-linux

# 安装 git:
sudo apt-get install git

# 克隆 OpenWrt 仓库
git clone https://git.openwrt.org/openwrt/openwrt.git openwrt-24.10.8
cd openwrt-24.10.8
git checkout v24.10.8
```

### 2.

```
sudo apt-get update
sudo apt-get install -y build-essential clang flex bison g++ gawk \
gcc-multilib g++-multilib gettext git libncurses5-dev libssl-dev \
python3-distutils rsync unzip zlib1g-dev file wget zstd \
device-tree-compiler
```

### 3. Feeds

```
./scripts/feeds update -a
./scripts/feeds install -a
```

### 4. DTS

```
cp /path/to/qca9563_comfast_cf-wa350.dts target/linux/ath79/dts/
```

### 5. 01\_leds

```
nano target/linux/ath79/generic/base-files/etc/board.d/01_leds
```

cf-e375ac:

```
comfast,cf-wa350)
    uciundef_set_led_switch "wan" "WAN" "red:wan" "switch0" "0x02"
    uciundef_set_led_switch "lan" "LAN" "green:lan" "switch0" "0x04"
    uciundef_set_led_wlan "wlan2g" "WLAN2G" "blue:wlan2g" "phy0radio"
;;
```

## 6. 02\_network

```
nano target/linux/ath79/generic/base-files/etc/board.d/02_network
```

( ath79\_setup\_interfaces:

```
comfast,cf-wa350)
    uciundef_add_switch "switch0" \
        "0 at eth0" "1:wan" "2:lan"
;;
```

( ath79\_setup\_macs:

```
comfast,cf-wa350)
    wan_mac=$(macaddr_add $(mtd_get_mac_binary art 0x0) 1)
;;
```

## 7. 11-ath10k-caldata

```
nano target/linux/ath79/generic/base-files/etc/hotplug.d/firmware/11-ath10k-caldata
```

```
:
```

```
comfast,cf-e375ac|\
```

```
:
```

```
comfast,cf-wa350|\
comfast,cf-e375ac|\
```

## 8. generic.mk

```
nano target/linux/ath79/image/generic.mk
```

```
cf-e375ac:
```

```
define Device/comfast_cf-wa350
    SOC := qca9563
    DEVICE_VENDOR := COMFAST
    DEVICE_MODEL := CF-WA350
    DEVICE_PACKAGES := kmod-ath10k-ct \
        ath10k-firmware-qca9888-ct -uboot-envtools
    IMAGE_SIZE := 16000k
    SUPPORTED_DEVICES += comfast,cf-wa350
endef
```

```
TARGET_DEVICES += comfast_cf-wa350
```

9.

```
make menuconfig
```

:

```
Target System -> Atheros ATH79
Subtarget -> Generic
Target Profile -> COMFAST CF-WA350
```

10.

```
make -j$(nproc) V=s
```



:

```
ls bin/targets/ath79/generic/*cf-wa350*
```

:

- openwrt-ath79-generic-comfast\_cf-wa350-squashfs-sysupgrade.bin ←
- openwrt-ath79-generic-comfast\_cf-wa350-initramfs-kernel.bin ←



1. partition ART
- 2.
3. LEDs GPIO pins :

```
cat /sys/kernel/debug/gpio
```

4.



|           |         |
|-----------|---------|
|           | QCA9563 |
| WiFi 5GHz | QCA9886 |
| Switch    | QCA8337 |
| RAM       | 128MB   |
| Flash     | 16MB    |

Table 2 – continued

|        |                                     |
|--------|-------------------------------------|
| LEDs   | 3 (red:wan, green:lan, blue:wlan2g) |
| Kernel | Linux 5.15.150 ) (                  |



CF-WA350   CF-E375AC

|           | CF-WA350                    | CF-E375AC                   |
|-----------|-----------------------------|-----------------------------|
| LEDs      | 3                           | 1   RGB                     |
| WAN GPIO  | <b>GPIO 7</b>               |                             |
| LAN GPIO  | <b>GPIO 21</b>              |                             |
| WLAN GPIO | <b>GPIO 8</b>               |                             |
| Network   | "0 at eth0" "1:wan" "2:lan" | "0 at eth0" "1:wan" "2:lan" |
| MAC       | art 0x0 + 1                 | art 0x0 + 1                 |



:

```
# 清除编译产物并重新编译
make clean
make -j$(nproc) V=s

# 清除编译产物并重新编译
make distclean
make menuconfig
make -j$(nproc) V=s
```

CF-WA350 V2.6.0.4