

Impact of Modulation Schemes on Wireless Performance

Simulation and Analysis of BPSK, QPSK, and QAM on AWGN Channel

Romaisa Zahid (073) , Sameen Noor (077)

Department of Computer Science

Fatima Jinnah Women University, Rawalpindi

Subject: Wireless Networks

Submitted to: Ma'am Nergis

Abstract

Digital modulation schemes are fundamental to wireless communication systems. This paper presents a comprehensive simulation-based analysis of five modulation schemes (BPSK, QPSK, 16-QAM, 64-QAM, and 256-QAM) operating over an Additive White Gaussian Noise (AWGN) channel. We measure Bit Error Rate (BER) as a function of Signal-to-Noise Ratio (SNR) for each modulation scheme using 200,000 bits per measurement across SNR range 0-20 dB. Simulation results are validated against theoretical formulas from communication theory, with agreement within 2-41% depending on modulation order. Key findings include: BPSK and QPSK require 7 dB SNR for $BER = 10^{-3}$, while 16-QAM, 64-QAM, and 256-QAM require 11 dB, 15 dB, and 20 dB respectively. These results quantify the fundamental trade-off between spectral efficiency (bits/symbol) and noise robustness, explaining why practical systems employ adaptive modulation. Implementation includes Gray coding for QAM schemes, optimal Maximum Likelihood detection, and professional visualization of results. The work validates that theory accurately predicts practice and provides quantitative design guidelines for engineers selecting modulation schemes for wireless systems.

Index Terms—*Digital modulation, BPSK, QPSK, QAM, BER, AWGN channel, adaptive modulation, wireless communications.*

I. INTRODUCTION

Wireless communication systems transmit digital data through noisy channels without physical connections. The core challenge is achieving high data rates while preserving signal integrity in the presence of noise, fading, and interference [1]. Modulation — the process of encoding digital bits into electromagnetic signals — is the primary tool for solving this engineering challenge [2].

Different modulation schemes embody fundamental design trade-offs. Binary Phase Shift Keying (BPSK) transmits 1 bit per symbol, offering maximum noise robustness but limited spectral efficiency. At the other extreme, 256-QAM encodes 8 bits per symbol, delivering high data throughput but requiring significantly stronger signal

conditions. The key quantitative question driving this research is: exactly how much signal strength (expressed as SNR) does each modulation scheme require to achieve acceptable error performance?

This question has direct practical relevance. WiFi access points measure received signal quality and dynamically select modulation to maximize throughput. 4G/LTE base stations adapt modulation based on channel measurements in real time. 5G networks employ sophisticated link-adaptation algorithms rooted in the same principles [3]. Despite widespread practical implementation, the quantitative relationship between modulation order and SNR requirement is not always clearly understood by students and junior engineers entering the field.

This work bridges the gap between theoretical communication principles and simulated practice. We implement and simulate five modulation schemes over a standard AWGN channel, validate results against closed-form theoretical formulas, and derive practical design guidelines for modulation selection. The contributions of this paper are:

- 1) Exact SNR thresholds for each modulation scheme at target BER = 10^{-3} .
- 2) Quantitative analysis of the spectral efficiency vs. noise robustness trade-off.
- 3) Experimental validation that communication theory accurately predicts simulated performance.
- 4) Practical design guidelines for engineers selecting modulation schemes in wireless deployments.

The remainder of this paper is organized as follows. Section II reviews related work on modulation analysis and wireless channel modeling. Section III describes the methodology including the channel model, modulation schemes, Gray coding, and performance metrics. Section IV details the Python-based implementation. Section V presents simulation results and theoretical validation. Section VI provides in-depth analysis and discussion. Section VII concludes the paper with key findings and future directions.

II. RELATED WORK

The theoretical foundations for modulation performance over AWGN channels are well-established in classical communication theory. Proakis and Salehi [1] provide a comprehensive mathematical framework for digital communication systems, including detailed derivations of Bit Error Rate (BER) expressions for Binary Phase Shift Keying (BPSK), Quadrature Phase Shift Keying (QPSK), and M-ary Quadrature Amplitude Modulation (M-QAM). Their work explains how noise affects symbol detection and establishes the analytical formulas that are widely used for performance evaluation. The derivation of $\text{BER} = 0.5 \times \text{erfc}(\sqrt{\text{SNR}})$ for binary modulation schemes and the generalized BER expressions for higher-order QAM systems form the theoretical foundation against which the simulation results in this study are validated.

The study of digital modulation has been an active area of research because modulation directly influences communication reliability, spectral efficiency, and overall system capacity. Researchers have continuously explored methods to increase data throughput while maintaining acceptable error performance. Early communication systems primarily employed low-order modulation schemes because of their robustness to noise. However, the growing demand for high-speed data services has encouraged the adoption of higher-order modulation techniques capable of transmitting multiple bits per symbol.

Rappaport et al. [2] describe how modern wireless systems implement Adaptive Modulation and Coding (AMC) to optimize communication performance under varying channel conditions. Their work demonstrates that practical systems continuously monitor channel quality and dynamically select modulation schemes based on Signal-to-Noise Ratio (SNR) measurements. When channel conditions are poor, lower-order modulation schemes such as BPSK and QPSK are selected to maximize reliability. As channel quality improves, higher-order QAM schemes are employed to increase throughput. This adaptive strategy enables wireless systems to achieve an effective balance between reliability and spectral efficiency. The quantitative SNR thresholds obtained in the present work provide valuable insight into the decision-making process used by adaptive modulation algorithms.

Parsons and Turkmani [3] investigated wireless propagation channels and established that Additive White Gaussian Noise (AWGN) represents the fundamental noise component present in all practical communication receivers.

Although real-world wireless channels are affected by additional impairments such as multipath fading, shadowing, Doppler effects, and co-channel interference, the AWGN model remains the most important baseline for performance evaluation. Many communication standards first analyze system performance under AWGN conditions before extending investigations to more complex channel models. Consequently, understanding modulation performance over AWGN channels is an essential prerequisite for advanced wireless communication research.

Several researchers have also focused on the importance of signal constellation design and symbol mapping techniques. Lin and Costello [4] provide a comprehensive treatment of Gray coding for multilevel modulation schemes. Their research demonstrates that proper bit-to-symbol mapping can significantly reduce BER by ensuring that adjacent constellation points differ by only one bit. In practical communication systems, noise often causes symbols to be detected as neighboring constellation points. Gray coding minimizes the number of bit errors associated with such symbol errors, thereby improving overall system performance. Because of these advantages, Gray-coded constellations have become standard in modern communication technologies, including IEEE 802.11 wireless networks and LTE cellular systems [5].

Research on higher-order modulation schemes has gained significant attention with the development of broadband wireless communication systems. Seifi et al. [5] examined the performance of advanced modulation formats such as 1024-QAM and 4096-QAM for emerging 5G and future 6G networks. Their findings indicate that while higher-order constellations provide substantial improvements in spectral efficiency, they also require considerably stronger signal conditions to maintain acceptable BER levels. This trade-off between throughput and reliability remains one of the most critical challenges in communication system design. The observations reported in their work are consistent with the results obtained in this study, where progressively higher SNR values are required as modulation order increases from BPSK to 256-QAM.

Recent studies have further explored the integration of modulation techniques with advanced wireless technologies such as Multiple Input Multiple Output (MIMO), Orthogonal Frequency Division Multiplexing (OFDM), beamforming, and intelligent communication systems. These technologies rely heavily on accurate characterization of modulation performance under noisy channel conditions. Understanding the BER behavior of individual modulation schemes therefore remains essential even in sophisticated communication architectures.

Overall, the existing literature establishes a strong theoretical and practical foundation for evaluating digital modulation schemes. However, there remains a need for comprehensive simulation-based studies that simultaneously compare multiple modulation formats using identical channel conditions and performance metrics. The present work addresses this requirement by providing a detailed comparative analysis of BPSK, QPSK, 16-QAM, 64-QAM, and 256-QAM over an AWGN channel. Through theoretical validation, BER analysis, constellation visualization, and spectral efficiency evaluation, this study contributes to a deeper understanding of modulation performance and its implications for modern wireless communication systems.

III. METHODOLOGY

The methodology adopted in this study is designed to systematically evaluate and compare the performance of different digital modulation schemes under identical channel conditions. A simulation-based approach was selected because it allows controlled analysis of communication system behavior while eliminating many unpredictable real-world factors. The primary objective is to investigate how modulation order influences Bit Error Rate (BER), spectral efficiency, and Signal-to-Noise Ratio (SNR) requirements in wireless communication systems. Five widely used modulation schemes—BPSK, QPSK, 16-QAM, 64-QAM, and 256-QAM—were implemented and tested over an Additive White Gaussian Noise (AWGN) channel. The simulation results were then compared with theoretical BER expressions to validate the accuracy of the implementation and provide quantitative insights into modulation performance.

A. Channel Model: AWGN

The wireless channel is modeled as **Additive White Gaussian Noise (AWGN)**, the simplest and most fundamental channel model in communication systems. The received signal is given by:

$$r(t) = s(t) + n(t)$$

where $s(t)$ is the transmitted signal and $n(t) \sim N(0, \sigma^2)$ is zero-mean white Gaussian noise. The noise power σ^2 is related to the SNR (expressed in dB) through:

$$\sigma^2 = 1 / (2 \times k \times 10^{(SNR_dB/10)})$$

where $k = \log_2(M)$ is the number of bits per symbol for an M-ary constellation. The factor of 2 accounts for noise contributions in both the In-phase (I) and Quadrature (Q) signal components.

The AWGN channel is commonly used as a benchmark because it isolates the effects of random noise without introducing additional impairments such as fading, interference, or shadowing. Although real wireless channels are often more complex, AWGN provides a reliable baseline for evaluating the fundamental performance limits of modulation schemes. Furthermore, many theoretical BER expressions are derived assuming AWGN conditions, making it an ideal environment for validating simulation results.

B. Modulation Schemes

Five modulation schemes representing progressive spectral efficiency are analyzed:

1) BPSK (Binary Phase Shift Keying)

- 2-point constellation $\{-1, +1\}$ on the real axis.
- 1 bit per symbol, spectral efficiency = 1 bit/s/Hz.
- Maximum noise robustness among all schemes studied.

BPSK is the simplest digital modulation technique and serves as the baseline for performance comparison. Because only two constellation points are used, the Euclidean distance between symbols is maximized, resulting in excellent resistance to noise and channel impairments.

2) QPSK (Quadrature Phase Shift Keying)

- 4-point constellation with points at $\{\pm 1/\sqrt{2} \pm j/\sqrt{2}\}$.
- 2 bits per symbol, spectral efficiency = 2 bit/s/Hz.
- Implemented as two independent BPSK streams on the I and Q channels simultaneously.

QPSK doubles the spectral efficiency of BPSK without significantly degrading BER performance. This balance between throughput and reliability makes QPSK one of the most widely used modulation schemes in practical wireless communication systems.

3) 16-QAM

- 16-point rectangular constellation in a 4×4 grid with amplitude levels $\{-3, -1, +1, +3\}$.
- 4 bits per symbol, spectral efficiency = 4 bit/s/Hz.

16-QAM increases transmission capacity by encoding four bits in each symbol. However, the reduced spacing between constellation points increases sensitivity to noise, requiring higher SNR values compared to BPSK and QPSK.

4) 64-QAM

- 64-point 8×8 rectangular constellation with amplitude levels $\{-7, -5, -3, -1, +1, +3, +5, +7\}$.
- 6 bits per symbol, spectral efficiency = 6 bit/s/Hz.

64-QAM is widely used in modern broadband communication systems because it provides significantly higher throughput. The increased constellation density, however, introduces greater susceptibility to noise and detection errors.

5) 256-QAM

- 256-point 16×16 rectangular constellation.
- 8 bits per symbol, spectral efficiency = 8 bit/s/Hz.
- Highest spectral efficiency studied, with maximum SNR requirement.

256-QAM offers the highest data transmission rate among the modulation schemes considered in this work. Due to the extremely dense constellation arrangement, reliable communication is only possible when channel conditions are favorable and SNR values are sufficiently high.

C. Gray Coding

All QAM constellations employ Gray coding, a bit assignment strategy in which adjacent constellation points differ by exactly one bit. The Gray code of an integer n is computed as:

$$\text{Gray}(n) = n \oplus (n \gg 1)$$

where $\oplus$ denotes bitwise XOR and $\gg$ denotes right bit-shift.

When noise causes the detector to select a neighboring constellation point, Gray coding ensures that only a single bit error occurs per symbol error event, rather than potentially multiple bit errors. This provides a 2–4× improvement in BER performance compared to arbitrary bit assignments [4].

Gray coding is particularly important for higher-order modulation schemes because the probability of neighboring symbol errors increases as constellation density grows. Consequently, Gray-coded mapping has become a standard feature in modern communication systems such as WiFi, LTE, and 5G networks.

D. Detection Algorithm

Optimal detection under AWGN is performed using the Maximum Likelihood (ML) criterion, which reduces to nearest-neighbor detection for equally probable symbols in AWGN:

$$\hat{s} = \arg \min_k |r - s_k|$$

This detector is mathematically proven to minimize the probability of symbol error for AWGN channels [1], achieving the Cramér–Rao lower bound on detection error probability.

The ML detector compares the received signal with all possible constellation points and selects the symbol having the minimum Euclidean distance from the received sample. Because AWGN introduces random deviations in both amplitude and phase, nearest-neighbor detection provides the most reliable decision rule and is widely adopted in practical communication receivers.

E. Theoretical BER Formulas

For BPSK and QPSK, the theoretical BER is identical and given by:

$$\text{BER} = 0.5 \times \text{erfc}(\sqrt{\text{SNR_linear}})$$

For M-QAM (where $M \in \{16, 64, 256\}$), the theoretical BER with Gray coding is:

$$\text{BER} = (4/k)(1 - 1/\sqrt{M}) \times 0.5 \times \text{erfc}(\sqrt{(1.5k \times \text{SNR}/(M-1))})$$

where $k = \log_2(M)$.

These formulas are derived from the Gaussian Q-function and provide smooth, analytically exact BER curves against which simulated data points are compared. Theoretical BER analysis serves as an important benchmark because it predicts the expected performance of modulation schemes under ideal channel conditions. Comparing simulation results with these expressions helps verify the correctness of the implemented algorithms.

F. Simulation Parameters

Simulation parameters were selected to ensure statistical significance across the BER range of interest. The key parameters are:

- Total bits per test point = 200,000
- SNR range = 0 to 20 dB in steps of 1 dB (21 discrete points)
- Target BER for design analysis = 10^{-3}
- Random seed = 42 for reproducibility

With 200,000 bits, the simulation captures approximately 200 error events at $\text{BER} = 10^{-3}$, providing adequate statistical stability.

The chosen SNR range covers both low-quality and high-quality communication conditions, allowing detailed observation of BER trends across different operating regions. A fixed random seed ensures reproducibility and consistency across simulation runs. The target BER value of 10^{-3} was selected because it is commonly used in communication engineering as a benchmark for acceptable system performance.

G. Performance Evaluation Metrics

To comprehensively assess modulation performance, several evaluation metrics were considered throughout the study. The primary metric is Bit Error Rate (BER), which quantifies the ratio of incorrectly detected bits to the total number of transmitted bits. BER directly reflects communication reliability and serves as the most widely used performance indicator in digital communication systems.

In addition to BER, spectral efficiency was analyzed to evaluate bandwidth utilization. Spectral efficiency measures the number of information bits transmitted per unit bandwidth and is expressed in bits per second per Hertz (bit/s/Hz). Throughput capability and SNR requirements were also examined to provide practical engineering insight into the trade-offs between reliability and transmission capacity. Together, these performance metrics enable a comprehensive comparison of the selected modulation schemes and support the development of practical design recommendations for wireless communication systems.

IV. IMPLEMENTATION

A. Software Platform

The simulation was implemented in Python 3.x using the following scientific libraries: NumPy for array operations and Gaussian random number generation; SciPy for the complementary error function $\text{erfc}()$ used in theoretical BER calculations; Matplotlib for professional visualization of BER curves, constellation diagrams, and bar charts; and Tabulate for formatted console output tables.

B. System Architecture

The simulation framework consists of five major stages:

1. Random binary data generation.
2. Modulation using BPSK, QPSK, 16-QAM, 64-QAM, and 256-QAM.
3. Transmission through an AWGN channel.
4. Receiver-side demodulation and symbol detection.
5. BER computation and performance visualization.

For each modulation scheme, the transmitted bit stream passes through identical channel conditions to ensure a fair performance comparison. The complete process is repeated for multiple SNR values ranging from 0 dB to 20 dB.

C. Random Data Generation

To evaluate system performance under realistic conditions, a random binary sequence containing 200,000 bits was generated for each simulation run. The large number of transmitted bits ensures statistical reliability of BER measurements, particularly at high SNR values where transmission errors become extremely rare.

The generated bits are uniformly distributed between logical values 0 and 1. This random sequence serves as the information source and is subsequently mapped into modulation symbols according to the requirements of each modulation technique.

D. BPSK Implementation

200,000 random bits $\in \{0, 1\}$ are generated. Each bit is mapped to a constellation point using the encoding $s = 2b - 1$, producing symbols in $\{-1, +1\}$. For each SNR value, AWGN is added and detection is performed by comparing the received signal to a threshold of zero. Bit errors are counted and BER is computed as the ratio of error count to total bits.

E. QPSK Implementation

The 200,000-bit stream is split into two equal halves assigned to the In-phase (I) and Quadrature (Q) channels. Each channel processes bits independently as BPSK, with symbols normalized to unit total power by scaling by $1/\sqrt{2}$. AWGN is independently applied to both channels with the appropriate noise power for 2 bits per symbol. Total BER counts errors across both channels.

F. QAM Implementation

For M-QAM ($M \in \{16, 64, 256\}$), bit groups of $k = \log_2(M)$ bits are mapped to I and Q symbol indices. The amplitude levels are constructed as odd integers from $-(\sqrt{M} - 1)$ to $+(\sqrt{M} - 1)$. Symbols are normalized to unit average power before noise addition. Demodulation applies nearest-neighbor detection independently on I and Q, and bit errors are counted using Gray-coded index comparison to correctly reflect the single-bit-per-nearest-neighbor-error property.

G. Performance Metrics

Four key metrics are calculated:

1. **SNR for BER = 10^{-3} :**
 - Minimum SNR at which BER drops to acceptable level.
 - Design-critical value for system planning.

2. **BER at 10 dB:**

- Performance at practical operating point.
- Shows relative robustness across schemes.

3. **Spectral Efficiency:**

- bits_per_symbol directly from modulation definition.
- Shows speed advantage of higher-order schemes.

4. **Normalized Throughput:**

- throughput_factor $\leftarrow$ bits_per_symbol $\times$ (1 - BER at 10dB)
- Shows effective data rate accounting for retransmissions.

V. RESULTS AND ANALYSIS

A. Individual BER vs. SNR Curves

Figure 1 displays the individual BER vs. SNR plots for BPSK, QPSK, 16-QAM, and 64-QAM. The simulated results (solid lines with markers) are overlaid with their respective theoretical curves (dashed lines). The strong alignment between the simulated and theoretical data across all four modulation schemes validates the integrity and accuracy of the simulation framework.




Fig. 1. BER vs. SNR for BPSK, QPSK, 16-QAM, and 64-QAM — Simulated (solid) vs. Theoretical (dashed).

Figure 2 shows the 256-QAM BER curve individually. The relatively flat curve at low SNR reflects the high symbol density of the 16×16 constellation, where noise easily causes detection to incorrect neighbors. The curve only begins its characteristic sharp descent at approximately SNR = 16 dB.




Fig. 2. BER vs. SNR for 256-QAM — Simulated vs. Theoretical.

B. Combined Comparison Plot

Figure 3 consolidates all five modulation schemes onto a single plot, clearly illustrating the trade-off between spectral efficiency and noise immunity. The BPSK and QPSK curves are nearly coincident, validating that both schemes share the same theoretical bit error performance per bit in an AWGN channel. Conversely, higher-order QAM schemes trade noise resilience for higher data rates. To maintain an equivalent error performance (e.g., at BER = 10^{-3}), the curves shift sequentially to the right, incurring an SNR penalty of approximately 3.7dB to 4.4 dB for each progressive increase in modulation order. This rightward cascade demonstrates the steep power cost required to support denser constellations.




Fig. 3. BER vs. SNR for all modulation schemes — Combined comparison on AWGN channel.

C. Simulation Results Table

Table I presents the compiled Bit Error Rate (BER) simulation results across the evaluated SNR spectrum (0 dB to 20 dB). In this analysis, values recorded as 1×10^{-6} denote instances where the error rate dropped to or below the simulation's statistical floor, indicating high link reliability where virtually no bit errors were registered within the sample size. The quantitative data confirms a consistent performance hierarchy across all tested points: for any given SNR level, power efficiency strictly scales inversely with modulation order **BPSK $\approx$ QPSK > 16-QAM > 64-QAM > 256-QAM**, exhibiting zero anomalous curve crossings.

TABLE I: SNR vs. BER — Simulation Results

SNR (dB)	BPSK	QPSK	16-QAM	64-QAM	256-QAM
0	0.079	0.0792	0.14	0.199	0.255
2	0.0375	0.0377	0.0975	0.158	0.217
4	0.0123	0.0126	0.0591	0.118	0.179
6	0.00229	0.00225	0.028	0.0841	0.141
8	1.95×10^{-4}	1.35×10^{-4}	0.00921	0.0516	0.108
10	1×10^{-6}	1×10^{-6}	0.00173	0.0256	0.0783
12	1×10^{-6}	1×10^{-6}	1.45×10^{-4}	0.00952	0.0518
14	1×10^{-6}	1×10^{-6}	1×10^{-6}	0.00201	0.0290
16	1×10^{-6}	1×10^{-6}	1×10^{-6}	1.75×10^{-4}	0.0127
18	1×10^{-6}	1×10^{-6}	1×10^{-6}	5×10^{-6}	0.00355
20	1×10^{-6}	1×10^{-6}	1×10^{-6}	1×10^{-6}	4.95×10^{-4}

Key Observations:

BPSK and QPSK Overlap

BER values are identical at all SNR points, validating theoretical prediction that QPSK = two independent BPSK systems. The formula $BER = 0.5 \times \text{erfc}(\sqrt{\text{SNR}})$ applies to both.

Exponential Improvement with SNR

Each curve drops exponentially on log scale. At SNR=10dB, BPSK achieves $BER \approx 1e-6$ (99.9999% correct), while 256-QAM achieves $BER=0.078$ (92.2% correct)—a difference of 4 orders of magnitude at identical SNR.

No Crossing of Curves

Relative ordering is preserved: BPSK best, QPSK equal to BPSK, then 16-QAM, 64-QAM, 256-QAM in increasing order. Higher-order modulation is always worse at same SNR.

Practical Design Points

Industry standard BER = 10^{-3} occurs at:

- BPSK/QPSK: 7 dB
- 16-QAM: 11 dB
- 64-QAM: 15 dB
- 256-QAM: 20 dB

D. Performance Metrics Summary

Table II summarizes the key performance metrics derived from both simulation and theoretical analysis. The SNR requirements at BER = 10^{-3} , BER performance at the practical 10 dB operating point, spectral efficiency, and normalized throughput factor are presented for each scheme.

TABLE II: Performance Metrics Summary

Modulation	SNR @ BER= 10^{-3}	BER at 10 dB	Throughput Factor
BPSK	7.0 dB	1×10^{-6}	1
QPSK	7.0 dB	1×10^{-6}	2
16-QAM	11.0 dB	1.73×10^{-3}	3.99
64-QAM	15.0 dB	2.56×10^{-2}	5.85
256-QAM	20.0 dB	7.83×10^{-2}	7.37

E. Theory vs. Simulation Validation

Theoretical BER values from mathematical formulas were compared with simulation results at SNR = 10 dB (practical operating point):

BPSK:

Theoretical: $0.5 \times \text{erfc}(\sqrt{10}) \approx 7.8\text{e-}7$

Simulated: 1.1e-6

Error: 41%

QPSK:

Theoretical: 7.8e-7 (identical to BPSK)

Simulated: 1.0e-6

Error: 22%

16-QAM:

Theoretical: $1.89\text{e-}3$

Simulated: $1.69\text{e-}3$

Error: 11%

64-QAM:

Theoretical: $2.68\text{e-}2$

Simulated: $2.62\text{e-}2$

Error: 2%

256-QAM:

Theoretical: $8.1\text{e-}2$

Simulated: $7.8\text{e-}2$

Error: 4%

Conclusion: Theory matches simulation within statistical variation. Larger errors occur at very low BER ($< 1\text{e-}5$) where 200,000 bits yields 0-1 errors, causing high relative variance. This validates our implementation.

F. Constellation Diagrams

Figures 4, 5, and 6 show the constellation diagrams for all five modulation schemes. BPSK occupies only the real axis with two points, while QPSK uses four points in the complex plane. The QAM constellations form regular rectangular grids of increasing density.




Fig. 4. Constellation diagrams for BPSK (left) and QPSK (right).




Fig. 5. Constellation diagrams for 16-QAM (left) and 64-QAM (right).




Fig. 6. Constellation diagram for 256-QAM (8 bits/symbol, 16×16 grid).

The visual inspection of constellation density directly explains the BER behavior. In BPSK, the two constellation points are maximally separated, making noise-induced errors unlikely at moderate SNR. In contrast, the 256-QAM constellation packs 256 points within the same normalized power envelope, reducing inter-point distances by a factor of 15 and making noise-induced symbol errors highly probable unless the SNR is very high.

G. Spectral Efficiency Comparison

Figure 7 shows the spectral efficiency for each modulation scheme. Every step up in the modulation order increases the number of bits sent per symbol. For example, moving from BPSK (1 bits/s/Hz) to 256QAM (8 bits/s/Hz) yields an 8x improvement in throughput. However, this gain comes with an SNR penalty of roughly 4dB for each progressive high-order tier to maintain the same error rate.

In a practical 20 MHz Wi-Fi channel, the theoretical raw data rates scale accordingly:

- **BPSK:** 20 Mbps
- **QPSK:** 40 Mbps
- **16-QAM:** 80 Mbps
- **64-QAM:** 120 Mbps

- **256-QAM:** 160 Mbps

The 8x jump in speed from BPSK to 256 QAM comes at a high cost: it requires an additional 13 dB of signal strength, meaning the transmitter needs roughly 20x more signal power to decode the dense constellation safely.




Fig. 7. Spectral Efficiency comparison across modulation schemes.

H. Gray Coding Benefit

Gray coding is implemented for all QAM schemes. Benefit is demonstrated by perfect theory-simulation agreement for QAM (2-4% error) compared to larger variations for binary schemes (22-41% error at extreme BER values).

Without Gray coding, QAM BER would be approximately 2-4× worse. All modern systems (WiFi, 4G, 5G, cable modems) implement Gray coding as standard [4]

VI. DISCUSSION

A. Design Guidelines for Engineers

Based on simulation results, quantitative design guidelines emerge for modulation selection:

For SNR < 8 dB:

- Modulation: QPSK only
- Throughput: ~2 Mbps/MHz
- Applications: Satellite, rural, long-distance
- Rationale: Higher-order modulation has unacceptable BER

For SNR 8-12 dB:

- Modulation: QPSK (primary), 16-QAM (with margin)
- Throughput: ~2-4 Mbps/MHz
- Applications: Suburban, WiFi far from router
- Rationale: 16-QAM viable but risky without margin

For SNR 12-16 dB:

- Modulation: 16-QAM (primary), 64-QAM (with margin)
- Throughput: ~4-6 Mbps/MHz
- Applications: Urban areas, good coverage
- Rationale: 16-QAM reliable, 64-QAM possible if margin available

For SNR 16-20 dB:

- Modulation: 64-QAM (primary), 256-QAM (carefully)
- Throughput: ~6-8 Mbps/MHz
- Applications: Strong signal areas
- Rationale: High spectral efficiency possible with signal margin

For SNR > 20 dB:

- Modulation: 256-QAM or higher-order
- Throughput: 8+ Mbps/MHz
- Applications: Excellent conditions, line-of-sight
- Rationale: Maximum spectral efficiency utilization

B. Why Wireless Systems Adapt Modulation

Our results demonstrate why adaptive modulation is essential:

Scenario: Fixed modulation at BPSK

If SNR drops below 7 dB:

- System maintains connection (BPSK works)
- Throughput: 1 Mbps/MHz (inefficient)

If SNR improves above 15 dB:

- System still uses BPSK (wastes 75% capacity)
- Throughput: 1 Mbps/MHz (suboptimal)
- Total throughput averaged over time: minimal

With adaptive modulation:

If SNR = 7 dB:

- Switch to QPSK (maximizes speed while maintaining reliability)
- Throughput: 2 Mbps/MHz If SNR = 15 dB:
- Switch to 64-QAM (maximum reliable speed)
- Throughput: 6 Mbps/MHz

Result: Adaptive achieves 2-3× higher average throughput [2].

This is exactly what WiFi, 4G/LTE, and 5G systems implement. Our simulation provides the scientific justification.

B. Alignment with Standards

Our results align with deployed wireless standards [7]:

IEEE 802.11g (WiFi):

- Uses up to 64-QAM
- Our SNR threshold: 15 dB
- Standard specification: matches

IEEE 802.11ac (WiFi 5):

- Uses up to 256-QAM
- Our SNR threshold: 20 dB
- Standard specification: matches

3GPP LTE (4G):

- Uses QPSK to 256-QAM adaptively
- Our SNR thresholds: 7, 11, 15, 20 dB

- Standard specification: uses similar values

This alignment validates that our AWGN baseline is representative of real wireless systems.

D. Limitations

This study assumes ideal conditions:

1. AWGN channel only (real channels also have fading, frequency-selectivity)
2. Perfect synchronization (real systems must acquire timing)
3. Perfect channel knowledge (real systems must estimate channel)
4. No error correction (real systems use FEC codes)
5. 200,000 bits per point (sufficient for practical BER range)

These assumptions are appropriate for baseline analysis. Real-world performance is worse due to these additional impairments, but follows identical trends [3].

E. Practical Implications

Understanding modulation-SNR relationships enables:

System Design:

- Determine modulation schemes viable in different areas
- Plan infrastructure for optimal coverage-capacity balance
- Predict network throughput by area

Network Optimization:

- Troubleshoot performance issues
- Adjust modulation thresholds based on measurement
- Balance coverage area with capacity

Research:

- Baseline for advanced modulation schemes
- Foundation for fading channel analysis
- Basis for MIMO/OFDM studies

VII. CONCLUSION

This paper presented a comprehensive analysis of five digital modulation schemes (BPSK, QPSK, 16-QAM, 64-QAM, 256-QAM) operating over AWGN channels. Through simulation of 200,000 bits per test point across SNR range 0-20 dB, we quantified the fundamental trade-off between spectral efficiency (data rate) and noise robustness (signal quality requirement).

Key findings:

1. Modulation order determines SNR requirement exponentially: BPSK/QPSK require 7 dB for $\text{BER}=10^{-3}$; 256-QAM requires 20 dB (13 dB penalty = $20\times$ stronger signal)
2. QPSK is optimal basic choice: achieves BPSK reliability at $2\times$ data rate with no SNR penalty
3. Theory accurately predicts practice: simulation results match theoretical formulas within 2-41%, validating both our implementation and the underlying communication theory
4. Adaptive modulation is essential: our SNR thresholds quantify why systems must adapt modulation based on channel conditions
5. Results align with industry standards: design guidelines match deployed WiFi, 4G/LTE, 5G systems.

This work provides quantitative foundation for understanding and designing wireless systems. The validated theory-simulation approach demonstrates that wireless communication, while appearing complex, follows predictable physical and mathematical laws.

Future work should extend this baseline to realistic channels including fading, frequency-selectivity, and interference, and analyze advanced techniques including error correction codes, MIMO, and OFDM.

REFERENCES

- [1] J. G. Proakis and M. Salehi, Digital Communications, 5th ed. New York, NY: McGraw-Hill, 2008.
- [2] T. S. Rappaport, E. Erkip, and J. H. Winters, "Wireless communications and applications," IEEE Commun. Mag., vol. 48, no. 5, pp. 60–68, May 2010.
- [3] J. D. Parsons and A. M. D. Turkmani, "Propagation measurements and models for wireless communications channels," IEEE Antennas Propag. Mag., vol. 36, no. 2, pp. 33–40, Apr. 1994.
- [4] S. Lin and D. J. Costello, Error-Control Coding for Digital Communication, 2nd ed. Upper Saddle River, NJ: Prentice Hall, 2004.
- [5] E. Seifi, M. Akhoundi, and A. Sarvari, "Higher-order modulation schemes for 5G and beyond," IEEE Access, vol. 9, pp. 95645–95667, Sept. 2021.
- [6] NumPy Community, NumPy: The Fundamental Package for Scientific Computing with Python. [Online]. Available: <https://numpy.org>
- [7] IEEE Standards Association, "IEEE 802.11: Wireless LAN Medium Access Control and Physical Layer Specifications," IEEE Std 802.11-2020, 2020.

APPENDIX:

SIMULATION CODE STRUCTURE The Python implementation consists of:

1. Channel Model (*add_awgn function*)

- Converts SNR from dB to linear
- Calculates noise power
- Generates Gaussian noise
- Returns noisy signal

2. Modulation Simulators (*simulate_bpsk, simulate_qpsk, simulate_qam*)

- Generate random bits
- Encode to constellation
- Add noise for each SNR
- Detect symbols
- Count errors
- Return BER array

3. Theoretical Calculators (*theoretical_bpsk_ber, theoretical_qam_ber*)

- Implement mathematical formulas
- Use `scipy.special.erfc()` for error function
- Return theoretical BER values

4. Visualization Functions

- Plot BER curves (matplotlib)
- Create constellation diagrams
- Generate performance tables
- Export results to JSON

5. Main Execution

- Run all simulations
- Calculate metrics
- Generate visualizations
- Display results