

CloudSync Pro — User Manual

Backup Appliance & Companion Software

Document Code: PM-CSP-001 | Version 3.2 | Atman Cloud Consultancy

1. Introduction

CloudSync Pro is a network-attached backup appliance paired with desktop and mobile companion apps. It automatically backs up files from up to 25 connected devices to local storage and, optionally, to Atman Cloud. This manual covers setup, daily operation, and troubleshooting for the CSP-200 and CSP-400 hardware models.

1.1 Box Contents

- CloudSync Pro appliance (CSP-200 or CSP-400)
- 12V power adapter
- 1x Ethernet cable (Cat 6)
- Quick start card
- Rack-mount bracket (CSP-400 only)

2. Initial Setup

2.1 Hardware Setup

Connect the appliance to your router using the supplied Ethernet cable, then connect the power adapter. The status LED will blink amber during boot (approximately 90 seconds) and turn solid green once the appliance is ready to be claimed.

2.2 Claiming the Appliance

Download the CloudSync companion app from atmancloud.com/downloads. On first launch, the app scans the local network for unclaimed appliances. Select your device, enter the 6-digit code printed on the bottom of the unit, and choose a backup schedule.

2.3 Backup Schedule Options

Schedule	Frequency	Recommended For
Continuous	Real-time, as files change	Active project folders, shared drives
Hourly	Every 60 minutes	General desktop use
Nightly	Once daily at 2:00 AM local time	Large media libraries, archives
Manual	User-triggered only	Air-gapped or bandwidth-limited setups

3. Storage & Retention

The CSP-200 ships with 4TB of usable storage (RAID 1); the CSP-400 ships with 16TB usable (RAID 5). Deleted files are retained in the Recovery Bin for 30 days before permanent removal, unless the appliance is in Legal Hold mode, in which case deleted files are retained indefinitely until Legal Hold is disabled by an administrator.

4. Troubleshooting

Symptom	Likely Cause	Fix
LED blinking red	Storage array degraded	Replace the failed drive bay indicated in the app; RAID will auto-rebuild.
LED blinking amber for >5 min	Firmware update in progress or failed	Wait 10 minutes; if unresolved, hold the reset button for 15 seconds.
Appliance not found during setup	Not on same subnet as phone/laptop	Connect setup device to the same Wi-Fi network as the appliance.
Backups stuck at 'Queued'	Companion app lost connection to appliance	Reinstall the companion app; check appliance status LED is solid green.
"Storage 95% full" warning	Retention policy holding too many old versions	Reduce version history window in Settings > Storage > Retention.

5. Warranty

CloudSync Pro hardware carries a 2-year limited warranty covering manufacturing defects. The warranty does not cover damage from power surges, physical drops, or unauthorized firmware modification. To initiate a warranty claim, contact support with your device serial number and proof of purchase date.