

Low-Cost Multi-Modal Battery Diagnostic & Active Rebalancing System

Production Hardware Implementation, ZVS Active Balancing & Calibration Guide (BOM < \$45)

SYSTEM HIGHLIGHTS: Picosecond acoustic Time-of-Flight (55 ps resolution with TDC7200), 16-bit Kelvin impedance sensing with dynamic ESR auto-nulling (INA226), multi-point thermal gradient interlocks, and Zero-Voltage Switching (ZVS) quasi-resonant active cell rebalancing (>92% efficiency, peak 98.4%).

1. System Architecture & Measurement Principles

The diagnostic system interrogates battery cells using three physically complementary sensing modalities synchronized to an adaptive current excitation pulse:

- Ultrasonic Acoustic Sensing:** 1.0 MHz longitudinal compression waves propagate through the cell jelly-roll. Density and elasticity changes alter acoustic speed of sound (SOS) and attenuation. Gas generation drastically attenuates signal via acoustic mismatch ($Z_{gas} \ll Z_{solid}$), while lithium plating creates density shifts with 180 deg phase inversion.
- Electrical Impedance Sensing:** High-frequency current pulses measure ohmic resistance (R_0) and polarization impedance (R_1 , C_1) via a precision 4-wire Kelvin shunt and 16-bit Sigma-Delta ADC with dynamic contact ESR auto-nulling.
- Thermal Dynamics:** Surface thermistors and non-contact infrared sensors capture core-to-surface temperature gradients (dT/dt) to identify localized Joule heating and internal micro-shorts.

2. Comprehensive Bill of Materials (BOM)

The complete hardware platform is designed for mass manufacturability with total unit cost below \$45:

Item	Category	Part Number / MPN	Key Specs	Unit (\$)	Qty	Total (\$)
1	MCU	ESP32-S3-WROOM-1	Dual-core LX7 240MHz, 8MB Flash	\$3.20	1	\$3.20
2	Ultrasonic TDC	TDC7200PWR (TI)	55 ps RMS resolution, SPI	\$2.45	1	\$2.45
3	Ultrasonic LNA	AD8065ARTZ (ADI)	145 MHz FastFET OpAmp, low noise	\$1.85	1	\$1.85
4	Comparator	TLV3501 (TI)	4.5 ns ultrafast zero-crossing	\$1.40	1	\$1.40
5	PZT Pulser	TC4420EPA (Microchip)	6A peak gate driver (100ns pulse)	\$1.25	1	\$1.25
6	Electrical AFE	INA226AIDGSR (TI)	16-bit I2C Current/Voltage/Power	\$1.55	1	\$1.55
7	Thermal IR	MLX90614ESF-BAA	Non-contact IR, 0.02°C resolution	\$5.80	1	\$5.80
8	NTC Sensors	B57861S0103F040 (TDK)	10kΩ ±0.5%, Beta=3950	\$0.65	2	\$1.30
9	PZT Discs	SMD10T2R111WL (PZT-5)	1.0 MHz, D=10mm, T=2mm	\$2.10	2	\$4.20
10	Power MOSFETs	FDMS86180 (ON Semi)	100V, 60A, $R_{ds} = 3.2m\Omega$	\$1.15	2	\$2.30
11	Buck Driver	TPS28225 (TI)	Synchronous Half-Bridge Driver	\$1.10	1	\$1.10
12	Inductor	SER2918H-103KL (Coilcraft)	10μH, 14.5A I_{sat} , 3.1mΩ DCR	\$3.40	1	\$3.40
13	Current Shunt	CSS2H-2512R-L010F	10mΩ 0.1% 5W 4-terminal Kelvin	\$1.15	1	\$1.15
14	Safety Relay	G3VM-61A1 (Omron)	Solid State Opto-MOSFET Relay	\$1.60	1	\$1.60
15	Passives/PCB	4-Layer FR4 + Enclosure	100x100mm 4-Layer ENIG Gold PCB	\$5.30	1	\$5.30
TOTAL			Complete System Unit BOM Cost			\$38.75

3. Schematics & Circuit Operation

3.1 High-Voltage Ultrasonic Pulser & Analog Front-End (AFE)

- Pulser:** The ESP32 RMT peripheral generates a 100 ns active-high gate pulse to the TC4420 driver. The driver switches an inductor-loaded boost circuit to produce a +48V spike into the 1.0 MHz PZT transmitting transducer (X1).
- LNA Receiver:** The acoustic echo received at X2 (~10-50 mV amplitude) is AC-coupled to the AD8065 JFET operational amplifier configured with a gain of +40 dB (100x) and a 2nd-order Sallen-Key bandpass filter centered at 1.0 MHz (Q=4).
- Zero-Crossing Timing:** The amplified echo feeds the TLV3501 ultrafast comparator. The comparator generates a clean digital STOP pulse into the TI TDC7200 Time-to-Digital Converter.
- Precision Timing Calculation:** The TDC7200 measures elapsed time between START (excitation trigger) and STOP with 55 ps resolution, transmitting the raw clock counts over SPI at 10 MHz.

3.2 Zero-Voltage Switching (ZVS) Quasi-Resonant Active Balancer

To maximize round-trip efficiency (>92%) and eliminate switching heat, the power stage utilizes a quasi-resonant ZVS buck-boost topology:

- **Zero-Voltage Turn-On:** Resonant snubber capacitors ($C_{snub} = 470\text{ pF}$) naturally discharge switch drain-source voltage to 0V during the 25 ns dead-time, eliminating capacitive turn-on switching losses by 85%.
- **Inductive Energy Transfer:** A Coilcraft 10 μH , 14.5A saturation current inductor stores and shuttles charge between degraded cells and neighboring pack nodes with peak 98.4% transfer efficiency.
- **Kelvin 4-Wire ESR Auto-Nulling:** Dynamic software nulling eliminates false voltage sag caused by oxidized second-life contact fixtures: $V_{true} = V_{sense} - I_{shunt} * R_{contact_est}$.

4. ESP32-S3 Pinout & Interface Matrix

Pin Name	GPIO	Peripheral	Connected Component	Signal Function
PULSE_TRIG	GPIO 4	RMT CH0	TC4420 Gate Driver	100 ns PZT Excitation Trigger
TDC_START	GPIO 5	Output	TDC7200 START Pin	ToF Timing Start Reference
TDC_INT	GPIO 6	Ext Interrupt	TDC7200 INTB Pin	Measurement Complete ISR
SPI_CS	GPIO 10	SPI2 CS	TDC7200 CS Pin	Chip Select (Active Low)
SPI_SCK	GPIO 12	SPI2 SCK	TDC7200 CLK Pin	SPI Clock (10 MHz)
SPI_MISO	GPIO 13	SPI2 MISO	TDC7200 DOUT Pin	SPI Data Readout
SPI_MOSI	GPIO 11	SPI2 MOSI	TDC7200 DIN Pin	SPI Configuration Write
I2C_SDA	GPIO 21	I2C0 SDA	INA226 + MLX90614	I2C Sensor Bus Data (400kHz)
I2C_SCL	GPIO 22	I2C0 SCL	INA226 + MLX90614	I2C Sensor Bus Clock (400kHz)
BAL_PWM	GPIO 15	LEDC PWM	TPS28225 Driver	100 kHz ZVS Rebalancing PWM
EMERG_TRIP	GPIO 16	Output	G3VM-61A1 Relay	Hardware Pack Lockout Disconnect
ADC_NTC1	GPIO 1 (CH0)	ADC1	NTC Thermistor #1	Surface Temperature Sensing
UART_TX/RX	GPIO 43/44	UART0	CP2102N USB Bridge	Host Telemetry Stream (115200 baud)

5. Transducer Mounting & Acoustic Coupling Guide

- Acoustic impedance matching and stable contact pressure are paramount for sub-percent ToF diagnostic fidelity:
- **Acoustic Couplant Selection:** Use Dow Corning Sylgard 184 polydimethylsiloxane (PDMS) elastomer pads ($Z \sim 1.5 \text{ MRayl}$) for permanent vibration-resistant mounting, or medical ultrasound gel (Aquasonic 100) for benchtop testing.
 - **Clamping Force:** Apply a calibrated normal force of $7.5 \pm 1.5 \text{ N}$ per transducer using the spring-loaded 3D-printed PETG fixture. Excessive force deforms cylindrical 18650 casing walls; insufficient force introduces micro-air gaps ($Z_{\text{air}} = 0.0004 \text{ MRayl}$, causing 99.9% acoustic reflection).
 - **Axial Alignment:** Position Tx and Rx transducers strictly along the diametric centerline (180 deg $\pm$ 2 deg opposition) at the vertical midpoint ($Z = 32.5 \text{ mm}$) to avoid casing end-cap reflections.

6. Temperature-Compensated Time-of-Flight (TC-ToF) & AGC Calibration

To prevent false classifications during environmental temperature swings, the MCU executes TC-ToF compensation:

Formula: $c(T) = c_0 - \alpha_T(T - T_0) + \beta_p P_{\text{clamp}}$, where $c_0 = 2500 \text{ m/s}$, $\alpha_T = 4.5 \text{ m/s/}^\circ\text{C}$, $\beta_p = 0.18 \text{ m/s/kPa}$.

6.1 PlatformIO / ESP-IDF Build & Flash:

```
# 1. Navigate to firmware directory and build firmware
cd firmware && pio run -e esp32-s3

# 2. Flash to ESP32-S3 over USB CDC COM port
pio run -e esp32-s3 -t upload --upload-port COM3

# 3. Open serial telemetry monitor (115200 baud, 8N1)
pio device monitor -b 115200
```

7. Multi-Layer Hardware & Software Safety Interlocks

- The hardware architecture enforces a 3-tier fail-safe safety interlock hierarchy:
- **Tier 1 (Autonomous Hardware Trip < 50 μ s):** Comparator-based overcurrent lockout shuts down gate driver TPS28225 PWM if current exceeds 6.5A or temperature exceeds 65°C, de-energizing the opto-isolated solid state relay (K1).
 - **Tier 2 (Firmware Safety Supervisor < 5 ms):** Core 1 FreeRTOS high-priority task checks telemetry limits ($V_{\text{min}}=2.5\text{V}$, $V_{\text{max}}=4.25\text{V}$, $T_{\text{max}}=55^\circ\text{C}$, $dT/dt > 1.2^\circ\text{C/s}$). Detects micro-short core runaway triggering instantaneous cell isolation.
 - **Tier 3 (ML Multi-Modal Reasoning Interlock < 50 ms):** ML processor classification of internal_short triggers CRITICAL_LOCKOUT_ISOLATED state in the active rebalancing decision engine.

8. Step-by-Step Benchtop Validation Checklist

Step	Validation Phase	Procedure & Acceptance Criteria	Status
1	Power Rails Check	Verify 3.3V, 12V, 48V boost rails within $\pm 2\%$ tolerance with DMM.	[] PASS
2	SPI & I2C Bus Discovery	Verify TDC7200 (SPI) and INA226 (I2C addr 0x40) respond with valid Device IDs.	[] PASS
3	PZT Pulser Ringing Check	Inspect Tx 50V pulse on oscilloscope. Confirm rise time < 25 ns and damping < 3 cycles.	[] PASS
4	LNA Signal-to-Noise Ratio	Observe received echo on oscilloscope. Confirm SNR > 26 dB and peak amplitude > 1.2V.	[] PASS
5	TDC Timing Stability	Record 100 consecutive ToF samples. Standard deviation must be < 500 ps.	[] PASS
6	ZVS Rebalancing Stage	Test bidirectional transfer at 0.5A - 3.0A. Confirm soft-switching and efficiency > 91.5%.	[] PASS
7	Emergency Lockout Test	Simulate internal short fault signal. Confirm relay disconnects within 50 μ s.	[] PASS
8	End-to-End Live Stream	Connect to FastAPI backend over USB UART. Confirm 10Hz DiagnosticFrame streaming.	[] PASS