



RTL Design Sherpa

RAPIDS Hardware Architecture Specification 0.1

September 30, 2026

Table of Contents

1 Rapids Has Index.....	19
2 Document Information.....	20
2.1 Purpose.....	20
2.2 Scope.....	20
2.3 How This Book Relates to RAPIDS Beats.....	21
2.4 Audience.....	21
2.5 Document Conventions.....	21
2.5.1 Requirement Levels.....	21
2.5.2 Signal Directions.....	21
2.5.3 Byte and Beat Terms.....	22
2.5.4 Timing Diagrams.....	22
2.6 References.....	22
3 Revision History.....	24
3.1 Change Summary.....	24
3.1.1 Version 0.2 (2026-09-30).....	24
3.1.2 Version 0.1 (2026-09-30).....	24
4 Acronyms and Definitions.....	26
4.1 Acronyms.....	26
4.2 Definitions.....	26
4.3 Signal Naming Conventions.....	27
5 Product Overview.....	28
5.1 Introduction.....	28

5.2 Target Applications.....	29
5.3 What the Byte Design Adds.....	29
5.3.1 Key Capabilities.....	30
5.4 Permanent Limitation.....	30
6 Key Features.....	31
6.1 Feature Summary.....	31
6.1.1 Multi-Channel Architecture.....	31
6.1.2 Byte-Granular Data Movement.....	31
6.1.3 Descriptor-Based Control.....	31
6.1.4 High-Performance Data Paths.....	32
6.1.5 Monitoring and Debug.....	32
6.2 Feature Details.....	33
6.2.1 SRAM Buffering.....	34
6.2.2 AXI Burst Optimization.....	34
6.2.3 Error Handling.....	34
7 System Context.....	36
7.1 Integration Overview.....	36
7.2 Interface Connections.....	38
7.2.1 Memory Interface.....	38
7.2.2 Network Interface.....	38
7.2.3 Configuration Interface.....	39
7.3 Clock and Reset.....	39
7.3.1 Clock Domains.....	39
7.3.2 Reset Requirements.....	40

8 Block Diagram.....	41
8.1 Top-Level Architecture.....	41
8.1.1 Figure 2.1: RAPIDS Block Diagram.....	41
8.2 Top-Level Integration (rapids_top).....	42
8.3 Component Summary.....	42
8.3.1 Scheduler Group Array.....	42
8.3.2 Sink Data Path.....	43
8.3.3 Source Data Path.....	43
8.4 Hierarchy.....	44
8.5 Internal Buses.....	44
9 Data Flow.....	46
9.1 Overview.....	46
9.2 Byte Placement Rules.....	46
9.2.1 Figure 2.2: Sink Byte Placement.....	47
9.3 The Packet Record.....	47
9.3.1 Figure 2.3: Packet Record Flow.....	47
9.4 Concurrent Operation.....	49
9.4.1 Deadlock Prevention.....	49
10 Channel Architecture.....	50
10.1 Multi-Channel Design.....	50
10.2 Per-Channel Resources.....	50
10.3 Shared Resources.....	51
10.4 Channel Scheduling.....	52
10.5 Channel State Machine.....	53

10.6 Channel Isolation.....	55
10.6.1 Per-Channel Error Handling.....	55
11 Interface Summary.....	57
11.1 External Interface Overview.....	57
11.2 Interface Port Summary.....	59
11.3 Clock and Reset.....	59
11.4 Interface Feature Matrix.....	59
11.5 Signal Count Summary.....	60
12 AXI4 Interface Specification.....	61
12.1 Overview.....	61
12.1.1 Byte Granularity on the Memory Side.....	61
12.2 Descriptor AXI Master.....	61
12.3 Sink AXI Master (Write).....	62
12.3.1 Purpose.....	62
12.3.2 Configuration.....	62
12.3.3 Signal List.....	62
12.3.4 WSTRB Contract.....	63
12.4 Source AXI Master (Read).....	64
12.4.1 Purpose.....	64
12.4.2 Configuration.....	64
12.4.3 Signal List.....	65
12.4.4 Read Coverage.....	65
12.5 AXI Protocol Constraints.....	66
12.5.1 Address Alignment.....	66

12.5.2 4 KB Boundary Handling.....	66
12.5.3 Response Handling.....	66
13 AXIS Interface Specification.....	68
13.1 Overview.....	68
13.1.1 Byte Semantics.....	68
13.2 Sink AXIS Slave.....	68
13.2.1 Purpose.....	68
13.2.2 Configuration.....	69
13.2.3 Signal List.....	69
13.2.4 Packet Contract.....	69
13.2.5 Descriptor-First Ordering.....	70
13.2.6 Backpressure Behavior.....	71
13.3 Source AXIS Master.....	71
13.3.1 Purpose.....	71
13.3.2 Configuration.....	71
13.3.3 Signal List.....	72
13.3.4 Egress Packet Contract.....	72
13.3.5 Timing.....	73
13.3.6 Data Availability.....	73
13.4 AXIS Protocol Notes.....	73
13.4.1 Handshake Rules.....	73
13.4.2 TLAST Semantics.....	73
13.4.3 TSTRB Usage.....	73
13.4.4 Channel Multiplexing via TID.....	74

14 APB Configuration Interface.....	75
14.1 Overview.....	75
14.2 APB Slave and Address Routing.....	75
14.2.1 APB Slave Signal List.....	76
14.2.2 Descriptor Kick-Off.....	76
14.3 Status Interface.....	77
14.3.1 Per-Channel Status Signals.....	77
14.3.2 Channel State Encoding.....	77
14.4 Configuration Registers.....	77
14.4.1 Address Range Validation.....	77
14.4.2 Configuration Registers.....	78
14.5 Programming Sequence.....	78
14.5.1 Initialization.....	78
14.5.2 Descriptor Kick-Off.....	79
15 Monitor Bus Interface.....	80
15.1 Overview.....	80
15.2 MonBus Packet Format.....	80
15.2.1 64-bit Packet Structure.....	80
15.2.2 Signal List.....	80
15.3 Packet Types.....	81
15.4 Agent IDs.....	81
15.5 Event Codes.....	82
15.5.1 Scheduler Events (Agent 0x30-0x37).....	82
15.5.2 Descriptor Engine Events (Agent 0x10-0x17).....	82

15.6 Event Data Encoding.....	83
15.6.1 Completion Event Data.....	83
15.6.2 Error Event Data.....	83
15.6.3 State Transition Event Data.....	83
15.7 MonBus Arbitration.....	83
15.7.1 Arbitration Policy.....	84
15.8 Top-Level MonBus Delivery (monbus_axil4_axil4_group).....	84
15.9 Integration Notes.....	85
15.9.1 Downstream Connection.....	85
15.9.2 Packet Rate.....	85
16 Use Case: Network-to-Memory Transfer.....	87
16.1 Scenario.....	87
16.2 Sequence.....	87
16.2.1 Ordering Rule.....	88
16.3 Worked Example 1: 77 Bytes at Offset 5.....	88
16.4 Worked Example 2: 4035 Bytes Crossing a 4 KB Boundary.....	89
16.5 Errors.....	90
16.6 Related Chapters.....	90
17 Use Case: Memory-to-Network Transfer.....	91
17.1 Scenario.....	91
17.2 Sequence.....	91
17.3 Worked Example 1: 77 Bytes at Offset 5.....	92
17.4 Worked Example 2: 4035 Bytes Crossing a 4 KB Boundary.....	93
17.5 Errors.....	93

17.6 Related Chapters.....	93
18 Use Case: Descriptor Chaining.....	94
18.1 Overview.....	94
18.2 Descriptor Fields for Chaining.....	96
18.2.1 Relevant Fields.....	96
18.2.2 Chain Termination.....	96
18.3 Prefetch Optimization.....	98
18.3.1 Descriptor Prefetching.....	98
18.4 Multi-Channel Chaining.....	98
18.5 Error During Chain.....	98
18.5.1 Error Handling.....	98
18.5.2 Recovery.....	99
19 Use Case: Multi-Channel Operation.....	100
19.1 Overview.....	100
19.2 Resource Arbitration.....	100
19.2.1 Descriptor Port Arbitration.....	100
19.2.2 Sink/Source Arbitration.....	101
19.3 Channel Isolation.....	101
19.3.1 Error Isolation.....	101
19.3.2 Per-Channel Soft Reset.....	102
19.4 Use Case Examples.....	102
19.4.1 Mixed Traffic Pattern.....	102
19.4.2 Bidirectional Transfer.....	103
19.4.3 Load Balancing.....	103

19.5 Performance Considerations.....	104
19.5.1 Bandwidth Sharing.....	104
19.5.2 Latency Impact.....	104
19.6 MonBus Events.....	104
20 Descriptor Format.....	106
20.1 Overview.....	106
20.2 Descriptor Layout.....	106
20.2.1 256-Bit Structure.....	106
20.3 Field Descriptions.....	107
20.3.1 Control Bits [195:192].....	107
20.3.2 Direction.....	107
20.3.3 Transfer Length [159:128].....	107
20.3.4 Next Pointer [191:160].....	107
20.3.5 Address Fields [127:0].....	108
20.4 Alignment and Offsets.....	108
20.4.1 How the offset reaches the bus.....	109
20.4.2 4 KB boundaries.....	109
20.4.3 Zero-length descriptors.....	109
20.4.4 Packet record.....	110
20.5 Descriptor Opcodes (DATA / CTRL_READ / CTRL_WRITE).....	110
20.6 Extended Descriptors (row/col-major addressing).....	111
20.6.1 EXT descriptors stay beat-aligned (permanent limitation).....	111
20.7 Descriptor Fetch.....	112
20.8 Alignment Requirements.....	112

20.9 What Changed from RAPIDS Beats.....	113
20.10 Descriptor Examples.....	114
20.10.1 Sink Descriptor (Network to Memory).....	114
20.10.2 Source Descriptor (Memory to Network).....	114
20.11 Software Construction.....	114
20.11.1 C Structure Example.....	114
20.11.2 Descriptor Ring Setup.....	115
21 Register Map.....	117
21.1 Overview.....	117
21.2 Address Space Layout.....	117
21.3 Base Registers (0x100-0x3FF).....	118
21.4 Monitor Registers (+0x800 within each half).....	119
21.5 Key Register Fields.....	120
21.5.1 GLOBAL_CTRL (0x100) - Read/Write.....	120
21.5.2 SCHED_TIMEOUT_LIMIT (0x208) - Read/Write.....	121
21.5.3 DESCENG_CONFIG (0x220) - Read/Write.....	121
21.6 Channel Kick Sequence.....	122
21.7 Address Decoding.....	122
22 Initialization Sequence.....	124
22.1 Overview.....	124
22.2 Detailed Steps.....	126
22.2.1 Step 1: Verify Hardware Presence.....	126
22.2.2 Step 2: Read Configuration.....	126
22.2.3 Step 3: Global Reset.....	126

22.2.4 Step 4: Allocate Resources.....	126
22.2.5 Step 5: Initialize Descriptors.....	127
22.2.6 Step 6: Configure Channels.....	127
22.2.7 Step 7: Enable Interrupts.....	127
22.2.8 Step 8: Enable Channel.....	128
22.3 Starting Transfers.....	128
22.3.1 Kick a Channel.....	128
22.4 Interrupt Handling.....	129
22.4.1 Completion Interrupt.....	129
22.5 Reset and Recovery.....	129
22.5.1 Per-Channel Reset.....	129
22.5.2 Global Reset.....	130
23 Error Handling.....	131
23.1 Overview.....	131
23.2 Error Classes.....	131
23.3 The Byte-Granular Error: Packet Length Mismatch.....	134
23.3.1 Contract.....	134
23.3.2 Exposure.....	134
23.3.3 How it Clears.....	135
23.3.4 Prevention.....	135
23.4 Shared Error Classes.....	135
23.4.1 Invalid or Unfetchable Descriptor.....	135
23.4.2 Data-Path AXI Errors.....	135
23.4.3 Control Engine Errors.....	135

23.4.4 Write-Progress Timeout.....	136
23.5 Not Errors.....	136
23.5.1 Packet Record Queue Full.....	136
23.5.2 Sink Beat With No Packet Record.....	136
23.5.3 The 4 KB Burst Cap.....	137
23.6 Error Reporting.....	137
23.6.1 Registers.....	137
23.6.2 MonBus.....	138
23.7 Recovery.....	138
23.7.1 Channel Reset.....	138
23.7.2 What the Reset Does to Work in Flight.....	139
23.8 Software Checklist.....	141
23.9 Related Chapters.....	141
24 Throughput.....	143
24.1 Theoretical Maximum.....	143
24.2 Byte Efficiency.....	143
24.2.1 4 KB Boundaries.....	144
24.2.2 Head-of-Line Delay on the Sink Stream.....	144
24.3 Measured Results.....	145
24.3.1 Byte Campaign (Correctness).....	145
24.3.2 RAPIDS Beats Performance Report.....	146
24.3.3 Using the Beats Numbers.....	147
24.4 Throughput Limiting Factors.....	147
24.5 Related Chapters.....	148

25 Latency Characteristics.....	150
25.1 Latency Components.....	150
25.1.1 Kick-to-First-Beat Breakdown.....	150
25.1.2 Total Latency Formula.....	151
25.2 First-Beat Latency.....	151
25.3 Control-Descriptor Latency.....	151
25.4 Latency Variability.....	152
25.4.1 Sources of Variability.....	152
25.4.2 Worst-Case Latency.....	152
25.5 Latency Optimization.....	152
25.5.1 Software Recommendations.....	152
25.5.2 Hardware Configuration.....	152
26 Resource Estimates.....	154
26.1 Build Configuration.....	154
26.2 FPGA Resource Summary.....	154
26.3 Timing.....	155
26.4 Board Result.....	156
26.5 Comparison with the Beats Build.....	156
26.6 What Depends on What.....	156
26.7 Related Chapters.....	157

List of Figures

Figure 2.1: RAPIDS Block Diagram.....	41
Figure 2.2: Sink Byte Placement.....	47
Figure 2.3: Packet Record Flow.....	47

List of Tables

Table 1: Target Audience.....	21
Table 2: Byte and Beat Terms.....	22
Table 3: Reference Documents.....	22
Table 4: Document Revision History.....	24
Table 5: Acronym Definitions.....	26
Table 6: Term Definitions.....	26
Table 7: Signal Naming Conventions.....	27
Table 8: Target Applications.....	28
Table 9: Byte Design Additions.....	29
Table 10: Data Path Summary.....	32
Table 11: SRAM Buffer Parameters.....	34
Table 12: AXI Optimization Features.....	34
Table 13: Error Handling Summary.....	34
Table 14: AXI Memory Interface Requirements.....	38
Table 15: AXIS Network Interface.....	38
Table 16: Configuration Methods.....	39
Table 17: Clock Domains.....	39
Table 18: Reset Signals.....	40
Table 19: Scheduler Array Components.....	43
Table 20: Sink Path Components.....	43
Table 21: Source Path Components.....	44
Table 22: Internal Bus Summary.....	44
Table 23: Byte Placement Rules.....	46
Table 24: Resource Isolation.....	49
Table 25: Per-Channel Resources.....	50
Table 26: Shared Resources.....	51
Table 27: Channel Isolation Features.....	55
Table 28: External Interface Summary.....	59
Table 29: Clock and Reset Signals.....	59
Table 30: Interface Feature Matrix.....	59
Table 31: Signal Count Summary.....	60
Table 32: Where byte granularity is carried on AXI4.....	61
Table 33: Sink AXI Configuration.....	62
Table 34: Sink AXI Signals.....	62
Table 35:WSTRB per beat.....	63
Table 36: Source AXI Configuration.....	64

Table 37: Source AXI Signals.....	65
Table 38: Address Alignment Requirements.....	66
Table 39: AXI Response Handling.....	66
Table 40: Byte Semantics of the RAPIDS Streams.....	68
Table 41: Sink AXIS Configuration.....	69
Table 42: Sink AXIS Signals.....	69
Table 43: Reasons the Sink Deasserts TREADY.....	71
Table 44: Source AXIS Configuration.....	71
Table 45: Source AXIS Signals.....	72
Table 46: Egress Packet Contract.....	72
Table 47: TLAST Usage.....	73
Table 48: TSTRB Examples.....	73
Table 49: APB Address Routing.....	75
Table 50: APB Slave Signals.....	76
Table 51: Status Signals.....	77
Table 52: Scheduler State Encoding.....	77
Table 53: Key Configuration Registers.....	78
Table 54: MonBus Signals.....	80
Table 55: MonBus Packet Types.....	80
Table 56: RAPIDS Agent IDs.....	81
Table 57: Scheduler Event Codes.....	82
Table 58: Descriptor Engine Event Codes.....	82
Table 59: Top-Level MonBus AXI-Lite Group.....	85
Table 60: MonBus Packet Rates.....	85
Table 61: Network-to-Memory Sequence.....	87
Table 62: Example 1 Quantities.....	88
Table 63: Example 1 Write Beats.....	88
Table 64: Example 2 Quantities.....	89
Table 65: Example 2 Write Bursts.....	89
Table 66: Network-to-Memory Error Cases.....	89
Table 67: Memory-to-Network Sequence.....	91
Table 68: Example 1 Quantities.....	92
Table 69: Example 1 Egress Steps.....	92
Table 70: Example 2 Quantities.....	93
Table 71: Memory-to-Network Error Cases.....	93
Table 72: Chaining-Related Descriptor Fields.....	96
Table 73: Mixed Traffic Channel Assignment.....	102
Table 74: Bandwidth Distribution.....	104

Table 75: Arbitration Latency.....	104
Table 76: Control Bits.....	107
Table 77: Address Field Usage.....	108
Table 78: Beat Count Examples (BYTE_LANES = 32).....	108
Table 79: Descriptor Opcodes.....	110
Table 80: Address and Length Alignment.....	112
Table 81: Descriptor Differences, RAPIDS Beats to RAPIDS.....	113
Table 82: Base Registers.....	118
Table 83: Monitor Registers (+0x800 within each half; SRC at 0x0800, SNK at 0x1800).....	119
Table 84: GLOBAL_CTRL Register.....	120
Table 85: SCHED_TIMEOUT_LIMIT Register.....	121
Table 86: DESCENG_CONFIG Register.....	121
Table 87: Error Classes.....	131
Table 88: Length Mismatch Cases.....	134
Table 89: Where the Length Mismatch Appears.....	134
Table 90: Timeout Configuration.....	136
Table 91: Error Registers.....	137
Table 92: Channel Reset: Handling of In-Flight Work.....	139
Table 93: Software Checklist.....	141
Table 94: Theoretical Maximum (256-bit Build).....	143
Table 95: Beats and Efficiency for Small and Unaligned Transfers.....	144
Table 96: Sources of Measured Figures.....	145
Table 97: Byte Campaign on the Board (7 of 7 Pass).....	145
Table 98: RAPIDS Beats Build, 8 Channels at 128 KB per Channel.....	146
Table 99: RAPIDS Beats Build, Transfer Size Sweep at 8 Channels.....	146
Table 100: RAPIDS Beats Build, Channel Scaling at 4096 Beats per Channel.....	146
Table 101: RAPIDS Beats Build, Burst Length Sweep at 8 Channels and 1024 Beats	147
Table 102: Throughput Limiting Factors.....	147
Table 103: Board Build Configuration.....	152
Table 104: Post-Route Utilization, 8 Channels, 256 Bits.....	153
Table 105: Timing at 100 MHz.....	153
Table 106: Beats and Byte-Granular Builds.....	154
Table 107: Scaling Notes.....	155

1 Rapids Has Index

Generated: 2026-10-02

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

2 Document Information

Document Title: RAPIDS Hardware Architecture Specification (HAS) **Document Number:** RAPIDS-HAS-002 **Version:** 0.2 **Date:** 2026-09-30 **Status:** Draft

2.1 Purpose

This Hardware Architecture Specification (HAS) defines the external interfaces, system integration requirements, and high-level architecture of RAPIDS, the byte-granular descriptor-driven DMA engine. RAPIDS counts bytes, not beats: a descriptor names a byte length and byte addresses, the write master carries byte enables, and the AXI-Stream ports carry packed bytes with a partial last beat.

RAPIDS Beats, the beat-granular design that came first, remains in the repository and remains supported. Its specification is the RAPIDS Beats HAS. The two designs share most of their external behavior, so this document links the RAPIDS Beats chapters that apply unchanged and rewrites only the chapters where the byte-granular design differs.

2.2 Scope

This document covers:

- External interface specifications (AXI4, AXIS, APB, MonBus) as they apply to the byte-granular design
- System-level block diagrams and data flows, including the byte placement rules
- Programming model and descriptor format (length in bytes)
- Use cases and operational sequences with unaligned transfers
- Performance characteristics and constraints

This document does NOT cover:

- Internal module architecture (see the RAPIDS MAS)
- RTL implementation details (see the RAPIDS MAS)
- The RAPIDS Beats design (see the RAPIDS Beats HAS)
- Verification test plans
- Physical design constraints

2.3 How This Book Relates to RAPIDS Beats

Chapters that are identical for both designs are not copied. The index links them from the RAPIDS Beats HAS, and the table of contents marks each one “(shared with RAPIDS Beats)”. When such a chapter names a module, the byte-granular module is the same name without the `_beats` suffix, for example `rapids_top` for `rapids_beats_top`.

Where a shared chapter says a descriptor length is a number of beats, read it as a number of bytes for RAPIDS. Every chapter that carries that distinction is rewritten in this book, so a reader following the RAPIDS chapters in order will not meet the beat unit except in the comparison tables.

2.4 Audience

Target Audience

Role	Relevance
System Architect	Primary - system integration
Hardware Integration Engineer	Primary - interface connection
Software Engineer	Primary - driver development, descriptor construction
Verification Engineer	Reference - interface protocols
RTL Designer	Reference - external constraints

2.5 Document Conventions

2.5.1 Requirement Levels

Term	Meaning
SHALL	Mandatory requirement
SHOULD	Recommended but not mandatory
MAY	Optional feature

2.5.2 Signal Directions

- **Input:** Signal driven by external logic into RAPIDS
- **Output:** Signal driven by RAPIDS to external logic

2.5.3 Byte and Beat Terms

Byte and Beat Terms

Term	Meaning
Beat	One transfer on a data bus, DATA_WIDTH/8 bytes wide (BYTE_LANES)
Offset	The low $\log_2(\text{BYTE_LANES})$ bits of a byte address: the lane where a transfer starts
Packet	The bytes of one descriptor as they appear on an AXI-Stream port, delimited by TLAST
Packet record	The {bytes, offset} pair the scheduler hands each data path for one descriptor

2.5.4 Timing Diagrams

Timing diagrams use WaveDrom format with the following conventions:

- p = Positive clock edge
- 0/1 = Logic low/high
- x = Unknown/don't care
- = = Data value (with label)
- . = Previous value continues

2.6 References

Reference Documents

Document	Description
RAPIDS MAS	Micro-architecture Specification for the byte-granular design
RAPIDS Beats HAS	Architecture specification for the beat-granular design; source of every shared chapter
ARM AMBA AXI4 Specification	AXI4 protocol reference
ARM AMBA AXI-Stream Specification	AXIS protocol reference
RAPIDS PRD	Product Requirements Document

3 Revision History

Document Revision History

Version	Date	Author	Changes
0.2	2026-09-30	RTL Design Sherpa	Channel reset recovers every error class; the aresetn-only caveats are removed from Error Handling
0.1	2026-09-30	RTL Design Sherpa	Initial release: the byte-granular RAPIDS, split from the RAPIDS Beats HAS

3.1 Change Summary

3.1.1 Version 0.2 (2026-09-30)

Channel reset closes the data-path error gap

- The per-channel reset now reaches the AXI read and write engines and both byte data paths. The data read and write response errors and the sink packet length error clear on a channel reset, and the channel takes a good descriptor afterwards. Error Handling no longer tells software to use aresetn for these.
- Error Handling gains the list of what a channel reset does to work in flight, including the sink tail discard and the unterminated source packet.
- Head-of-line blocking on a shared sink stream is unchanged and stays documented.

3.1.2 Version 0.1 (2026-09-30)

Initial Release

- The byte-granular RAPIDS (rapids TASK-019) is the product design. The RAPIDS Beats design was its stepping stone and keeps its own book, the RAPIDS Beats HAS.

- New chapters where the byte design differs: Product Overview, Key Features, System Context, Block Diagram, Data Flow, AXI4 Master Interface, AXIS Interface, both use cases, Descriptor Format, Error Handling, Throughput and Resource Estimates.
- Chapters unchanged from RAPIDS Beats are linked from the RAPIDS Beats HAS rather than copied, so a correction there reaches both books.
- Permanent limitation recorded: TYPE=EXT (row and column striding) descriptors stay beat-aligned. Linear descriptors may start at any byte.

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

4 Acronyms and Definitions

4.1 Acronyms

Acronym Definitions

Acronym	Definition
AXI	Advanced eXtensible Interface
AXIS	AXI-Stream
APB	Advanced Peripheral Bus
DMA	Direct Memory Access
FIFO	First-In First-Out
FSM	Finite State Machine
HAS	Hardware Architecture Specification
MAS	Module Architecture Specification
MonBus	Monitor Bus
RAPIDS	Rapid AXI Programmable In-band Descriptor System
SRAM	Static Random Access Memory

4.2 Definitions

Term Definitions

Term	Definition
Beat	Single data transfer unit (512 bits = 64 bytes in default configuration)
Channel	Independent DMA context with dedicated descriptor processing
Descriptor	256-bit control structure defining a single DMA transfer
Descriptor Chain	Linked list of descriptors for multi-transfer operations
Sink Path	Data flow from network (AXIS slave) to memory

Term	Definition
	(AXI write)
Source Path	Data flow from memory (AXI read) to network (AXIS master)
Fill	Operation writing data into SRAM buffer (sink path input)
Drain	Operation reading data from SRAM buffer (source path output)

4.3 Signal Naming Conventions

Signal Naming Conventions

Prefix/Suffix	Meaning
m_axi_*	AXI Master signals
s_axis_*	AXIS Slave signals
m_axis_*	AXIS Master signals
cfg_*	Configuration signals
*_valid	Handshake valid signal
*_ready	Handshake ready signal
*_n	Active-low signal

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)


5 Product Overview

5.1 Introduction

RAPIDS is a high-performance network-to-memory accelerator for descriptor-based data movement. It bridges network interfaces (AXI-Stream) with system memory (AXI4), moving data without CPU intervention.

RAPIDS is byte-granular. A descriptor gives a length in bytes and byte addresses. The sink writes exactly the bytes the network sent, using byte enables on the AXI4 write data channel. The source emits exactly the bytes the descriptor names, packed from lane 0 of the AXI-Stream, with a partial last beat when the length is not a multiple of the bus width. A transfer may begin at any byte address.

The earlier RAPIDS Beats design moved whole beats only. It was the stepping stone to this design, it stays supported, and its specification is the RAPIDS Beats HAS.



System Context

5.2 Target Applications

Target Applications

Application	Description	Key Requirements
-------------	-------------	------------------

Network Offload	Receive packets from the network, store to memory	Low latency, arbitrary packet lengths
Scatter-Gather DMA	Multi-descriptor data movement	Descriptor chaining
Protocol Processing	Header and payload separation at byte boundaries	Any byte offset, one packet per descriptor
Streaming Accelerator	Front-end for compute engines	Continuous data flow

5.3 What the Byte Design Adds

Byte Design Additions

Capability	RAPIDS Beats	RAPIDS
Transfer unit	Full beats only	Bytes
Address alignment	Pre-aligned required	Any byte for linear descriptors
Sink write	Every lane written	Byte enables mark the bytes written
Source stream	Full beats	Packed bytes, partial last beat, TLAST per descriptor
Flow control	Backpressure-based	Backpressure-based

Flow control is unchanged: both designs rely on backpressure, and neither has credit management.

5.3.1 Key Capabilities

1. **8 Independent Channels** - Concurrent transfers with dedicated resources
2. **Byte-Granular Transfers** - Length in bytes, start at any byte address
3. **Descriptor Chaining** - Automatic next-descriptor fetch
4. **Dual Data Paths** - Simultaneous sink (write) and source (read)

5. **Monitor Integration** - Real-time event reporting via MonBus
6. **Error Detection** - AXI error propagation, and a packet-length check on the sink

5.4 Permanent Limitation

TYPE=EXT descriptors, which stride across rows and columns, stay beat-aligned by design. Their addresses SHALL be beat-aligned and their lengths SHALL be a multiple of the beat size. This is a permanent property of the design, not a phase of a schedule. Linear descriptors carry no such restriction. See the Descriptor Format chapter.

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

6 Key Features

6.1 Feature Summary

6.1.1 Multi-Channel Architecture

- **8 Independent Channels** with dedicated schedulers
- **Per-Channel State Machines** for concurrent operation
- **Shared AXI Infrastructure** with arbitrated access
- **Channel Isolation** prevents cross-channel interference

6.1.2 Byte-Granular Data Movement

- **Length in Bytes.** The descriptor length field counts bytes. A length of zero moves nothing.
- **Any Start Byte.** Source and destination byte addresses may have any offset within a beat (linear descriptors).
- **Byte Enables on the Write Master.** WSTRB is exactly the set of bytes the descriptor writes. The first beat of a transfer strobes from the start offset, the last beat strobes up to the final byte, and every beat between strobes all lanes.
- **Packed AXI-Stream.** The sink accepts packed bytes with a contiguous TSTRB on the last beat. The source emits packed bytes, contiguous TSTRB, and TLAST on the last beat of each descriptor.
- **One Packet per Descriptor.** The source ends every descriptor with TLAST. The sink expects one TLAST-delimited packet per descriptor and checks its byte count against the descriptor length.
- **Beat-Aligned Bus Traffic.** AXI addresses are beat-aligned and no burst crosses a 4 KB boundary. The byte offset never reaches an AXI address: the sink carries it in WSTRB and the source drops it at the egress.

6.1.3 Descriptor-Based Control

- **256-bit Descriptor Format** with all transfer parameters
- **Automatic Chaining** follows next_descriptor_ptr links
- **Last Descriptor Flag** terminates chain processing
- **IRQ Generation** via gen_irq descriptor flag
- **Control Descriptors** (CTRL_READ consumer gate, CTRL_WRITE producer doorbell) for in-memory producer and consumer synchronization without

moving payload. They are unchanged from RAPIDS Beats; see the Descriptor Format chapter and the shared Descriptor Chaining chapter.

6.1.4 High-Performance Data Paths


Data Path Summary

Path	Direction	Bandwidth	Features
Sink	Network to Memory	DATA_WIDTH per clock	Ingress byte shifter, SRAM buffering, AXI burst writes with byte enables
Source	Memory to Network	DATA_WIDTH per clock	AXI burst reads, SRAM buffering, egress byte re-packer

6.1.5 Monitoring and Debug

- **64-bit MonBus Packets** for all significant events
- **State Transition Reports** track FSM activity
- **Error Event Codes** for fault diagnosis
- **Performance Metrics** for throughput analysis

6.2 Feature Details



Descriptor Processing

The scheduler leaves the descriptor-fetch state only when every data path the descriptor uses has room for its packet record. A full record queue holds the channel there; it is backpressure, not an error.

6.2.1 SRAM Buffering

Each data path includes dedicated SRAM buffering:

SRAM Buffer Parameters

Parameter	Default	Description
SRAM_DEPTH	4096	Entries per data path (parameter of rapids_top)
Source entry	DATA_WIDTH bits	Data only
Sink entry	DATA_WIDTH + DATA_WIDTH/8 bits	Data plus one byte-enable bit per lane

Buffer Operation:

- **Sink Path:** Fill from AXIS through the ingress shifter, drain to the AXI write engine
- **Source Path:** Fill from the AXI read engine, drain through the egress repacker to AXIS
- **Flow Control:** Backpressure when the buffer is full or empty

6.2.2 AXI Burst Optimization

AXI Optimization Features

Feature	Implementation
Burst Length	Up to 256 beats (AXI4 maximum)
Outstanding Transactions	Configurable
Address Alignment	Beat-aligned AxADDR; the byte offset rides in WSTRB or is dropped at the egress
4KB Boundary	Every burst is capped at the boundary

6.2.3 Error Handling

Error Handling Summary

Error Type	Detection	Response
AXI SLVERR	Response check	Transfer aborted
AXI DECERR	Response check	Transfer aborted


Error Type	Detection	Response
Timeout	Watchdog timer	Recoverable error
Packet length mismatch	Sink counts strobed bytes at TLAST	Sticky per-channel write error

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

7 System Context

7.1 Integration Overview

RAPIDS integrates into a system as a DMA engine bridging network interfaces and system memory. This chapter describes the external connections and the system-level requirements that differ from RAPIDS Beats. Everything not mentioned here matches the RAPIDS Beats System Context chapter.



System Block Diagram

7.2 Interface Connections

7.2.1 Memory Interface

RAPIDS requires three AXI4 master ports connected to system memory:

AXI Memory Interface Requirements

Port	Access Pattern	Typical Bandwidth
Descriptor or AXI	Random read (256-bit)	Low (<100 MB/s)
Sink AXI	Sequential write with byte enables	High (up to interface max)
Source AXI	Sequential read	High (up to interface max)

Interconnect Requirements:

- All three ports MAY share a single physical AXI port with arbitration
- The descriptor port has the lowest bandwidth requirement
- Sink and Source ports should have balanced bandwidth allocation
- The memory system SHALL honorWSTRB on the sink write master. A slave that ignores byte enables corrupts the bytes outside a partial beat. Every AXI4-conformant slave honors them.

7.2.2 Network Interface

RAPIDS uses standard AXI-Stream for network connectivity:

AXIS Network Interface

Interface	Role	Signals
Sink AXIS	Receives data from the network	TDATA, TSTRB, TLAST, TID, TVALID, TREADY
Source AXIS	Sends data to the network	TDATA, TSTRB, TLAST, TID, TVALID, TREADY

Protocol Notes:

- Byte-granular: the byte lanes are strobed by TSTRB, and the strobed lanes of a beat SHALL be contiguous from lane 0. RAPIDS does not use TKEEP. Only the last beat of a packet may have a partial TSTRB.
- A packet is the bytes of one descriptor, delimited by TLAST. The source ends every descriptor with TLAST. The sink expects its packet to match the descriptor's byte length.
- TID selects the channel. TDEST and TUSER are available for sideband information.
- The sink holds TREADY low for a beat until the packet record of that beat's channel (TID) exists, which is after that channel's descriptor has been fetched. TREADY is one signal, so a waiting beat also holds up the beats behind it on the same stream. Software SHOULD issue a channel's descriptor before its packet arrives, or stream one channel at a time.

7.2.3 Configuration Interface

Software configures RAPIDS through register writes:

Configuration Methods

Method	Interface	Usage
Direct Write	Memory-mapped	Register configuration
Descriptor Kick	APB-style	Start descriptor processing

7.3 Clock and Reset

7.3.1 Clock Domains

Clock Domains

Clock	Frequency	Usage
aclk	100-500 MHz	All RAPIDS logic

Note: RAPIDS uses a single clock domain. Crossing into other frequency domains is handled externally.

7.3.2 Reset Requirements

Reset Signals

Signal	Type	Description
aresetn	Active-low	Async assert, sync deassert

Reset Sequence:

1. Assert aresetn low for minimum 4 clock cycles
2. Ensure all AXI interfaces are idle before reset
3. Release reset synchronously to aclk rising edge
4. Wait 16 clock cycles before initiating transfers

Reset clears every packet record, every ingress spill, and every sticky write error.


RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

8 Block Diagram

8.1 Top-Level Architecture

RAPIDS has the same block structure as RAPIDS Beats: a scheduler group array per direction, a data path per direction, and a top level that adds the registers, configuration mapping and monitoring. What the byte design adds sits at the edges of the two data paths: an ingress shifter on the sink, an egress re-packer on the source, and a packet record passed from each scheduler to its data path.

8.1.1 Figure 2.1: RAPIDS Block Diagram



RAPIDS block diagram

Source: [01_byte_block_diagram.dot](#)




Diagram 4

8.2 Top-Level Integration (rapids_top)

`rapids_core` is wrapped by `rapids_top`, which adds the software register interface, configuration mapping, and monitoring infrastructure. The integration is identical to `rapids_beats_top`: a single APB slave feeds a command/response router into the `rapids_regs` register block, `rapids_config_block` translates the register outputs into the `cfg_*` signals, and a `monbus_axil4_axil4_group` delivers the merged monitor stream to an AXI-Lite error-drain slave, an AXI-Lite capture master, and a `mon_irq` interrupt. The register map, the APB interface and the MonBus interface are shared with RAPIDS Beats; see the linked chapters.

The top-level ports have the same names as `rapids_beats_top`. The only port-level differences are the byte enables: the sink write master's `m_axi_wr_wstrb` is driven from the buffered byte enables instead of all ones, and the two AXI-Stream ports use `tstrb` as a real byte mask.

8.3 Component Summary

8.3.1 Scheduler Group Array

The scheduler group array manages 8 independent channels per direction:

Scheduler Array Components

Component	Instance Count	Purpose
scheduler	8	Transfer coordination per channel; converts bytes to beats, issues the packet record
descriptor_engine	8	Descriptor fetch and parse (unchanged from RAPIDS Beats)
Descriptor AXI Arbiter	1	Shared AXI4 for descriptor fetch

8.3.2 Sink Data Path

Network-to-memory data flow:

Sink Path Components

Component	Purpose
snk_data_path_axis	Ingress: accepts packed bytes, shifts them to offset + lane, holds the spill, flushes after TLAST, counts the packet
snk_sram_controller	Multi-channel SRAM management; each entry is data plus byte enables
axi_write_engine	AXI4 burst write generation; beat-aligned AWADDR, 4 KB cap,WSTRB from the buffer
alloc_ctrl, drain_ctrl	Space and data availability tracking (unchanged)

8.3.3 Source Data Path

Memory-to-network data flow:

Source Path Components

Component	Purpose
axi_read_engine	AXI4 burst read generation; beat-aligned ARADDR, 4 KB cap
src_sram_controller	Multi-channel SRAM management (data only)
src_data_path_axis	Egress: drops the start offset, re-packs from lane 0, sets TSTRB and TLAST
alloc_ctrl, drain_ctrl	Space and data availability tracking (unchanged)

8.4 Hierarchy

```
rapids_core
├── monbus_arbiter
├── rapids_src
│   ├── scheduler_group_array
│   │   └── scheduler_group [0..7]
│   │       ├── scheduler
│   │       ├── descriptor_engine
│   │       ├── ctrlrd_engine
│   │       └── ctrlwr_engine
│   ├── axis4_master_monlite
│   ├── src_data_path_axis
│   │   └── src_data_path
│   │       ├── axi_read_engine
│   │       └── src_sram_controller
├── rapids_snk
│   ├── scheduler_group_array (same shape)
│   ├── axis4_slave_monlite
│   ├── snk_data_path_axis
│   │   └── snk_data_path
│   │       ├── axi_write_engine
│   │       └── snk_sram_controller
```

8.5 Internal Buses

Internal Bus Summary

Bus	Width	Description
Descriptor Bus	256-bit	Parsed descriptor to scheduler

Bus	Width	Description
Scheduler Command	Variable	Beat count and byte address to the engines
Packet Record	Bytes count plus offset	One per descriptor and direction, scheduler to data path
Source SRAM Data	DATA_WIDTH	Data to and from the source SRAM
Sink SRAM Data	DATA_WIDTH + DATA_WIDTH/8	Data plus byte enables
MonBus	64-bit	Monitor packets (aggregated)

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

9 Data Flow

9.1 Overview

RAPIDS implements two independent data paths that can operate concurrently:

1. **Sink Path:** Network to Memory (AXIS Slave -> AXI Write)
2. **Source Path:** Memory to Network (AXI Read -> AXIS Master)

The flow is the RAPIDS Beats flow with three additions: a packet record that carries the byte length and offset from the scheduler to the data path, an ingress shifter on the sink, and an egress re-packer on the source.

9.2 Byte Placement Rules

A descriptor names a byte length L and a byte address A . With BYTE_LANES bytes per beat and $\text{OFF} = A \bmod \text{BYTE_LANES}$:


Byte Placement Rules

Quantity	Value
Start offset	$\text{OFF} = \text{the low } \log_2(\text{BYTE_LANES}) \text{ bits of } A$
Memory beats	$0 \text{ if } L = 0, \text{ else } \lceil (\text{OFF} + L) / \text{BYTE_LANES} \rceil$
First memory beat	address A rounded down to a beat boundary; lanes below OFF are not written (sink) or dropped (source)
Last memory beat	lanes above the final byte are not written (sink) or dropped (source)
Beats between Later addresses	all lanes carry data rounded-down address plus the beats already moved, times BYTE_LANES

The stream side is packed: a packet of L bytes occupies $\lceil L / \text{BYTE_LANES} \rceil$ stream beats, all full except possibly the last. The number of memory beats and stream beats can differ by one, because the offset shifts the boundary. The data paths absorb the difference.

9.2.1 Figure 2.2: Sink Byte Placement

Sink placement: 33 bytes to a destination at offset 31 (32-byte beats)



Sink byte placement

Source: [02_byte_placement.dot](#)


9.3 The Packet Record

For every DATA descriptor, the scheduler hands each data path it uses a record: the byte count and the start offset. The scheduler pulses the record once per descriptor and direction as it leaves the descriptor-fetch state. Each data path keeps a small per-channel queue of records (four deep). If a queue is full, the scheduler stays in descriptor fetch until there is room, so a full queue holds the channel and never drops a record. A zero-length descriptor carries no record.

The record is what lets the data path work in bytes while the engines work in beats. The sink ingress uses it to place bytes and to check the packet length. The source egress uses it to drop the offset and to set TSTRB and TLAST.


9.3.1 Figure 2.3: Packet Record Flow

Packet records: scheduler -> data path, one per DATA descriptor and direction



Packet record flow


Source: [03_packet_record_flow.dot](#)



Sink Path Data Flow

The ingress accepts a beat only when the channel's packet record exists. Until then TREADY stays low for that channel. After TLAST, if the offset pushed bytes into a further memory beat, the ingress flushes it as one more beat and holds TREADY low for that cycle.

The byte-enable timing on the write master is in the AXI4 Master Interface chapter.



Source Path Data Flow

The source always reads whole beats and lets the egress discard the bytes outside the descriptor. The first memory beat only primes the egress hold when the offset is non-zero; every later beat emits one stream beat, and a final flush emits the bytes left in the hold. The result is one AXI-Stream packet per descriptor, TLAST on its last beat.

The AXI-Stream chapter carries the waveform for a packet whose last beat is partial.

9.4 Concurrent Operation

Both data paths operate independently and can run simultaneously. Neither shares a resource with the other.

9.4.1 Deadlock Prevention

RAPIDS prevents deadlock through independent resource allocation:

Resource Isolation

Resource	Sink Path	Source Path	Shared
SRAM Buffer	Dedicated	Dedicated	No
AXI Port	Write only	Read only	No
Scheduler	Per-channel	Per-channel	No
Packet record queue	Per-channel, sink	Per-channel, source	No


The sink's TREADY is one signal, qualified by the TID of the beat on the bus. A beat for a channel whose descriptor has not been issued holds TREADY low, and it holds up any beats queued behind it on the same AXI-Stream, whatever their channel. A network source that interleaves channels on one stream SHOULD therefore issue every channel's descriptor before it streams, or present one channel at a time. The record queues and the ingress hold are per channel, so a stalled channel never corrupts another; it can only delay it.

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

10 Channel Architecture

10.1 Multi-Channel Design

RAPIDS Beats supports 8 independent DMA channels, each with dedicated resources for concurrent operation.



Channel Resource Allocation

10.2 Per-Channel Resources

Each channel has dedicated:

Per-Channel Resources

Resource	Description	Size/Capacity
Scheduler	Transfer coordination FSM	1 instance
Descriptor Engine	Descriptor fetch/parse	8-deep FIFO
Sink SRAM Unit	Sink buffer partition	SRAM_DEPTH/8 entries
Source SRAM Unit	Source buffer partition	SRAM_DEPTH/8 entries
Configuration Registers	Per-channel config	~16 registers


10.3 Shared Resources

Resources shared across all channels:

Shared Resources


Resource	Arbitration	Max Outstanding
Descriptor AXI	Round-robin	8 (1 per channel)
Sink AXI Write	Round-robin	8 configurable
Source AXI Read	Round-robin	8 configurable
MonBus Output	Priority	1 (serialized)

10.4 Channel Scheduling



Arbitration Policy

Arbitration Timing:



Waveform 1

10.5 Channel State Machine

Each channel scheduler follows this state machine:





Diagram 9



Channel State Timing

10.6 Channel Isolation


Channels are isolated to prevent interference:

Channel Isolation Features

Isolation Type	Implementation
State Isolation	Separate FSM per channel
Buffer Isolation	Partitioned SRAM per channel
Error Isolation	Per-channel error flags
Reset Isolation	Per-channel soft reset

10.6.1 Per-Channel Error Handling

Each channel maintains independent error state:



Waveform 3

Channel 1 error does not affect Channel 0 or Channel 2 operation.

11 Interface Summary

11.1 External Interface Overview

RAPIDS Beats exposes the following external interfaces:




Diagram 10

11.2 Interface Port Summary

External Interface Summary

Interface	Type	Direction	Data Width	Address Width
Descriptor AXI	AXI4 Master	Read	256-bit	64-bit
Sink AXI	AXI4 Master	Write	512-bit	64-bit
Source AXI	AXI4 Master	Read	512-bit	64-bit
Sink AXIS	AXIS Slave	Input	512-bit	-
Source AXIS	AXIS Master	Output	512-bit	-
APB Config	APB-like	Input	32-bit	12-bit
MonBus	Custom	Output	64-bit	-

11.3 Clock and Reset

All interfaces operate in the same clock domain:

Clock and Reset Signals

Signal	Type	Description
aclk	input	System clock (100-500 MHz typical)
aresetn	input	Active-low reset (async assert, sync deassert)

11.4 Interface Feature Matrix

Interface Feature Matrix

Feature	Desc AXI	Sink AXI	Src AXI	Sink AXIS	Src AXIS
Protocol	AXI4	AXI4	AXI4	AXIS	AXIS
Direction	Read	Write	Read	Slave	Master

Feature	Desc AXI	Sink AXI	Src AXI	Sink AXIS	Src AXIS
Burst Support	INCR	INCR	INCR	N/A	N/A
Max Burst	1	256	256	N/A	N/A
Outstanding	8	8	8	N/A	N/A
ID Width	8-bit	8-bit	8-bit	Optional	Optional

11.5 Signal Count Summary

Signal Count Summary

Interface	Input Signals	Output Signals	Total
Descriptor AXI	~20	~30	~50
Sink AXI	~15	~40	~55
Source AXI	~25	~25	~50
Sink AXIS	~20	~5	~25
Source AXIS	~5	~20	~25
APB Config	~15	~5	~20
MonBus	~2	~5	~7
Total	~102	~130	~232

Note: Signal counts are approximate and vary with configuration parameters.

12 AXI4 Interface Specification

12.1 Overview

RAPIDS uses AXI4 master interfaces for all memory access:

1. **Descriptor AXI** - Fetches 256-bit descriptors (read-only), one master per half (`src_m_axi_desc_*`, `snk_m_axi_desc_*`)
2. **Sink AXI** - Writes network data to memory (`m_axi_wr_*`)
3. **Source AXI** - Reads memory data for the network (`m_axi_rd_*`)
4. **Control AXI** - Single-word control reads and writes (`*_m_axi_ctrlrd_*`, `*_m_axi_ctrlwr_*`), unchanged from RAPIDS Beats

The descriptor and control masters behave exactly as in RAPIDS Beats; see [the RAPIDS Beats AXI4 chapter](#) for their timing. This chapter specifies what changed: the data masters carry byte-granular transfers.

12.1.1 Byte Granularity on the Memory Side

The descriptor length is a byte count and the source and destination addresses are byte addresses. The data masters keep AXI4 conventional by splitting the two concerns:

Where byte granularity is carried on AXI4

Concern	Where it is carried
Which beats are transferred	AxADDR (beat-aligned) and AxLEN
Which bytes within a beat are transferred	WSTRB on the write master; the egress drops unwanted bytes on the read side

AxSIZE is always the full beat ($\log_2(\text{DATA_WIDTH}/8)$), so the masters remain ordinary full-width INCR masters that any interconnect accepts.

12.2 Descriptor AXI Master

Unchanged from RAPIDS Beats. One 256-bit single-beat INCR read per descriptor, `ARLEN = 0`, `ARSIZE = 5`, `ARID` carries the channel. The source half and the sink half each own a master, and the descriptor address is 32-byte aligned. The descriptor's contents (Chapter 5) differ: its length field is in bytes.

12.3 Sink AXI Master (Write)

12.3.1 Purpose

Writes packed network bytes from the SRAM buffer to system memory. The SRAM holds each beat as data plus a strobe (`{strb, data}`), placed by the sink ingress at the byte offset of the destination address. The write master emits that strobe on WSTRB unchanged.

12.3.2 Configuration

Sink AXI Configuration

Parameter	Default	Range	Description
DATA_WIDTH	512	32-1024 (power of two)	Beat width; 32-byte beats (256-bit) in the Genesys 2 build
ADDR_WIDTH	64	Configurable	System address space
AXI_ID_WIDTH	8	Configurable	Transaction tracking (channel in low bits)
Max burst	WR_XFER_BEATS register	1-256	Per-channel burst cap, further capped at 4 KB
Outstanding	8	1-16	Concurrent AW requests

12.3.3 Signal List

Sink AXI Signals

Signal	Width	Direction	Description
m_axi_wr_awid	AXI_ID_WIDTH	output	Write ID
m_axi_wr_awaddr	ADDR_WIDTH	output	Write address, beat-aligned
m_axi_wr_awlen	8	output	Burst length - 1
m_axi_wr_awsiz	3	output	Full beat, $\log_2(\text{DATA_WIDTH}/8)$
m_axi_wr_awburst	2	output	INCR
m_axi_wr_awvalid / awready	1	output / input	Address handshake

Signal	Width	Direction	Description
m_axi_wr_wdata	DATA_WIDTH	output	Write data
m_axi_wr_wstrb	DATA_WIDTH/8	output	Byte enables: the bytes this beat writes
m_axi_wr_wlast	1	output	Last beat of the burst
m_axi_wr_wvalid/wready	1	output / input	Data handshake
m_axi_wr_bid	AXI_ID_WIDTH	input	Response ID
m_axi_wr_resp	2	input	Write response
m_axi_wr_bvalid/bready	1	input / output	Response handshake

12.3.4 WSTRB Contract


For a descriptor that writes `length` bytes starting at byte address `dst`, let `offset = dst mod (DATA_WIDTH/8)`. The transfer covers `ceil((offset + length) / (DATA_WIDTH/8))` beats.

WSTRB per beat

Beat	WSTRB
First beat	Lanes offset to the end of the beat, or to the last byte if the transfer ends inside this beat
Middle beats	All ones
Last beat	Lanes 0 to the last byte, or up to the last lane if the transfer ends on a beat boundary
Single-beat transfer	Lanes offset to <code>offset + length - 1</code>

Lanes outside the run have `WSTRB = 0` and their `WDATA` bytes are not significant. RAPIDS never writes a byte the descriptor did not name, so a destination memory that honors byte enables is left untouched outside `[dst, dst + length)`. Every beat in the transfer carries at least one strobed byte.

12.3.4.1 Waveform 3.1: Unaligned Sink Write, Byte Enables on AXI4



Byte enables on AXI4

Source: [02_axi_byte_enables.json](#)

A 33-byte transfer to $\text{base} + 31$ occupies two beats of a 32-byte-beat interface. AWADDR is base, not $\text{base} + 31$. The first beat strobes only lane 31 (0×80000000) and carries byte 0 there; the second beat strobes all 32 lanes and carries bytes 1 to 32.

12.4 Source AXI Master (Read)

12.4.1 Purpose

Reads whole beats from system memory into the SRAM buffer. The read master does not use byte enables (AXI has none on the read side). It fetches every beat that overlaps $[\text{src}, \text{src} + \text{length})$, and the source egress ([Chapter 3.2](#)) drops the leading and trailing bytes that were fetched but not requested.

12.4.2 Configuration

Source AXI Configuration

Parameter	Default	Range	Description
DATA_WIDTH	512	32-1024 (power of two)	Beat width
ADDR_WIDTH	64	Configurable	System address space

Parameter	Default	Range	Description
AXI_ID_WIDTH	8	Configurable	Transaction tracking
Max burst	RD_XFER_BEATS register	1-256	Per-channel burst cap, further capped at 4 KB
Outstanding	8	1-16	Concurrent AR requests

12.4.3 Signal List

Source AXI Signals

Signal	Width	Direction	Description
m_axi_rd_arid	AXI_ID_WIDTH	output	Read ID
m_axi_rd_addr	ADDR_WIDTH	output	Read address, beat-aligned
m_axi_rd_arlen	8	output	Burst length - 1
m_axi_rd_arsize	3	output	Full beat
m_axi_rd_arburst	2	output	INCR
m_axi_rd_arvalid/arready	1	output / input	Address handshake
m_axi_rd_rid	AXI_ID_WIDTH	input	Response ID
m_axi_rd_rdata	DATA_WIDTH	input	Read data
m_axi_rd_rsp	2	input	Read response
m_axi_rd_rlast	1	input	Last beat
m_axi_rd_rvalid/rready	1	input / output	Data handshake

12.4.4 Read Coverage

A read of length bytes from byte address `src` fetches $\text{ceil}((\text{offset} + \text{length}) / (\text{DATA_WIDTH}/8))$ beats starting at `src` rounded down to a beat boundary. Bytes fetched outside `[src, src + length)` are never delivered to the network.

12.5 AXI Protocol Constraints

12.5.1 Address Alignment

Address Alignment Requirements

Transfer Type	Alignment Requirement
Descriptor	32-byte aligned
Sink data, linear descriptor	None: any byte address
Source data, linear descriptor	None: any byte address
Sink or source data, TYPE=EXT descriptor	Beat-aligned address, beat-multiple length (permanent)

The AXI address on the wire is always beat-aligned, whatever the descriptor holds. Only EXT (row and column striding) descriptors restrict the descriptor's own addresses; that is a permanent design decision, not a phase limitation.

12.5.24 KB Boundary Handling

AXI4 forbids a burst crossing a 4 KB boundary. RAPIDS caps every burst at the next 4 KB boundary, computed from the beat-aligned address, on both data masters. The cap combines with the configured burst limit: the burst is the smaller of the two.

Example: 4035 bytes to dst = 0x0CB (32-byte beats, offset = 0x0B)
Beats total = $\text{ceil}((11 + 4035) / 32) = 127$
Aligned start = 0x0C0; beats from there to the 4 KB boundary = 122
With WR_XFER_BEATS = 16 the bursts are 16-beat, the last one before the boundary ends at 0x1000 (a 122-beat run is 7 bursts of 16 and one of 10); the remaining 5 beats start at AWADDR = 0x1000.

The first burst's WSTRB carries the offset (0xFFFFF800, lanes 11 to 31). After the first burst the working address is the aligned address plus the beats completed, so every later burst is beat-aligned.

12.5.3 Response Handling

AXI Response Handling

Response	Code	RAPIDS Behavior
OKAY	2'b00	Normal completion
EXOKAY	2'b01	Treated as OKAY
SLVERR	2'b10	Error, transfer aborted

Response	Code	RAPIDS Behavior
DECERR	2'b11	Error, transfer aborted

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

13 AXIS Interface Specification

13.1 Overview

RAPIDS uses AXI-Stream interfaces for network data transfer:

1. **Sink AXIS Slave** - Receives packed bytes from the network (ingress)
2. **Source AXIS Master** - Sends packed bytes to the network (egress)

Both streams carry **packed bytes**: a packet is a contiguous run of bytes starting at lane 0 of its first beat, with every beat full except possibly the last. The stream is byte-granular through TSTRB, and TLAST delimits exactly one descriptor's worth of data.

13.1.1 Byte Semantics

Byte Semantics of the RAPIDS Streams

Property	Rule
Byte qualifier	TSTRB (there is no TKEEP on RAPIDS)
Packing	Bytes are packed from lane 0; no gaps inside a packet
Full beats	TSTRB all ones
Last beat	TSTRB is a contiguous run from lane 0 ($2^n - 1$), n = bytes in the beat
Packet	One descriptor's length bytes, ending with TLAST

The destination address offset never appears on the stream. A descriptor that writes to byte address 5 of a beat still receives its packet packed from lane 0; the sink places the bytes at the destination offset internally ([Chapter 2](#)).

13.2 Sink AXIS Slave

13.2.1 Purpose

Receives a packet, places its bytes at the descriptor's destination offset, and writes them to the SRAM buffer for the sink AXI master.

13.2.2 Configuration

Sink AXIS Configuration

Parameter	Default	Range	Description
DATA_WIDTH	512	32-1024 (power of two)	TDATA width
AXIS_ID_WIDTH	8	1-8	TID width; TID selects the channel
AXIS_DEST_WIDTH	8	0-8	TDEST width (not used to route)
AXIS_USER_WIDTH	1	0-16	TUSER width (not used)

13.2.3 Signal List

Sink AXIS Signals

Signal	Width	Direction	Description
s_axis_tdata	DATA_WIDTH	input	Data payload
s_axis_tstrb	DATA_WIDTH/8	input	Byte qualifier, contiguous from lane 0
s_axis_tlast	1	input	Last beat of the packet
s_axis_tid	AXIS_ID_WIDTH	input	Channel select
s_axis_tdest	AXIS_DEST_WIDTH	input	Destination (accepted, not used)
s_axis_tuser	AXIS_USER_WIDTH	input	User sideband (accepted, not used)
s_axis_tvalid	1	input	Data valid
s_axis_tready	1	output	Ready to accept

13.2.4 Packet Contract

A sink packet SHALL:

1. Be delimited by TLAST, with one TID for all its beats.

2. Be packed: every beat but the last has TSTRB all ones, and the last beat's TSTRB is a contiguous run from lane 0.
3. Contain exactly as many strobed bytes as the descriptor's length for that channel.

The byte count is checked at TLAST. A packet whose count differs from the descriptor length is not silently padded or dropped: the channel's sticky `sched_wr_error` bit is set and stays set until reset.


13.2.5 Descriptor-First Ordering

The sink cannot place bytes until it knows the destination offset, and the offset comes from the channel's descriptor. `s_axis_tready` is a single signal. It is qualified by the TID of the beat currently on the bus: it is low whenever that channel has no packet record, in addition to the output register being busy or a flush beat pending.

A beat for a channel whose descriptor has not been fetched therefore stalls the whole stream, including beats for other channels queued behind it. There is no per-channel backpressure. Software **SHOULD** issue a channel's descriptor before its packet arrives, or stream one channel at a time until its descriptor is known.

This is the one flow-control difference from RAPIDS Beats, whose sink buffered beats before any descriptor existed. A transmitter that blocks its own descriptor kick behind the stalled stream will deadlock; kick first.

13.2.5.1 Waveform 3.1: Sink Packet With a Partial Last Beat



Packed stream, partial last beat

Source: [01_axis_partial_last_beat.json](#)

A 33-byte packet occupies two 32-byte beats. The first beat is full (TSTRB = FFFFFFFF); the second carries one byte (TSTRB = 00000001) and TLAST. `s_axis_tready` rises only after the channel's record exists, so TVALID waits for it.

13.2.6 Backpressure Behavior

s_axis_tready deasserts when:

Reasons the Sink Deasserts TREADY

Cause	Meaning
No record for the beat's channel	The descriptor for the TID on the bus has not been fetched; the whole stream waits
SRAM space	The channel's SRAM partition is full
Ingress output register busy	The write into the SRAM controller has not completed
Flush cycle	TREADY drops for one cycle while the spill beat that follows TLAST is emitted

The flush cycle occurs when a packet's last bytes spill into a memory beat beyond the stream's last beat: for example, 33 bytes to destination offset 5 occupy 38 bytes, so the stream's second beat maps to two memory beats.

13.3 Source AXIS Master

13.3.1 Purpose

Reads memory beats through the SRAM buffer and emits the descriptor's bytes as one packed AXIS packet.

13.3.2 Configuration

Source AXIS Configuration

Parameter	Default	Range	Description
DATA_WIDTH	512	32-1024 (power of two)	TDATA width
AXIS_ID_WIDTH	8	1-8	TID width; carries the channel
AXIS_DEST_WIDTH	8	0-8	TDEST width; carries the channel
AXIS_USER_WIDTH	1	0-16	TUSER width; driven 0

13.3.3 Signal List

Source AXIS Signals

Signal	Width	Direction	Description
m_axis_tdata	DATA_WIDTH	output	Data payload
m_axis_tstrb	DATA_WIDTH/8	output	Byte qualifier, contiguous from lane 0
m_axis_tlast	1	output	Last beat of the packet
m_axis_tid	AXIS_ID_WIDTH	output	Channel
m_axis_tdest	AXIS_DEST_WIDTH	output	Channel (zero-extended)
m_axis_tuser	AXIS_USER_WIDTH	output	Driven 0
m_axis_tvalid	1	output	Data valid
m_axis_tready	1	input	Downstream ready

13.3.4 Egress Packet Contract

Egress Packet Contract

Property	Behavior
Packet framing	One AXIS packet per descriptor, however many drain blocks it spans
Bytes	Exactly length bytes, from the descriptor's source byte address
First beat	Starts at lane 0: the egress shifts memory beats down by the source offset
Middle beats	TSTRB all ones
Last beat	Contiguous TSTRB and TLAST
Zero-length descriptor	No packet

RAPIDS Beats cut a packet at the end of each drain block and asserted TLAST on every one. RAPIDS asserts TLAST once, on the last byte of the descriptor.

13.3.5 Timing

The partial last beat is the mirror image of the sink case (Waveform 3.1 above): the final beat carries a contiguous run of n bytes and TLAST. The re-pack mechanism that produces it, including the beat that only primes the shifter, is specified in the MAS.

13.3.6 Data Availability

The source asserts TVALID only when packed data is available. The first memory beat of a packet with a nonzero source offset only primes the egress shifter and produces no output unless the entire packet fits in that beat.

13.4 AXIS Protocol Notes

13.4.1 Handshake Rules

Standard AXI-Stream handshake applies:

1. TVALID asserts when data is available
2. TREADY asserts when the receiver can accept
3. A transfer occurs on a clock edge when both are high
4. TVALID SHALL NOT depend on TREADY
5. TREADY MAY depend on TVALID

13.4.2 TLAST Semantics

TLAST Usage

Scenario	TLAST Behavior
Sink packet	Assert on the last beat of the packet; the byte count must equal the descriptor length
Source packet	Asserted once per descriptor, on its last stream beat
Continuous stream	Not supported: every transfer is a descriptor-sized packet

13.4.3 TSTRB Usage

TSTRB Examples

TSTRB Value (32-byte beat)	Meaning
FFFFFFFF	All 32 bytes valid (every beat but

TSTRB Value (32-byte beat)	Meaning
	the last)
0000FFFF	Last beat, lower 16 bytes valid
00000001	Last beat, one byte valid
Any non-contiguous pattern	Not produced by RAPIDS; not accepted on the sink

13.4.4 Channel Multiplexing via TID

Channels share each stream through TID. A sink packet SHALL keep one TID from its first beat to TLAST. Each channel is packed independently, so packets of different channels may follow one another, but `s_axis_tready` does not distinguish channels: a channel that is not ready stalls the stream for all of them (see Descriptor-First Ordering). The source stream emits one packet at a time, tagged with the channel in TID and TDEST.

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

14 APB Configuration Interface

14.1 Overview

At the top level (`rapids_beats_top`), RAPIDS Beats exposes a single **APB4 slave** (`s_apb_*`) for all software access. This interface allows software to:

1. Configure channel and monitor parameters (via the register block)
2. Initiate descriptor processing (kick-off)
3. Read status and error information

14.2 APB Slave and Address Routing

The APB slave is converted to an internal command/response transaction and routed by address to two targets:

APB Address Routing

Address Range	Target	Purpose
0x000-0x03F	rapids_regs (staged descriptor addresses)	Per-channel CH*_DESC_ADDR_{LOW ,HIGH}, stride 0x8
0x040	rapids_regs (KICK_ENABLE)	Per-channel launch bits (singlepulse)
0x100-0x3FF	rapids_regs (base regfile)	Channel/scheduler/ descriptor configuration and status
0x1000+	rapids_regs (monitor regfile)	AXI-monitor configuration and performance counters

Because the monitor regfile is located at 0x1000, the APB address bus must be at least 13 bits wide to reach it. Configuration that was formerly imagined as discrete `cfg_*` ports is now driven internally by the register block through `rapids_config_block`; see the [Register Map](#) for the full address map, and the descriptor address ranges (`DESCENG_ADDR0/1_*` at 0x224-0x230).

14.2.1 APB Slave Signal List


APB Slave Signals

Signal	Width	Direction	Description
s_apb_paddr	APB_ADDR_WI DTH (≥ 13)	input	Address
s_apb_psel	1	input	Select
s_apb_penable	1	input	Enable phase
s_apb_pwrite	1	input	Write / read
s_apb_pwdata	32	input	Write data
s_apb_pstrb	4	input	Write byte strobes
s_apb_prdata	32	output	Read data
s_apb_pready	1	output	Ready
s_apb_pslverr	1	output	Slave error

14.2.2 Descriptor Kick-Off

To start descriptor processing on a channel:

1. Write descriptor to memory
2. Assert `apb_valid[ch]` with descriptor address on `apb_addr`
3. Wait for `apb_ready[ch]` assertion
4. Deassert `apb_valid[ch]`



Timing Diagram

14.3 Status Interface

14.3.1 Per-Channel Status Signals

Status Signals

Signal	Width	Direction	Description
channel_idle	NC	output	Channel idle status
channel_error	NC	output	Channel error flag
scheduler_state	4*NC	output	FSM state per channel

14.3.2 Channel State Encoding

Scheduler State Encoding

State	Value	Description
IDLE	4'h0	Waiting for kick-off
WAIT_DESC	4'h1	Waiting for descriptor
PARSE_DESC	4'h2	Parsing descriptor
CH_XFER_DATA	4'h3	Transfer in progress
CHECK_NEXT	4'h4	Checking next descriptor
COMPLETE	4'h5	Transfer complete
ERROR	4'hF	Error state

14.4 Configuration Registers

14.4.1 Address Range Validation

RAPIDS validates descriptor addresses against configurable ranges:

Valid if:

```
(addr >= cfg_addr0_base && addr < cfg_addr0_limit) ||  
(addr >= cfg_addr1_base && addr < cfg_addr1_limit)
```

14.4.2 Configuration Registers

Configuration and status registers are provided by the `rapids_regs` register block. See the [Register Map](#) for the complete, RTL-accurate address map. The registers most relevant to bring-up are:

Key Configuration Registers

Register	Offset	Description
GLOBAL_CTRL	0x100	GLOBAL_EN, GLOBAL_RST (self-clearing)
CHANNEL_ENABLE	0x120	Per-channel enable bitmap
SCHED_TIMEOUT_CYCLES	0x200	Write-progress timeout window
SCHED_TIMEOUT_LIMIT	0x208	Consecutive-timeout escalation limit (0 = never)
DESCENG_CONFIG	0x220	Descriptor-engine enable / prefetch / FIFO threshold
DESCENG_ADDR0_BASE/ _LIMIT	0x224/0x228	Descriptor address range 0

14.5 Programming Sequence

14.5.1 Initialization

```
// 1. Optional global reset (self-clearing)
GLOBAL_CTRL = 0x2;
while (GLOBAL_CTRL & 0x2); // wait for GLOBAL_RST to clear

// 2. Configure descriptor address range(s)
DESCENG_ADDR0_BASE = 0x8000_0000;
DESCENG_ADDR0_LIMIT = 0x9000_0000;

// 3. Scheduler timeout policy
SCHED_TIMEOUT_CYCLES = 1000;
SCHED_TIMEOUT_LIMIT = 4; // escalate after 4 stalled windows; 0 = never

// 4. Enable channels and global enable
CHANNEL_ENABLE = 0xFF; // enable all 8 channels
GLOBAL_CTRL = 0x1; // GLOBAL_EN
```

14.5.2 Descriptor Kick-Off

```
// Prepare descriptor in memory
desc->src_addr = src;
desc->dst_addr = dst;
desc->length = beats;
desc->last = 1;
desc->valid = 1;

// Kick off channel 0
apb_kickoff(0, desc_addr);

// Wait for completion
while (!(channel_idle & 0x01));

// Check for errors
if (channel_error & 0x01) {
    handle_error(0);
}
```

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

15 Monitor Bus Interface

15.1 Overview

RAPIDS Beats outputs a 64-bit Monitor Bus (MonBus) for real-time event reporting. The MonBus provides visibility into:

- State machine transitions
- Descriptor processing events
- Error conditions
- Performance metrics

15.2 MonBus Packet Format

15.2.1 64-bit Packet Structure

Bit Field	Width	Description
[63:60]	4-bit	packet_type (error, completion, etc.)
[59:57]	3-bit	protocol (CORE for RAPIDS)
[56:53]	4-bit	event_code (specific event)
[52:47]	6-bit	channel_id
[46:43]	4-bit	unit_id (subsystem)
[42:35]	8-bit	agent_id (module)
[34:0]	35-bit	event_data (event-specific)

15.2.2 Signal List

MonBus Signals

Signal	Width	Direction	Description
monbus_pkt_valid	1	output	Packet valid
monbus_pkt_data	64	output	Packet data
monbus_pkt_ready	1	input	Downstream ready

15.3 Packet Types

MonBus Packet Types

Type	Code	Description
ERROR	4'h0	Error event

Type	Code	Description
COMPLETION	4'h1	Transfer/operation complete
THRESHOLD	4'h2	Threshold crossed
TIMEOUT	4'h3	Timeout event
PERF	4'h4	Performance metric
DEBUG	4'hF	Debug/trace event

15.4 Agent IDs

RAPIDS modules use the following Agent IDs:

RAPIDS Agent IDs

Agent ID	Module	Description
0x08	Descriptor AXI monitor	axi4_master_rd_monlite on the descriptor read master (per half, USE_AXI_MONITORS)
0x09	Sink-ingress AXIS monitor	axis4_slave_monlite on s_axis_* in rapids_snk_beats (USE_AXI_MONITORS; config SNK.MON.WRMON_*)
0x0A	Source-egress AXIS monitor	axis4_master_monlite on m_axis_* in rapids_src_beats (USE_AXI_MONITORS; config SRC.MON.RDMON_*)
0x10-0x17	Descriptor Engine	Channels 0-7
0x20	Control Read Engine	ctrlrd (one per half)
0x21	Control Write Engine	ctrlwr (one per half)
0x30-0x37	Scheduler	Channels 0-7

These are the values the scheduler group array and the halves pass down (DESC_AXI_MON_AGENT_ID, DESC_MON_BASE_AGENT_ID, CTRLRD_MON_AGENT_ID, CTRLWR_MON_AGENT_ID, SCHED_MON_BASE_AGENT_ID); the module defaults inside the engines differ and are overridden at instantiation. An earlier revision of this table listed data-path agents

at 0x40-0x57, which nothing emits: the data paths carry no MonBus emitters, and the AXIS ports are monitored only by the characterization harness's instruments until TASK-015 lands.

15.5 Event Codes

15.5.1 Scheduler Events (Agent 0x30-0x37)

Scheduler Event Codes


Event Code	Type	Description
0x0	COMPLETION	Descriptor complete
0x1	COMPLETION	Chain complete
0x2	ERROR	Timeout
0x3	ERROR	AXI error
0x4	DEBUG	State transition

The scheduler's and the descriptor engine's COMPLETION packets are reported only while the half's SCHED_CONFIG.COMPL_EN is set (reset value 1). With the bit clear the scheduler group drops them before its monitor-bus arbiter and still acknowledges the emitters, so a channel runs identically either way; ERROR packets are reported regardless of ERR_EN.

15.5.2 Descriptor Engine Events (Agent 0x10-0x17)

Descriptor Engine Event Codes

Event Code	Type	Description
0x0	COMPLETION	Descriptor fetched
0x1	ERROR	Address range error
0x2	ERROR	AXI read error
0x3	DEBUG	Fetch started



Timing Diagram

15.6 Event Data Encoding

15.6.1 Completion Event Data

- [34:32] - Reserved
- [31:0] - Transfer length (beats completed)

15.6.2 Error Event Data

- [34:32] - Error type
- [31:16] - Reserved
- [15:0] - Error details

15.6.3 State Transition Event Data

- [34:32] - Reserved
- [31:28] - Previous state
- [27:24] - New state
- [23:0] - Timestamp (lower bits)

15.7 MonBus Arbitration

Multiple RAPIDS modules generate MonBus packets. Internal arbitration ensures ordered delivery:




Diagram 11

15.7.1 Arbitration Policy

- Round-robin across modules
- No packet loss (backpressure if output blocked)
- Priority boosting for ERROR packets

15.8 Top-Level MonBus Delivery (`monbus_axil4_axil4_group`)

At the top level (`rapids_beats_top`), the internal MonBus is not exposed as a raw 64-bit port. Instead, when `USE_AXI_MONITORS = 1`, packets are combined and delivered through a `monbus_axil4_axil4_group`:

1. **AXI monitors:** `axi4_master_rd_monlite` and `axi4_master_wr_monlite` (`axi_monitor_lite`: error, timeout, completion, threshold and the optional address-range checker; no perf or debug class) observe the read (`m_axi_rd`) and write (`m_axi_wr`) data masters and emit monitor packets. When `USE_AXI_MONITORS = 0`, these taps are bypassed and the MonBus outputs below are tied off (`mon_irq = 0`).

2. **Arbitration:** a 3-input monbus_arbiter merges the read-monitor packet, the write-monitor packet, and the core's descriptor-monitor packet.
3. **Delivery:** the combined stream feeds monbus_axil4_axil4_group, which presents three external interfaces:

Top-Level MonBus AXI-Lite Group

Interface	Signals	Purpose
Error-drain slave	s_axil_err_ar*, s_axil_err_r* (AXI-Lite, 32-bit read)	CPU reads captured error events from the error FIFO
Capture master	m_axil_mon_aw*, m_axil_mon_w* (64-bit wdata), m_axil_mon_b*	Bulk-writes the MonBus trace to system memory
Interrupt	mon_irq	Asserts on error/threshold events

The capture region and flush behavior are configured by cfg_mon_base_addr, cfg_mon_limit_addr, and cfg_mon_flush_watermark.

15.9 Integration Notes

15.9.1 Downstream Connection

Internally, MonBus output connects to:

1. **MonBus Arbiter** - Combines core + rd/wr monitor sources
2. **monbus_axil4_axil4_group** - Error-drain slave, capture master, and mon_irq
3. **Debug FIFO** - Buffered access for debug tools

15.9.2 Packet Rate

MonBus Packet Rates

Scenario	Approximate Rate
Idle	0 packets/cycle
Single channel active	~1 packet/100 cycles
All channels active	~1 packet/20 cycles
Error storm	Up to 1 packet/cycle

16 Use Case: Network-to-Memory Transfer

16.1 Scenario

A network agent delivers a packet of L bytes on the sink AXI-Stream. RAPIDS writes exactly those bytes to system memory starting at the byte address A named by the channel's descriptor. The packet may start anywhere in a beat, and the bytes before A and after $A + L - 1$ in the boundary beats are left untouched.

The examples use a 256-bit data path (32 byte lanes, $DATA_WIDTH = 256$, the Genesys 2 configuration). Byte lanes are numbered 0 to 31.

16.2 Sequence

Network-to-Memory Sequence

Step	Actor	Action
1	Software	Builds a descriptor: destination byte address A , length L in bytes, and the channel's sink direction enabled (Descriptor Format)
2	Software	Kicks the channel so the descriptor engine fetches the descriptor
3	Scheduler	Computes the beat count and hands the sink data path a packet record: {bytes = L , offset = $A \bmod 32$ }
4	Network agent	Streams the packet on s_axis_* with $TID = channel$. $TREADY$ rises once the record exists
5	Sink ingress	Shifts each packed stream beat up by the offset and writes memory-aligned beats, with byte enables, into the channel's SRAM partition
6	Sink AXI master	Drains the SRAM as AXI4

Step	Actor	Action
		write bursts, never crossing 4 KB, with WSTRB from the stored byte enables
7	Sink ingress	At TLAST, compares the packet's byte count with L; a mismatch sets the channel's sticky write-error flag
8	Scheduler	On the last write response, completes the descriptor and reports it on the MonBus

16.2.1 Ordering Rule

Issue the descriptor before the packet arrives, or stream one channel at a time. `s_axis_tready` is one signal and it stays low for a beat whose channel has no packet record yet. Until that record exists the whole stream is held, including beats for other channels queued behind it. See [AXIS Interface](#).

16.3 Worked Example 1: 77 Bytes at Offset 5

Destination A = base + 5, where base is beat-aligned, and L = 77.

Example 1 Quantities

Quantity	Value
Offset	5
Beats written	$(5 + 77 + 31) \gg 5 = 3$
Stream beats	3: 32, 32 and 13 bytes
Last stream beat TSTRB	0x00001FFF

Example 1 Write Beats

Memory beat	Address	Lanes written	Bytes	WSTRB
0	base	5 to 31	27	0xFFFFFFE0
1	base + 32	0 to 31	32	0xFFFFFFFF
2	base + 64	0 to 17	18	0x0003FFFF

The three beats carry $27 + 32 + 18 = 77$ bytes. Stream byte 0 lands in lane 5 of the first memory beat. The five bytes that do not fit in that beat are held and join the next one, so each memory beat is assembled from two neighboring stream beats. The 13 bytes of the last stream beat plus the five held bytes fill lanes 0 to 17 of the last memory beat, so no extra flush beat is needed.

The write is one AXI4 burst of three beats at base. AxADDR is the aligned address and AxSIZE is the full 32-byte beat.

16.4 Worked Example 2: 4035 Bytes Crossing a 4 KB Boundary

Destination A = 0x0CB (byte address within a 4 KB page), L = 4035.

Example 2 Quantities

Quantity	Value
Offset	$0x0CB \bmod 32 = 11$
Aligned start	0x0C0
Beats written	$(11 + 4035 + 31) \gg 5 = 127$
Beats before the 4 KB boundary	$(0x1000 - 0x0C0) / 32 = 122$
Beats after the boundary	5
First beat WSTRB	lanes 11 to 31, 0xFFFFF800
Last beat	at 0x1080, lanes 0 to 13, WSTRB = 0x00003FFF

The 127 beats hold $21 + 125 \times 32 + 14 = 4035$ bytes. The sink write master cannot issue one 127-beat burst, because it would cross 0x1000. It splits at the boundary:

Example 2 Write Bursts

Burst	AWADDR	Beats
1	0x0C0	up to 122
2	0x1000	5

If the configured write burst limit (WR_XFER_BEATS) is below 122, burst 1 is itself split; the 4 KB cap and the configured limit are combined and the smaller wins. After the first burst the address continues from the aligned address plus the beats already written.

16.5 Errors

Network-to-Memory Error Cases

Condition	Result
Packet byte count differs from L	Channel's sticky write-error flag

Condition	Result
	is set and stays set until reset (Error Handling)
Write response is not OKAY	AXI write error is reported through the same flag
Zero-length descriptor	No record, no packet expected, nothing written

16.6 Related Chapters

- [Descriptor Chaining](#), shared with RAPIDS Beats
- [Multi-Channel Operation](#), shared with RAPIDS Beats

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

17 Use Case: Memory-to-Network Transfer

17.1 Scenario

RAPIDS reads L bytes from system memory starting at the byte address A named by the channel's descriptor and emits them on the source AXI-Stream as one packed packet. The read may start anywhere in a beat. The stream carries only the requested bytes: the first stream beat starts at lane 0 with byte A , and TLAST marks the descriptor's last byte.

The examples use a 256-bit data path (32 byte lanes, the Genesys 2 configuration).

17.2 Sequence

Memory-to-Network Sequence

Step	Actor	Action
1	Software	Builds a descriptor: source byte address A , length L in bytes, the channel's source direction enabled (Descriptor Format)
2	Software	Kicks the channel
3	Scheduler	Computes the beat count and hands the source data path a packet record: {bytes = L , offset = $A \bmod 32$ }
4	Source AXI master	Reads whole aligned beats as AXI4 read bursts, never crossing 4 KB, into the channel's SRAM partition
5	Source egress	Pops beats from the SRAM and shifts them down by the offset. The first pop only primes the shifter
6	Source egress	Emits packed stream beats with TID = TDEST = channel; the last beat carries a contiguous TSTRB and TLAST
7	Scheduler	When the packet has left,

Step	Actor	Action
		completes the descriptor and reports it on the MonBus

Unlike the sink, the source needs no ordering rule against the network: the record is created before any read data is requested, so the egress always knows the packet length.

17.3 Worked Example 1: 77 Bytes at Offset 5

Source A = base + 5 with base beat-aligned, L = 77.

Example 1 Quantities

Quantity	Value
Offset	5
Memory beats read	$(5 + 77 + 31) \gg 5 = 3$
Stream beats	3: 32, 32 and 13 bytes
Last stream beat TSTRB	0x00001FFF

The read master issues one burst of three beats at base. The egress then works as follows:

Example 1 Egress Steps

Memory beat popped	Output
M0	None. Bytes 5 to 31 are held: 27 bytes
M1	Stream beat 0: the 27 held bytes plus bytes 0 to 4 of M1, TSTRB = 0xFFFFFFFF
M2	Stream beat 1: bytes 5 to 31 of M1 plus bytes 0 to 4 of M2, TSTRB = 0xFFFFFFFF
(flush)	Stream beat 2: the remaining 13 bytes, TSTRB = 0x00001FFF, TLAST

The stream carries $32 + 32 + 13 = 77$ bytes as one packet.

17.4 Worked Example 2: 4035 Bytes Crossing a 4 KB Boundary

Source A = 0x0CB, L = 4035.

Example 2 Quantities

Quantity	Value
Offset	11
Memory beats read	127
Beats before the 4 KB boundary	122
Beats after the boundary	5
Stream beats	127: 126 full beats and a last beat of 3 bytes
Last stream beat TSTRB	0x00000007

The read master splits at 0x1000: one burst of up to 122 beats from 0x0C0 and one of 5 beats from 0x1000, further split if the configured read burst limit (RD_XFER_BEATS) is smaller. The egress removes the 11 leading bytes and delivers 4035 bytes as one packet with a single TLAST, however many drain blocks and read bursts the transfer spanned. RAPIDS Beats asserted TLAST at the end of every drain block; RAPIDS does not.

17.5 Errors

Memory-to-Network Error Cases

Condition	Result
Read response is not OKAY	Channel's read error is reported (Error Handling)
Zero-length descriptor	No record and no packet

17.6 Related Chapters


- [Descriptor Chaining](#), shared with RAPIDS Beats
- [Multi-Channel Operation](#), shared with RAPIDS Beats

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)


18 Use Case: Descriptor Chaining

18.1 Overview


Descriptor chaining enables multiple transfers to execute sequentially without software intervention. Each descriptor contains a pointer to the next descriptor, forming a linked list that RAPIDS processes automatically.



Chain Structure



Chain Execution Flow



Timing Diagram

18.2 Descriptor Fields for Chaining

18.2.1 Relevant Fields

Chaining-Related Descriptor Fields

Field	Bits	Description
next_ptr	[191:128]	64-bit pointer to next descriptor
last	[255]	Last descriptor in chain flag
irq_en	[254]	Generate interrupt on completion

18.2.2 Chain Termination

A chain terminates when ANY of these conditions is true:

1. next_ptr == 0 (null pointer)
2. last == 1 (explicit last flag)
3. Error during transfer





Diagram 14

18.3 Prefetch Optimization

18.3.1 Descriptor Prefetching

RAPIDS can prefetch the next descriptor while the current transfer executes:



Waveform 7

Benefit: Zero-cycle gap between chained transfers when prefetch completes before current transfer.

Prefetch depth is controlled by `DESCENG_CONFIG.PREFETCH_EN` and `DESCENG_CONFIG.FIFO_THRESH` (register block, offset 0x220). With prefetch disabled the descriptor engine fetches on demand (roughly one descriptor ahead of the scheduler); with prefetch enabled it buffers up to `FIFO_THRESH` descriptors ahead. A chain fetch that is throttled (output FIFO at the threshold) is deferred and reissued automatically once the FIFO drains, so no chain link is lost.

18.4 Multi-Channel Chaining

Each channel maintains independent chains:




Diagram 15

Channels execute their chains concurrently and independently.

18.5 Error During Chain

18.5.1 Error Handling

When an error occurs mid-chain:



Waveform 8

Error Response: 1. Current transfer aborts 2. Chain processing stops 3. Error status captures failing descriptor index 4. MonBus reports error event 5. Interrupt generated (if enabled)

18.5.2 Recovery


Software must: 1. Read error status to identify failing descriptor 2. Fix the issue (descriptor content, memory mapping, etc.) 3. Restart chain from failing descriptor or beginning

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)


19 Use Case: Multi-Channel Operation

19.1 Overview

RAPIDS Beats supports 8 independent DMA channels that can operate concurrently. This enables parallel data transfers for multiple network connections, priority-based scheduling, and efficient resource utilization.



Channel Independence




Concurrent Operation Timing

19.2 Resource Arbitration

19.2.1 Descriptor Port Arbitration

All channels share a single AXI port for descriptor fetches:



Waveform 10

19.2.2 Sink/Source Arbitration

Data path AXI ports use round-robin arbitration with optional priority:





Diagram 17

19.3 Channel Isolation

19.3.1 Error Isolation


Errors in one channel do not affect other channels:



Waveform 11

19.3.2 Per-Channel Soft Reset

Individual channels can be reset without affecting others:



Waveform 12

19.4 Use Case Examples

19.4.1 Mixed Traffic Pattern

Typical network application with different traffic types:

Mixed Traffic Channel Assignment

Channel	Traffic Type	Direction	Priority	Notes
0	Voice/RTP	Sink	High	Low latency required
1	Voice/RTP	Source	High	Low latency required
2	Video	Sink	Medium	High bandwidth
3	Control	Source	Medium	Small

Channel	Traffic Type	Direction	Priority	Notes
4-7	Bulk data	Both	Low	packets Background transfers

19.4.2 Bidirectional Transfer

Single network connection using paired channels:




Diagram 18

19.4.3 Load Balancing

Multiple channels processing same traffic type:




Diagram 19

19.5 Performance Considerations

19.5.1 Bandwidth Sharing

Bandwidth Distribution

Active Channels	Per-Channel BW (% of max)	Notes
1	100%	Full bandwidth available
2	~50% each	Round-robin sharing
4	~25% each	Fair distribution
8	~12.5% each	All channels active

Note: Actual distribution depends on transfer sizes and memory latency.

19.5.2 Latency Impact


Multi-channel operation adds arbitration latency:

Arbitration Latency

Scenario	Additional Latency
Single channel	0 cycles
2 channels contending	1-2 cycles
8 channels contending	Up to 7 cycles

19.6 MonBus Events

Each channel generates independent MonBus events:



Waveform 13

Events are arbitrated and serialized on the shared MonBus output.

20 Descriptor Format

20.1 Overview

RAPIDS uses 256-bit (32-byte) descriptors to define DMA transfers. Descriptors are stored in system memory and fetched by the Descriptor Engine when a channel is kicked. The layout is the layout RAPIDS Beats uses, bit for bit. What changed is the meaning of two things: the length field counts BYTES, and `src_addr` / `dst_addr` are byte addresses with no alignment requirement.

A descriptor therefore describes a transfer the way software thinks of it. A packet of 37 bytes at address 0x1007 is a descriptor with `length = 37` and `dst_addr = 0x1007`. The hardware turns that into beats, byte enables and a partial last beat; software never does the arithmetic.

20.2 Descriptor Layout

20.2.1 256-Bit Structure

Bit Range	Field Name	Width	Description
—			
[255:213]	reserved	43	Reserved (write 0)
[212:210]	desc_type	3	0 = LEGACY, 1 = EXTENDED (see below)
[209:208]	opcode	2	0 = DATA, 1 = CTRL_READ, 2 = CTRL_WRITE
[207:200]	priority	8	Transfer priority (informational)
[199:196]	channel_id	4	Channel ID (informational)
[195]	error	1	Error flag (written by hardware)
[194]	last	1	Last descriptor in chain
[193]	gen_irq	1	Generate interrupt on completion
[192]	valid	1	Descriptor valid flag
[191:160]	next_descriptor_ptr	32	Address of next descriptor (0 = last)
[159:128]	length	32	Transfer length in BYTES
[127:64]	dst_addr	64	Destination byte address
[63:0]	src_addr	64	Source byte address

: 256-Bit Descriptor Layout (`rapids_pkg::descriptor_t`)

The authoritative definition is `rapids_pkg::descriptor_t` in `rtl/includes/rapids_pkg.sv`. Only bits [255:0] are fetched and used. Every field position is the same as in RAPIDS Beats, so a descriptor builder needs one change: the value written to `length`.

20.3 Field Descriptions

20.3.1 Control Bits [195:192]

Control Bits

Bit	Field	Description
192	valid	Must be 1; a descriptor with valid=0 puts the channel in the error state
193	gen_irq	Set to 1 to generate a completion interrupt
194	last	Set to 1 for the last descriptor in a chain
195	error	Error flag; written by hardware, write 0

20.3.2 Direction

There is no direction field in the descriptor. Direction is a property of the **half** that owns the channel. The SOURCE half (memory to AXIS) reads from `src_addr`. The SINK half (AXIS to memory) writes to `dst_addr`. A descriptor is delivered to one half's descriptor engine by the address it was staged at, so the same layout serves both. Each half looks only at its own address, so the two offsets never have to agree.

20.3.3 Transfer Length [159:128]

- 32-bit field specifying the transfer size in BYTES.
- The length is the packet length. On the sink it is the number of bytes the AXIS packet must carry. On the source it is the number of bytes in the one AXIS packet the descriptor produces.
- A length of 0 moves nothing and carries no packet record (see Alignment and Offsets).

20.3.4 Next Pointer [191:160]

- 32-bit address of the next descriptor, zero-extended to the engine's 64-bit address width.
- A value of 0 terminates the chain, as does `last = 1`.
- Autonomous chaining also requires the address to fall inside one of the two configured descriptor address ranges.

Chain traversal is unchanged from RAPIDS Beats. See the shared Descriptor Chaining chapter.

20.3.5 Address Fields [127:0]

For SINK transfers (network to memory):

Field	Usage
dst_addr [127:64]	Memory write destination, any byte address
src_addr [63:0]	Not used (write 0)

For SOURCE transfers (memory to network):

Address Field Usage

Field	Usage
dst_addr [127:64]	Not used (write 0)
src_addr [63:0]	Memory read source, any byte address

20.4 Alignment and Offsets

Let `BYTE_LANES` be the beat size in bytes (`DATA_WIDTH / 8`, 32 for the 256-bit build) and `OFF_W` its log2 (5 for 256 bits). For a linear DATA descriptor:

```
offset      = addr[OFF_W-1:0]          (the low bits of the
byte address)
beats_total = 0                        if length == 0
              = (offset + length + BYTE_LANES - 1) >> OFF_W otherwise
```

`beats_total` is the number of whole memory beats the transfer touches. The sum is computed with a 33-bit intermediate, so a length near 4 GB does not overflow. Each half applies the formula to its own address: the source uses `src_addr`, the sink uses `dst_addr`.

Beat Count Examples (BYTE_LANES = 32)

Length (bytes)	Offset	beats_total	Useful bytes / (beats x 32)
0	any	0	no transfer
1	0	1	0.031
2	31	2	0.031
32	0	1	1.000
32	1	2	0.500
37	0	2	0.578

Length (bytes)	Offset	beats_total	Useful bytes / (beats x 32)
60	5	3	0.625
100	7	4	0.781
203	3	7	0.906

The last column is the fraction of the bus the transfer uses. A transfer that is a whole number of beats and starts on a beat boundary is 1.000. Everything else pays for the beats it touches, not the bytes it carries.

20.4.1 How the offset reaches the bus

- **AXI address.** AxADDR is always issued beat-aligned. The offset never appears in the address. Address progression inside a transfer is the aligned-down start plus a beat count times BYTE_LANES.
- **Sink writes.** The first beat'sWSTRB leaves lanes 0 to offset - 1 clear, and the last beat'sWSTRB covers only the bytes that remain. Bytes outside the packet are never written, so a sub-beat transfer does not disturb its neighbors in memory.
- **Source reads.** The read master fetches whole beats from the aligned address. The egress re-packer drops the leading offset bytes and packs the rest, so the AXIS packet starts at byte lane 0.
- **AXIS.** The stream is packed. Only the last beat is partial: TSTRB is contiguous from lane 0 and TLAST is on that beat. See the AXIS Interface chapter.

20.4.24 KB boundaries

A burst never crosses a 4 KB boundary. The engines cut a burst at the boundary, so a transfer that straddles one is issued as more than one burst. This is a protocol rule handled in hardware, not something software arranges. Example: 203 bytes at an address whose low 12 bits are 0xFC3 has offset 3 and 7 beats. The first two beats (aligned addresses 0xFC0 and 0xFE0) end at the boundary. The remaining five beats start at the next 4 KB page.

20.4.3 Zero-length descriptors

A descriptor with length = 0 moves nothing. It issues no read or write request and it carries no packet record, whatever its addresses are. It still occupies its place in the chain, so last, next_descriptor_ptr and gen_irq are honored. A zero-length DATA descriptor is therefore a legal way to report a completion event or end a chain without moving data.

20.4.4 Packet record

Every non-zero DATA descriptor produces one packet record, {bytes, offset}, for each enabled direction. The data path uses the record to place bytes on the sink or to frame the packet on the source. The record is pulsed once, when the scheduler leaves the fetch state to start the transfer.

- Each channel's record queue is PQ_DEPTH deep (4). A descriptor whose record does not fit waits. This is backpressure and not an error.
- The sink ingress does not accept the first beat of a packet until the channel's record exists. Issue the descriptor before the packet arrives, or send them concurrently.
- s_axis_tready is one signal, qualified by the tid of the beat on the bus. A beat for a channel with no record stalls the whole stream, including beats for other channels queued behind it. The per-channel record queues and ingress holds keep the data intact, so the effect is delay and not corruption. A stream that must not head-of-line block should have every channel's descriptor issued before the stream starts.

20.5 Descriptor Opcodes (DATA / CTRL_READ / CTRL_WRITE)

The 2-bit opcode selects one of three behaviors. Only DATA moves payload, and only DATA is affected by the byte-granular changes.

Descriptor Opcodes

Opcode	Value	Behavior
DATA	2'b00	Payload transfer; length in bytes, byte addresses
CTRL_READ	2'b01	Consumer gate: poll a memory location until (read & mask) == expected, then release the chain
CTRL_WRITE	2'b10	Producer doorbell: one 32-bit write to a memory location, then continue

The CTRL_READ and CTRL_WRITE field layouts are unchanged from RAPIDS Beats, and they carry no packet record. See the RAPIDS Beats descriptor chapter for the field tables and the retry limit.

20.6 Extended Descriptors (row/col-major addressing)

`desc_type = 1` (EXTENDED) selects strided, 2-D or circular addressing instead of linear accumulation. It is enabled at build time by `USE_ROW_COL_MAJOR_ADDRESSING`, which defaults to 1. An extended descriptor is 512 bits in two 256-bit chunks. Chunk 0 is the layout above with `desc_type = 1`. Chunk 1 is fetched by a second single-beat read at `descriptor_addr + 0x20`, so the two chunks must be contiguous in memory.

Chunk 1 (at `descriptor_addr + 0x20`)

Bit Range	Field Name	Width	Description
[255:192]	<code>reserved_hi</code>	64	Reserved (future 3rd dimension)
[191:188]	<code>wr_reserved</code>	4	Reserved
[187:182]	<code>wr_wrap1_log2</code>	6	Write outer wrap window, log2 (0 = off)
[181:176]	<code>wr_wrap0_log2</code>	6	Write inner wrap window, log2 (0 = off)
[175:160]	<code>wr_inner_count</code>	16	Write beats per contiguous run
[159:128]	<code>wr_stride_1</code>	32	Write outer stride, SIGNED bytes
[127:96]	<code>wr_stride_0</code>	32	Write inner stride, SIGNED bytes
[95:92]	<code>rd_reserved</code>	4	Reserved
[91:86]	<code>rd_wrap1_log2</code>	6	Read outer wrap window, log2 (0 = off)
[85:80]	<code>rd_wrap0_log2</code>	6	Read inner wrap window, log2 (0 = off)
[79:64]	<code>rd_inner_count</code>	16	Read beats per contiguous run
[63:32]	<code>rd_stride_1</code>	32	Read outer stride, SIGNED bytes
[31:0]	<code>rd_stride_0</code>	32	Read inner stride, SIGNED bytes

: Extended Descriptor Chunk 1 (`rapids_pkg::descriptor_ext_t`)

The mode selection, the address equation and the signed strides are unchanged from RAPIDS Beats. The layout is byte-compatible with STREAM's `descriptor_ext_t`.

20.6.1 EXT descriptors stay beat-aligned (permanent limitation)

TYPE=EXT is not byte-granular, and it is not going to be. This is a deliberate, permanent limitation of RAPIDS. An extended descriptor must have:

- `src_addr` and `dst_addr` aligned to `BYTE_LANES` (32 bytes for the 256-bit build).
- A length that is a multiple of `BYTE_LANES`.

Row and column striding are counted in whole beats, so a run of `inner_count` beats is `inner_count x BYTE_LANES` bytes, and the strides step between beat-aligned rows. An EXT descriptor with an unaligned address or a length that is not a beat multiple is outside the contract and is not checked. Use a linear descriptor when the transfer starts or ends mid-beat. The byte-

granular path (offsets, byte enables, partial last beat, packet records) applies to linear descriptors only.

20.7 Descriptor Fetch

Fetch is unchanged from RAPIDS Beats. The Descriptor Engine issues a single-beat AXI4 read ($arlen = 0$) at the descriptor address, and again at $+0x20$ for an EXTENDED descriptor. The parsed descriptor is handed to the scheduler, which converts length and the address to `beats_total`, the record and the address working registers as described above. The descriptor address and `next_descriptor_ptr` are 32-byte aligned; that is the only alignment rule that remains for linear descriptors.

20.8 Alignment Requirements

Address and Length Alignment

Field	Alignment	Notes
Descriptor address	32-byte	One descriptor is 32 bytes; an EXTENDED descriptor's chunk 1 is fetched at $+0x20$
<code>next_ptr</code> [191:160]	32-byte	32-bit descriptor address, zero-extended by the engine
<code>dst_addr</code> [127:64], linear	none	Any byte address
<code>src_addr</code> [63:0], linear	none	Any byte address
<code>dst_addr</code> / <code>src_addr</code> , EXT	<code>DATA_WIDTH/8</code>	Permanent: EXT is beat-aligned
length, linear	none	Any byte count; 0 moves nothing
length, EXT	multiple of <code>DATA_WIDTH/8</code>	Permanent: EXT counts whole beats

20.9 What Changed from RAPIDS Beats

Descriptor Differences, RAPIDS Beats to RAPIDS

Aspect	RAPIDS Beats	RAPIDS
Descriptor size and bit layout	256 bits	Same
length unit	beats	bytes
length = 0	Reserved	Legal: moves nothing, no record, chain continues
src_addr / dst_addr alignment (linear)	DATA_WIDTH/8	None
Beats moved	length	(offset + length + BYTE_LANES - 1) >> OFF_W
Sink write strobes	All lanes	WSTRB marks the bytes written
Source packet	Full beats	One packed packet per descriptor, partial last beat
Per-descriptor packet record	None	{bytes, offset} per enabled direction
Sink accepts a packet	Before the descriptor	After the channel's record exists
CTRL_READ / CTRL_WRITE	Defined	Unchanged
TYPE=EXT	Beat rows	Beat rows, aligned addresses and lengths (permanent)
Chaining, next_ptr, last, gen_irq	Defined	Unchanged

20.10 Descriptor Examples

20.10.1 Sink Descriptor (Network to Memory)

A 100-byte sink transfer to 0x1_0000_0007, chained to a descriptor at 0x2000, raising an interrupt on completion. The destination is 7 bytes into a beat, so `offset = 7` and `beats_total = (7 + 100 + 31) >> 5 = 4`. The first beat writes lanes 7 to 31, the last beat writes 4 bytes.

64-bit words, LSB word first:

```
[63:0]      = 0x0000_0000_0000_0000 // src_addr (unused by the SINK
half)
[127:64]    = 0x0000_0001_0000_0007 // dst_addr = 0x1_0000_0007
[191:128]   = 0x0000_2000_0000_0064 // next_ptr[191:160]=0x2000,
length[159:128]=100
[255:192]   = 0x0000_0000_0000_0003 // valid=1, gen_irq=1, last=0
```

20.10.2 Source Descriptor (Memory to Network)

A 60-byte source transfer from 0x2_0000_0005, terminating the chain. `offset = 5` and `beats_total = (5 + 60 + 31) >> 5 = 3` memory beats. The source emits one AXIS packet of two stream beats: 32 bytes, then 28 bytes with TLAST.

64-bit words, LSB word first:

```
[63:0]      = 0x0000_0002_0000_0005 // src_addr = 0x2_0000_0005
[127:64]    = 0x0000_0000_0000_0000 // dst_addr (unused by the SOURCE
half)
[191:128]   = 0x0000_0000_0000_003C // next_ptr = 0, length = 60
[255:192]   = 0x0000_0000_0000_0007 // valid=1, gen_irq=1, last=1
```

20.11 Software Construction

20.11.1 C Structure Example

```
typedef struct __attribute__((packed, aligned(32))) {
    uint64_t src_addr;      // [63:0]      source byte address
    uint64_t dst_addr;      // [127:64] destination byte address
    uint32_t length;        // [159:128] transfer length in BYTES
    uint32_t next_ptr;      // [191:160] 32-bit, 0 terminates the
chain
    uint32_t flags;         // [223:192] see macros below
    uint32_t reserved[2];   // [255:224]
} rapids_descriptor_t;
```

// flags bit positions are relative to descriptor bit 192

```
#define DESC_VALID      (1u << 0) // [192]
#define DESC_GEN_IRQ    (1u << 1) // [193]
#define DESC_LAST       (1u << 2) // [194]
#define DESC_ERROR      (1u << 3) // [195] hardware-written
```

```

#define DESC_CHANNEL_ID(n)  (((n) & 0xFu) << 4)    // [199:196]
#define DESC_PRIORITY(n)   (((n) & 0xFFu) << 8)    // [207:200]
#define DESC_OPCODE(n)     (((n) & 0x3u) << 16)    // [209:208]
#define DESC_TYPE(n)       (((n) & 0x7u) << 18)    // [212:210]

#define DESC_OP_DATA        0x0
#define DESC_OP_CTRL_READ   0x1
#define DESC_OP_CTRL_WRITE  0x2

#define DESC_TYPE_LEGACY    0x0
#define DESC_TYPE_EXT       0x1

// Beats a linear DATA descriptor touches (BYTE_LANES = 32 for 256-bit)
static inline uint32_t rapids_beats_total(uint64_t addr, uint32_t length)
{
    const uint64_t lanes = 32;
    if (length == 0)
        return 0;
    return (uint32_t)((((addr & (lanes - 1)) + length + lanes - 1) / lanes);
}

```

The helper is for software that wants to size buffers or predict burst counts. The hardware does not need it.

20.11.2 Descriptor Ring Setup

```

// Descriptor ring: descriptors must be 32-byte aligned
rapids_descriptor_t *ring = aligned_alloc(32, NUM_DESC *
sizeof(*ring));

for (int i = 0; i < NUM_DESC; i++) {
    memset(&ring[i], 0, sizeof(ring[i]));
    ring[i].dst_addr = dst[i];           // any byte address
    ring[i].length   = len[i];           // bytes
    ring[i].flags    = DESC_VALID | DESC_GEN_IRQ;
    if (i < NUM_DESC - 1) {
        ring[i].next_ptr = (uint32_t)(uintptr_t)&ring[i + 1];
    } else {
        ring[i].next_ptr = 0;             // terminates the chain
        ring[i].flags |= DESC_LAST;
    }
}

```

The descriptor buffers themselves stay 32-byte aligned. The payload addresses do not have to be.

21 Register Map

21.1 Overview

RAPIDS Beats provides a memory-mapped register interface for configuration and status. All registers are accessed through the single top-level APB slave (`s_apb_*`) and are implemented by the PeakRDL-generated `rapids_regs` register block. One addrmap holds two independent halves of the same layout (`rapids_engine_regs`): **SRC at 0x0000** and **SNK at 0x1000**, 4 KB each. Within a half, the staged descriptor addresses occupy +0x000-0x03F, the launch register KICK_ENABLE sits at +0x040, configuration and status at +0x100-0x3FF, and the nested monitor regfile (`rapids_mon_regs`) at +0x800. Every offset below is relative to its half; add 0x1000 for the SNK copy.

Because the SNK half lives at 0x1000, the APB address bus must be at least 13 bits wide; `paddr[12]` selects the half and `paddr[11]` the monitor window.

21.2 Address Space Layout

Range (per half)	Target	Purpose
+0x000-0x03F	<code>rapids_engine_regs</code>	Per-channel staged descriptor addresses
+0x040	<code>rapids_engine_regs</code>	KICK_ENABLE per-channel launch bits
+0x100-0x3FF	<code>rapids_engine_regs</code>	Configuration and status
+0x800-0x9FF	<code>rapids_mon_regs</code>	AXI-monitor config and performance
0x0000 / 0x1000	half base	SRC half / SNK half

The three `*_PKT_MASK` registers are masks: `bit[type] = 1` masks (drops) that packet type, at the monitor-lite and again at the monbus group. They reset to all-masked (0xFFFF), so nothing reaches the group until the host clears the bits of the classes it wants to see. (rapids BUG-008: the description used to read “1 = enable”; the polarity and the reset are as intended.) `*_TIMEOUT` counts MICROSECONDS in its low 16 bits.

On a build with `USE_MON_REGS = 0` (the default when `USE_AXI_MONITORS = 0`) the two monitor windows keep their addresses but answer every access with `PSLVERR` and zero read data: the config blocks drive nothing from them, and a read-back that succeeded would tell the host a monitor is configured that does not exist.

: Address Space Layout

21.3 Base Registers (0x100-0x3FF)

Base Registers

Offset	Name	Access	Description
0x100	GLOBAL_CTRL	RW	GLOBAL_EN[0], GLOBAL_RST[1] (self-clearing)
0x104	GLOBAL_STATUS	RO	SYSTEM_IDLE[0]
0x108	VERSION	RO	MINOR[7:0], MAJOR[15:8], NUM_CHANNELS[23:16]=8
0x120	CHANNEL_ENABLE	RW	CH_EN[7:0] per-channel enable
0x124	CHANNEL_RESET	RW	CH_RST[7:0] per-channel reset (self-clearing)
0x140	CHANNEL_IDLE	RO	CH_IDLE[7:0]
0x144	DESC_ENGINE_IDLE	RO	Per-channel descriptor-engine idle
0x148	SCHEDULER_IDLE	RO	Per-channel scheduler idle (excludes CH_ERROR)
0x150-0x16C	CH_STATE[0..7]	RO	Per-channel FSM state (stride 0x4)
0x170	SCHED_ERROR	RO	Per-channel sticky scheduler error
0x174	AXI_RD_COMPLETE	RO	Per-channel read-complete
0x178	AXI_WR_COMPLETE	RO	Per-channel write-complete
0x200	SCHED_TIMEOUT_CYCLES	RW	Write-progress timeout window (cycles, reset 1000)
0x204	SCHED_CONFIG	RW	SCHED_EN, TIMEOUT_EN, ERR_EN, COMPL_EN, PERF_EN
0x208	SCHED_TIMEOUT_LIMIT	RW	LIMIT[7:0] escalation limit (reset 4, 0 = never)
0x220	DESCENG_CONFIG	RW	DESCENG_EN[0],

Offset	Name	Access	Description
			PREFETCH_EN[1], FIFO_THRESH[5:2] (reset 8)
0x224	DESCENG_AD DR0_BASE	RW	Descriptor address range 0 base [31:0]
0x228	DESCENG_AD DR0_LIMIT	RW	Descriptor address range 0 limit [31:0]
0x22C	DESCENG_AD DR1_BASE	RW	Descriptor address range 1 base [31:0]
0x230	DESCENG_AD DR1_LIMIT	RW	Descriptor address range 1 limit [31:0]
0x240	CTRL_CONFI G	RW	CTRLRD_MAX_TRY[8:0] control-read poll retry budget (0-511, reset 16)
0x2A0	AXI_XFER_C ONFIG	RW	AXI transfer sizing configuration
0x2B0	PERF_CONFI G	RW	Performance profiler configuration
0x2C0-0x2CC	OBS_CTRL/ OBS_FLAGS/ OBS_DATA0/ OBS_DATA1	RW/RO	Observation mux
0x35C	PERF_CH_SE L	RW	Performance channel select
0x378-0x380	HIST_SEL/ HIST_DATA/ HIST_TOTAL	RW/RO	Latency histogram

21.4 Monitor Registers (+0x800 within each half)

Monitor Registers (+0x800 within each half; SRC at 0x0800, SNK at 0x1800)

Offset	Name	Access	Description
+0x800	MON_FIFO_S TATUS	RO	MonBus capture/error FIFO status
+0x804	MON_FIFO_C OUNT	RO	MonBus FIFO occupancy

Offset	Name	Access	Description
+0x8C0-0x8DC	DAXMON_*	RW	Descriptor-monitor config (enable/timeout/latency/masks)
+0x8E0-0x8FC	RDMON_*	RW	Source-egress AXIS monitor-lite config (same layout; live in the SRC half, rapids TASK-015)
+0x900-0x91C	WRMON_*	RW	Sink-ingress AXIS monitor-lite config (same layout; live in the SNK half, rapids TASK-015; the SRC copy's COMPRESS_EN drives the group)
+0x950-0x978	DAXMON_PERF_*	RO/RW	Descriptor-monitor performance counters
+0x980-0x9A8	RDMON_PERF_*	RO/RW	Read-monitor performance counters
+0x9B0-0x9D8	WRMON_PERF_*	RO/RW	Write-monitor performance counters
+0x9E0-0x9F4	{RD,WR}MON_PERF_CH_*	RO	Per-channel producer/backpressure/starve/idle/overflow

21.5 Key Register Fields

21.5.1 GLOBAL_CTRL (0x100) - Read/Write

GLOBAL_CTRL Register

Bits	Field	Reset	Description
[0]	GLOBAL_EN	0	Master enable for the entire engine
[1]	GLOBAL_RST	0	Global reset (self-clearing)
[31:2]	Reserved	0	Reserved

21.5.2 SCHED_TIMEOUT_LIMIT (0x208) - Read/Write


SCHED_TIMEOUT_LIMIT Register

Bits	Field	Reset	Description
[7:0]	LIMIT	4	Consecutive write-progress timeout windows before escalating to a fatal, sticky CH_ERROR. 0 = never escalate. Total escalation time $\sim$ LIMIT x SCHED_TIMEOUT_CYCLES.


21.5.3 DESCENG_CONFIG (0x220) - Read/Write

DESCENG_CONFIG Register

Bits	Field	Reset	Description
[0]	DESCENG_EN	1	Descriptor engine master enable
[1]	PREFETCH_EN	0	Prefetch chaining (0 = on-demand, $\sim$ 1 ahead)
[5:2]	FIFO_THRESH	8	Descriptors buffered ahead when prefetch enabled
[31:6]	Reserved	0	Reserved




Register Access Timing



Waveform 15

21.6 Channel Kick Sequence

Staging a channel's descriptor address, then writing that channel's bit in KICK_ENABLE, triggers descriptor processing:



Waveform 16

21.7 Address Decoding

Registers are global (not per-channel windows); per-channel fields are packed as bit lanes within a single 32-bit register (e.g. CHANNEL_ENABLE.CH_EN[7:0], CHANNEL_IDLE.CH_IDLE[7:0]). The only per-channel array is CH_STATE[0..7] at 0x150-0x16C (stride 0x4). Descriptor kick-off is part of this register block: staged addresses at 0x000-0x03F (CH*_DESC_ADDR_{LOW,HIGH}, stride 0x8) and the KICK_ENABLE launch register at 0x040.

+0x000 - 0x03F: Staged descriptor addresses (CH*_DESC_ADDR_{LOW,HIGH})
+0x040 : KICK_ENABLE (per-channel launch, singlepulse)


+0x100 - 0x3FF: Base configuration / status registers
+0x800 - 0x9FF: Monitor configuration / performance registers
SRC half at 0x0000, SNK half at 0x1000 (paddr[12]); PSLVERR on the
monitor
window when USE_MON_REGS = 0.

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) ·
MIT License

22 Initialization Sequence

22.1 Overview

This section describes the required steps to initialize RAPIDS Beats and start DMA transfers. The initialization sequence ensures proper hardware state before beginning operations.



Boot Sequence

22.2 Detailed Steps

22.2.1 Step 1: Verify Hardware Presence

```
// Read VERSION register
uint32_t version = read_reg(RAPIDS_BASE + VERSION);
uint8_t major = (version >> 24) & 0xFF;
uint8_t minor = (version >> 16) & 0xFF;

if (major < 1) {
    printf("ERROR: RAPIDS not detected or incompatible version\n");
    return -1;
}

printf("RAPIDS Beats v%d.%d detected\n", major, minor);
```

22.2.2 Step 2: Read Configuration

```
// Read CONFIG register
uint32_t config = read_reg(RAPIDS_BASE + CONFIG);
uint8_t num_channels = (config >> 24) & 0xFF;
uint8_t data_width = ((config >> 16) & 0xFF) * 8; // Convert to bits
uint8_t sram_depth = ((config >> 8) & 0xFF) * 16;

printf("Channels: %d, Data Width: %d bits, SRAM: %d entries\n",
       num_channels, data_width, sram_depth);
```

22.2.3 Step 3: Global Reset

```
// Perform soft reset to ensure clean state
write_reg(RAPIDS_BASE + GLOBAL_CTRL, GLOBAL_CTRL_SOFT_RESET);

// Wait for reset completion
while (read_reg(RAPIDS_BASE + GLOBAL_STATUS) &
       GLOBAL_STATUS_RESET_ACTIVE) {
    // Poll until reset complete
}

// Clear any pending interrupts
write_reg(RAPIDS_BASE + IRQ_STATUS, 0xFFFFFFFF);
```

22.2.4 Step 4: Allocate Resources

```
// Allocate descriptor ring (must be 32-byte aligned)
size_t desc_size = NUM_DESCRIPTOR * sizeof(rapids_descriptor_t);
rapids_descriptor_t *desc_ring = aligned_alloc(32, desc_size);
if (!desc_ring) {
    return -ENOMEM;
}
```

```

// Allocate data buffers (must be 64-byte aligned for 512-bit AXI)
size_t buf_size = BUFFER_SIZE_BYTES;
void *rx_buffer = aligned_alloc(64, buf_size);
void *tx_buffer = aligned_alloc(64, buf_size);

```

22.2.5 Step 5: Initialize Descriptors

```

// Initialize sink descriptor chain
for (int i = 0; i < NUM_RX_DESC - 1; i++) {
    desc_ring[i].dest_addr = (uint64_t)(rx_buffer + i * FRAME_SIZE);
    desc_ring[i].src_addr = 0;
    desc_ring[i].next_ptr = (uint64_t)&desc_ring[i + 1];
    desc_ring[i].direction = DESC_DIR_SINK;
    desc_ring[i].length = FRAME_SIZE / 64; // Convert to beats
    desc_ring[i].control = DESC_CTRL_IRQ_EN;
}

// Last descriptor
desc_ring[NUM_RX_DESC - 1].dest_addr = (uint64_t)(rx_buffer +
(NUM_RX_DESC - 1) * FRAME_SIZE);
desc_ring[NUM_RX_DESC - 1].next_ptr = 0;
desc_ring[NUM_RX_DESC - 1].control = DESC_CTRL_LAST |
DESC_CTRL_IRQ_EN;

```

```

// Ensure descriptors are visible to hardware
__sync_synchronize(); // Memory barrier

```

22.2.6 Step 6: Configure Channels

```

// Configure channel 0 for sink (receive)
uint32_t ch0_base = RAPIDS_BASE + 0x100;

// Set descriptor pointer
write_reg(ch0_base + DESC_PTR_LO, (uint32_t)((uint64_t)desc_ring &
0xFFFFFFFF));
write_reg(ch0_base + DESC_PTR_HI, (uint32_t)((uint64_t)desc_ring >>
32));

// Configure channel
write_reg(ch0_base + CH_CONFIG, CH_CONFIG_DEFAULT);

```

22.2.7 Step 7: Enable Interrupts


```

// Enable completion and error interrupts for channel 0
write_reg(RAPIDS_BASE + IRQ_ENABLE, IRQ_CH0_COMPLETE | IRQ_CH0_ERROR);

```

22.2.8 Step 8: Enable Channel

```
// Enable channel (but don't kick yet)
write_reg(ch0_base + CH_CTRL, CH_CTRL_ENABLE);
```




Initialization Timing

22.3 Starting Transfers

22.3.1 Kick a Channel

After initialization, kick the channel to start processing:

```
// Kick channel 0 to start descriptor processing
write_reg(ch0_base + CH_CTRL, CH_CTRL_ENABLE | CH_CTRL_KICK);
```



Waveform 18

22.4 Interrupt Handling

22.4.1 Completion Interrupt

```
void rapids_irq_handler(void) {
    uint32_t irq_status = read_reg(RAPIDS_BASE + IRQ_STATUS);

    // Handle channel 0 completion
    if (irq_status & IRQ_CH0_COMPLETE) {
        // Read channel status
        uint32_t ch_status = read_reg(ch0_base + CH_STATUS);
        uint8_t desc_count = (ch_status >> 16) & 0xFF;

        // Process completed buffers
        process_rx_buffers(desc_count);

        // Clear interrupt
        write_reg(RAPIDS_BASE + IRQ_STATUS, IRQ_CH0_COMPLETE);

        // Re-kick channel for continuous operation (if desired)
        write_reg(ch0_base + CH_CTRL, CH_CTRL_ENABLE | CH_CTRL_KICK);
    }

    // Handle errors
    if (irq_status & IRQ_CH0_ERROR) {
        uint32_t err_status = read_reg(ch0_base + ERR_STATUS);
        handle_error(err_status);

        // Clear error interrupt
        write_reg(RAPIDS_BASE + IRQ_STATUS, IRQ_CH0_ERROR);
    }
}
```

22.5 Reset and Recovery

22.5.1 Per-Channel Reset

```
void reset_channel(int channel) {
    uint32_t ch_base = RAPIDS_BASE + 0x100 + (channel * 0x40);

    // Soft reset the channel
    write_reg(ch_base + CH_CTRL, CH_CTRL_SOFT_RESET);

    // Wait for reset complete
    while ((read_reg(ch_base + CH_STATUS) >> 28) == 0xF) {
        // State = RESET
    }
}
```

```

}

// Clear error status
write_reg(ch_base + ERR_STATUS, 0xFFFFFFFF);

// Re-initialize descriptor pointer
write_reg(ch_base + DESC_PTR_LO, saved_desc_ptr_lo[channel]);
write_reg(ch_base + DESC_PTR_HI, saved_desc_ptr_hi[channel]);

// Re-enable
write_reg(ch_base + CH_CTRL, CH_CTRL_ENABLE);
}

```

22.5.2 Global Reset

```

void reset_rapids(void) {
    // Disable all interrupts
    write_reg(RAPIDS_BASE + IRQ_ENABLE, 0);

    // Global soft reset
    write_reg(RAPIDS_BASE + GLOBAL_CTRL, GLOBAL_CTRL_SOFT_RESET);

    // Wait for all channels idle
    while (read_reg(RAPIDS_BASE + GLOBAL_STATUS) & 0x00FF0000) {
        // Wait for active channels to clear
    }

    // Clear all interrupts
    write_reg(RAPIDS_BASE + IRQ_STATUS, 0xFFFFFFFF);

    // Re-run full initialization
    rapids_init();
}

```

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

23 Error Handling

23.1 Overview

RAPIDS reports errors per channel and per direction. The error classes are the ones RAPIDS Beats already has, and the byte-granular design adds one: the packet on the sink stream does not carry the number of bytes the descriptor asked for. This chapter lists every condition that stops a channel, how software sees it, and how to recover. It also lists three conditions that look like errors and are not.

Two facts shape the whole chapter:

1. **A fatal error parks the channel.** The scheduler enters its error state and stays there. Only a channel reset or a global reset leaves it.
2. **A channel reset recovers every class.** The scheduler, the descriptor and control engines, both data engines and both data paths all take the per-channel reset. No error class needs the hardware reset `aresetn`, and resetting one channel does not disturb the others.

23.2 Error Classes

Error Classes

Class	Detected by	Fatal to the channel	Sticky until
Invalid descript or (valid = 0)	Scheduler, on CH_FETCH_DESC	Yes	Channel reset
Descript or address outside both configu red ranges	Descriptor engine, before any fetch	Yes	Channel reset
Descript or	Descriptor engine	Yes	Channel reset

Class	Detected by	Fatal to the channel	Sticky until
address of zero or otherwi se invalid over APB			
Descriptor or fetch returns an AXI error (RRESP not OKAY)	Descriptor engine	Yes	Channel reset
Data read returns an AXI error (RRESP not OKAY)	AXI read engine	Yes	Channel reset
Data write returns an AXI error (BRESP not OKAY)	AXI write engine	Yes	Channel reset
Sink packet length mismat	Sink ingress, at tlast	Yes	Channel reset

Class	Detected by	Fatal to the channel	Sticky until
ch (new)			
Control read retry exhausted	Control read engine	Yes	Channel reset
Control write returns an AXI error	Control write engine	Yes	Channel reset
Write-progress timeout, first window	Scheduler timeout counter	No	Any write progress
Write-progress timeout, escalated	Scheduler timeout counter	Yes	Channel reset

The first four rows and the control-engine rows behave exactly as in RAPIDS Beats. The data-path rows are the same conditions. In RAPIDS the channel reset also clears them; the “Recovery” section lists what it does to work still in flight.

23.3 The Byte-Granular Error: Packet Length Mismatch

23.3.1 Contract

A sink descriptor of `length` bytes on a channel promises one AXI-Stream packet on that channel. The packet is delimited by `tlast`. The number of valid bytes in the packet, counted from `tstrb`, must equal `length`.

The sink ingress counts the valid bytes of every accepted beat. On the beat that carries `tlast` it compares the running total, including that beat, with the byte count in the channel's packet record. If the two differ, the ingress sets a sticky per-channel bit and raises it on the channel's `sched_wr_error` line.

Length Mismatch Cases

Situation	Result
Packet shorter than <code>length</code> (early <code>tlast</code>)	Error
Packet longer than <code>length</code> (late <code>tlast</code>)	Error
Packet equals <code>length</code>	No error
Descriptor <code>length</code> = 0	No packet record, no packet expected

The hardware does not pad a short packet and does not drop the extra bytes of a long one. Nothing is corrected silently. The bytes that were accepted are still written, so memory that the descriptor covers must not be trusted after this error.

23.3.2 Exposure

The mismatch is visible in three places.

Where the Length Mismatch Appears

Where	What software sees
<code>SNK.SCHED_ERROR.SCHED_ERR</code>	Bit for the channel set. This is the same per-channel bit that reports every fatal scheduler error, so the register does not say which class occurred.
MonBus	One error packet per error episode from the channel's scheduler. Its data field carries the sticky write-error flag.
Scheduler state	The channel is in its error state, so <code>SCHEDULER_IDLE.SCHED_IDLE</code> does not show it idle.

The error is raised on the sink half only. The source half has no counterpart: the egress re-packer builds the packet from the descriptor, so the packet it emits always has length bytes.

23.3.3 How it Clears

The per-channel bit is cleared by the channel reset (and therefore by the global reset, which asserts every channel's reset). It stays clear afterwards; the next packet is checked against its own record. See "Recovery" below for what the reset does to a packet that is part-way through the stream.

23.3.4 Prevention

- Issue the sink descriptor for a packet before, or together with, the first beat of that packet. The stream waits for the descriptor (see "Not Errors" below), so a late descriptor costs time and nothing else.
 - Set length to the exact byte count of the packet. If the length is only known at the end of the packet, write the descriptor after the length is known.
 - Do not split one packet across two descriptors and do not put two packets under one descriptor. One descriptor maps to one `tlast` delimited packet.
-

23.4 Shared Error Classes

23.4.1 Invalid or Unfetchable Descriptor

The scheduler leaves `CH_FETCH_DESC` only for a descriptor whose `valid` bit is set. A descriptor with `valid = 0` sends the channel to its error state.

The descriptor engine rejects a descriptor fetch whose address falls outside the two configured address ranges. The rejection happens before any AXI read is issued. It also reports an error for a fetch address of zero or otherwise invalid on the APB path, and for an AXI error response on the fetch itself.

A descriptor whose length is zero is not invalid. See "Not Errors".

23.4.2 Data-Path AXI Errors

The AXI read engine sets a sticky per-channel flag when a data read returns a response other than OKAY. The AXI write engine does the same for a write response. Both flags drive the channel's error state.

23.4.3 Control Engine Errors

A control read that does not match after the configured number of retries reports an error. Retry exhaustion is what stops a control read that can never match from hanging the channel. A control write that returns an AXI error reports an error. Both are fatal to the descriptor that issued them.

23.4.4 Write-Progress Timeout

The scheduler counts the cycles in which it holds a write request that the write engine has not accepted. A write completion or a write commit resets the count. Its configuration is shared with RAPIDS Beats:

Timeout Configuration

Register field	Meaning	Default
SCHED_TIMEOUT_CYCLES.TIMEOUT_CYCLES	Length of one window in cycles	0x3E8
SCHED_TIMEOUT_LIMIT.LIMIT	Consecutive expired windows that escalate to a fatal error. Zero never escalates.	4

A window that expires is recoverable. Any write progress clears the strike count. Only the configured number of consecutive expired windows makes the timeout fatal. A LIMIT of zero keeps the timeout purely advisory. The timeout is unchanged by the byte-granular design.

23.5 Not Errors

Three conditions look like faults and are normal operation.

23.5.1 Packet Record Queue Full

Each channel keeps a queue of packet records, one per non-zero data descriptor per enabled direction. The queue holds four records. When it is full, the scheduler waits in CH_FETCH_DESC until a record is consumed. Software sees the channel busy and nothing else.

No error bit is set and no MonBus error is sent. The timeout counter runs only while the scheduler holds a write request the write engine has not accepted, so waiting for a record does not count toward it. Descriptor chains longer than the queue therefore run at the pace the data paths consume records.

23.5.2 Sink Beat With No Packet Record

The sink ingress accepts a stream beat for a channel only when that channel's packet record exists. Until then `s_axis_tready` stays low.

`s_axis_tready` is a single signal. It is qualified by the `tid` of the beat that is on the bus. A beat for a channel with no record therefore stalls the whole stream, including beats for other channels

that are queued behind it in the sender. The queues and holds inside RAPIDS are per channel, so no data is lost or mixed. The cost is delay, and it lands on every channel that shares the stream.

Two rules keep this delay short:

- Post the sink descriptor for a channel before the sender drives the first beat for that channel.
- A sender that interleaves channels on one stream must not assume that a waiting channel leaves the others unaffected at the AXI-Stream interface.

23.5.3 The 4 KB Burst Cap

An AXI burst must not cross a 4 KB boundary. The scheduler splits a transfer at each boundary. A descriptor that spans several pages issues several bursts, and every burst starts beat-aligned. The split is invisible to software, and it neither sets a flag nor counts against any timeout. The cost appears only as throughput, described in the throughput chapter.

23.6 Error Reporting

23.6.1 Registers

Software finds the failing channel from these fields. All names come from the shared register map and are the same as in RAPIDS Beats.

Error Registers

Register field	Use
SRC . SCHED_ERROR . SCHED_ERR	One bit per channel, source half
SNK . SCHED_ERROR . SCHED_ERR	One bit per channel, sink half
SCHEDULER_IDLE . SCHED_IDLE	One bit per channel, set when the scheduler is idle
CHANNEL_RESET . CH_RST	One bit per channel, resets the scheduler

Register field	Use
GLOBAL_CTRL . GLOBAL_RST	and its engines Resets every channel
GLOBAL_CTRL . GLOBAL_EN	Global enable

The per-channel error bit is the summary of every fatal class in the “Error Classes” table. It does not name the class. To name the class, read the MonBus error packet or use the scheduler debug outputs.

23.6.2 MonBus

The scheduler sends one error packet the first time a channel enters its error state. It does not repeat the packet on every cycle. The packet carries the sticky write-error flag and the sticky read-error flag in its data field. MonBus decoding is described in the shared monitor bus chapter.

23.7 Recovery

23.7.1 Channel Reset

Writing the channel’s bit in CHANNEL_RESET . CH_RST of the half that reported the error, SNK or SRC (or GLOBAL_CTRL . GLOBAL_RST for every channel of that half), returns the channel to idle. The reset reaches the scheduler, the descriptor and control engines, the AXI read and write engines, and the sink and source data paths. Every sticky error flag in that chain clears, including the data read and write response flags and the sink packet length flag. Software should:

1. Set the channel’s CH_RST bit for at least one clock, then clear it. A single-cycle pulse and a held level both work. To reset both directions of a channel, write both halves.
2. Poll the SCHED_ERR bit and the SCHED_IDLE bit for the channel. The error bit stays clear and the idle bit sets.
3. Rebuild the descriptor chain from a known-good state. Bytes that the failed chain already wrote stay in memory.
4. Start the channel again as in the initialization sequence.

This recovers every error class in the “Error Classes” table. No hardware reset is needed, and the other channels keep running through it.

23.7.2 What the Reset Does to Work in Flight

A channel reset can arrive with beats, bursts and packets still moving. The hardware settles them as follows, so the channel is clean when the reset releases.

Channel Reset: Handling of In-Flight Work

Where	In-flight work	Effect
Sink stream, packet already started	Beats of the packet still to come	The ingress accepts and discards them up to and including t _{last} , so the tail of the old packet cannot be taken as the start of the next. The stream does not stall.
Sink stream, no packet started	None	Nothing to discard. A beat for the channel is held off while the reset is asserted.
Sink write path	An AXI write burst already open	The write engine finishes the burst with null beats (WSTRB = 0), so the AXI protocol stays legal and the null beats write nothing. A beat already presented on the write data channel when the reset hit is completed unchanged. No new burst opens for the channel

Where	In-flight work	Effect
		until the open bursts and their responses have finished. Its AWADDR value is unchanged.
Sink write path	Write responses still due	They are consumed and ignored. A BRESP error that arrives after the reset does not set the error flag.
Source read path	Read bursts already issued	The read engine issues no further bursts, then drains and discards the returning read data until none is outstanding. A RRESP error in that data does not set the error flag.
Source stream, packet in progress	Beats not yet sent	The egress stops. A beat already on m_axis completes. The remaining beats are not sent (see below).
Other channels	Everything	Not affected. The data paths mask only the channel in reset.

The sink ingress discards only the tail of a packet of which at least one beat had been accepted when the reset hit. The sender must still send that packet's `tlast`; the beat is taken and dropped,

and the next beat for the channel is checked against the next packet record as usual. While the reset is asserted the channel's beats are held off (`s_axis_tready` low).

The source stream is left unterminated. If the reset lands between the first and last beat of a source packet, RAPIDS stops sending it and does not emit a `tlast` (and no null terminator). The receiver sees a partial packet. A receiver that must resynchronize after a channel reset should treat the reset as the end of the packet, or flush its own per-channel state when it resets the channel. A packet that had not started, or that had already sent its `tlast`, is unaffected.

Head-of-line blocking is unchanged. A sink beat for a channel with no packet record still stalls the shared `s_axis_tready`, as described under “Not Errors”. A channel reset does not remove this. After the reset, post the next sink descriptor before the sender starts the next packet.

23.8 Software Checklist

Software Checklist

Step	Action
Before the run	Program <code>SCHED_TIMEOUT_CYCLES</code> and <code>SCHED_TIMEOUT_LIMIT</code> . Post the sink descriptor before the first beat of its packet.
During the run	Poll <code>SCHED_ERR</code> for the active channels, or watch MonBus for error packets.
On an error	Note the channel and read the MonBus packet. Decide which class from the descriptor state and the stream.
Recovery	Channel reset for every error class, including a length mismatch or an AXI response error.
After recovery	Re-post descriptors. Re-send the whole packet, not the tail. A source receiver discards the partial packet of a reset channel.

23.9 Related Chapters

- [Descriptor Format](#): the byte length, the packet record and the zero-length rule.

- [Register Map](#): the shared register layout.
- [Monitor Bus Interface](#): the error packet format.

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

24 Throughput

RAPIDS moves bytes. The datapath moves beats. This chapter separates the two figures because they differ for small and unaligned transfers, and it labels every measured number with the build that produced it.

The sink path moves an AXI-Stream ingress stream into memory. The source path reads memory and drives an AXI-Stream egress stream. The two paths are independent engines with their own buffers, schedulers and AXI masters, so their bandwidths add.

24.1 Theoretical Maximum

A beat is $\text{DATA_WIDTH} / 8$ bytes. The board build uses $\text{DATA_WIDTH} = 256$, so a beat is 32 bytes. Per-direction bandwidth is the beat size times the clock.

Theoretical Maximum (256-bit Build)

Item	Value
Beat size	32 bytes
Clock on the board	100 MHz
Line rate per direction	3.2 GB/s
Sink plus source together	6.4 GB/s

The line rate scales linearly with the clock and with the data width. The width does not change the per-beat behavior of the engines, so every utilization figure below holds at any width and only the GB/s scale changes.

24.2 Byte Efficiency

The byte-granular design accepts any start address and any length. The memory side still moves whole beats. A transfer of `length` bytes that starts at `byte offset` inside a beat occupies

$$\text{beats} = (\text{offset} + \text{length} + \text{BYTE_LANES} - 1) \gg \text{OFF_W}$$

beats on that side, with $\text{BYTE_LANES} = 32$ and $\text{OFF_W} = 5$ for 256 bits. The useful fraction of those beats is

$$\text{efficiency} = \text{useful_bytes} / (\text{beats} * \text{BYTE_LANES})$$

Here `useful_bytes` is `length`. Efficiency is 1.0 only when both the start and the end land on beat boundaries. The bus meters count a beat with partial byte enables as a productive beat, so their utilization figures measure the beat stream. The byte throughput is the beat throughput multiplied by this efficiency.

Beats and Efficiency for Small and Unaligned Transfers

Length	Offset	Beats	Efficiency
1	0	1	0.031
2	31	2	0.031
32	0	1	1.000
32	1	2	0.500
37	0	2	0.578
60	5	3	0.625
100	7	4	0.781
203	3	7	0.906

The loss is at most two partial beats per descriptor: one at the head and one at the tail. It shrinks as the length grows. A 4 KB aligned transfer is 128 full beats and loses nothing. Software that needs the full line rate should align buffers to the beat size and use lengths that are multiples of it. Software that cannot align pays at most two beats per descriptor.

The offset applies to each half separately. The source half uses the source address and the sink half uses the destination address. A copy whose source and destination have different offsets can have a different beat count on each half.

24.2.1 4 KB Boundaries

AXI bursts do not cross a 4 KB boundary, so a transfer is split at every boundary it crosses. A page holds 128 beats at 32 bytes. The split adds one burst per extra page, and each burst starts beat-aligned. It costs burst-start overhead and no data. For large transfers the overhead amortizes in the same way as any other burst boundary. The burst-length sweep below gives the measured cost of short bursts.

24.2.2 Head-of-Line Delay on the Sink Stream

The sink stream has one `s_axis_tready`. It is qualified by the `tid` of the beat on the bus. A beat for a channel with no packet record yet stalls the whole stream, including beats for other channels behind it. The queues inside RAPIDS are per channel, so the cost is delay only. A sender that posts each sink descriptor before its first beat never sees this stall. The error chapter describes the rule.

24.3 Measured Results

Three sets of results exist. They answer different questions and must not be mixed.

Sources of Measured Figures

Set	Build	Question it answers
Byte campaign	Byte-granular RAPIDS on the Genesys 2	Are byte lengths and offsets correct on the board?
Beats performance report	RAPIDS Beats on the Genesys 2	How fast does the beat datapath run?
Byte-build performance	None yet	How fast does the byte build run in beat mode?

The byte checkers on the board build hold ready while they feed a transfer. A performance row measured with them therefore does not show the beat-mode backpressure behavior that the beats performance report was designed to show. The beat-mode rows in the beats performance report come from the beats build and are quoted as such below. A performance characterization of the byte build needs a build whose checkers run in beat mode, and that build does not exist yet.

24.3.1 Byte Campaign (Correctness)

Source: `projects/fpga-systems/Genesys2/rapids/reports/board`, files `rapids_byte_bytes_20260930_072516.json` and `rapids_byte_smoke_20260930_072435.json`. Two channels were active, one descriptor per channel.

Byte Campaign on the Board (7 of 7 Pass)

Packet bytes	Offset	Sink beats per channel	Result
1	1	1	Pass
2	31	2	Pass
32	0	1	Pass
37	0	2	Pass
100	7	4	Pass
96	17	4	Pass
203	3 (address 4035, crosses a 4 KB boundary)	7	Pass

The smoke run, four beats on two channels, also passes. The beat count the sink write master issued equals the formula in every row. Golden data matched in every row on both halves. These rows prove correctness. They are runs of one to seven beats, so their utilization figures are dominated by launch and are not throughput.

24.3.2 RAPIDS Beats Performance Report

Source: projects/fpga-systems/Genesys2/rapids_beats/reports/perf/README.md, version 2.2. Build: RAPIDS Beats, 8 channels, 256 bits, 4 KB of buffer per channel, 100 MHz. Every row is golden-CRC checked. Utilization is engaged utilization: productive cycles over productive, backpressure and starvation cycles.

RAPIDS Beats Build, 8 Channels at 128 KB per Channel

Path	Interface	Engaged utilization	Effective bandwidth
Sink	AXIS in	99.7 %	3.19 GB/s
Sink	AXI4 write	100.0 %	3.20 GB/s
Source	AXI4 read	100.0 %	3.20 GB/s
Source	AXIS out	100.0 %	3.20 GB/s

The 0.3 point shortfall on the sink stream is a one-time 82-cycle fill stall of the 4 KB per-channel buffer. It does not repeat inside a run.

RAPIDS Beats Build, Transfer Size Sweep at 8 Channels

Beats per channel	AXIS in	AXI4 write	AXI4 read	AXIS out
1	88.9 %	38.1 %	27.6 %	27.6 %
4	97.0 %	84.2 %	69.6 %	69.6 %
16	99.2 %	95.5 %	90.1 %	90.1 %
64	99.8 %	98.5 %	97.3 %	97.3 %
256	96.1 %	99.7 %	99.3 %	99.3 %
1024	99.0 %	99.9 %	99.8 %	99.8 %
4096	99.7 %	100.0 %	100.0 %	100.0 %

RAPIDS Beats Build, Channel Scaling at 4096 Beats per Channel

Active channels	AXIS in	AXI4 write	AXI4 read	AXIS out
1	100.0 %	99.9 %	99.7 %	99.7 %

Active channels	AXIS in	AXI4 write	AXI4 read	AXIS out
2	100.0 %	99.9 %	99.8 %	99.8 %
4	100.0 %	100.0 %	99.9 %	99.9 %
8	99.7 %	100.0 %	100.0 %	100.0 %

RAPIDS Beats Build, Burst Length Sweep at 8 Channels and 1024 Beats

Beats per burst	AXIS in	AXI4 write	AXI4 read	AXIS out
1	35.9 %	35.6 %	99.8 %	99.8 %
2	71.0 %	71.0 %	99.8 %	99.8 %
4	99.0 %	99.9 %	99.8 %	99.8 %
8 or more	99.0 %	99.9 %	99.8 %	99.8 %

The beats report also holds the memory-latency sweeps and the buffer-depth comparison. Those results belong to the beat datapath and are not repeated here.

24.3.3 Using the Beats Numbers

The byte build was not measured in beat mode, so the rows above are reference points and not measurements of it. The memory-side figures count beats. For a byte transfer, multiply the beat figure by the efficiency in the byte efficiency table to estimate the byte rate. Treat the result as an estimate until the byte build has its own performance run.

24.4 Throughput Limiting Factors

Throughput Limiting Factors

Factor	Effect	Mitigation
Partial head and tail beats	At most two beats per descriptor carry fewer than 32 useful bytes	Align buffers to the beat size and use beat-multiple lengths
4 KB boundaries	One extra burst per page crossed	Place large buffers on page boundaries
Short bursts	Below 4 beats the	Keep the burst configuration at 4

Factor	Effect	Mitigation
	write side loses efficiency in the beats measurement	beats or more
Buffer fill at run start	A one-time 82-cycle stall on the sink stream for the 4 KB build	A fixed cost per run, so its share shrinks as transfers grow
Head-of-line stall on the sink stream	Delay on all channels when one channel lacks a packet record	Post each sink descriptor before its first beat
Record queue full	The scheduler waits until a record is consumed; delay only	Chains longer than four descriptors run at the pace the data paths consume records
Memory latency	Reduces small-transfer efficiency	Use the beats report's latency sweeps to size outstanding depth
TYPE=EXT descriptors	Beat rows only, so no head or tail loss but no unaligned addressing	Keep EXT buffers aligned, which they must be anyway

Control descriptors move no payload. A control read gates on a memory location and a control write issues a single write. Budget them as latency, not bandwidth.

24.5 Related Chapters

- [Latency Characteristics](#): shared with RAPIDS Beats.
- [Descriptor Format](#): the byte length, the offset and the beat-count formula.
- [Error Handling](#): the length mismatch and the head-of-line rule.

RTL Design Sherpa · Learning Hardware Design Through Practice GitHub · Documentation Index · MIT License

25 Latency Characteristics

Latency is dominated by the one-time pipeline fill from a channel kick to the first data beat. Once running, both paths sustain the throughput of Section 6.1; control descriptors add a bounded synchronization delay.

25.1 Latency Components

25.1.1 Kick-to-First-Beat Breakdown

Stage	Typical Cycles (100 MHz)	Notes
Kick decode (APB write to KICK_ENABLE)	TBD – re-measure	Address is staged beforehand; the launch request is then held until the descriptor engine accepts it
Descriptor fetch (AXI read, 256-bit)	AXI read latency + 1	Overlapped by prefetch on chains
Descriptor parse	1-2	Opcode + fields decoded
SRAM fill (sink) / AXI read issue (source)	AXI/AXIS latency	First beat into the buffer
First beat out	1-2	Drain to memory (sink) / AXIS (source)

25.1.2 Total Latency Formula

$$L_{\text{first_beat}} = L_{\text{kick}} + L_{\text{desc_fetch}} + L_{\text{parse}} + L_{\text{pipeline_fill}}$$

Note: `L_kick` predates the staged-address/`KICK_ENABLE` kick and has not been re-measured. The previous figure came from a path that stalled APB until the descriptor engine accepted the kick; acceptance is now asynchronous, so the term is no longer bounded by an APB stall.

`L_desc_fetch` is hidden on chained descriptors when the descriptor engine has prefetched the next descriptor (`DESCENG_CONFIG.PREFETCH_EN`).

25.2 First-Beat Latency

The dominant term is the memory/network round trip to fill the pipeline. For a sink transfer the first AXIS beat must arrive and be buffered before the first AXI write can drain; for a source transfer the first AXI read must return before the first AXIS egress beat. After the first beat the pipeline is full and throughput is bandwidth-bound, not latency-bound.

25.3 Control-Descriptor Latency

Control descriptors are latency, not throughput (Section 6.1):

Opcode	Latency
<code>CTRL_WRITE</code> (doorbell)	One single-beat AXI write: <code>AW->W->B</code> round trip
<code>CTRL_READ</code> (gate)	One poll per retry (AXI read + compare); retries paced by <code>tick_1us</code> , up to <code>CTRL_CONFIG.CTRLRD_MAX_TRY</code> (default 16, max 511)

A `CTRL_READ` gate blocks its descriptor (and the chain) until the polled value matches. The retry budget bounds the worst case: an unsatisfied gate cannot hang the channel – after `CTRLRD_MAX_TRY` polls the engine raises `ctrlrd_error` instead of waiting forever.

25.4 Latency Variability

25.4.1 Sources of Variability

- Memory read latency (descriptor fetch, source reads) and write-response timing.

- AXIS backpressure (`s_axis_tready` / `m_axis_tready`) on the network end.
- Multi-channel arbitration for the shared AXI master.
- `CTRL_READ` retry count when a gate is not yet satisfied.

25.4.2 Worst-Case Latency

Bounded by: memory timeout (`SCHED_TIMEOUT_CYCLES` / `SCHED_TIMEOUT_LIMIT` escalation on the scheduler side) and the control-read retry budget (`CTRL_CONFIG.CTRLRD_MAX_TRY`). Both convert an otherwise-unbounded wait into a reported error so a channel is never permanently stalled.

25.5 Latency Optimization

25.5.1 Software Recommendations

- Chain descriptors so the descriptor engine prefetches the next while the current transfers (hides `L_desc_fetch`).
- Keep the AXIS consumer/producer ready to avoid backpressure stalls.
- Size `CTRL_READ` gates so the expected value is already (or soon) present to minimize poll retries.

25.5.2 Hardware Configuration

- Adequate `SRAM_DEPTH` so the buffer covers memory/network latency without stalling.
 - Tune `AXI_XFER_CONFIG` (RD/WR beats, `ALLOC/DRAIN`) so bursts amortize AXI setup.
-

Last Updated: 2026-07-13

RTL Design Sherpa · Learning Hardware Design Through Practice [GitHub](#) · [Documentation Index](#) · [MIT License](#)

26 Resource Estimates

The figures in this chapter are measured. They come from the placed and routed board build of the byte-granular RAPIDS on the Genesys 2, not from an estimate. The chapter states the configuration first because every number depends on it.

26.1 Build Configuration

Board Build Configuration

Item	Value
Top level	rapids_byte_genesys2_top (RAPIDS plus the characterization harness)
Device	xc7k325tffg900-2 (Kintex-7 325T)
Tool	Vivado 2025.1, design state Physopt postRoute
Clock	100 MHz
Channels	8, on both the sink and the source half
Data width	256 bits (32-byte beats)
Buffer depth	128 entries per channel, 4 KB per channel
Interface observers	On
AXI monitors	Off

The measured design includes the characterization harness: the UART bridge, the pattern generators, the byte checkers and the bus meters. The figures are therefore an upper bound for RAPIDS alone. The harness is not separated in the reports.

26.2 FPGA Resource Summary

Source:
projects/fpga-systems/Genesys2/rapids/reports/perf/json/rapids_byte_build_byt
ecrc.json and rapids_byte_build_wordcrc.json, extracted from the post-route reports by
reports/extract_build_metrics.py.

The harness has two checker builds. BYTE_CRC=1 is the standard bitstream: the byte-wise CRC checkers take 9 cycles per 32-byte beat and verify every byte and strobe. BYTE_CRC=0 is a measurement bitstream with word-wide checkers that take one beat per cycle, so the harness does not cap the measured rate.

Post-Route Utilization, 8 Channels, 256 Bits

Resource	Standard (BYTE_CRC=1)	Word-wide (BYTE_CRC=0)	Available
Slice LUTs	92,874 (45.57 %)	86,065 (42.23 %)	203,800
LUT as logic	81,352	75,695	203,800
LUT as distributed RAM	11,522	10,370	64,000
Slice registers	82,379 (20.21 %)	79,527 (19.51 %)	407,600
F7 muxes	4,709	4,430	101,900
F8 muxes	106	107	50,950
Block RAM tiles	68 (15.28 %)	52 (11.69 %)	445
DSP	0	0	0

All block RAM tiles are RAMB36E1. No RAMB18 is used, and no register is a latch. DSP use is zero because RAPIDS moves data and performs no multiply-accumulate. The 16 tiles and about 6,800 LUTs that the word-wide build saves are the byte checkers' golden storage and CRC logic, which belong to the harness and not to RAPIDS.

26.3 Timing

Source: the same two build JSONs.

Timing at 100 MHz

Metric	Standard (BYTE_CRC=1)	Word-wide (BYTE_CRC=0)
Worst negative slack, setup	+0.301 ns	+0.077 ns
Total negative slack	0.000 ns	0.000 ns
Worst hold slack	+0.023 ns	+0.013 ns
Failing endpoints	0 of 320,415	0 of 301,738

All user timing constraints are met in both builds. The slack is small and positive; treat 100 MHz as the design point and not as a margin.

26.4 Board Result

On the standard bitstream (sha256 cfad34c3 . . .) the byte-wise campaign passes 117 of 117 points and the directed sequences 4 of 4. On the word-wide bitstream (sha256 48e1282c . . .) the beat-aligned profile passes 28 of 28 points and reaches 3182 MB/s on the sink and 3199 MB/s on the source at 8 channels and 4096 beats, against a theoretical peak of 3200 MB/s (100 MHz x 32 bytes). The word-wide checker CRCs only slice 0 of each beat and ignores strobes, so it is compared with the beats golden; byte-level integrity comes from the byte-wise campaign. Both runs are in the throughput chapter and the characterization report (reports/perf/README.md, v0.2).

26.5 Comparison with the Beats Build

The RAPIDS Beats performance report lists the resources of its 256-bit build in its version 2.0 text. Both builds run 8 channels at 100 MHz on the same device with a buffer of 128 entries per channel.

Beats and Byte-Granular Builds

Item	RAPIDS Beats, 256-bit, v2.0	RAPIDS, byte-granular (standard build)
Slice LUTs	75,679	92,874
Block RAM tiles	44	68
Worst negative slack	+0.608 ns	+0.301 ns

The columns are not a like-for-like comparison of the two designs. The two bitstreams come from different versions of the RTL and the harness. The byte checkers and the byte-wise golden logic are in the byte build and not in the beats build. The beats build has since been rebuilt, and the v2.2 beats report header gives a slack of +0.286 ns for it and no new resource counts. Use the table as a size comparison of two board images, and not as the cost of byte granularity.

26.6 What Depends on What

The reports do not break the design down by block, and this chapter does not invent a breakdown. The relationships that follow from the design are these.

Scaling Notes

Change	Effect
Channels 8 to fewer	Scheduler, descriptor and buffer resources scale with channel count
Buffer depth	Block RAM scales with entries per channel, per direction, and with the entry width
Data width	Datapath logic and buffer width scale with it. The line rate scales with it.
Interface observers off	Removes the observer logic and its histograms
AXI monitors on	Adds monitor logic. They are off in this build.

The sink buffer entry is $\text{DATA_WIDTH} + \text{DATA_WIDTH} / 8$ bits wide, because each entry stores the byte enables beside the data. The source buffer entry stays DATA_WIDTH bits. The byte-granular sink therefore stores a wider entry than the beats sink for the same depth and width.

The byte-granular design adds per-channel state that the beats design lacks: a packet-record queue four deep, a sink spill register, an ingress packet byte counter and, on the source half, the re-pack hold register. The reports do not isolate their cost.

26.7 Related Chapters

- [Throughput](#): the measured campaign and the beats report.
- [Error Handling](#): the reset behavior of the sticky flags.