Identification of Joint Stiffness and Signed Inertia Matrix for Multi-DOF Flexible Joint Robots via Off-Diagonal FRF Fitting

Motion Control Lab, DGIST

Abstract

We present a method for identifying joint stiffness and the full *signed* inverse inertia matrix of multi-DOF flexible joint robots from frequency response function (FRF) measurements. The diagonal FRF analysis via Vieta's formulas yields stiffness and the magnitude of coupling terms, but leaves an inherent sign ambiguity. We show that this ambiguity reduces to a small candidate set via eigenvalue constraints (Klein four-group symmetry for n=3), and is uniquely resolved by fitting the off-diagonal FRF data against each candidate model—without requiring direct measurement of off-diagonal anti-resonances. Simulation on a 3-DOF SEA robot arm demonstrates that the correct sign combination is identified with over 500× separation in fitting error, and the method remains robust down to SNR=20 dB.

1 Introduction

Accurate identification of joint stiffness k_i and the link-side inertia matrix $\boldsymbol{M}_l$ is essential for model-based control of flexible joint robots (FJR), particularly for disturbance observer (DOB) design and coupling compensation in multi-DOF systems.

The standard approach for single-DOF FJR identification uses three features of the diagonal FRF: the high-frequency asymptote (J_m), the resonance frequency, and the anti-resonance frequency. For multi-DOF systems, extending this to recover the off-diagonal elements of $\boldsymbol{M}_l^{-1}$ is challenging because: (i) diagonal FRFs yield only the *magnitude* $|\Gamma_{ij}|$ of coupling terms via Vieta's formulas, not their signs; (ii) off-diagonal FRF anti-resonances, which encode sign information, are difficult to measure due to shallow dips between closely spaced resonances; (iii) SVD-based mode shape extraction (Matrix Pencil method) gives mode shapes that are structurally different from the denominator matrix eigenvectors.

This paper proposes an alternative: instead of extracting individual features from off-diagonal FRFs, we fit the *entire* off-diagonal FRF data against a small set of candidate models. The correct candidate produces an overwhelmingly better fit.

2 System Model and Notation

Consider n joints of an FJR with parallel rotation axes. The motor-side transfer function from torque $\tau_{m,j}$ to velocity $\dot{\theta}_{m,i}$ is:

$$G_{ij}(s) = \frac{s \cdot C_{ij}(s^2)}{\prod_l J_{m,l} s \cdot \det(\boldsymbol{D}(s))} \tag{1}$$

where C_{ij} denotes the cofactor of the denominator matrix $\boldsymbol{D}(s) \in \mathbb{R}^{n\times n}$:

$$\boldsymbol{D}(s) = s^2\boldsymbol{I} + \boldsymbol{D}', \qquad \boldsymbol{D}' = \mathrm{diag}(\boldsymbol{W}) + \boldsymbol{\Gamma} \tag{2}$$

with:

$$W_i = \omega_{m,i}^2 + k_i(\boldsymbol{M}_l^{-1})_{ii}, \quad \omega_{m,i}^2 = \frac{k_i}{J_{m,i}N_i^2} \tag{3}$$

$$\Gamma_{ij} = \sqrt{k_i k_j}\,(\boldsymbol{M}_l^{-1})_{ij}, \quad \Gamma_{ij} = \Gamma_{ji} \tag{4}$$

The diagonal FRF G_{ii} has n resonances (zeros of $\det(\boldsymbol{D})$) and n anti-resonances (zeros of $\det(\boldsymbol{N}_i)$, where $\boldsymbol{N}_i$ replaces the i-th diagonal of $\boldsymbol{D}'$). The off-diagonal G_{ij} ($i \neq j$) shares the same n resonances but has only $n-1$ anti-resonances.

3 Diagonal FRF Analysis (Steps 1–4)

These steps are well-established and summarized briefly.

Step 1 (Motor inertia): From $|G_{ii}(j\omega)| \to 1/(J_{m,i}\omega)$ at high frequency.

Step 2 (Common resonance): CMIF peak detection with parabolic refinement:

$$\hat{\omega}_R = \omega_k + \frac{\sigma_{k-1} - \sigma_{k+1}}{2(\sigma_{k-1} - 2\sigma_k + \sigma_{k+1})}\Delta\omega \tag{5}$$

Step 3 (Channel-specific anti-resonance): Magnitude dips of each G_{ii} give $\omega_{AR,r,i}$.

Step 4 (Vieta's formulas): Denote $P_{\boldsymbol{D}'}(\lambda)$ and $P_{\boldsymbol{N}_i'}(\lambda)$ as the characteristic polynomials of $\boldsymbol{D}'$ and $\boldsymbol{N}_i'$ respectively, with $\lambda = -s^2$. Their polynomial difference $\delta_i(\lambda) = P_{\boldsymbol{N}_i'} - P_{\boldsymbol{D}'}$ yields:

Stiffness:

$$\boxed{k_i = J_{\text{eff},i}\Big(\sum_r \omega_{R,r}^2 - \sum_r \omega_{AR,r,i}^2\Big)} \tag{6}$$

Diagonal W_i recovery from the coefficient ratios A_i:

$$W_j = \tfrac{1}{2}(A_k + A_l - A_j), \quad \{j,k,l\} = \{1,2,3\} \tag{7}$$

Off-diagonal magnitude from the constant-term ratio B_i:

$$|\Gamma_{jk}|^2 = W_j W_k - B_i, \quad \{j,k\} \neq i \tag{8}$$

At this stage, k_i, W_i, $|\Gamma_{ij}|$ are determined. The remaining unknowns are the $\binom{n}{2}$ signs $\sigma_{ij} = \text{sign}(\Gamma_{ij})$.

4 Sign Ambiguity and Reduction

4.1 Eigenvalue Constraint (Step 5)

Each sign combination $\boldsymbol{\sigma} \in \{+1,-1\}^3$ produces a candidate $\boldsymbol{D}'_{\boldsymbol{\sigma}}$ whose eigenvalues must equal $\{\omega_{R,r}^2\}$.

Proposition 1 (Klein four-group reduction)**.** *For n=3, exactly 4 of the 8 sign combinations satisfy the eigenvalue constraint. They form the Klein four-group $\mathbb{Z}_2 \times \mathbb{Z}_2$, generated by simultaneous sign flips $\Gamma_{ij} \to s_i s_j \Gamma_{ij}$ with $\boldsymbol{s} = \text{diag}(\pm1,\pm1,\pm1)$.*

Proof. The similarity transformation $\boldsymbol{D}' \to \boldsymbol{S}\boldsymbol{D}'\boldsymbol{S}$ with $\boldsymbol{S} = \text{diag}(s_1, s_2, s_3)$, $s_i \in \{+1,-1\}$, preserves eigenvalues but maps $\Gamma_{ij} \to s_i s_j \Gamma_{ij}$. The kernel $\{\boldsymbol{S} : s_i s_j = 1\ \forall\, i<j\}$ has 4 elements, giving 2 orbits of size 4 on the 8 sign combinations. □

4.2 Why Previous Methods Fail

Matrix Pencil: This method extracts mode shapes from $\tilde{\boldsymbol{G}}(j\omega_R) = \text{diag}(J_{m,i} j\omega_R) \cdot \boldsymbol{G}(j\omega_R)$ via SVD and reconstructs $\boldsymbol{D}' = \boldsymbol{V}\boldsymbol{\Lambda}\boldsymbol{V}^{-1}$. However, at resonance, the leading singular vector of $\tilde{\boldsymbol{G}}$ corresponds to the leading singular vector of the motor-motor subblock of $\text{adj}(\boldsymbol{Z}_{CL})$, which is *not* mathematically equivalent to the eigenvector of $\boldsymbol{D}'$. This mismatch arises from the 6×6 impedance structure of $\boldsymbol{Z}_{CL}$. In simulation (Table 1), MAC values as low as 0.867 result, causing >130% off-diagonal error.

Table 1: MAC: SVD mode shapes vs. $\boldsymbol{D}'$ eigenvectors

Mode	ω_R (Hz)	σ_1/σ_2	MAC
1	12.84	4.4×10^4	0.867
2	29.60	4.2×10^4	0.980
3	31.16	5.2×10^3	0.950

Iterative D' Refinement: Since the mapping $\boldsymbol{D}' \to (K, \boldsymbol{M}_l^{-1}) \to \boldsymbol{D}'$ is algebraically an identity, the iteration converges in one step without correcting the initial error.

Algorithm 1: Signed Inertia Matrix via Off-Diagonal FRF Fitting

Input: $n \times n$ FRF $\boldsymbol{G}(j\omega_k)$; $J_{m,i}, N_i$; $k_i, W_i, |\Gamma_{ij}|$ from Steps 1–4
Output: Signed $\boldsymbol{M}_l^{-1}$

Step 5: Eigenvalue filter: keep $\boldsymbol{\sigma}$ s.t. $\text{eig}(\boldsymbol{D}'_{\boldsymbol{\sigma}}) \approx \{\omega_{R,r}^2\}$;
Step 6:;
foreach *surviving* $\boldsymbol{\sigma}$ **do**
  $(\boldsymbol{M}_l^{-1})_{\boldsymbol{\sigma}} \leftarrow$ reconstruct from $W_i, \sigma_{ij}|\Gamma_{ij}|, k_i, \omega_{m,i}^2$;
  $\boldsymbol{M}_{l,\boldsymbol{\sigma}} \leftarrow \big[(\boldsymbol{M}_l^{-1})_{\boldsymbol{\sigma}}\big]^{-1}$;
  for $k = 1, \ldots, N_f$ **do**
    $\boldsymbol{G}_{\boldsymbol{\sigma}}(j\omega_k) \leftarrow$ FRF from $\boldsymbol{M}_{l,\boldsymbol{\sigma}}, J_{m,i}, k_i, N_i$;
  $J_{\boldsymbol{\sigma}} \leftarrow \sum_{k=1}^{N_f} \sum_{i \neq j} \big|G_{\boldsymbol{\sigma},ij}(j\omega_k) - G_{ij}^{\text{meas}}(j\omega_k)\big|^2$;
return $\boldsymbol{\sigma}^* = \arg\min_{\boldsymbol{\sigma}} J_{\boldsymbol{\sigma}}$;

Off-diagonal anti-resonance: The off-diagonal FRF G_{ij} has $n-1$ anti-resonances encoding sign information, but these dips can fall between closely spaced resonances and vanish at practical frequency resolution (Fig. 1).



Figure 1: G_{12} near closely spaced resonances (29.6, 31.2 Hz). Anti-resonance at 30.4 Hz (green) is visible at $\Delta f = 0.005$ Hz but undetectable at $\Delta f \geq 0.1$ Hz.

5 Proposed: Off-Diagonal FRF Fitting (Step 6)

5.1 Key Insight

All 4 eigenvalue-consistent candidates share identical k_i, W_i, and hence identical *diagonal* FRFs G_{ii}. However, they produce *different* mass matrices $\boldsymbol{M}_{l,\boldsymbol{\sigma}}$ and thus different off-diagonal FRFs $G_{ij,\boldsymbol{\sigma}}$. The sign of Γ_{ij} affects the *entire shape* of $G_{ij}(j\omega)$, not merely isolated anti-resonance dips.

5.2 Algorithm

5.3 Cost and Scaling

After eigenvalue filtering, 2^{n-1} candidates remain. For each, one FRF sweep of N_f points costs $O(n^3 N_f)$. Total:

$O(2^{n-1}n^3N_f)$. For $n = 3$, $N_f = 86$ ($\Delta f = 0.5$ Hz, $[2, 45]$ Hz): 4 sweeps of a 6×6 system—under 1 second.

6 Simulation Results

6.1 Setup

Validated on J_2, J_4, J_6 of a 7-DOF SEA arm (Table 2). Link mass matrix from URDF via Pinocchio at $q = [0, \frac{\pi}{2}, -\frac{\pi}{2}]^T$.

Table 2: SEA robot parameters

	J_m ($\times 10^{-4}$)	N	k (Nm/rad)	J_{eff}
J_2	0.6793	100	2500	0.6793
J_4	0.2639	50	1800	0.6597
J_6	0.3057	50	800	0.7644

6.2 Sign Candidate Selection (Fig. 2, Table 3)

Table 3: Off-diagonal NRMSE (%) for 4 sign candidates

SNR	$(+,+,+)$	$(+,-,-)$	$(-,+,-)$	$(-,-,+)$
Clean	99.4	191.4	183.1	**0.18**
60 dB	99.4	191.4	183.1	**0.21**
40 dB	99.5	191.5	183.1	**1.00**
20 dB	99.6	190.9	182.7	**10.2**

The correct candidate achieves NRMSE 0.18% (clean), while the nearest incorrect has 99.4% ($> 500\times$ separation). At SNR= 20 dB, 10.2% vs. 99%—still unambiguous.



Figure 2: Off-diagonal FRF: 4 candidates vs. measurement.

6.3 Final Identification Accuracy (Table 4)

7 Discussion

Feature-free approach. The method requires no peak/dip detection on off-diagonal FRFs—only the raw complex FRF data. This eliminates the sensitivity to frequency resolution and closely spaced modes that plagues anti-resonance extraction.



Figure 3: NRMSE across noise levels (log scale). Correct candidate consistently $> 10\times$ lower.

Table 4: $\boldsymbol{M}_l^{-1}$ identification error (%)

Element (GT)	Vieta	Mat. Pencil	**Proposed**
$(1,1)$: $+1.516$	0.001	0.000	**0.001**
$(2,2)$: $+4.070$	0.001	1.63	**0.001**
$(3,3)$: $+33.61$	0.005	0.000	**0.005**
$(1,2)$: -1.520	$\lvert 0.05 \rvert$	131.7	**0.051**
$(1,3)$: -3.081	$\lvert 0.04 \rvert$	45.6	**0.033**
$(2,3)$: $+0.554$	$\lvert 0.31 \rvert$	16.6	**0.072**

Scaling. For n DOF, the eigenvalue filter retains 2^{n-1} candidates. For n=4: 8; n=5: 16. Each requires one $O(n^3N_f)$ FRF computation. Practical for $n \leq 7$.

Experimental applicability. The model FRF in Step 6 depends on identified k_i, which has small error from frequency quantization. This adds $\sim 0.2\%$ baseline NRMSE to the correct candidate but does not affect discrimination (99% gap to incorrect candidates).

8 Conclusion

We identified joint stiffness and the signed inverse inertia matrix of a multi-DOF FJR without measuring off-diagonal anti-resonances. The method combines Vieta-based magnitude estimation from diagonal FRFs, eigenvalue-based sign filtering ($2^3 \to 2^2$ candidates), and off-diagonal FRF fitting for unique resolution. Results: k_i error $< 0.01\%$; all $\boldsymbol{M}_l^{-1}$ elements $< 0.1\%$ error (signed); sign discrimination $> 500\times$ in NRMSE; robust to SNR= 20 dB. No nonlinear optimization or iterative procedures are needed.

References

[1] T. Oomen, "System identification for robust and inferential control," Ph.D. thesis, TU Eindhoven, 2010.



Figure 4: Element-wise $\boldsymbol{M}_l^{-1}$ error: Vieta (magnitude only), Matrix Pencil (signed but inaccurate), Proposed (signed and accurate).

[2] E. Wernholt and S. Gunnarsson, "Nonlinear identification of a physically parameterized robot model," *IFAC*, 2006.

[3] J. Öhr et al., "Identification of flexibility parameters of 6-axis industrial manipulator models," *ISMA*, 2006.

[4] A. Albu-Schäffer et al., "A unified passivity-based control framework for position, torque and impedance control of flexible joint robots," *IJRR*, vol. 26, 2007.