

ETC Reference Guide

High End Systems SolaFrame 1000 DMX Channel Map

SolaFrame 1000 DMX Channel Map

(Firmware Version 1.2.8 and Later)

Standard Protocol			
Channel	Function	Channel	Function
1	Pan Coarse	25	Blade 4 Angle A
2	Pan Fine	26	Blade 4 Angle B
3	Tilt Coarse	27	Frame Rotation Course
4	Tilt Fine	28	Frame Rotation Fine
5	Color Mix Function	29	Animation Function
6	Cyan	30	Animation Rotate
7	Magenta	31	Prism / Diffusion Function
8	Yellow	32	Prism Rotate Coarse
9	CTO	33	Prism Rotate Fine
10	Static Color Function	34	Diffusion
11	Static Color Position	35	Focus Coarse
12	Gobo 1 Function	36	Focus Fine
13	Gobo 1 Position	37	Zoom Coarse
14	Gobo 2 Function	38	Zoom Fine
15	Gobo 2 Position	39	Iris
16	Gobo 2 Rotate Function	40	Shutter / LED Functions
17	Gobo 2 Rotate Coarse	41	Shutter / LED
18	Gobo 2 Rotate Fine	42	Dimmer Coarse
19	Blade 1 Angle A	43	Dimmer Fine
20	Blade 1 Angle B	44	LED Animation
21	Blade 2 Angle A	45	LED Animation Speed
22	Blade 2 Angle B	46	LED Animation Xfade
23	Blade 3 Angle A	47	Mspeed
24	Blade 3 Angle B	48	Control



Corporate Headquarters ■ Middleton, WI, USA | +1 608 831 4116

Global Offices ■ London, UK | Rome, IT | Holzkirchen, DE | Paris, FR | Hong Kong | Dubai, UAE | Singapore
New York, NY | Orlando, FL | Los Angeles, CA | Austin, TX

Web etcconnect.com | **Support** support.etcconnect.com | **Contact** etcconnect.com/contactETC

© 2021 Electronic Theatre Controls, Inc. | Trademark and patent info: etcconnect.com/ip

Product information and specifications subject to change. ETC intends this document to be provided in its entirety.

2570M2400 Rev B Released 2021-07

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

SolaFrame 1000 Standard Protocol

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
1 / 2	Pan (Coarse / Fine)	See note 8 on page 10	0	65535	0%	100%	0000h	FFFFh	32767
3 / 4	Tilt (Coarse / Fine)	See note 8 on page 10	0	65535	0%	100%	0000h	FFFFh	32767
5	Color Mix Function	Pure Mix	0	31	0%	12%	00h	1Fh	0
		Cycle	32	47	13%	18%	20h	2Fh	
		Random	48	63	19%	25%	30h	3Fh	
		Reserved (see note 5 on page 9)	64	255	25%	100%	40h	FFh	
6 7 8	Cyan Magenta Yellow	Pure Mix							255
		Full Saturation to Open	0	255	0%	100%	00h	FFh	
		Cycle and Random Modes. Scan Speed controlled by Cyan Channel.							
		Slow to Fast	0	255	0%	100%	00h	FFh	
9	CTO	Full Saturation to Open	0	255	0%	100%	00h	FFh	255
10	Static Color Function	Indexed (see note 1 on page 9)	0	15	0%	6%	00h	0Fh	48
		Forward Spin	16	31	6%	12%	10h	1Fh	
		Reverse Spin	32	47	13%	18%	20h	2Fh	
		Continuous (see note 1 on page 9)	48	63	19%	25%	30h	3Fh	
		Fast Scan	64	79	25%	31%	40h	4Fh	
		Random	80	95	31%	37%	50h	5Fh	
		Reserved (see note 5 on page 9)	96	255	38%	100%	60h	FFh	

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
11	Static Color Position	Indexed Modes							0
		Open (White)	0	16	0%	6%	00h	10h	
		Open / Red	17	32	7%	13%	11h	20h	
		Red	33	48	13%	19%	21h	30h	
		Red / Light Blue	49	64	19%	25%	31h	40h	
		Light Blue	65	80	25%	31%	41h	50h	
		Light Blue / Green	81	96	32%	38%	51h	60h	
		Green	97	112	38%	44%	61h	70h	
		Green / TM30	113	128	44%	50%	71h	80h	
		TM30	129	144	51%	56%	81h	90h	
		TM30 / Orange	145	160	57%	63%	91h	A0h	
		Orange	161	176	63%	69%	A1h	B0h	
		Orange / Dark Blue	177	192	69%	75%	B1h	C0h	
		Dark Blue	193	208	76%	82%	C1h	D0h	
		Dark Blue / Open	209	224	82%	88%	D1h	E0h	
		Open (White)	225	255	88%	100%	E1h	FFh	
		Scan Modes							
		Open / Red	0	35	0%	14%	00h	23h	
		Red / Light Blue	36	71	14%	28%	24h	47h	
		Light Blue / Green	72	107	28%	42%	48h	6Bh	
		Green / TM30	108	143	42%	56%	6Ch	8Fh	
		TM30 / Orange	144	179	56%	70%	90h	B3h	
		Orange / Dark Blue	180	215	71%	84%	B4h	D7h	
		Dark Blue / Open	216	255	85%	100%	D8h	FFh	
		Spin and Random Modes							
		Stop to Fast	0	255	0%	100%	00h	FFh	
		Continuous Mode							
		Positioning from 0-360 degrees	0	255	0%	100%	00h	FFh	
12	Gobo 1 Function	Indexed (see note 1 on page 9)	0	15	0%	6%	00h	0Fh	0
		Forward Wheel Spin	16	31	6%	12%	10h	1Fh	
		Reverse Wheel Spin	32	47	13%	18%	20h	2Fh	
		Scan	48	63	19%	25%	30h	3Fh	
		Random	64	79	25%	31%	40h	4Fh	
		Reserved (see note 5 on page 9)	80	255	31%	100%	50h	FFh	

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
13	Gobo 1 Position	Indexed Modes							0
		Open	0	24	0%	9%	00h	18h	
		Tunnel	25	49	10%	19%	19h	31h	
		Triangles	50	74	20%	29%	32h	4Ah	
		Organic	75	99	29%	39%	48h	63h	
		Shatter	100	124	39%	49%	64h	7Ch	
		Abstract	125	149	49%	58%	7Dh	95h	
		Cobble	150	174	59%	68%	96h	AEh	
		Endgrain	175	199	69%	78%	AFh	C7h	
		Warped	200	224	78%	88%	C8h	E0h	
		Open	225	255	88%	100%	E1h	FFh	
		Spin and Random Modes							
		Rotate Stop	0	3	0%	1%	00h	03h	
		Slowest to Fastest	4	255	2%	100%	04h	FFh	
		Scan Modes							
		Open / Tunnel	0	27	0%	11%	00h	1Bh	
		Tunnel / Triangles	28	55	11%	22%	1Ch	37h	
		Triangles / Organic	56	83	22%	33%	38h	53h	
		Organic / Shatter	84	111	33%	44%	54h	6Fh	
		Shatter / Abstract	112	139	44%	55%	70h	8Bh	
		Abstract / Cobble	140	167	55%	65%	8Ch	A7h	
		Cobble / Endgrain	168	195	66%	76%	A8h	C3h	
		Endgrain / Warped	196	223	77%	87%	C4h	DFh	
		Warped / Open	224	255	88%	100%	E0h	FFh	
14	Gobo 2 Function	Indexed (see note 1 on page 9)	0	15	0%	6%	00h	0Fh	0
		Forward Wheel Spin	16	31	6%	12%	10h	1Fh	
		Reverse Wheel Spin	32	47	13%	18%	20h	2Fh	
		Scan	48	63	19%	25%	30h	3Fh	
		Random	64	79	25%	31%	40h	4Fh	
		Reserved (see note 5 on page 9)	80	255	31%	100%	50h	FFh	

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
15	Gobo 2 Position	Indexed Modes							0
		Open	0	27	0%	11%	00h	1Bh	
		Bar	28	55	11%	22%	1Ch	37h	
		Stripe Strips	56	83	22%	33%	38h	53h	
		Fracked	84	111	33%	44%	54h	6Fh	
		Starvolver	112	139	44%	55%	70h	8Bh	
		Pinwheel Dots	140	167	55%	65%	8Ch	A7h	
		Ice	168	195	66%	76%	A8h	C3h	
		Shower	196	223	77%	87%	C4h	DFh	
		Open	224	225	88%	88%	E0h	E1h	
		Scan Modes							
		Rotate Stop	0	3	0%	1%	00h	03h	
		Slowest to Fastest	4	255	2%	100%	04h	FFh	
		Spin and Random Modes							
		Open / Bar	0	31	0%	12%	00h	1Fh	
		Bar / Stripe Strips	32	63	13%	25%	20h	3Fh	
		Stripe Strips / Fracked	64	95	25%	37%	40h	5Fh	
		Fracked / Starvolver	96	127	38%	50%	60h	7Fh	
		Starvolver / Pinwheel Dots	128	159	50%	62%	80h	9Fh	
		Pinwheel Dots / Ice	160	191	63%	75%	A0h	BFh	
		Ice / Shower	192	223	75%	87%	C0h	DFh	
		Shower / Open	224	255	88%	100%	E0h	FFh	
16	Gobo 2 Rotate Function	Indexed (see note 1 on page 9)	0	15	0%	6%	00h	0Fh	0
		Forward Rotate	16	31	6%	12%	10h	1Fh	
		Reverse Rotate	32	47	13%	18%	20h	2Fh	
		Forward Strobe Rotate (Gobo Animate)	48	63	19%	25%	30h	3Fh	
		Reverse Strobe Rotate (Gobo Animate)	64	79	25%	31%	40h	4Fh	
		Reserved (see note 5 on page 9)	80	255	31%	100%	50h	FFh	
17 / 18	Gobo 2 Rotate (Coarse / Fine)	Indexed/Blink Modes							32767
		Position 0-360 degrees	0	65535	0%	100%	0000h	FFFFh	
		Forward/Reverse/Forward Strobe/Reverse Strobe Rotate Modes							
		Rotate Stop	0	1023	0%	2%	0000h	03FFh	
		Rotate Slowest to Fastest	1024	65535	2%	100%	0400h	FFFFh	
19	Blade 1 Angle A (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
20	Blade 1 Angle B (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
21	Blade 2 Angle A (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
22	Blade 2 Angle B (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
23	Blade 3 Angle A (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
24	Blade 3 Angle B (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
25	Blade 4 Angle A (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
26	Blade 4 Angle B (see note 6 on page 9)	Removed to Inserted	0	255	0%	100%	00h	FFh	0
27 / 28	Frame Rotation (Coarse / Fine)	Frame Angle Negative	0	32766	0%	50%	0000h	7FFEh	0
		Frame Angle 0 degrees	32767	32767	50%	50%	7FFFh	7FFFh	
		Frame Angle Positive	62768	65535	96%	100%	F530h	FFFFh	
29	Animation Function	Removed to Inserted	0	255	0%	100%	00h	FFh	0
30	Animation Rotate	Forward Spin Speed Stopped to Fast	0	63	0%	25%	00h	3Fh	0
		Reverse Spin Speed Stopped to Fast	64	127	25%	50%	40h	7Fh	
		Forward Strobe Rotate Stopped to Fast	128	191	50%	75%	80h	BFh	
		Reverse Strobe Rotate Stopped to Fast	192	255	75%	100%	C0h	FFh	
31	Prism / Diffusion Function	Removed (see note 7 on page 9)	0	15	0%	6%	00h	0Fh	0
		Continuous	16	31	6%	12%	10h	1Fh	
		Forward Spin	32	47	13%	18%	20h	2Fh	
		Reverse Spin	48	63	19%	25%	30h	3Fh	
		Forward Strobe Rotate (Effect Animate)	64	79	25%	31%	40h	4Fh	
		Reverse Strobe Rotate (Effect Animate)	80	95	31%	37%	50h	5Fh	
		Reserved (see note 5 on page 9)	96	255	38%	100%	60h	FFh	
32 / 33	Prism Rotate (Coarse / Fine)	Continuous Mode							32767
		Position 0-360 degrees	0	65535	0%	100%	0000h	FFFFh	
		Forward/Reverse/Forward Strobe/Reverse Strobe Rotate Modes							
		Rotate Stop	0	1023	0%	2%	0000h	03FFh	
		Rotate Slowest to Fastest	1024	65535	2%	100%	0400h	FFFFh	
34	Diffusion	Removed to Inserted	0	255	0%	100%	00h	FFh	0
35 / 36	Focus (Coarse / Fine)	Focus In to Out	0	65535	0%	100%	0000h	FFFFh	32767
37 / 38	Zoom (Coarse / Fine)	Zoom In to Out	0	65535	0%	100%	0000h	FFFFh	32767
39	Iris	Closed to Open	0	255	0%	100%	00h	FFh	255

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
40	Shutter / LED Functions	Normal Shutter Functions	0	31	0%	12%	00h	1Fh	0
		Random Random Strobe	32	63	13%	25%	20h	3Fh	
		Synchronous Random Strobe (see note 3 on page 9)	64	95	25%	37%	40h	5Fh	
		Reserved (see note 5 on page 9)	96	255	38%	100%	60h	FFh	
41	Shutter / LED	Normal/Random/Sync Random Shutter Functions							255
		Close	0	23	0%	9%	00h	17h	
		Strobe Rate (Slow to Fast)	24	229	9%	90%	18h	E5h	
		Open	230	255	90%	100%	E6h	FFh	
42 / 43	Dimmer (Coarse / Fine)	Off to Full	0	65535	0%	100%	0000h	FFFFh	0
44	LED Animation (see note 2 on page 9)	Macro off	0	3	0%	1%	00h	03h	0
		L to R - 1	4	7	2%	3%	04h	07h	
		L to R - 2	8	11	3%	4%	08h	0Bh	
		L to R - 3	12	15	5%	6%	0Ch	0Fh	
		R to L - 1	16	19	6%	7%	10h	13h	
		R to L - 2	20	23	8%	9%	14h	17h	
		R to L - 3	24	27	9%	11%	18h	1Bh	
		Scan - 1	28	31	11%	12%	1Ch	1Fh	
		Scan - 2	32	35	13%	14%	20h	23h	
		Scan - 3	36	39	14%	15%	24h	27h	
		Invert L to R - 1	40	43	16%	17%	28h	2Bh	
		Invert L to R - 2	44	47	17%	18%	2Ch	2Fh	
		Invert L to R - 3	48	51	19%	20%	30h	33h	
		Invert R to L - 1	52	55	20%	22%	34h	37h	
		Invert R to L - 2	56	59	22%	23%	38h	3Bh	
		Invert R to L - 3	60	63	24%	25%	3Ch	3Fh	
		Invert Scan - 1	64	67	25%	26%	40h	43h	
		Invert Scan - 2	68	71	27%	28%	44h	47h	
		Invert Scan - 3	72	75	28%	29%	48h	4Bh	
		Out / In - 2	76	79	30%	31%	4Ch	4Fh	
		Out / In - 4	80	83	31%	33%	50h	53h	
		In / Out - 2	84	87	33%	34%	54h	57h	
		Out / In / Out - 2	88	91	35%	36%	58h	5Bh	
		Alternate - 4	92	95	36%	37%	5Ch	5Fh	
		...							
		Reserved (see note 5 on page 9)	96	255	38%	100%	60h	FFh	
45	LED Animation Speed	Stop	0	0	0%	0%	00h	00h	128
		Decreasing Speed	1	127	0%	50%	01h	7Fh	
		Programmed Speed x1	128	128	50%	50%	80h	80h	
		Increasing Speed	129	255	51%	100%	81h	FFh	

ETC Reference Guide



SolaFrame 1000 DMX Channel Map

Channel	Function	Description	Decimal Low	Decimal High	Percent Low	Percent High	Hex Low	Hex High	Controller Defaults
46	LED Animation Xfade	Stop	0	0	0%	0%	00h	00h	128
		Decreasing Speed	1	127	0%	50%	01h	7Fh	
		Programmed Speed x1	128	128	50%	50%	80h	80h	
		Increasing Speed	129	255	51%	100%	81h	FFh	
46	Mspeed	Disable	0	3	0%	1%	00h	03h	0
		Longest (252.7 s) to Shortest (0.15 s)	4	255	2%	100%	04h	FFh	
48	Control (see note 4 on page 9)	The Control channel should not be crossfaded. No shutter channel requirement.							0
		Safe (Normal Operation)	0	9	0%	4%	00h	09h	
		Reserved (see note 5 on page 9)	10	19	4%	7%	0Ah	13h	
		Display Off (send 20 packets)	20	28	8%	11%	14h	1Ch	
		Display On (send 20 packets)	29	35	11%	14%	1Dh	23h	
		Reserved (see note 5 on page 9)	36	48	14%	19%	24h	30h	
		Home All (send 20 packets)	49	68	19%	27%	31h	44h	
		Shutdown (send 80 packets)	69	75	27%	29%	45h	4Bh	
		Fan Control Modes							
		Studio Fan Control Mode (send 20 packets)	76	82	30%	32%	4Ch	52h	
		Continuous Fan Control Mode (send 20 packets)	83	89	33%	35%	53h	59h	
		Standard Fan Control Mode (send 20 packets)	90	96	35%	38%	5Ah	60h	
		Studio Continuous Fan Control Mode	97	103	38%	40%	61h	67h	
		Disable Pan / Tilt Motors	104	110	41%	43%	68h	6Eh	
		Dimming Mode - 100 Hz	111	113	44%	44%	6Fh	71h	
		Dimming Mode - 2.4 kHz	114	116	45%	45%	72h	74h	
		Dimming Mode - 16 kHz	117	119	46%	47%	75h	77h	
		Reserved (see note 5 on page 9)	120	160	47%	63%	78h	A0h	
		Internal Prog 1 Scene 1-8 EEPROM	161	171	63%	67%	A1h	ABh	
		Internal Prog 2 Scene 9-16 EEPROM	172	182	67%	71%	ACH	B6h	
		Internal Prog 3 Scene 17-24 EEPROM	183	193	72%	76%	B7h	C1h	
		Internal Prog 4 Scene 25-32 EEPROM	194	204	76%	80%	C2h	CCh	
		Internal Prog 5 Scene 33-40 EEPROM	205	215	80%	84%	CDh	D7h	
		Internal Prog 6 Scene 41-48 EEPROM	216	226	85%	89%	D8h	E2h	
		Internal Prog 7 Scene 49-56 EEPROM	227	237	89%	93%	E3h	EDh	
		Reserved (see note 5 on page 9)	238	255	93%	100%	Eeh	FFh	

ETC Reference Guide







SolaFrame 1000 DMX Channel Map

Notes

1	Continuous/Indexed mode should take the quickest path from 255-0 and 0-255. Continuous mode color wheel aperture centers are as follows: <table> <tr> <th>Color</th><th>Center of Color DMX Value</th></tr> <tr> <td>Open</td><td>0</td></tr> <tr> <td>Red</td><td>36</td></tr> <tr> <td>Light Blue</td><td>73</td></tr> <tr> <td>Green</td><td>109</td></tr> <tr> <td>TM-30</td><td>146</td></tr> <tr> <td>Orange</td><td>182</td></tr> <tr> <td>Dark Blue</td><td>219</td></tr> </table>	Color	Center of Color DMX Value	Open	0	Red	36	Light Blue	73	Green	109	TM-30	146	Orange	182	Dark Blue	219
Color	Center of Color DMX Value																
Open	0																
Red	36																
Light Blue	73																
Green	109																
TM-30	146																
Orange	182																
Dark Blue	219																
2	Macros operate independently. The Xfade and speed channels act as multipliers of the programmed speed in the discrete macro steps. Speed/Xfade Channel Operation <table> <tr> <th>Channel</th><th>Description</th></tr> <tr> <td>0</td><td>Stops playback or cross fade</td></tr> <tr> <td>1-127</td><td>Decreases playback speed/cross fade time ($* < 1$)</td></tr> <tr> <td>128</td><td>Playback or cross fade speed is as programmed ($* 1$)</td></tr> <tr> <td>129-255</td><td>Increases playback speed/cross fade time ($* > 1$)</td></tr> </table>	Channel	Description	0	Stops playback or cross fade	1-127	Decreases playback speed/cross fade time ($* < 1$)	128	Playback or cross fade speed is as programmed ($* 1$)	129-255	Increases playback speed/cross fade time ($* > 1$)						
Channel	Description																
0	Stops playback or cross fade																
1-127	Decreases playback speed/cross fade time ($* < 1$)																
128	Playback or cross fade speed is as programmed ($* 1$)																
129-255	Increases playback speed/cross fade time ($* > 1$)																
3	Synchronous Random Strobes are synchronous across fixtures.																
4	When the fixture is turned off it will retain the selected mode.																
5	Reserved ranges should function according to the controller default value.																
6	Framing blades are arranged according to graphics below.  																
7	Diffusion and Prism are on the same plane. If both are engaged at the same time, Prism will enter the light path.																

ETC Reference Guide

SolaFrame 1000 DMX Channel Map


DMX Fixture Orientation Tilt Movement Range: 265°; Pan Movement Range: 540° Pan and tilt lock locations are highlighted in orange.	
8	 0 DMX ← 255 DMX Display Power Tilt = 255 DMX Pan = 128 DMX  Display Power Tilt = 128 DMX Pan = 128 DMX  Display Power Tilt = 0 DMX Pan = 128 DMX  Display 0 DMX 255 DMX Power Pan = 0 DMX Tilt = 37 DMX  Display Power Pan = 128 DMX Tilt = 37 DMX  Display Power Pan = 255 DMX Tilt = 37 DMX
9	RDM Manufacturers ID: 0x4c52
10	RDM Device ID: - SolaFrame 1000: 0x544 - SolaFrame 1000 High CRI: 0x548

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

SolaFrame 1000 LED Macros

All macros are defined from left to right assuming the fixture is sitting on a table with the pan lock facing you. LED 1 is on the left, and LED 8 is on the right.



Macro 1 - L to R - 1								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	0	0	0	0	0	0	0
2	0	255	0	0	0	0	0	0
3	0	0	255	0	0	0	0	0
4	0	0	0	255	0	0	0	0
5	0	0	0	0	255	0	0	0
6	0	0	0	0	0	255	0	0
7	0	0	0	0	0	0	255	0
8	0	0	0	0	0	0	0	255

Macro 2 - L to R - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	0	0	0	0	0	0
2	0	0	255	255	0	0	0	0
3	0	0	0	0	255	255	0	0
4	0	0	0	0	0	0	255	255

Macro 3 - L to R - 3								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	255	0	0	0	0	0
2	0	255	255	255	0	0	0	0
3	0	0	255	255	255	0	0	0
4	0	0	0	255	255	255	0	0
5	0	0	0	0	255	255	255	0
6	0	0	0	0	0	255	255	255

Macro 4 R to L - 1								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	0	0	0	0	0	255
2	0	0	0	0	0	0	255	0
3	0	0	0	0	0	255	0	0
4	0	0	0	0	255	0	0	0
5	0	0	0	255	0	0	0	0
6	0	0	255	0	0	0	0	0
7	0	255	0	0	0	0	0	0
8	255	0	0	0	0	0	0	0

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Macro 5 - R to L - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	0	0	0	0	255	255
2	0	0	0	0	255	255	0	0
3	0	0	255	255	0	0	0	0
4	255	255	0	0	0	0	0	0

Macro 6 - R to L - 3								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	0	0	0	255	255	255
2	0	0	0	0	255	255	255	0
3	0	0	0	255	255	255	0	0
4	0	0	255	255	255	0	0	0
5	0	255	255	255	0	0	0	0
6	255	255	255	0	0	0	0	0

Macro 7 - Scan - 1								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	0	0	0	0	0	0	0
2	0	255	0	0	0	0	0	0
3	0	0	255	0	0	0	0	0
4	0	0	0	255	0	0	0	0
5	0	0	0	0	255	0	0	0
6	0	0	0	0	0	255	0	0
7	0	0	0	0	0	0	255	0
8	0	0	0	0	0	0	0	255
9	0	0	0	0	0	0	255	0
10	0	0	0	0	0	255	0	0
11	0	0	0	0	255	0	0	0
12	0	0	0	255	0	0	0	0
13	0	0	255	0	0	0	0	0
14	0	255	0	0	0	0	0	0

Macro 8 - Scan - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	0	0	0	0	0	0
2	0	0	255	255	0	0	0	0
3	0	0	0	0	255	255	0	0
4	0	0	0	0	0	0	255	255
5	0	0	0	0	255	255	0	0
6	0	0	255	255	0	0	0	0

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Macro 9 - Scan - 3								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	255	0	0	0	0	0
2	0	255	255	255	0	0	0	0
3	0	0	255	255	255	0	0	0
4	0	0	0	255	255	255	0	0
5	0	0	0	0	255	255	255	0
6	0	0	0	0	0	255	255	255
7	0	0	0	0	255	255	255	0
8	0	0	0	255	255	255	0	0
9	0	0	255	255	255	0	0	0
10	0	255	255	255	0	0	0	0

Macro 10 - Invert L to R - 1								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	255	255	255	255	255	255	255
2	255	0	255	255	255	255	255	255
3	255	255	0	255	255	255	255	255
4	255	255	255	0	255	255	255	255
5	255	255	255	255	0	255	255	255
6	255	255	255	255	255	0	255	255
7	255	255	255	255	255	255	0	255
8	255	255	255	255	255	255	255	0

Macro 11 - Invert L to R - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	255	255	255	255	255	255
2	255	255	0	0	255	255	255	255
3	255	255	255	255	0	0	255	255
4	255	255	255	255	255	255	0	0

Macro 12 - Invert L to R - 3								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	0	255	255	255	255	255
2	255	0	0	0	255	255	255	255
3	255	255	0	0	0	255	255	255
4	255	255	255	0	0	0	255	255
5	255	255	255	255	0	0	0	255
6	255	255	255	255	255	0	0	0

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Macro 13 - Invert R to L - 1								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	255	255	255	255	255	0
2	255	255	255	255	255	255	0	255
3	255	255	255	255	255	0	255	255
4	255	255	255	255	0	255	255	255
5	255	255	255	0	255	255	255	255
6	255	255	0	255	255	255	255	255
7	255	0	255	255	255	255	255	255
8	0	255	255	255	255	255	255	255

Macro 14 - Invert R to L - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	255	255	255	255	0	0
2	255	255	255	255	0	0	255	255
3	255	255	0	0	255	255	255	255
4	0	0	255	255	255	255	255	255

Macro 15 - Invert R to L - 3								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	255	255	255	0	0	0
2	255	255	255	255	0	0	0	255
3	255	255	255	0	0	0	255	255
4	255	255	0	0	0	255	255	255
5	255	0	0	0	255	255	255	255
6	0	0	0	255	255	255	255	255

Macro 16 - Invert Scan - 1								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	255	255	255	255	255	255	255
2	255	0	255	255	255	255	255	255
3	255	255	0	255	255	255	255	255
4	255	255	255	0	255	255	255	255
5	255	255	255	255	0	255	255	255
6	255	255	255	255	255	0	255	255
7	255	255	255	255	255	255	0	255
8	255	255	255	255	255	255	255	0
9	255	255	255	255	255	255	0	255
10	255	255	255	255	255	0	255	255
11	255	255	255	255	0	255	255	255
12	255	255	255	0	255	255	255	255
13	255	255	0	255	255	255	255	255
14	255	0	255	255	255	255	255	255

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Macro 17 - Invert Scan - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	255	255	255	255	255	255
2	255	255	0	0	255	255	255	255
3	255	255	255	255	0	0	255	255
4	255	255	255	255	255	255	0	0
5	255	255	255	255	0	0	255	255
6	255	255	0	0	255	255	255	255

Macro 18 - Invert Scan - 3								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	0	255	255	255	255	255
2	255	0	0	0	255	255	255	255
3	255	255	0	0	0	255	255	255
4	255	255	255	0	0	0	255	255
5	255	255	255	255	0	0	0	255
6	255	255	255	255	255	0	0	0
7	255	255	255	255	0	0	0	255
8	255	255	255	0	0	0	255	255
9	255	255	0	0	0	255	255	255
10	255	0	0	0	255	255	255	255

Macro 19 - Out / In - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	0	0	0	0	0	0	255
2	0	255	0	0	0	0	255	0
3	0	0	255	0	0	255	0	0
4	0	0	0	255	255	0	0	0

Macro 20 - Out / In - 4								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	0	0	0	0	255	255
2	0	0	255	255	255	255	0	0

Macro 21 - In / Out - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	0	0	0	255	255	0	0	0
2	0	0	255	0	0	255	0	0
3	0	255	0	0	0	0	255	0
4	255	0	0	0	0	0	0	255

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Macro 22 - Out / In / Out - 2								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	0	0	0	0	0	0	255
2	0	255	0	0	0	0	255	0
3	0	0	255	0	0	255	0	0
4	0	0	0	255	255	0	0	0
5	0	0	255	0	0	255	0	0
6	0	255	0	0	0	0	255	0

Macro 23 - Alternate - 4								
Step	LED 1	LED 2	LED 3	LED 4	LED 5	LED 6	LED 7	LED 8
1	255	255	255	255	0	0	0	0
2	0	0	0	0	255	255	255	255

ETC Reference Guide

SolaFrame 1000 DMX Channel Map

Revision History

Revision	Change	Release Date
B	Updated the 16-bit function data. Added the Dimming Mode pulse width modulation (PWM) frequency selections to Channel 48, Control. Added the DMX orientation graphic to the Notes. Added the LED Macros section.	July 2021
A	Initial release	2018